

iphone7 Plus U3101 音频 对地阻值图

M	L	K	J	H	G	F	E	D	C	B	A	
GND	OL	OL	368	OL	NC	NC	NC	NC	OL	GND	GND	1
NC	OL	OL	GND	GND	OL	NC	GND	NC	NC	NC	NC	2
NC	OL	OL	OL	674	OL	NC	GND	NC	NC	NC	NC	3
GND	GND	NC	OL	GND	GND	GND	GND	NC	NC	NC	NC	4
GND	OL	OL	GND	732	GND	GND	NC	NC	440	505	280	5
OL	OL	OL	OL	GND	GND	GND	NC	NC	439	486	GND	6
381	GND	OL	OL	GND	GND	GND	NC	GND	449	449	449	7
NC	NC	NC	GND	GND	GND	GND	GND	448	434	433	433	8
NC	NC	446	NC	GND	GND	GND	GND	GND	439	704	704	9
GND	GND	NC	NC	379	55	GND	GND	GND	GND	NC	447	10
NC	GND	NC	278	380	GND	GND	GND	NC	444	444	444	11
NC	NC	NC	688	735	279	OL	OL	279	462	GND	GND	12

