1. ALL RESISTANCE VALUES ARE IN OHMS, 0.1 WATT +/- 5%.
2. ALL CAPACITANCE VALUES ARE IN MICROFARADS.
3. ALL CRYSTALS & OSCILLATOR VALUES ARE IN HERTZ.

REV	ZONE	ECN	DESCRIPTION OF CHANGE	CK APPD / DATE	ENG APPD / DATE
?		?	?	?	?

SCHEMATIC,"Alamo"(K3)

08 JANUARY 2008

Page (.csa)		Contents	Sync	Date
1	1	Table of Contents	N/A	N/A
2	2	System Block Diagram	K2_MLB	01/08/2008
3	3	Power Block Diagram	K2_MLB	01/08/2008
4	4	BOM Configuration	K2_MLB	01/08/2008
5	5	Revision History	K2_MLB	01/08/2008
6	6	Power Conn / Alias	K2_MLB	01/08/2008
7	7	Functional / ICT Test	K3_MASTER	N/A
8	9	GROUNDING ALIASES	K2_MLB	01/08/2008
9	10	CPU FSB	K2_MLB	01/08/2008
10	11	CPU Power & Ground	K2_MLB	01/08/2008
11	12	CPU Decoupling & VID	K2_MLB	01/08/2008
12	13	eXtended Debug Port (XDP)	K2_MLB	01/08/2008
13	14	NB CPU Interface	K2_MLB	01/08/2008
14	15	NB PEG / Video Interfaces	K2_MLB	01/08/2008
15	16	NB Misc Interfaces	K2_MLB	01/08/2008
16	17	NB DDR2 Interfaces	K2_MLB	01/08/2008
17	18	NB Power 1	K2_MLB	01/08/2008
18	19	NB Power 2	K2_MLB	01/08/2008
19	20	NB Grounds	K2_MLB	01/08/2008
20	21	NB Standard Decoupling	K2_MLB	01/08/2008
21	22	NB Graphics Decoupling	K2_MLB	01/08/2008
22	23	SB Enet, Disk, FSB, LPC	K2_MLB	01/08/2008
23	24	SB PCI, PCIe, DMI, USB	K2_MLB	01/08/2008
24	25	SB Pwr Mgt, GPIO, Clink	K2_MLB	01/08/2008
25	26	SB Power & Ground	K2_MLB	01/08/2008
26	27	SB Decoupling	K2_MLB	01/08/2008
27	28	SB Misc	K2_MLB	01/08/2008
28	29	Clock (CK505)	K2_MLB	01/08/2008
29	30	Clock Termination	K2_MLB	01/08/2008
30	31	DDR2 SO-DIMM Connector A	K2_MLB	01/08/2008
31	32	DDR2 SO-DIMM Connector B	K2_MLB	01/08/2008
32	33	Memory Active Termination	K2_MLB	01/08/2008
33	34	PCI-E MiniCard Connector	K2_MLB	01/08/2008
34	37	Ethernet (Yukon)	K2_MLB	01/08/2008
35	38	YUKON/ULTRA SUPPORT	K2_MLB	01/08/2008
36	39	ETHERNET CONNECTOR	K2_MLB	01/08/2008
37	40	FW: 1394B CONTROLLER	K2_MLB	01/08/2008
38	42	FW: 1394B MISC	K2_MLB	01/08/2008
39	43	FIREWIRE CONNECTORS	K2_MLB	01/08/2008
40	44	PATA Connector	K3_MASTER	N/A
41	45	SATA Connectors	K2_MLB	01/08/2008
42	46	EXTERNAL USB CONNECTORS	K2_MLB	01/08/2008
43	47	Internal USB Connections	K2_MLB	01/08/2008
44	49	SMC	K2_MLB	01/08/2008
45	50	SMC Support	K2_MLB	01/08/2008
46	51	LPC+ Debug Connector	K2_MLB	01/08/2008
47	52	SMBUS CONNECTIONS	K2_MLB	01/08/2008
48	53	Current & Voltage Sensing	K2_MLB	01/08/2008
49	55	Thermal Sensors	K2_MLB	01/08/2008
50	56	HD AND OD FAN	K3_MASTER	N/A
51	57	CPU FAN	K2_MLB	01/08/2008
52	61	SPI BootROM	K2_MLB	01/08/2008
53	69	POWER SEQUENCING BLOCK DIAGRAM	K2_MLB	01/08/2008
54	70	PGOOD and Power Sequencing	K2_MLB	01/08/2008
55	71	IMVP6 CPU VCore Regulator	K2_MLB	01/08/2008
56	72	IMVP6 3RD PHASE	K2_MLB	01/08/2008
57	73	1.5V / 1.05V SUPPLIES	K2_MLB	01/08/2008
58	74	1.25V / MCH CORE SUPPLIES	K2_MLB	01/08/2008
59	75	1.8V S3 /0.9V S0 SUPPLIES	K3_MASTER	N/A
60	76	5V S5 / 3.3V S3 SUPPLIES	K2_MLB	01/08/2008
61	77	3.3V / 2.5V POWER SUPPLIES	K2_MLB	01/08/2008
62	78	S3 & S0 FETs	K2_MLB	01/08/2008
63	84	MXM PCI-E & PWR	K3_MASTER	N/A
64	85	MXM I/O	K3_MASTER	N/A
65	90	INTERNAL DISPLAY CONNS	K2_MLB	01/08/2008
66	91	Analog Video Support	K2_MLB	01/08/2008
67	94	External Display Conns	K2_MLB	01/08/2008
68	98	MLB: AUDIO CONNECTOR	K2_MLB	01/08/2008
69	100	CPU/FSB Constraints	K2_MLB	01/08/2008
70	101	NB Constraints	K2_MLB	01/08/2008
71	102	Memory Constraints	K2_MLB	01/08/2008
72	103	SB Constraints (1 of 2)	K2_MLB	01/08/2008
73	104	SB Constraints (2 of 2)	K2_MLB	01/08/2008
74	105	Clock Constraints	K2_MLB	01/08/2008
75	106	FireWire & SMC Constraints	K2_MLB	01/08/2008
76	108	M72/M78 SPECIFIC CONSTRAINTS	K2_MLB	01/08/2008
77	109	M72/M78 RULE DEFINITIONS	K2_MLB	01/08/2008
78	110	Cross Reference Page		
79	111	Cross Reference Page		
80	112	Cross Reference Page		
81	113	Cross Reference Page		
82	114	Cross Reference Page		
83	115	Cross Reference Page		
84	116	Cross Reference Page		
85	117	Cross Reference Page		
86	118	Cross Reference Page		

www.laptopschematics.com

DRAWING
TITLE=M72
ABBREV=DRAWING
LAST_MODIFIED=Tue Jan 8 14:42:38 2008

DIMENSIONS ARE IN MILLIMETERS
XX ±
X.XX ±
X.XXX ±
ANGLES ±
DO NOT SCALE DRAWING

THIRD ANGLE PROJECTION

METRIC

DRAFTER		DESIGN CK	
ENG APPD		MFG APPD	
QA APPD		DESIGNER	
RELEASE		SCALE	NONE

MATERIAL/FINISH NOTED AS APPLICABLE

SIZE D

APPLE INC.

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE
II NOT TO REPRODUCE OR COPY IT
III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

TITLE
SCH,"Alamo"(K3),MLB

DRAWING NUMBER 051-7484 REV. A

SHT 1 OF 118



www.laptop-schematics.com

System Block Diagram

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 2 OF 118	



www.laptop-schematics.com

Power Block Diagram

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A

SCALE	SHT	OF
NONE	3	118

BOM Variants

BOM NUMBER	BOM NAME	BOM OPTIONS
630-9183	PCBA,K3,MLB,BEST	24_INCH_LCD,2P8GHZ_CPU,BASIC,CR_STD,12V_PWR_SENSE
630-9215	PCBA,K3,MLB,CTO	24_INCH_LCD,3P06GHZ_CPU,BASIC,CR_STD,12V_PWR_SENSE
607-2079	K3 MLB DEVELOPMENT	DEVELOPMENT,XDP_CONN,LPCPLUS

BOM NUMBER	BOM NAME	BOM OPTIONS
630-8956	PCBA,MLB,K2,GOOD	20_INCH_LCD,2P4GHZ_CPU,BASIC,CR_STD,K2_GOOD
630-9214	PCBA,MLB,K2,BETTER	20_INCH_LCD,2P66GHZ_CPU,BASIC,CR_STD,12V_PWR_SENSE,K2_BETTER
607-1336	K2 MLB DEVELOPMENT	DEVELOPMENT,XDP_CONN,LPCPLUS

BOM GROUPS

BOM GROUP	BOM OPTIONS
BASIC	5V1V8REG_SKIP,ALTERNATE,COMMON,XDP,MXM_ROM,NBCFG_PEG_REVERSE,TMDS_RES_0_OHM,MXM_PWR_SENSE,2V5_S0_REG,CPU_TDIODE,PRODUCTION

CPUS

PART#	QTY	DESCRIPTION	REFERENCE DESIGNATOR(S)	CRITICAL	BOM OPTION
337S3582	1	IC,PDC,PRQ,C0,3.06G,1066FSB,6M,55W,PGA	CPU	CRITICAL	3P06GHZ_CPU
337S3581	1	IC,PDC,PRQ,C0,2.8G,1066FSB,6M,55W,PGA	CPU	CRITICAL	2P8GHZ_CPU
337S3580	1	IC,PDC,PRQ,C0,2.66G,1066FSB,6M,55W,PGA	CPU	CRITICAL	2P66GHZ_CPU
337S3579	1	IC,PDC,PRQ,C0,2.4G,1066FSB,6M,55W,PGA	CPU	CRITICAL	2P4GHZ_CPU

MISC.

PART#	QTY	DESCRIPTION	REFERENCE DESIGNATOR(S)	CRITICAL	BOM OPTION
155S0306	4	FLTR,CMN MDE,90 OHM,200MA,LF2012	L9400,L9401,L9402,L9403	CRITICAL	TMDS_CHOKE
116S0004	8	RES,0-OHM,1/16W,5%,0402	R9400,R9402,R9403,R9404,R9405,R9408,R9409,R9415		TMDS_RES_0_OHM

COMMON

	PART#	QTY	DESCRIPTION	REFERENCE DESIGNATOR(S)	CRITICAL	BOM OPTION
	338S0569	1	IC,NB,CRESTLINE,XM,C0,PRQ	U1400	CRITICAL	
	338S0434	1	IC,SB,ICH8M,B1,PRQ	U2300	CRITICAL	
	338S0523	1	IC,FW643-06,1394B	U4000	CRITICAL	
537 - 359S0127	359S0130	1	CK505 - SILEGO SLG2AP101	U2900	CRITICAL	
	820-2149	1	PCB,FAB,IO ALIGNMENT,M72	IO1	CRITICAL	
	825-6447	1	MLB LABEL,48.0X4.8	X14	CRITICAL	
	341T0112	1	EFI ROM,K2/K3	U6100	CRITICAL	

K3 PARTS

	PART#	QTY	DESCRIPTION	REFERENCE DESIGNATOR(S)	CRITICAL	BOM OPTION
	051-7484	1	PCB,SCHEM,MLB,K3	SCH1		24_INCH_LCD
056-2484 (MCO) 057-0498 (PANEL)	820-2301	1	PCB,FAB,MLB,K3,HF	MLB1		24_INCH_LCD
(338S0274 - BLNK)	341T0114	1	IC,SMC,K3	U4900	CRITICAL	24_INCH_LCD
	114S0312	1	RES,9.31K,0402,1%,1/16W,LF	R7117		24_INCH_LCD
	132S0010	1	CAP,CER,390PF,10%,50V,0402	C7113		24_INCH_LCD
	132S0178	1	CAP,CER,0.47UF,10%,6.3V,0402	C7128		24_INCH_LCD
	132S0082	1	CAP,CER,0.068UF,10%,16V,0402	C7134		24_INCH_LCD
MXM ROM (335S0155 - BLNK) (341S2234 - K3)	335S0155	1	IC,2K I2C EEPROM,BLANK	U8570	CRITICAL	24_INCH_LCD

K2 PARTS

	PART#	QTY	DESCRIPTION	REFERENCE DESIGNATOR(S)	CRITICAL	BOM OPTION
	051-7388	1	PCB,SCHEM,MLB,K2	SCH1		20_INCH_LCD
056-2483 (MCO) 057-0497 (PANEL)	820-2223	1	PCB,FAB,MLB,K2,HF	MLB1		20_INCH_LCD
(338S0274 - BLNK)	341T0113	1	IC,SMC,K2	U4900	CRITICAL	20_INCH_LCD
	114S0312	1	RES,9.31K,0402,1%,1/16W,LF	R7117		20_INCH_LCD
	132S0205	1	CAP,CER,270PF,10%,50V,0402	C7113		20_INCH_LCD
	132S0178	1	CAP,CER,0.47UF,10%,6.3V,0402	C7128		20_INCH_LCD
	132S0082	1	CAP,CER,0.068UF,10%,10V,0402	C7134		20_INCH_LCD
MXM ROM (335S0155 - BLNK) (341S2233 - K2)	335S0155	1	IC,2K I2C EEPROM,BLANK	U8570	CRITICAL	20_INCH_LCD

ALTERNATES

PART NUMBER	ALTERNATE FOR PART NUMBER	BOM OPTION	REF DES	COMMENTS:
138S0603	138S0602			CAP
124-0369	124-0363	C7109,C7154,C7254,C7340,C7440,C7480,C7530,C7532		CAP
124-0371	124-0363	C7109,C7154,C7254,C7340,C7440,C7480,C7530,C7532		CAP
124-0361	124-0370		C7490,C7491	CAP
126S0118	126S0086	C1235,C2100,C2120,C2130,C2140		CAP
126S0119	126S0092		C625	CAP
128S0197	128S0114	C1251,C1252,C1253,C1254,C1255		CAP
152S0759	152S0317		L2173	INDUCTOR
152S0758	152S0488		L2703	INDUCTOR
371S0464	371S0154		D7624,D7664	DIODES
359S0142	359S0130		U2900	CLOCK CHIP
155S0232	155S0289	FL4300,FL4310,L4612,L4622,L4632		CHOKE

www.laptop-schematics.com

BOM Configuration

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 4 OF 118	

www.laptop-schematics.com

www.laptop-schematics.com

www.laptop-schematics.com

NOTE: All page numbers are .csa, not PDF. See page 1 for .csa -> PDF mapping.

Revision History

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 5 OF 118	



"S0" RAILS

ONLY ON IN RUN

- PP0V9_S0 — MAKE_BASE=TRUE; VOLTAGE=0.9V; MIN_LINE_WIDTH=0.4 mm; MIN_NECK_WIDTH=0.2 mm; NET_SPACING_TYPE=PWR; MAX_NECK_LENGTH=3 MM
  - =PP0V9_S0M_MEM_TERM 33
- PPVCORE_CPU — MAKE_BASE=TRUE; VOLTAGE=1.25V; MIN_LINE_WIDTH=0.6MM; MIN_NECK_WIDTH=0.3MM; NET_SPACING_TYPE=PWR; MAX_NECK_LENGTH=3 MM
  - =PPVCORE_S0_CPU 11 12 53
- PP1V8_S0 — MAKE_BASE=TRUE; VOLTAGE=1.8V; MIN_LINE_WIDTH=0.4 mm; MIN_NECK_WIDTH=0.2 mm; NET_SPACING_TYPE=PWR; MAX_NECK_LENGTH=3 MM
  - =PP1V8_S0_MXM 84
- PP2V5_S0 — MAKE_BASE=TRUE; VOLTAGE=2.5V; MIN_LINE_WIDTH=0.4 mm; MIN_NECK_WIDTH=0.2 mm; NET_SPACING_TYPE=PWR; MAX_NECK_LENGTH=3 MM
  - =PP2V5_S0_MXM 85
- PPMCH_CORE_S0 — MAKE_BASE=TRUE; VOLTAGE=1.05V; MIN_LINE_WIDTH=0.6 mm; MIN_NECK_WIDTH=0.2 mm; NET_SPACING_TYPE=PWR; MAX_NECK_LENGTH=3 MM
  - =PPVCORE_S0_NB 18 21
  - =PPVCORE_S0_NB_FOLLOW 21
  - =PP1V05_S0_CPU 10 11 12 13 50
  - =PP1V25R1V05_S0_FSB_NB 14 30
  - =PP1V25R1V05_S0_NB_VTT 19 21
  - =PP1V05_S0_SB_CPU_IO 23 26 27
- PP1V05_S0 — MAKE_BASE=TRUE; VOLTAGE=1.05V; MIN_LINE_WIDTH=0.6 mm; MIN_NECK_WIDTH=0.2 mm; NET_SPACING_TYPE=PWR; MAX_NECK_LENGTH=3 MM
  - =PP1V05_S0M_NB_VCCAXM 18 21
  - =PP1V05_S0_NB_PCIE 21
  - =PP1V05_S0_NB_FOLLOW 21
  - =PPVCORE_S0_SB 26 27
- PP1V5_S0 — MAKE_BASE=TRUE; VOLTAGE=1.5V; MIN_LINE_WIDTH=0.5 mm; MIN_NECK_WIDTH=0.2 mm; NET_SPACING_TYPE=PWR; MAX_NECK_LENGTH=3 MM
  - =PP1V5_S0_CPU 11 12
  - =PP1V5_S0_NB_TVDAC 22
  - =PP1V5_S0_SB_VCC1_5_A_ARX 26 27
  - =PP1V5_S0_SB_VCC1_5_A_ATX 26 27
  - =PP1V5_S0_SB_VCCUSBPLL 26 27
  - =PP1V5_S0_SB_VCC1_5_A_USB_CORE 26 27
  - =PP1V5_S0_SB_VCC1_5_A 26
  - =PP1V5_S0_SB 27
  - =PP1V5_S0_MINI 34
- PP1V25_S0 — MIN_LINE_WIDTH=0.6 mm; MIN_NECK_WIDTH=0.2 mm; VOLTAGE=1.25V; MAKE_BASE=TRUE; NET_SPACING_TYPE=PWR; MAX_NECK_LENGTH=3 MM
  - =PP1V25_S0_NB_VCCDMI 19 21
  - =PP1V25_S0M_NB_VCCA 21
  - =PP1V25_S0M_NB_VCC 21
  - =PP1V25_S0_NB_PLL 21
  - =PP1V25_S0_NB_VCC 21
  - =PP1V25_S0M_NB_PLL 21
  - =PP1V25_S0_SB_DMI 26 27
- PP3V3_S0 — MAKE_BASE=TRUE; VOLTAGE=3.3V; MIN_LINE_WIDTH=0.6 mm; MIN_NECK_WIDTH=0.2 mm; NET_SPACING_TYPE=PWR; MAX_NECK_LENGTH=3 MM
  - =PP3V3_S0_NB_VCCHV 16 19 21
  - =PP3V3_S0_SB 27
  - =PP3V3_S0_SB_GPIO 23 25
  - =PP3V3_S0_SB_VCCGLAN3_3 26
  - =PP3V3_S0_SB_VCC3_3_PCI 26 27
  - =PP3V3_S0_SB_VCC3_3_IDE 26 27
  - =PP3V3_S0_SB_PCI 24
  - =PP3V3_S0_SB_PM 28
  - =PP3V3_S0_PATA 44
  - =PP3V3_S0_FAN 56 57
  - =PPSPD_S0_MEM 31 32
  - =PP3V3_S0_IMVP 71
  - =PP3V3_S0_AUDIO 98
  - =PP3V3_S0_LPCPLUS 51
  - =PP3V3_S0_SMBUS_SB 52
  - =PP3V3_S0_SMC_LS 50
  - =PP3V3_S0_SMBUS_SMC_0_S0 52
  - =PP3V3_S0_SMBUS_SMC_B_S0 52
  - =PP3V3_S0_SMBUS_SMC_MGMT 52
  - =PP3V3_S0_CK505 29 30
  - =PP3V3_S0_MXM 85
  - =PP3V3_S0_SATALED 45
  - =PP3V3_S0M_CK505 29 30
  - =PP3V3_S0MW0L_SB_CLINK0 25
  - =PP3V3_S0_SB_VCC3_3_DMI 26 27
  - =PP3V3_S0_SB_VCC3_3_SATA 26 27
  - =PP3V3_S0_SB_VCC3_3_VCCPCORE 26
  - =PP3V3R1V5_S0_SB_VCCHDA 26 27
  - =PP3V3_S0MW0L_SB_VCCLAN3_3 26 27
  - =PP3V3_S0MW0L_SB_VCCCL3_3 26 27
  - =PP3V3_S0_TSENS 55
  - =PP3V3_S0_SMC 53
  - =PP3V3_S0_NB_VCCA_PEG_BG 19 21
  - =PP3V3_S0_NB_FOLLOW 21
  - =PP3V3_S0_VIDEO 90 91 94
  - =PP3V3_S0_ENET 38
- PP5V_S0 — MAKE_BASE=TRUE; VOLTAGE=5V; MIN_LINE_WIDTH=0.6 mm; MIN_NECK_WIDTH=0.2 mm; NET_SPACING_TYPE=PWR; MAX_NECK_LENGTH=3 MM
  - =PP5V_S0_SB 27
  - =PP5V_S0_PATA 44
  - =PP5V_S0_LPCPLUS 7 51
  - =PP5V_S0_AUDIO 98
  - =PP5V_S0_SATA 6
  - =PP5V_S0_MXM 84
  - =PPV_S0_LCD_20INCH 90
- PP12V_S0 — MAKE_BASE=TRUE; VOLTAGE=12V; MIN_LINE_WIDTH=0.6 mm; MIN_NECK_WIDTH=0.2 mm; NET_SPACING_TYPE=PWR; MAX_NECK_LENGTH=3 MM
  - =PP12V_S0_FAN 56 57
  - =PP12V_S0_AUDIO_SPKRAMP 98
  - =PP12V_S0_CPU 53 71 72
  - =PPV_S0_LCD_24INCH 90
  - =PPV_S0_MXM_PWRSRC 53

"S3" RAILS

ON IN RUN AND SLEEP

- PP1V8_S3 — MAKE_BASE=TRUE; VOLTAGE=1.8V; MIN_LINE_WIDTH=0.6 mm; MIN_NECK_WIDTH=0.2 mm; NET_SPACING_TYPE=PWR; MAX_NECK_LENGTH=3 MM
  - =PP1V8_S3M_MEM_NB 16 18 21 22
  - =PP1V8_S3M_NB_VCC 21
  - =PP1V8_S3_MEM 31 32
  - =PP1V8_S3_MEMVTT 75
  - =PP1V8_S3_ENET 38
- PP3V3_S3 — MAKE_BASE=TRUE; VOLTAGE=3.3V; MIN_LINE_WIDTH=0.6 mm; MIN_NECK_WIDTH=0.2 mm; NET_SPACING_TYPE=PWR; MAX_NECK_LENGTH=3 MM
  - =PP3V3_S3_MINI 34
  - =PP3V3_S3_ENET 38 39
  - =PP3V3_S3_BT 47
- PP5V_S3 — MAKE_BASE=TRUE; VOLTAGE=5V; MIN_LINE_WIDTH=0.6 mm; MIN_NECK_WIDTH=0.2 mm; NET_SPACING_TYPE=PWR; MAX_NECK_LENGTH=3 MM
  - =PP5V_S3_BNDI 47
  - =PP5V_S3_MEMVTT 75

"S5" RAILS

ALWAYS ON WHEN UNIT HAS AC POWER (TRICKLE)

- PP3V3_S5 — MAKE_BASE=TRUE; VOLTAGE=3.3V; MIN_LINE_WIDTH=0.6 mm; MIN_NECK_WIDTH=0.2 mm; NET_SPACING_TYPE=PWR; MAX_NECK_LENGTH=3 MM
  - =PP3V3_S5_SB 25 27 28
  - =PP3V3_S5_SB_USB 24
  - =PP3V3_S5_SB_PM 28
  - =PP3V3_S5_SB_VCCSUS3_3 26 27
  - =PP3V3_S5_SB_VCCSUS3_3_USB 26 27
  - =PP3V3_S5_SMBUS_SB_ME 52
  - =PP3V3_S5_FW 40 42 43
  - =PP3V3_S5_SMC 49 50
  - =PP3V3_S5_ROM 61
  - =PP3V3_S5_SB_GPIO 25
  - =PP3V3_S5_SB_CLINK1 25
  - =PP3V3_S5_SB_3V3_VCCSUSHDA 26 27
  - =PP3V3_S5_LPCPLUS 7 51
  - =PP3V3_S5_SMBUS_SMC_BSA 52
  - =PP3V3_S5_FAN 56 57
  - =PP3V3_S5_SMCUSBMUX 46
  - =PP3V3_S5_SMBUS_SMC_A_S5 52
- PP5V_S5 — MAKE_BASE=TRUE; VOLTAGE=5V; MIN_LINE_WIDTH=0.6 mm; MIN_NECK_WIDTH=0.2 mm; NET_SPACING_TYPE=PWR; MAX_NECK_LENGTH=3 MM
  - =PP5V_S5_SB 27
  - =PPVIN_S5_SMCVREF 50
  - =PP5V_S5_USB 46
- PP12V_S5 — MAKE_BASE=TRUE; VOLTAGE=12V; MIN_LINE_WIDTH=0.6 mm; MIN_NECK_WIDTH=0.2 mm; NET_SPACING_TYPE=PWR; MAX_NECK_LENGTH=3 MM
  - =PP12V_S5_FET
  - =PP12V_S5_FW 43



PART NUMBER	QTY	DESCRIPTION	REFERENCE DES	CRITICAL	BOM OPTION
113S0082	1	RES,MF,1/10W,910OHM,5,0603,SMD,LF	R605		20_INCH_LCD
113S0095	1	RES,MF,1/10W,3.3KOHM,5,0603,SMD,LF	R605		24_INCH_LCD

Power Conn / Alias

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 6 OF 118	

www.laptopschematics.com

FUNCTIONAL TESTPOINTS FOR MAC-1 & ICT

LAYOUT NOTE: PLACE NEAR J1000

100 14 10 7	FSB_A_L<6>	PP1000	OMIT P4MM
100 14 10 7	FSB_ADSTB_L<0>	PP1001	OMIT P4MM
100 14 10 7	FSB_A_L<27>	PP1002	OMIT P4MM
100 14 10 7	FSB_ADSTB_L<1>	PP1003	OMIT P4MM
100 14 10 7	FSB_D_L<0>	PP1004	OMIT P4MM
100 14 10 7	FSB_DSTB_L_N<0>	PP1005	OMIT P4MM
100 14 10 7	FSB_DSTB_L_P<0>	PP1006	OMIT P4MM
100 14 10 7	FSB_DINV_L<0>	PP1007	OMIT P4MM
100 14 10 7	FSB_D_L<16>	PP1008	OMIT P4MM
100 14 10 7	FSB_DSTB_L_N<1>	PP1009	OMIT P4MM
100 14 10 7	FSB_DSTB_L_P<1>	PP1010	OMIT P4MM
100 14 10 7	FSB_DINV_L<1>	PP1011	OMIT P4MM
100 14 10 7	FSB_D_L<41>	PP1012	OMIT P4MM
100 14 10 7	FSB_DSTB_L_N<2>	PP1013	OMIT P4MM
100 14 10 7	FSB_DSTB_L_P<2>	PP1014	OMIT P4MM
100 14 10 7	FSB_DINV_L<2>	PP1015	OMIT P4MM
100 14 10 7	FSB_D_L<59>	PP1016	OMIT P4MM
100 14 10 7	FSB_DSTB_L_N<3>	PP1017	OMIT P4MM
100 14 10 7	FSB_DSTB_L_P<3>	PP1018	OMIT P4MM
100 14 10 7	FSB_DINV_L<3>	PP1019	OMIT P4MM
100 14 10 7	FSB_LOCK_L	PP1020	OMIT P4MM
100 14 13 10	FSB_CPURST_L	PP1021	OMIT P4MM
100 51 23 10	CPU_INIT_L	PP1022	OMIT P4MM
100 23 10	CPU_A20M_L	PP1023	OMIT P4MM
100 23 10	CPU_IGNNE_L	PP1024	OMIT P4MM
100 23 10	CPU_STPCLK_L	PP1025	OMIT P4MM
100 23 10	CPU_INTR	PP1026	OMIT P4MM
100 23 10	CPU_NMI	PP1027	OMIT P4MM
100 23 10	CPU_SMI_L	PP1028	OMIT P4MM
100 14 10 7	FSB_REQ_L<0>	PP1029	OMIT P4MM
100 14 10 7	FSB_REQ_L<1>	PP1030	OMIT P4MM
100 14 10 7	FSB_REQ_L<2>	PP1031	OMIT P4MM
100 14 10 7	FSB_REQ_L<3>	PP1032	OMIT P4MM
100 14 10 7	FSB_REQ_L<4>	PP1033	OMIT P4MM
105 30 10	FSB_CLK_CPU_P	PP1034	OMIT P4MM
105 30 10	FSB_CLK_CPU_N	PP1035	OMIT P4MM

LAYOUT NOTE: PLACE NEAR U2100

105 30 23	SB_CLK100M_SATA_P	PP2100	OMIT P4MM
105 30 23	SB_CLK100M_SATA_N	PP2101	OMIT P4MM
103 44 23	IDE_PDIOR_L	PP2102	OMIT P4MM
103 44 23	IDE_PDIORDY	PP2103	OMIT P4MM
103 44 23	IDE_PDD<9>	PP2104	OMIT P4MM
104 34 24	PCIE_MINI_D2R_P	PP2105	OMIT P4MM
104 34 24	PCIE_MINI_D2R_N	PP2106	OMIT P4MM
104 37 24	PCIE_ENET_D2R_P	PP2107	OMIT P4MM
104 37 24	PCIE_ENET_D2R_N	PP2108	OMIT P4MM
104 42 40	PCIE_FW_D2R_P	PP2132	OMIT P4MM
104 42 40	PCIE_FW_D2R_N	PP2133	OMIT P4MM
101 24 16	DMI_N2S_P<0>	PP2109	OMIT P4MM
101 24 16	DMI_N2S_N<0>	PP2110	OMIT P4MM
105 30 24	SB_CLK100M_DMI_P	PP2111	OMIT P4MM
105 30 24 7	SB_CLK100M_DMI_N	PP2112	OMIT P4MM
49 28 25	PM_SYSRST_L	PP2113	OMIT P4MM
51 49 25 7	PM_CLKRUN_L	PP2114	OMIT P4MM
105 30 25	SB_CLK14P3M_TIMER	PP2115	OMIT P4MM
105 30 25	SB_CLK48M_USBCTLR	PP2116	OMIT P4MM
105 30 24	PCI_CLK33M_SB	PP2117	OMIT P4MM
28 23	SB_RTC_RST_L	PP2118	OMIT P4MM
103 45 23	SATA_A_D2R_P	PP2119	OMIT P4MM
103 45 23	SATA_A_D2R_N	PP2120	OMIT P4MM
51 49 23 7	LPC_AD<1>	PP2121	OMIT P4MM
103 47 24	USB_CAMERA_P	PP2122	OMIT P4MM
103 47 24	USB_CAMERA_N	PP2123	OMIT P4MM
103 47 24	USB_IR_P	PP2124	OMIT P4MM
103 47 24	USB_IR_N	PP2125	OMIT P4MM
103 47 24	USB_BT_P	PP2126	OMIT P4MM
103 47 24	USB_BT_N	PP2127	OMIT P4MM
103 61	SPI_SCLK	PP2128	OMIT P4MM
103 61 24	SPI_SO	PP2129	OMIT P4MM
104 25 16 7	CLINK_NB_CLK	PP2130	OMIT P4MM
104 25 16 7	CLINK_NB_DATA	PP2131	OMIT P4MM

LAYOUT NOTE: PLACE NEAR U1400

100 14 10 7	FSB_A_L<6>	PP1400	OMIT P4MM
100 14 10 7	FSB_ADSTB_L<0>	PP1401	OMIT P4MM
100 14 10 7	FSB_A_L<27>	PP1402	OMIT P4MM
100 14 10 7	FSB_ADSTB_L<1>	PP1403	OMIT P4MM
100 14 10 7	FSB_D_L<0>	PP1404	OMIT P4MM
100 14 10 7	FSB_DSTB_L_N<0>	PP1405	OMIT P4MM
100 14 10 7	FSB_DSTB_L_P<0>	PP1406	OMIT P4MM
100 14 10 7	FSB_DINV_L<0>	PP1407	OMIT P4MM
100 14 10 7	FSB_D_L<16>	PP1408	OMIT P4MM
100 14 10 7	FSB_DSTB_L_N<1>	PP1409	OMIT P4MM
100 14 10 7	FSB_DSTB_L_P<1>	PP1410	OMIT P4MM
100 14 10 7	FSB_DINV_L<1>	PP1411	OMIT P4MM
100 14 10 7	FSB_D_L<41>	PP1412	OMIT P4MM
100 14 10 7	FSB_DSTB_L_N<2>	PP1413	OMIT P4MM
100 14 10 7	FSB_DSTB_L_P<2>	PP1414	OMIT P4MM
100 14 10 7	FSB_DINV_L<2>	PP1415	OMIT P4MM
100 14 10 7	FSB_D_L<59>	PP1416	OMIT P4MM
100 14 10 7	FSB_DSTB_L_N<3>	PP1417	OMIT P4MM
100 14 10 7	FSB_DSTB_L_P<3>	PP1418	OMIT P4MM
100 14 10 7	FSB_DINV_L<3>	PP1419	OMIT P4MM
100 14 10 7	FSB_LOCK_L	PP1420	OMIT P4MM
100 14 10	FSB_HIT_L	PP1421	OMIT P4MM
100 14 10	FSB_HITM_L	PP1422	OMIT P4MM
100 14 10	FSB_BNR_L	PP1423	OMIT P4MM
100 14 10	FSB_BREQ0_L	PP1424	OMIT P4MM
100 14 10	FSB_DBSY_L	PP1425	OMIT P4MM
100 14 10	FSB_DPWR_L	PP1426	OMIT P4MM
100 14 10 7	FSB_REQ_L<0>	PP1427	OMIT P4MM
100 14 10 7	FSB_REQ_L<1>	PP1428	OMIT P4MM
100 14 10 7	FSB_REQ_L<2>	PP1429	OMIT P4MM
100 14 10 7	FSB_REQ_L<3>	PP1430	OMIT P4MM
100 14 10 7	FSB_REQ_L<4>	PP1431	OMIT P4MM
105 30 14	FSB_CLK_NB_P	PP1432	OMIT P4MM
105 30 14 7	FSB_CLK_NB_N	PP1433	OMIT P4MM
71 70 22 16 7	VR_PWRGOOD_DELAY	PP1434	OMIT P4MM
28 16	NB_RESET_L	PP1435	OMIT P4MM
105 30 16	NB_CLK100M_PCIE_P	PP1436	OMIT P4MM
105 30 16 7	NB_CLK100M_PCIE_N	PP1437	OMIT P4MM
101 24 16	DMI_S2N_N<0>	PP1438	OMIT P4MM
101 24 16	DMI_S2N_P<0>	PP1439	OMIT P4MM
22 16	=PP0V9_S3M_MEM_NBVREFA	PP1440	OMIT P4MM
22 16	=PP0V9_S3M_MEM_NBVREFB	PP1441	OMIT P4MM
102 31 17	MEM_A_DQ<7>	PP1442	OMIT P4MM
102 31 17	MEM_A_DQ<14>	PP1443	OMIT P4MM
102 31 17	MEM_A_DQ<16>	PP1444	OMIT P4MM
102 31 17	MEM_A_DQ<25>	PP1445	OMIT P4MM
102 31 17	MEM_A_DQ<39>	PP1446	OMIT P4MM
102 31 17	MEM_A_DQ<47>	PP1447	OMIT P4MM
102 31 17	MEM_A_DQ<54>	PP1448	OMIT P4MM
102 31 17	MEM_A_DQ<59>	PP1449	OMIT P4MM
102 31 17	MEM_A_DQS_P<0>	PP1450	OMIT P4MM
102 31 17	MEM_A_DQS_N<0>	PP1451	OMIT P4MM
102 31 17	MEM_A_DQS_P<1>	PP1452	OMIT P4MM
102 31 17	MEM_A_DQS_N<1>	PP1453	OMIT P4MM
102 31 17	MEM_A_DQS_P<2>	PP1454	OMIT P4MM
102 31 17	MEM_A_DQS_N<2>	PP1455	OMIT P4MM
102 31 17	MEM_A_DQS_P<3>	PP1456	OMIT P4MM
102 31 17	MEM_A_DQS_N<3>	PP1457	OMIT P4MM
102 31 17	MEM_A_DQS_P<4>	PP1458	OMIT P4MM
102 31 17	MEM_A_DQS_N<4>	PP1459	OMIT P4MM
102 31 17	MEM_A_DQS_P<5>	PP1460	OMIT P4MM
102 31 17	MEM_A_DQS_N<5>	PP1461	OMIT P4MM
102 31 17	MEM_A_DQS_P<6>	PP1462	OMIT P4MM
102 31 17	MEM_A_DQS_N<6>	PP1463	OMIT P4MM
102 31 17	MEM_A_DQS_P<7>	PP1464	OMIT P4MM
102 31 17	MEM_A_DQS_N<7>	PP1465	OMIT P4MM
102 32 17	MEM_B_DQ<6>	PP1466	OMIT P4MM
102 32 17	MEM_B_DQ<8>	PP1467	OMIT P4MM
102 32 17	MEM_B_DQ<23>	PP1468	OMIT P4MM
102 32 17	MEM_B_DQ<25>	PP1469	OMIT P4MM
102 32 17	MEM_B_DQ<38>	PP1470	OMIT P4MM
102 32 17	MEM_B_DQ<44>	PP1471	OMIT P4MM
102 32 17	MEM_B_DQ<48>	PP1472	OMIT P4MM
102 32 17	MEM_B_DQ<62>	PP1473	OMIT P4MM
102 32 17	MEM_B_DQS_P<0>	PP1474	OMIT P4MM
102 32 17	MEM_B_DQS_N<0>	PP1475	OMIT P4MM
102 32 17	MEM_B_DQS_P<1>	PP1476	OMIT P4MM
102 32 17	MEM_B_DQS_N<1>	PP1477	OMIT P4MM
102 32 17	MEM_B_DQS_P<2>	PP1478	OMIT P4MM
102 32 17	MEM_B_DQS_N<2>	PP1479	OMIT P4MM
102 32 17	MEM_B_DQS_P<3>	PP1480	OMIT P4MM
102 32 17	MEM_B_DQS_N<3>	PP1481	OMIT P4MM
102 32 17	MEM_B_DQS_P<4>	PP1482	OMIT P4MM
102 32 17	MEM_B_DQS_N<4>	PP1483	OMIT P4MM
102 32 17	MEM_B_DQS_P<5>	PP1484	OMIT P4MM
102 32 17	MEM_B_DQS_N<5>	PP1485	OMIT P4MM
102 32 17	MEM_B_DQS_P<6>	PP1486	OMIT P4MM
102 32 17	MEM_B_DQS_N<6>	PP1487	OMIT P4MM
102 32 17	MEM_B_DQS_P<7>	PP1488	OMIT P4MM
102 32 17	MEM_B_DQS_N<7>	PP1489	OMIT P4MM
101 84 15	PEG_D2R_P<7>	PP1490	OMIT P4MM
101 84 15	PEG_D2R_N<7>	PP1491	OMIT P4MM
104 25 16 7	CLINK_NB_CLK	PP1492	OMIT P4MM
104 25 16 7	CLINK_NB_DATA	PP1493	OMIT P4MM

LAYOUT NOTE: PLACE NEAR U3700

105 37 30	PCIE_CLK100M_ENET_P	PP3700	OMIT P4MM
105 37 30	PCIE_CLK100M_ENET_N	PP3701	OMIT P4MM
108 37	PCIE_ENET_R2D_P	PP3702	OMIT P4MM
108 37	PCIE_ENET_R2D_N	PP3703	OMIT P4MM
37 28	ENET_RESET_L	PP3704	OMIT P4MM

LAYOUT NOTE: PLACE NEAR U4000

105 40 30	PCIE_CLK100M_FW_P	PP4000	OMIT P4MM
105 40 30	PCIE_CLK100M_FW_N	PP4001	OMIT P4MM
108 40	PCIE_FW_R2D_P	PP4002	OMIT P4MM
108 40	PCIE_FW_R2D_N	PP4003	OMIT P4MM
40 28	FW_RESET_L	PP4004	OMIT P4MM

LAYOUT NOTE: PLACE NEAR U4900

105 49 30	PCI_CLK33M_SMC	PP4900	OMIT P4MM
49 28	SMC_LRESET_L	PP4901	OMIT P4MM
51 50 49 7	SMC_RESET_L	PP4902	OMIT P4MM
51 49 23 7	LPC_AD<1>	PP4903	OMIT P4MM

LPC CONNECTOR

51 6	IN	=PP3V3_S5_LPCPLUS	FUNC_TEST=TRUE
51 6	IN	=PP5V_S0_LPCPLUS	FUNC_TEST=TRUE
51	IN	FWH_INIT_L	FUNC_TEST=TRUE
105 51 30	IN	PCI_CLK33M_LPCPLUS	FUNC_TEST=TRUE
51 49 23	IN	LPC_AD<0>	FUNC_TEST=TRUE
51 49 23 7	IN	LPC_AD<1>	FUNC_TEST=TRUE
51 49 23	IN	LPC_AD<2>	FUNC_TEST=TRUE
51 49 23	IN	LPC_AD<3>	FUNC_TEST=TRUE
51 49 23	IN	LPC_FRAME_L	FUNC_TEST=TRUE
51 49 25 7	IN	PM_CLKRUN_L	FUNC_TEST=TRUE
51 24	IN	BOOT_LPC_SPI_L	FUNC_TEST=TRUE
51 50 49	IN	SMC_TMS	FUNC_TEST=TRUE
51 28	IN	DEBUG_RESET_L	FUNC_TEST=TRUE
51 49	IN	SMC_TRST_L	FUNC_TEST=TRUE
51 50 49	IN	SMC_TDO	FUNC_TEST=TRUE
51 49	IN	SMC_MD1	FUNC_TEST=TRUE
51 50 49 46	IN	SMC_TX_L	FUNC_TEST=TRUE
51 49 25	IN	INT_SERIRQ	FUNC_TEST=TRUE
51 50 49 25 7	IN	PM_SUS_STAT_L	FUNC_TEST=TRUE
51 50 49	IN	SMC_TDI	FUNC_TEST=TRUE
51 50 49	IN	SMC_TCK	FUNC_TEST=TRUE
51 50 49 7	IN	SMC_RESET_L	FUNC_TEST=TRUE
51 49	IN	SMC_NMI	FUNC_TEST=TRUE
51 50 49 46	IN	SMC_RX_L	FUNC_TEST=TRUE
51 25	IN	LINDACARD_GPIO	FUNC_TEST=TRUE
	IN	16 TP'S	FUNC_TEST=TRUE

PWROK SEQUENCING

84 70 50 49 7	IN	ALL_SYS_PWRGD	FUNC_TEST=TRUE
70 28 25 7	IN	PM_SB_PWROK	FUNC_TEST=TRUE

STARTUP (BOOT/WAKE) TIMING

71 49	IN	IMVP_VR_ON	FUNC_TEST=TRUE
28 25	IN	VR_PWRGD_CLKEN	FUNC_TEST=TRUE
71 70 22 16 7	IN	VR_PWRGOOD_DELAY	FUNC_TEST=TRUE
70 28 25 7	IN	PM_SB_PWROK	FUNC_TEST=TRUE

SHUTDOWN/SLEEP TIMING

51 50 49 25 7	IN	PM_SUS_STAT_L	FUNC_TEST=TRUE
78 75 70 49 25 6	IN	PM_SLP_S3_L	FUNC_TEST=TRUE
78 75 49 46 25 7	IN	PM_S4_STATE_L	FUNC_TEST=TRUE
84 70 50 49 7	IN	ALL_SYS_PWRGD	FUNC_TEST=TRUE
100 23 13 10	IN	CPU_PWRGD	FUNC_TEST=TRUE

"S0" RAILS

75 70 6	IN	PP0V9_S0	FUNC_TEST=TRUE
72 71 6	IN	PPVCORE_CPU	FUNC_TEST=TRUE
78 70 6	IN	PP1V8_S0	FUNC_TEST=TRUE
77 6	IN	PP2V5_S0	FUNC_TEST=TRUE
74 73 55 6	IN	PPMCH_CORE_S0	FUNC_TEST=TRUE
73 34 6	IN	PP1V05_S0	FUNC_TEST=TRUE
74 6	IN	PP1V25_S0	FUNC_TEST=TRUE
78 77 70 53 13 7 6	IN	PP3V3_S0	FUNC_TEST=TRUE
94 78 74 73 72 71 70 6	IN	PP5V_S0	FUNC_TEST=TRUE
76 74 73 53 6	IN	PP12V_S0	FUNC_TEST=TRUE
73 6	IN	PP1V5_S0	FUNC_TEST=TRUE

3 TP'S

"S3" RAILS

3 TP'S

78 75 6	IN	PP1V8_S3	FUNC_TEST=TRUE
78 76 75 70 7 6	IN	PP3V3_S3	FUNC_TEST=TRUE
78 76 75 70 6	IN	PP5V_S3	FUNC_TEST=TRUE
78 75 49 46 25 7	IN	PM_S4_STATE_L	FUNC_TEST=TRUE

"S5" RAILS

3 TP'S

77 75 70 6	IN	PP3V3_S5	FUNC_TEST=TRUE
78 77 76 70 6	IN	PP5V_S5	FUNC_TEST=TRUE
76 75 70 53 6	IN	PP12V_S5	FUNC_TEST=TRUE

5 TP'S

FOR ICT

105 30 16 7	IN	NB_CLK100M_PCIE_N	FUNC_TEST=TRUE
105 30 14 7	IN	FSB_CLK_NB_N	FUNC_TEST=TRUE
16	IN	TP_NB_CFG<13>	FUNC_TEST=TRUE
16	IN	TP_NB_CFG<12>	FUNC_TEST=TRUE
16	IN	TP_NB_CFG<18>	FUNC_TEST=TRUE
16	IN	NB_CFG<19>	FUNC_TEST=TRUE
104 24	IN	PCI_REQ1_L	FUNC_TEST=TRUE
104 24	IN	PCI_REQ2_L	FUNC_TEST=TRUE
105 30 24 7	IN	SB_CLK100M_DMI_N	FUNC_TEST=TRUE
30	IN	TP_CK505_REF1	FUNC_TEST=TRUE
30	IN	TP_CK505_PCI1_CLK	FUNC_TEST=TRUE
40	IN	TP_FW_TCK	FUNC_TEST=TRUE
40	IN	TP_FW_TMS	FUNC_TEST=TRUE
40	IN	TP_FW_TDI	FUNC_TEST=TRUE
40	IN	TP_FW_TDO	FUNC_TEST=TRUE
40	IN	FW_TRST_L	FUNC_TEST=TRUE
40	IN	TP_FW_SM	FUNC_TEST=TRUE
40	IN	TP_FW_SE	FUNC_TEST=TRUE
40	IN	TP_FW_NAND_TREE	FUNC_TEST=TRUE
40	IN	TP_FW_CE	FUNC_TEST=TRUE
103 61	IN	SPI_CE_L<0>	FUNC_TEST=TRUE
103 61	IN	SPI_A_SO_R	FUNC_TEST=TRUE

MISC GROUND VIAS - NEEDED?

ZH500 HOLE-VIA, ZH510 HOLE-VIA, ZH520 HOLE-VIA
ZH501 HOLE-VIA, ZH511 HOLE-VIA, ZH521 HOLE-VIA
ZH502 HOLE-VIA, ZH512 HOLE-VIA, ZH522 HOLE-VIA
ZH503 HOLE-VIA, ZH513 HOLE-VIA, ZH523 HOLE-VIA
ZH504 HOLE-VIA, ZH514 HOLE-VIA, ZH524 HOLE-VIA
ZH505 HOLE-VIA, ZH515 HOLE-VIA, ZH525 HOLE-VIA
ZH506 HOLE-VIA, ZH516 HOLE-VIA, ZH526 HOLE-VIA
ZH507 HOLE-VIA, ZH517 HOLE-VIA, ZH527 HOLE-VIA
ZH508 HOLE-VIA, ZH518 HOLE-VIA, ZH528 HOLE-VIA
ZH509 HOLE-VIA, ZH519 HOLE-VIA, ZH529 HOLE-VIA

PP3V3_S3 — C701 0.01UF 10% 50V X7R 402 — C702 0.01UF 10% 50V X7R 402 — C703 0.01UF 10% 50V X7R 402 — C704 0.01UF 10% 50V X7R 402 — PP3V3_S0

CRITICAL SC0700 EMI-SPRING CLIP-SM1
CRITICAL SC0701 EMI-SPRING CLIP-SM1
CRITICAL SC0702 EMI-SPRING CLIP-SM-K2
BTW DIMMS

998-0845 FOR NB HEATSINK

OMIT ZH0722 3P9R3P15, ZH0723 3P9R3P15, ZH0724 3P9R3P15, ZH0725 3P9R3P15

CRITICAL 452-0508 CRITICAL
SDF0726 HSK-NUT-6.5MM TH, SDF0727 HSK-NUT-6.5MM TH

998-0850 FOR CPU HEATSINK

OMIT ZH0700 4P75R4, ZH0701 4P75R4, ZH0702 4P75R4, ZH0703 4P75R4

CRITICAL 860-0895
SDF0717 STDOFF-7P0OD15P0H-TH, SDF0721 STDOFF-7P0OD15P0H-TH, SDF0750 STDOFF-7P0OD15P0H-TH, SDF0751 STDOFF-7P0OD15P0H-TH

998-0847

OMIT ZH0711 4P25R3P5, ZH0712 4P25R3P5, ZH0714 4P25R3P5, ZH0715 4P25R3P5, ZH0718 4P25R3P5, ZH0720 4P25R3P5, ZH0750 4P25R3P5

www.laptop-schematics.com

Functional / ICT Test

SYNC_MASTER=K3_MASTER SYNC_DATE=N/A

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A

SCALE NONE SHT 7 OF 118

GND RAILS

98 GND_AUDIO_SPKRAMP
VOLTAGE=0V
MIN_LINE_WIDTH=0.6MM
MIN_NECK_WIDTH=0.25MM
NET_SPACING_TYPE=GND

www.laptop-schematics.com

CHASSIS GND

GND
MIN_LINE_WIDTH=0.6MM
MIN_NECK_WIDTH=0.2MM
VOLTAGE=0V
NET_SPACING_TYPE=GND
MAKE_BASE=TRUE
MAX_NECK_LENGTH=4.1 MM

46 GND_CHASSIS_USB

43 GND_CHASSIS_FIREWIRE
39 GND_CHASSIS_ENET
94 =GND_CHASSIS_DVI

NOTE:
PER EMC REQUIREMENTS, ALL CHASSIS GROUNDS ARE TIED DIRECTLY TO GND

www.laptop-schematics.com

www.laptop-schematics.com

GROUNDING ALIASES

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A

SCALE NONE SHT 9 OF 118

www.laptop-schematics.com

CRITICAL

J1000
MEROM
BGA-SKT-P
1 OF 4

ADDR GROUP0
FSB_A_L<3> J4 A3*
FSB_A_L<4> L5 A4*
FSB_A_L<5> L4 A5*
FSB_A_L<6> K5 A6*
FSB_A_L<7> M3 A7*
FSB_A_L<8> N2 A8*
FSB_A_L<9> J1 A9*
FSB_A_L<10> N3 A10*
FSB_A_L<11> P5 A11*
FSB_A_L<12> P2 A12*
FSB_A_L<13> L2 A13*
FSB_A_L<14> P4 A14*
FSB_A_L<15> P1 A15*
FSB_A_L<16> R1 A16*
FSB_ADSTB_L<0> M1 ADSTB0*

ADDR GROUP1
FSB_A_L<17> Y2 A17*
FSB_A_L<18> U5 A18*
FSB_A_L<19> R3 A19*
FSB_A_L<20> W6 A20*
FSB_A_L<21> U4 A21*
FSB_A_L<22> Y5 A22*
FSB_A_L<23> U1 A23*
FSB_A_L<24> R4 A24*
FSB_A_L<25> T5 A25*
FSB_A_L<26> T3 A26*
FSB_A_L<27> W2 A27*
FSB_A_L<28> W5 A28*
FSB_A_L<29> Y3 A29*
FSB_A_L<30> U2 A30*
FSB_A_L<31> V4 A31*
FSB_A_L<32> W3 A32*
FSB_A_L<33> AA4 A33*
FSB_A_L<34> AB2 A34*
FSB_A_L<35> AA3 A35*
FSB_ADSTB_L<1> V1 ADSTB1*

ICH
CPU_A20M_L A6 A20M*
CPU_FERR_L A5 FERR*
CPU_IGNNE_L C4 IGNNE*
CPU_STPCLK_L D5 STPCLK*
CPU_INTR C6 LINT0
CPU_NMI B4 LINT1
CPU_SMI_L A3 SMI*

RESERVED
TP_CPU_RSVD0 M4 RSVD0
TP_CPU_RSVD1 N5 RSVD1
TP_CPU_RSVD2 T2 RSVD2
TP_CPU_RSVD3 V3 RSVD3
TP_CPU_RSVD4 B2 RSVD4
TP_CPU_RSVD5 C3 RSVD5
TP_CPU_RSVD6 D2 RSVD6
TP_CPU_RSVD7 D22 RSVD7
TP_CPU_RSVD8 D3 RSVD8
TP_CPU_RSVD9 F6 RSVD9

CONTROL
ADS* H1 FSB_ADS_L
BNR* E2 FSB_BNR_L
BPRI* G5 FSB_BPRI_L
DEFER* H5 FSB_DEFER_L
DRDY* F21 FSB_DRDY_L
DBSY* E1 FSB_DBSY_L
BR0* F1 FSB_BREQ0_L
IERR* D20 CPU_IERR_L
INIT* B3 CPU_INIT_L
LOCK* H4 FSB_LOCK_L
RESET* C1 FSB_CPURST_L
RS0* F3 FSB_RS_L<0>
RS1* F4 FSB_RS_L<1>
RS2* G3 FSB_RS_L<2>
TRDY* G2 FSB_TRDY_L
HIT* G6 FSB_HIT_L
HITM* E4 FSB_HITM_L

XDP/ITP SIGNALS
BPM0* AD4 XDP_BPM_L<0>
BPM1* AD3 XDP_BPM_L<1>
BPM2* AD1 XDP_BPM_L<2>
BPM3* AC4 XDP_BPM_L<3>
PRDY* AC2 XDP_BPM_L<4>
PREQ* AC1 XDP_BPM_L<5>
TCK AC5 XDP_TCK
TDI AA6 XDP_TDI
TDO AB3 XDP_TDO
TMS AB5 XDP_TMS
TRST* AB6 XDP_TRST_L
DBR* C20 XDP_DBRESET_L

THERMAL
PROCHOT* D21 CPU_PROCHOT_L
THERMDA A24 CPU_THERMD_P
THERMDC B25 CPU_THERMD_N
THERMTRIP* C7 PM_THRMTRIP_L

H CLK
BCLK0 A22 FSB_CLK_CPU_P
BCLK1 A21 FSB_CLK_CPU_N

=PP1V05_S0_CPU
R1002 54.9 1% 1/16W MF-LF 402
PLACE TESTPOINT ON FSB_IERR_L WITH A GND 0.1" AWAY

R1003 54.9 1% 1/16W MF-LF 402
R1004 68 5% 1/16W MF-LF 402
PM_THRMTRIP# SHOULD CONNECT TO ICH AND GMCH WITHOUT T (NO STUB)

R1005 1K 1% 1/16W MF-LF 402
R1006 2.0K 1% 1/16W MF-LF 402
0.5" MAX LENGTH FOR CPU_GTLREF

NOSTUFF C1000 0.1uF 10% 16V X5R 402
PLACE C1000 CLOSE TO CPU_TEST4 PIN. MAKE SURE CPU_TEST4 IS REFERENCED TO GND

R1020 54.9 1% 1/16W MF-LF 402
R1021 54.9 1% 1/16W MF-LF 402
R1022 54.9 1% 1/16W MF-LF 402
R1023 649 1% 1/16W MF-LF 402
R1024 54.9 1% 1/16W MF-LF 402
PLACEMENT_NOTE=Place R1024 near ITP connector (if present)

CRITICAL

J1000
MEROM
BGA-SKT-P
2 OF 4

DATA GRP 0
FSB_D_L<0> E22 D0*
FSB_D_L<1> F24 D1*
FSB_D_L<2> E26 D2*
FSB_D_L<3> G22 D3*
FSB_D_L<4> F23 D4*
FSB_D_L<5> G25 D5*
FSB_D_L<6> E25 D6*
FSB_D_L<7> E23 D7*
FSB_D_L<8> K24 D8*
FSB_D_L<9> G24 D9*
FSB_D_L<10> J24 D10*
FSB_D_L<11> J23 D11*
FSB_D_L<12> H22 D12*
FSB_D_L<13> F26 D13*
FSB_D_L<14> K22 D14*
FSB_D_L<15> H23 D15*
FSB_DSTB_L_N<0> J26 DSTBN0*
FSB_DSTB_L_P<0> H26 DSTBP0*
FSB_DINV_L<0> H25 DINV0*

DATA GRP 1
FSB_D_L<16> N22 D16*
FSB_D_L<17> K25 D17*
FSB_D_L<18> P26 D18*
FSB_D_L<19> R23 D19*
FSB_D_L<20> L23 D20*
FSB_D_L<21> M24 D21*
FSB_D_L<22> L22 D22*
FSB_D_L<23> M23 D23*
FSB_D_L<24> P25 D24*
FSB_D_L<25> P23 D25*
FSB_D_L<26> P22 D26*
FSB_D_L<27> T24 D27*
FSB_D_L<28> R24 D28*
FSB_D_L<29> L25 D29*
FSB_D_L<30> T25 D30*
FSB_D_L<31> N25 D31*
FSB_DSTB_L_N<1> L26 DSTBN1*
FSB_DSTB_L_P<1> M26 DATBP1*
FSB_DINV_L<1> N24 DINV1*

DATA GRP 2
FSB_D_L<32> Y22 D32*
FSB_D_L<33> AB24 D33*
FSB_D_L<34> V24 D34*
FSB_D_L<35> V26 D35*
FSB_D_L<36> V23 D36*
FSB_D_L<37> T22 D37*
FSB_D_L<38> U25 D38*
FSB_D_L<39> U23 D39*
FSB_D_L<40> Y25 D40*
FSB_D_L<41> W22 D41*
FSB_D_L<42> Y23 D42*
FSB_D_L<43> W24 D43*
FSB_D_L<44> W25 D44*
FSB_D_L<45> AA23 D45*
FSB_D_L<46> AA24 D46*
FSB_D_L<47> AB25 D47*
FSB_DSTBN2* Y26 FSB_DSTB_L_N<2>
FSB_DSTBP2* AA26 FSB_DSTB_L_P<2>
FSB_DINV_L<2> U22 DINV2*

DATA GRP 3
FSB_D_L<48> AE24 D48*
FSB_D_L<49> AD24 D49*
FSB_D_L<50> AA21 D50*
FSB_D_L<51> AB22 D51*
FSB_D_L<52> AB21 D52*
FSB_D_L<53> AC26 D53*
FSB_D_L<54> AD20 D54*
FSB_D_L<55> AE22 D55*
FSB_D_L<56> AF23 D56*
FSB_D_L<57> AC25 D57*
FSB_D_L<58> AE21 D58*
FSB_D_L<59> AD21 D59*
FSB_D_L<60> AC22 D60*
FSB_D_L<61> AD23 D61*
FSB_D_L<62> AF22 D62*
FSB_D_L<63> AC23 D63*
DSTBN3* AE25 FSB_DSTB_L_N<3>
DSTBP3* AF24 FSB_DSTB_L_P<3>
DINV3* AC20 FSB_DINV_L<3>

MISC
GTLREF AD26
TEST1 C23
TEST2 D25
TEST3 C24
TEST4 AF26
TEST5 AF1
TEST6 A26
BSEL0 B22
BSEL1 B23
BSEL2 C21
COMP0 R26 CPU_COMP<0>
COMP1 U26 CPU_COMP<1>
COMP2 AA1 CPU_COMP<2>
COMP3 Y1 CPU_COMP<3>
DPRSTP* E5 CPU_DPRSTP_L
DPSLP* B5 CPU_DPSLP_L
DPWR* D24 FSB_DPWR_L
PWRGOOD D6 CPU_PWRGD
SLP* D7 FSB_CPUSLP_L
PSI* AE6 CPU_PSI_L

R1012 1K 5% 1/16W MF-LF 402 NOSTUFF
R1030 0 5% 1/16W MF-LF 402 NOSTUFF
R1007 1K 5% 1/16W MF-LF 402 NOSTUFF

R1016 27.4 1% 1/16W MF-LF 402
R1017 54.9 1% 1/16W MF-LF 402
R1018 27.4 1% 1/16W MF-LF 402
R1019 54.9 1% 1/16W MF-LF 402

LAYOUT NOTE:
COMP0,2 CONNECT WITH ZO=27.4OHM, MAKE TRACE LENGTH SHORTER THAN 0.5".
COMP1,3 CONNECT WITH ZO=55OHM, MAKE TRACE LENGTH SHORTER THAN 0.5".

NOTE: SYNCED FROM T9_MLB, CHANGED SOCKET TO 511S0038 (P)

CPU FSB

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A

SCALE	SHT	OF
NONE	10	118



www.laptop-schematics.com

Current numbers from Merom for Santa Rosa EMTS, doc #20905.

NOTE: SYNCED FROM T9_MLB, CHANGED SOCKET TO 511S0038 (P)

CPU Power & Ground

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 11 OF 118	

CPU VCORE HF AND BULK DECOUPLING

6X 220UF. 32X 22UF 0805

53 11 6 =PPVCORE_S0_CPU

NOTE: CHANGED TO X5R CAPS TO MATCH PREVIOUS IMACS AND FOR C4

LAYOUT NOTE:
PLACE INSIDE SOCKET CAVITY (ON BOTTOMSIDE)

NOSTUFF C1200 22UF 20% 6.3V CERM-X5R 805
C1201 22UF 20% 6.3V CERM-X5R 805
C1202 22UF 20% 6.3V CERM-X5R 805
C1203 22UF 20% 6.3V CERM-X5R 805
C1204 22UF 20% 6.3V CERM-X5R 805
C1205 22UF 20% 6.3V CERM-X5R 805
C1206 22UF 20% 6.3V CERM-X5R 805
C1207 22UF 20% 6.3V CERM-X5R 805
C1208 22UF 20% 6.3V CERM-X5R 805
C1209 22UF 20% 6.3V CERM-X5R 805

LAYOUT NOTE:
PLACE INSIDE SOCKET CAVITY (ON BOTTOMSIDE)

C1210 22UF 20% 6.3V CERM-X5R 805
C1211 22UF 20% 6.3V CERM-X5R 805
C1212 22UF 20% 6.3V CERM-X5R 805
C1213 22UF 20% 6.3V CERM-X5R 805
C1214 22UF 20% 6.3V CERM-X5R 805
C1215 22UF 20% 6.3V CERM-X5R 805
C1216 22UF 20% 6.3V CERM-X5R 805
C1217 22UF 20% 6.3V CERM-X5R 805
C1218 22UF 20% 6.3V CERM-X5R 805
C1219 22UF 20% 6.3V CERM-X5R 805

LAYOUT NOTE:
PLACE NEAR SOCKET NORTH SIDE (ON TOPSIDE)

C1220 22UF 20% 6.3V CERM-X5R 805
C1221 22UF 20% 6.3V CERM-X5R 805
NOSTUFF C1222 22UF 20% 6.3V CERM-X5R 805
NOSTUFF C1223 22UF 20% 6.3V CERM-X5R 805
NOSTUFF C1224 22UF 20% 6.3V CERM-X5R 805
NOSTUFF C1225 22UF 20% 6.3V CERM-X5R 805

LAYOUT NOTE:
PLACE NEAR SOCKET SOUTH SIDE (ON TOPSIDE)

C1226 22UF 20% 6.3V CERM-X5R 805
C1227 22UF 20% 6.3V CERM-X5R 805
NOSTUFF C1228 22UF 20% 6.3V CERM-X5R 805
NOSTUFF C1229 22UF 20% 6.3V CERM-X5R 805
C1230 22UF 20% 6.3V CERM-X5R 805
NOSTUFF C1231 22UF 20% 6.3V CERM-X5R 805

LAYOUT NOTE:
PLACE ON BOTTOMSIDE

CRITICAL NOSTUFF C1250 220UF 20% 2V POLY CASE-D2-SM1
CRITICAL C1251 220UF 20% 2V POLY CASE-D2-SM1
CRITICAL C1254 220UF 20% 2V POLY CASE-D2-SM1
CRITICAL C1255 220UF 20% 2V POLY CASE-D2-SM1
CRITICAL C1252 220UF 20% 2V POLY CASE-D2-SM1
CRITICAL C1253 220UF 20% 2V POLY CASE-D2-SM1

LAYOUT NOTE:
PLACE ON BOTTOMSIDE

CPU VCORE VID CONNECTIONS

Resistors to allow for override of CPU VID
Will probably be removed before production

R1290 0 5% 1/16W MF-LF 402
100 11 CPU_VID<0> — IMVP6_VID<0> 71 100
R1291 0 5% 1/16W MF-LF 402
100 11 CPU_VID<1> — IMVP6_VID<1> 71 100
R1292 0 5% 1/16W MF-LF 402
100 11 CPU_VID<2> — IMVP6_VID<2> 71 100
R1293 0 5% 1/16W MF-LF 402
100 11 CPU_VID<3> — IMVP6_VID<3> 71 100
R1294 0 5% 1/16W MF-LF 402
100 11 CPU_VID<4> — IMVP6_VID<4> 71 100
R1295 0 5% 1/16W MF-LF 402
100 11 CPU_VID<5> — IMVP6_VID<5> 71 100
R1296 0 5% 1/16W MF-LF 402
100 11 CPU_VID<6> — IMVP6_VID<6> 71 100

VCCA (CPU AVdd) DECOUPLING

11 6 =PP1V5_S0_CPU — 1x 10uF, 1x 0.01uF

C1280 10uF 20% 6.3V X5R 603
C1281 0.01UF 10% 16V CERM 402

LAYOUT NOTE:
PLACE C1281 NEAR PIN B26 OF U1000

VCCP (CPU I/O) DECOUPLING

50 13 11 10 6 =PP1V05_S0_CPU — 1X 330UF, 6X 0.1UF 0402

CRITICAL C1235 330UF 20% 6.3V ELEC 6.3X8-SM
C1236 0.1UF 20% 10V CERM 402
C1237 0.1UF 20% 10V CERM 402
C1238 0.1UF 20% 10V CERM 402
C1239 0.1UF 20% 10V CERM 402
C1240 0.1UF 20% 10V CERM 402
C1241 0.1UF 20% 10V CERM 402

LAYOUT NOTE:
PLACE C1235 CLOSE TO CPU

CPU Decoupling & VID

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 12 OF 118	

www.laptop-schematics.com

Mini-XDP Connector

NOTE: This is not the standard XDP pinout.

Use with 920-0451 adapter board to support CPU, NB & SB debugging.



Direction of XDP module

Please avoid any obstructions
on even-numbered side of J1300

www.laptop-schematics.com

eXtended Debug Port (XDP)

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 13 OF 118	



www.laptop-schematics.com

NB CPU Interface

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 14 OF 118	

LVDS Disable

Can leave all signals NC if LVDS is not implemented.
Tie VCC_TX_LVDS and VCCA_LVDS to GND.

If SDVO is used, VCCD_LVDS must remain powered with proper decoupling. Otherwise, tie VCCD_LVDS to GND also.

TV-Out Signal Usage:

Composite: DACA only
S-Video: DACB & DACC only
Component: DACA, DACB & DACC

Unused DAC outputs must remain powered, but can omit filtering components. Unused DAC outputs should connect to GND through 75-ohm resistors.

TV-Out Disable / CRT Enable

Tie TVx_DAC and TVx_RTN to GND. Must power all TVDAC rails. VCCA_TVx_DAC and VCCA_DAC_BG can share filtering with VCCA_CRT_DAC.

CRT Disable / TV-Out Enable

Tie R/R#/G/G#/B/B#, HSYNC and VSYNC to GND. All CRT/TVDAC rails must be powered. All rails must be filtered except for VCCA_CRT.

CRT & TV-Out Disable

Tie TVx_DAC, TVx_RTN, R/R#/G/G#/B/B#, HSYNC, VSYNC and CRT_TVO_IREF to GND.
Can tie the following rails to GND:
VCCA_CRT_DAC, VCCA_DAC_BG, VCCA_TVx_DAC, VCCD_CRT, VCCD_QDAC and VCC_SYNC.

NOTE: Must keep VDDC_TVDAC powered and filtered at all times!

Internal Graphics Disable

Follow instructions for LVDS and CRT & TV-Out Disable above.
Can also tie CRT_DDC_*, L_CTRL_*, L_DDC_*, SDVO_CTRL_* and TV_DCONSELx to GND.
Tie DPLL_REF_CLK and DPLL_REF_SSCLK to GND.
Tie DPLL_REF_CLK* and DPLL_REF_SSCLK* to VCC (VCore).
Tie VCCA_DPLLA and VCCA_DPLLB to VCC (VCore).
Tie VCC_AXG and VCC_AXG_NCTF to GND.
Leave GFX_VID<3..0> and GFX_VR_EN as NC.



www.laptop-schematics.com

NB PEG / Video Interfaces

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 15 OF 118	

NB_CFG<3>	RESERVED
NB_CFG<4>	RESERVED
NB_CFG<5> DMI x2 Select	High = DMIx4 Low = DMIx2
NB_CFG<6>	RESERVED
NB_CFG<7>	RESERVED
NB_CFG<8>	RESERVED
NB_CFG<9> PCIe Graphics Lane Reversal	High = Normal Low = Reversed
NB_CFG<10>	RESERVED
NB_CFG<11>	RESERVED
NB_CFG<12>	See Below
NB_CFG<13>	See Below
NB_CFG<14>	RESERVED
NB_CFG<15>	RESERVED
NB_CFG<16> FSB Dynamic ODT	High = Enabled Low = Disabled
NB_CFG<17>	RESERVED
NB_CFG<18>	RESERVED
NB_CFG<19> DMI Lane Reversal	High = Reversed Low = Normal
NB_CFG<20> Concurrent SDVO/PCIe x1	High = Both active Low = Only SDVO or PCIe x16

NB_CFG<13:12>

00 = RESERVED
01 = XOR Mode Enabled
10 = All-Z Mode Enabled
11 = Normal Operation

NB_CFG<5> → R1655 3.9K → NBCFG_DMI_X2
NB_CFG<9> → R1659 3.9K → NBCFG_PEG_REVERSE
NB_CFG<16> → R1666 3.9K → NBCFG_DYN_ODT_DISABLE
=PP3V3_S0_NB_VCCHV → R1669 3.9K → NBCFG_DMI_REVERSE → NB_CFG<19>
=PP3V3_S0_NB_VCCHV → R1670 3.9K → NBCFG_SDVO_AND_PCIE → NB_CFG<20>

NB CFG<8:0> used for debug access

NB CFG<13:12> require ICT access

=PP3V3_S0_NB_VCCHV
R1630 10K 5% 1/16W MF-LF 402
R1631 10K 5% 1/16W MF-LF 402
PM_EXTTS_L<0>
PM_EXTTS_L<1>

OMIT

U1400
CRESTLINE
FCBGA
(2 OF 10)

RSVD

TP_NB_RSVD<1>	P36	RSVD1
TP_NB_RSVD<2>	P37	RSVD2
TP_NB_RSVD<3>	R35	RSVD3
TP_NB_RSVD<4>	N35	RSVD4
TP_NB_RSVD<5>	AR12	RSVD5
TP_NB_RSVD<6>	AR13	RSVD6
TP_NB_RSVD<7>	AM12	RSVD7
TP_NB_RSVD<8>	AN13	RSVD8
TP_NB_RSVD<9>	J12	RSVD9
TP_NB_RSVD<10>	AR37	RSVD10
TP_NB_RSVD<11>	AM36	RSVD11
TP_NB_RSVD<12>	AL36	RSVD12
TP_NB_RSVD<13>	AM37	RSVD13
TP_NB_RSVD<14>	D20	RSVD14
TP_NB_RSVD<20>	H10	RSVD20
TP_NB_RSVD<21>	B51	RSVD21
TP_NB_RSVD<22>	BJ20	RSVD22
TP_NB_RSVD<23>	BK22	RSVD23
TP_NB_RSVD<24>	BF19	RSVD24
TP_NB_RSVD<25>	BH20	RSVD25
TP_NB_RSVD<26>	BK18	RSVD26
TP_NB_RSVD<27>	BJ18	RSVD27
TP_MEM_CLKP2	BF23	SM_CK2
TP_MEM_CLKN2	BG23	SM_CK2*
TP_MEM_CLKP5	BC23	SM_CK5
TP_MEM_CLKN5	BD24	SM_CK5*
MEM_A_A<14>	BJ29	SA_MA14
MEM_B_A<14>	BE24	SB_MA14
TP_NB_RSVD<34>	BH39	RSVD34
TP_NB_RSVD<35>	AW20	RSVD35
TP_NB_RSVD<36>	BK20	RSVD36
TP_LVDS_A_DATAN3	C48	RSVD37
TP_LVDS_A_DATAP3	D47	RSVD38
TP_LVDS_B_DATAN3	B44	RSVD39
TP_LVDS_B_DATAP3	C44	RSVD40
TP_NB_RSVD<41>	A35	RSVD41
TP_NB_RSVD<42>	B37	RSVD42
TP_NB_RSVD<43>	B36	RSVD43
TP_NB_RSVD<44>	B34	RSVD44
TP_NB_RSVD<45>	C34	RSVD45

CFG

NB_BSEL<0>	P27	CFG0
NB_BSEL<1>	N27	CFG1
NB_BSEL<2>	N24	CFG2
NB_CFG<3>	C21	CFG3 IPU
NB_CFG<4>	C23	CFG4 IPU
NB_CFG<5>	F23	CFG5 IPU
NB_CFG<6>	N23	CFG6 IPU
NB_CFG<7>	G23	CFG7 IPU
NB_CFG<8>	J20	CFG8 IPU
NB_CFG<9>	C20	CFG9 IPU
TP_NB_CFG<10>	R24	CFG10 IPU
TP_NB_CFG<11>	L23	CFG11 IPU
TP_NB_CFG<12>	J23	CFG12 IPU
TP_NB_CFG<13>	E23	CFG13 IPU
TP_NB_CFG<14>	E20	CFG14 IPU
TP_NB_CFG<15>	K23	CFG15 IPU
NB_CFG<16>	M20	CFG16 IPU
TP_NB_CFG<17>	M24	CFG17 IPU
TP_NB_CFG<18>	L32	CFG18 IPD
NB_CFG<19>	N33	CFG19 IPD
NB_CFG<20>	L35	CFG20 IPD

PM

PM_BMBUSY_L	G41	PM_BM_BUSY*
CPU_DPRSTP_L	L39	PM_DPRSTP*
	L36	PM_EXT_TS0*
	J36	PM_EXT_TS1*
VR_PWRGOOD_DELAY	AW49	PWROK
NB_RESET_L	AV28	RSTIN*
PM_THRMTRIP_L	N20	THERMTRIP*
PM_DPRSLPVR	G36	DPRSLPVR

NC

TP_NB_NC<1>	BJ51	NC1
TP_NB_NC<2>	BK51	NC2
TP_NB_NC<3>	BK50	NC3
TP_NB_NC<4>	BL50	NC4
TP_NB_NC<5>	BL49	NC5
TP_NB_NC<6>	BL3	NC6
TP_NB_NC<7>	BL2	NC7
TP_NB_NC<8>	BK1	NC8
TP_NB_NC<9>	BJ1	NC9
TP_NB_NC<10>	E1	NC10
TP_NB_NC<11>	A5	NC11
TP_NB_NC<12>	C51	NC12
TP_NB_NC<13>	B50	NC13
TP_NB_NC<14>	A50	NC14
TP_NB_NC<15>	A49	NC15
TP_NB_NC<16>	BK2	NC16

DDR MUXING

SM_CK0	AV29	MEM_CLK_P<0>
SM_CK1	BB23	MEM_CLK_P<1>
SM_CK3	BA25	MEM_CLK_P<3>
SM_CK4	AV23	MEM_CLK_P<4>
SM_CK0*	AW30	MEM_CLK_N<0>
SM_CK1*	BA23	MEM_CLK_N<1>
SM_CK3*	AW25	MEM_CLK_N<3>
SM_CK4*	AW23	MEM_CLK_N<4>
SM_CKE0	BE29	MEM_CKE<0>
SM_CKE1	AY32	MEM_CKE<1>
SM_CKE3	BD39	MEM_CKE<3>
SM_CKE4	BG37	MEM_CKE<4>
SM_CS0*	BG20	MEM_CS_L<0>
SM_CS1*	BK16	MEM_CS_L<1>
SM_CS2*	BG16	MEM_CS_L<2>
SM_CS3*	BE13	MEM_CS_L<3>
SM_ODT0	BH18	MEM_ODT<0>
SM_ODT1	BJ15	MEM_ODT<1>
SM_ODT2	BJ14	MEM_ODT<2>
SM_ODT3	BE16	MEM_ODT<3>
SM_RCOMP	BL15	MEM_RCOMP
SM_RCOMP*	BK14	MEM_RCOMP_L
SM_RCOMP_VOH	BK31	MEM_RCOMP_VOH
SM_RCOMP_VOL	BL31	MEM_RCOMP_VOL
SM_VREF0	AR49	=PP0V9_S3M_MEM_NBVREFA
SM_VREF1	AW4	=PP0V9_S3M_MEM_NBVREFB

CLK

DPLL_REF_CLK	B42	=NB_CLK96M_DOT_P
DPLL_REF_CLK*	C42	=NB_CLK96M_DOT_N
DPLL_REF_SSCLK	H48	=NB_CLK100M_DPLLSS_P
DPLL_REF_SSCLK*	H47	=NB_CLK100M_DPLLSS_N
PEG_CLK	K44	NB_CLK100M_PCIE_P
PEG_CLK*	K45	NB_CLK100M_PCIE_N

Clk used for PEG and DMI

DMI

DMI_RXN0	AN47	DMI_S2N_N<0>
DMI_RXN1	AJ38	DMI_S2N_N<1>
DMI_RXN2	AN42	DMI_S2N_N<2>
DMI_RXN3	AN46	DMI_S2N_N<3>
DMI_RXP0	AM47	DMI_S2N_P<0>
DMI_RXP1	AJ39	DMI_S2N_P<1>
DMI_RXP2	AN41	DMI_S2N_P<2>
DMI_RXP3	AN45	DMI_S2N_P<3>
DMI_TXN0	AJ46	DMI_N2S_N<0>
DMI_TXN1	AJ41	DMI_N2S_N<1>
DMI_TXN2	AM40	DMI_N2S_N<2>
DMI_TXN3	AM44	DMI_N2S_N<3>
DMI_TXP0	AJ47	DMI_N2S_P<0>
DMI_TXP1	AJ42	DMI_N2S_P<1>
DMI_TXP2	AM39	DMI_N2S_P<2>
DMI_TXP3	AM43	DMI_N2S_P<3>

GRAPHICS VID

		GFX_VID<0>
		GFX_VID<1>
GFX_VID0	E35	GFX_VID<2>
GFX_VID1	A39	GFX_VID<3>
GFX_VID2	C38	GFX_VID<4>
GFX_VID3	B39	=GFX_VR_EN
GFX_VR_EN	E36	

MISC

CL_CLK	AM49	CLINK_NB_CLK
CL_DATA	AK50	CLINK_NB_DATA
CL_PWROK	AT43	=NB_CLINK_MPWROK
CL_RST*	AN49	CLINK_NB_RESET_L
CL_VREF	AM50	NB_CLINK_VREF
SDVO_CTRL_CLK	H35	SDVO_CTRLCLK
SDVO_CTRL_DATA	K36	SDVO_CTRLDATA
CLKREQ*	G39	NB_CLKREQ_L
ICH_SYNC*	G40	NB_SB_SYNC_L
TEST1	A37	NB_TEST1
TEST2	R32	NB_TEST2

=PP1V8_S3M_MEM_NB
R1610 20 1% 1/16W MF-LF 402
R1620 1K 1% 1/16W MF-LF 402
C1623 0.01UF 10% 16V CERM 402
C1622 2.2UF 20% 6.3V CERM1 603
R1622 3.01K 1% 1/16W MF-LF 402
R1611 20 1% 1/16W MF-LF 402
C1625 0.01UF 10% 16V CERM 402
C1624 2.2UF 20% 6.3V CERM1 603
R1624 1K 1% 1/16W MF-LF 402
C1615 0.1uF 20% 10V CERM 402
C1616 0.1uF 20% 10V CERM 402

PP1V25_S0M_NB_VCCAXD
R1640 1K 1% 1/16W MF-LF 402
C1640 0.1uF 20% 10V CERM 402
R1641 392 1% 1/16W MF-LF 402

R1691 20K 5% 1/16W MF-LF 402
R1690 0 5% 1/16W MF-LF 402

NOTE: GMCH CL_PWROK input must be PWRGD signal for PP3V3_S0M, PP3V3_S0MWOL, PP1V8_S3M, PP1V25_S0M, PP1V05_S0M, PP0V9_S3M and PP0V9_S0M.
If ME/AMT is not used, short CL_PWROK to PWROK.

NB Misc Interfaces

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE
II NOT TO REPRODUCE OR COPY IT
III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 16 OF 118	

www.laptop-schematics.com





www.laptop-schematics.com

NB DDR2 Interfaces

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 17 OF 118	



www.laptop-schematics.com



www.laptopschematics.com

Current numbers from Crestline EDS, doc #21749.

NB Power 2

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 19 OF 118	

OMIT

U1400
CRESTLINE
FCBGA
(9 OF 10)
VSS

A13	VSS1	VSS100	AW24
A15	VSS2	VSS101	AW29
A17	VSS3	VSS102	AW32
A24	VSS4	VSS103	AW5
AA21	VSS5	VSS104	AW7
AA24	VSS6	VSS105	AY10
AA29	VSS7	VSS106	AY24
AB20	VSS8	VSS107	AY37
AB23	VSS9	VSS108	AY42
AB26	VSS10	VSS109	AY43
AB28	VSS11	VSS110	AY45
AB31	VSS12	VSS111	AY47
AC10	VSS13	VSS112	AY50
AC13	VSS14	VSS113	B10
AC3	VSS15	VSS114	B20
AC39	VSS16	VSS115	B24
AC43	VSS17	VSS116	B29
AC47	VSS18	VSS117	B30
AD1	VSS19	VSS118	B35
AD21	VSS20	VSS119	B38
AD26	VSS21	VSS120	B43
AD29	VSS22	VSS121	B46
AD3	VSS23	VSS122	B5
AD41	VSS24	VSS123	B8
AD45	VSS25	VSS124	BA1
AD49	VSS26	VSS125	BA17
AD5	VSS27	VSS126	BA18
AD50	VSS28	VSS127	BA2
AD8	VSS29	VSS128	BA24
AE10	VSS30	VSS129	BB12
AE14	VSS31	VSS130	BB25
AE6	VSS32	VSS131	BB40
AF20	VSS33	VSS132	BB44
AF23	VSS34	VSS133	BB49
AF24	VSS35	VSS134	BB8
AF31	VSS36	VSS135	BC16
AG2	VSS37	VSS136	BC24
AG38	VSS38	VSS137	BC25
AG43	VSS39	VSS138	BC36
AG47	VSS40	VSS139	BC40
AG50	VSS41	VSS140	BC51
AH3	VSS42	VSS141	BD13
AH40	VSS43	VSS142	BD2
AH41	VSS44	VSS143	BD28
AH7	VSS45	VSS144	BD45
AH9	VSS46	VSS145	BD48
AJ11	VSS47	VSS146	BD5
AJ13	VSS48	VSS147	BE1
AJ21	VSS49	VSS148	BE19
AJ24	VSS50	VSS149	BE23
AJ29	VSS51	VSS150	BE30
AJ32	VSS52	VSS151	BE42
AJ43	VSS53	VSS152	BE51
AJ45	VSS54	VSS153	BE8
AJ49	VSS55	VSS154	BF12
AK20	VSS56	VSS155	BF16
AK21	VSS57	VSS156	BF36
AK26	VSS58	VSS157	BG19
AK28	VSS59	VSS158	BG2
AK31	VSS60	VSS159	BG24
AK51	VSS61	VSS160	BG29
AL1	VSS62	VSS161	BG39
AM11	VSS63	VSS162	BG48
AM13	VSS64	VSS163	BG5
AM3	VSS65	VSS164	BG51
AM4	VSS66	VSS165	BH17
AM41	VSS67	VSS166	BH30
AM45	VSS68	VSS167	BH44
AN1	VSS69	VSS168	BH46
AN38	VSS70	VSS169	BH8
AN39	VSS71	VSS170	BJ11
AN43	VSS72	VSS171	BJ13
AN5	VSS73	VSS172	BJ38
AN7	VSS74	VSS173	BJ4
AP4	VSS75	VSS174	BJ42
AP48	VSS76	VSS175	BJ46
AP50	VSS77	VSS176	BK15
AR11	VSS78	VSS177	BK17
AR2	VSS79	VSS178	BK25
AR39	VSS80	VSS179	BK29
AR44	VSS81	VSS180	BK36
AR47	VSS82	VSS181	BK40
AR7	VSS83	VSS182	BK44
AT10	VSS84	VSS183	BK6
AT14	VSS85	VSS184	BK8
AT41	VSS86	VSS185	BL11
AT49	VSS87	VSS186	BL13
AU1	VSS88	VSS187	BL19
AU23	VSS89	VSS188	BL22
AU29	VSS90	VSS189	BL37
AU3	VSS91	VSS190	BL47
AU36	VSS92	VSS191	C12
AU49	VSS93	VSS192	C16
AU51	VSS94	VSS193	C19
AV39	VSS95	VSS194	C28
AV48	VSS96	VSS195	C29
AW1	VSS97	VSS196	C33
AW12	VSS98	VSS197	C36
AW16	VSS99	VSS198	C41

OMIT

U1400
CRESTLINE
FCBGA
(10 OF 10)
VSS

C46	VSS199	VSS287	W11		
C50	VSS200	VSS288	W39		
C7	VSS201	VSS289	W43		
D13	VSS202	VSS290	W47		
D24	VSS203	VSS291	W5		
D3	VSS204	VSS292	W7		
D32	VSS205	VSS293	Y13		
D39	VSS206	VSS294	Y2		
D45	VSS207	VSS295	Y41		
D49	VSS208	VSS296	Y45		
E10	VSS209	VSS297	Y49		
E16	VSS210	VSS298	Y5		
E24	VSS211	VSS299	Y50		
E28	VSS212	VSS300	Y11		
E32	VSS213	VSS301	P29		
E47	VSS214				
F19	VSS215				
F36	VSS216	TDE_SENSE	VSS302	T29	=NB_TDE_SENSE
F4	VSS217				
F40	VSS218				
F50	VSS219	TDE_FORCE	VSS303	T31	=NB_TDE_FORCE
G1	VSS220				
G13	VSS221				
G16	VSS222	TDB_FORCE	VSS304	T33	=NB_TDB_FORCE
G19	VSS223				
G24	VSS224				
G28	VSS225	TDB_SENSE	VSS305	R28	=NB_TDB_SENSE
G29	VSS226				
G33	VSS227				
G42	VSS228				
G45	VSS229	VSS306	AA32		
G48	VSS230	VSS307	AB32		
G8	VSS231	VSS308	AD32		
H24	VSS232	VSS309	AF28		
H28	VSS233	VSS310	AF29		
H4	VSS234	VSS311	AT27		
H45	VSS235	VSS312	AV25		
J11	VSS236	VSS313	H50		
J16	VSS237				
J2	VSS238				
J24	VSS239				
J28	VSS240				
J33	VSS241				
J35	VSS242				
J39	VSS243				
K12	VSS245				
K47	VSS246				
K8	VSS247				
L1	VSS248				
L17	VSS249				
L20	VSS250				
L24	VSS251				
L28	VSS252				
L3	VSS253				
L33	VSS254				
L49	VSS255				
M28	VSS256				
M42	VSS257				
M46	VSS258				
M49	VSS259				
M5	VSS260				
M50	VSS261				
M9	VSS262				
N11	VSS263				
N14	VSS264				
N17	VSS265				
N29	VSS266				
N32	VSS267				
N36	VSS268				
N39	VSS269				
N44	VSS270				
N49	VSS271				
N7	VSS272				
P19	VSS273				
P2	VSS274				
P23	VSS275				
P3	VSS276				
P50	VSS277				
R49	VSS278				
T39	VSS279				
T43	VSS280				
T47	VSS281				
U41	VSS282				
U45	VSS283				
U50	VSS284				
V2	VSS285				
V3	VSS286				

Crestline Thermal Diode Pins

Mainly for investigation. If not used, alias these nets directly to GND.

NOTE: TDE = _P

NOTE: TDB = _N

www.laptop-schematics.com

NB Grounds

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 20 OF 118	

www.laptop-schematics.com

GMCH Core Power

=PPVCORE_S0_NB

1573mA (Int Graphics)
1310mA (Ext Graphics)

C2100 330UF 20% 6.3V ELEC 6.3X8-SM
C2101 22uF 20% 6.3V CERM 805
C2102 0.22uF 20% 6.3V X5R 402
C2103 0.22uF 20% 6.3V X5R 402
C2104 0.1uF 20% 10V CERM 402

PLACEMENT_NOTE=Place in GMCH cavity

WF: Matanzas has 2-pin 270uF bulk cap

GMCH ME Core Power

=PP1V05_S0M_NB_VCCAXM

540 mA

C2110 22uF 20% 6.3V CERM 805
C2111 0.22uF 20% 6.3V X5R 402
C2112 0.22uF 20% 6.3V X5R 402
C2113 0.1uF 20% 10V CERM 402
C2114 0.1uF 20% 10V CERM 402
C2115 0.1uF 20% 10V CERM 402

PLACEMENT_NOTE=Place in GMCH cavity

GMCH FSB I/O Rail

=PP1V25R1V05_S0_NB_VTT

850 mA (800MHz FSB)
770 mA (667MHz FSB)

C2120 330UF 20% 6.3V ELEC 6.3X8-SM
C2121 4.7uF 20% 6.3V CERM 603
C2122 4.7uF 20% 6.3V CERM 603
C2123 2.2uF 10% 6.3V CERM1 603
C2124 0.47UF 10% 6.3V CERM-X5R 402

PLACEMENT_NOTE=Place close to U1400

WF: Matanzas has 270uF

GMCH Memory I/O Rail

=PP1V8_S3M_MEM_NB

3300 mA (2ch 667MHz)
2700 mA (2ch 533MHz)
1700 mA (1ch 667MHz)
1395 mA (1ch 533MHz)
5 mA (standby)

C2130 330UF 20% 6.3V ELEC 6.3X8-SM
C2135 0.1uF 20% 10V CERM 402
C2131 22uF 20% 6.3V CERM 805
C2132 22uF 20% 6.3V CERM 805

PLACEMENT_NOTE=Place close to U1400

WF: "Place where LVDS and DDR2 taps." (C2125)

Placeholder for 3.9nH, 1A, 32mOhm

=PP1V25_S0M_NB_VCCA

675 mA (667MHz DDR2)
585 mA (533MHz DDR2)

R2141 0 5% 1/10W MF-LF 603
C2140 330UF 20% 6.3V ELEC 6.3X8-SM
NO STUFF C2141 22uF 20% 6.3V CERM 805
C2142 22uF 20% 6.3V CERM 805
C2143 4.7UF 20% 6.3V CERM 603
C2144 1UF 10% 10V X5R 402-1

PP1V25_S0M_NB_VCCA_SM
MIN_LINE_WIDTH=0.4 MM
MIN_NECK_WIDTH=0.2 MM
VOLTAGE=1.25V

640 mA (667MHz DDR2)
550 mA (533MHz DDR2)

Placeholder for 2.2nH, 1.4A, 17mOhm

R2145 0 5% 1/10W MF-LF 603
C2145 22uF 20% 6.3V CERM 805
NO STUFF C2146 2.2uF 20% 6.3V CERM1 603
C2148 0.1uF 20% 10V CERM 402

PP1V25_S0M_NB_VCCA_SM_CK
MIN_LINE_WIDTH=0.4 MM
MIN_NECK_WIDTH=0.2 MM
VOLTAGE=1.25V

35 mA

Placeholder for 5.6nH, 0.9A, 45mOhm max

=PP1V25_S0M_NB_VCC

515 mA

NO STUFF L2150 FERR-120-OHM-0.2A 0603
R2150 0 5% 1/10W MF-LF 603
NO STUFF C2150 22uF 20% 6.3V CERM 805
C2151 1UF 10% 10V X5R 402-1

PP1V25_S0M_NB_VCCAXD
MIN_LINE_WIDTH=0.4 MM
MIN_NECK_WIDTH=0.2 MM
VOLTAGE=1.25V

515 mA

100 mA =PP3V3_S0_NB_VCCHV
100 mA =PP1V25_S0_NB_VCCDMI

C2160 0.1uF 20% 10V CERM 402
C2161 0.1uF 20% 10V CERM 402

=PP3V3_S0_NB_VCCA_PEG_BG

C2165 0.1uF 20% 10V CERM 402

0.4 mA

=GND_NB_VSSA_PEG_BG

Layout Note: Route to caps, then GND

=PP1V25_S0_NB_VCC

495 mA

R2170 0 5% 1/10W MF-LF 603

PP1V25_S0_NB_VCCAXF
MIN_LINE_WIDTH=0.4 MM
MIN_NECK_WIDTH=0.2 MM
VOLTAGE=1.25V

495 mA

C2170 10uF 20% 6.3V X5R 603
C2171 1UF 10% 10V X5R 402-1

=PP1V25_S0_NB_PCIE

1520 mA

Layout Note: Place L and C close to MCH

L2173 91NH 1210 CRITICAL
C2173 220UF 20% 16V ELEC SM-CASE-C1

PP1V05_S0_NB_VCCPEG
MIN_LINE_WIDTH=0.5 MM
MIN_NECK_WIDTH=0.2 MM
VOLTAGE=1.05V
MAKE_BASE=TRUE

1260 mA

C2174 10uF 20% 6.3V X5R 603

Layout Note: 10uF caps should be close to MCH on opposite side.

PP1V05_S0_NB_VCCRXRDMI
MIN_LINE_WIDTH=0.5 MM
MIN_NECK_WIDTH=0.2 MM
VOLTAGE=1.05V

260 mA

C2177 10uF 20% 6.3V X5R 603

Layout Note: 10uF caps should be close to MCH on opposite side.

=PP1V25_S0M_NB_PLL

450 mA

L2181 FERR-120-OHM-0.2A 0603
C2181 22UF 20% 6.3V CERM 805

PP1V25_S0M_NB_VCCA_HPLL
MIN_LINE_WIDTH=0.25 MM
MIN_NECK_WIDTH=0.2 MM
VOLTAGE=1.25V

50 mA

C2182 0.1uF 20% 10V CERM 402

PLACEMENT_NOTE=Place C2182 by U1400.AL2

L2183 FERR-120-OHM-0.2A 0603
R2183 0.51 1% 1/10W MF-LF 402
C2184 0.1uF 20% 10V CERM 402

PP1V25_S0M_NB_VCCA_MPLL
MIN_LINE_WIDTH=0.3 MM
MIN_NECK_WIDTH=0.2 MM
VOLTAGE=1.25V

150 mA

PLACEMENT_NOTE=Place C2184 by U1400.AM2

PP1V25_S0M_NB_MPLL_RC
MIN_LINE_WIDTH=0.3 MM
MIN_NECK_WIDTH=0.2 MM
VOLTAGE=1.25V

C2183 22UF 20% 6.3V CERM 805

=PP1V25_S0M_NB_VCCD_HPLL

250 mA

C2180 0.1uF 20% 10V CERM 402

PLACEMENT_NOTE=Place C2180 by U1400.AN2

=PP1V05_S0_NB_FOLLOW

D2185 SOT23 BAT54E3

PP3V3_S0_NB1V05_FOLLOW_R
MIN_LINE_WIDTH=0.4 MM
MIN_NECK_WIDTH=0.2 MM
VOLTAGE=3.3V

R2185 10 1% 1/16W MF-LF 402

=PP3V3_S0_NB_FOLLOW

BOMOPTION=CR_E

=PPVCORE_S0_NB_FOLLOW

D2186 SOT23 BAT54E3

PP3V3_S0_NBCORE_FOLLOW_R
MIN_LINE_WIDTH=0.4 MM
MIN_NECK_WIDTH=0.2 MM
VOLTAGE=3.3V

R2186 10 1% 1/16W MF-LF 402

BOMOPTION=CR_E

NOTE: This follower is redundant if VCORE is always 1.05V.

=PP1V25_S0_NB_PLL

100 mA

L2190 FERR-220-OHM 0805
R2190 1.1 1% 1/16W MF-LF 402
C2191 0.1uF 20% 10V CERM 402
C2192 0.1uF 20% 10V CERM 402

PP1V25_S0_NB_PEGPLL
MIN_LINE_WIDTH=0.25 MM
MIN_NECK_WIDTH=0.2 MM
VOLTAGE=1.25V

100 mA

PP1V25_S0_NB_PEGPLL_RC
MIN_LINE_WIDTH=0.25 MM
MIN_NECK_WIDTH=0.2 MM
VOLTAGE=1.25V

C2190 10uF 20% 6.3V X5R 603

=PP1V8_S3M_NB_VCC

200 mA

L2195 1.0UH-220MA-0.12-OHM 0805
R2195 1.1 1% 1/16W MF-LF 402
C2196 22uF 20% 6.3V CERM 805
C2197 0.1uF 20% 10V CERM 402

PP1V8_S3M_NB_VCCSMCK
MIN_LINE_WIDTH=0.25 MM
MIN_NECK_WIDTH=0.2 MM
VOLTAGE=1.8V

200 mA

PP1V8_S3M_NB_VCCSMCK_RC
MIN_LINE_WIDTH=0.25 MM
MIN_NECK_WIDTH=0.2 MM
VOLTAGE=1.8V

C2195 10UF 20% 6.3V X5R 603

NOTE:
SYNCED FROM T9_MLB_NOME ON 10/31/06
CHANGED C2100,20,30,40,73 TO ELEC

Current numbers from Crestline EDS, doc #21749.

NB Standard Decoupling

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE
II NOT TO REPRODUCE OR COPY IT
III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 21 OF 118	

NOTE:
SANTA ROSA DESIGN GUIDE REV 1.5
P. 227-228 TABLE 95

15	LVDS_BKLT_CTL	TRUE	TP_LVDS_BKLT_CTL
15	LVDS_BKLT_EN	TRUE	TP_LVDS_BKLT_EN
15 13	LVDS_CTRL_CLK		
15 13	LVDS_CTRL_DATA		
15	LVDS_DDC_CLK		
15	LVDS_DDC_DATA		
15	LVDS_VDD_EN	TRUE	TP_LVDS_VDD_EN
15	LVDS_IBG	TRUE	TP_LVDS_IBG
15	LVDS_VREFH	TRUE	TP_LVDS_VREFH
15	LVDS_VREFL	TRUE	TP_LVDS_VREFL
15	LVDS_A_CLK_N	TRUE	TP_LVDS_A_CLK_N
15	LVDS_A_CLK_P	TRUE	TP_LVDS_A_CLK_P
15	LVDS_B_CLK_N	TRUE	TP_LVDS_B_CLK_N
15	LVDS_B_CLK_P	TRUE	TP_LVDS_B_CLK_P
15	LVDS_A_DATA_N<0>	TRUE	TP_LVDS_A_DATA_N<0>
15	LVDS_A_DATA_N<1>	TRUE	TP_LVDS_A_DATA_N<1>
15	LVDS_A_DATA_N<2>	TRUE	TP_LVDS_A_DATA_N<2>
15	LVDS_A_DATA_P<0>	TRUE	TP_LVDS_A_DATA_P<0>
15	LVDS_A_DATA_P<1>	TRUE	TP_LVDS_A_DATA_P<1>
15	LVDS_A_DATA_P<2>	TRUE	TP_LVDS_A_DATA_P<2>
15	LVDS_B_DATA_N<0>	TRUE	TP_LVDS_B_DATA_N<0>
15	LVDS_B_DATA_N<1>	TRUE	TP_LVDS_B_DATA_N<1>
15	LVDS_B_DATA_N<2>	TRUE	TP_LVDS_B_DATA_N<2>
15	LVDS_B_DATA_P<0>	TRUE	TP_LVDS_B_DATA_P<0>
15	LVDS_B_DATA_P<1>	TRUE	TP_LVDS_B_DATA_P<1>
15	LVDS_B_DATA_P<2>	TRUE	TP_LVDS_B_DATA_P<2>
15	=TV_A_DAC		
15	=TV_B_DAC		
15	=TV_C_DAC		
15	=TV_A_RTN		
15	=TV_B_RTN		
15	=TV_C_RTN		
15	TV_DCONSEL<0>		
15	TV_DCONSEL<1>		
15	=CRT_BLUE		
15	=CRT_BLUE_L		
15	=CRT_GREEN		
15	=CRT_GREEN_L		
15	=CRT_RED		
15	=CRT_RED_L		
15	CRT_DDC_CLK		
15	CRT_DDC_DATA		
15	=CRT_HSYNC_R		
15	=CRT_TVO_IREF		
15	=CRT_VSYNC_R		
16	=NB_CLK96M_DOT_P		
16	=NB_CLK96M_DOT_N		
16	=NB_CLK100M_DPLLSS_P		
16	=NB_CLK100M_DPLLSS_N		
16	SDVO_CTRLCLK		
16	SDVO_CTRLDATA		
16	GFX_VID<1>	TRUE	TP_GFX_VID<1>
16	GFX_VID<2>	TRUE	TP_GFX_VID<2>
16	GFX_VID<3>	TRUE	TP_GFX_VID<3>
16	GFX_VID<4>	TRUE	TP_GFX_VID<4>
16	=GFX_VR_EN	TRUE	TP_GFX_VR_EN

NOTE:
SANTA ROSA DESIGN GUIDE REV 1.5
P. 227-228 TABLE 95

	PP1V25_S0_NB_VCCA_DPLLA	19
	PP1V25_S0_NB_VCCA_DPLLB	19
	=PP1V5_S0_NB_VCCD_CRT	19
	PP1V5_S0_NB_VCCD_QDAC	19
	=PPVCORE_S0_NB_GFX	18
	PP3V3_S0_NB_VCCA_CRTDAC	19
	PP3V3_S0_NB_VCCA_TVDACA	19
	PP3V3_S0_NB_VCCA_TVDACB	19
	PP3V3_S0_NB_VCCA_TVDACC	19
	PP3V3_S0_NB_VCCA_DAC_BG	19
	=GND_NB_VSSA_DAC_BG	19
	PP1V8_S0_NB_VCCTXLVDS	19
TP_NB_VSSA_LVDS TRUE	=GND_NB_VSSA_LVDS	19
	=PP1V8_S0_NB_VCCD_LVDS	19
	=PP3V3_S0_NB_VCCSYNC	19

NOTE:
SANTA ROSA PLATFORM P180 FIG 119 - NC
ALSO CONFIRMED WITH INTEL

16 =NB_CLINK_MPWROK — TRUE — VR_PWRGOOD_DELAY 7 16 70 71

VCCD_TVDAC ALSO POWERS INTERNAL THERMAL SENSORS.

6 =PP1V5_S0_NB_TVDAC
65 mA

CRITICAL
C2201
22000pF-1000mA
16V
NPM1B
PP1V5_S0_NB_VCCD_TVDAC 19
MIN_LINE_WIDTH=0.3 MM
MIN_NECK_WIDTH=0.2 MM
VOLTAGE=1.5V
60 mA

C2213
10uF
20%
6.3V
X5R
603

C2200
0.1uF
20%
10V
CERM
402

Layout Note:
THESE CAPS SHOULD BE
within 6.35 mm of NB edge

21 18 16 6 =PP1V8_S3M_MEM_NB

R2200 1K 5% 1/16W MF-LF 402
R2202 1K 5% 1/16W MF-LF 402
R2201 1K 5% 1/16W MF-LF 402
R2203 1K 5% 1/16W MF-LF 402

PP0V9_S3M_MEM_NBVREFA — TRUE — =PP0V9_S3M_MEM_NBVREFA 7 16
VOLTAGE=0.9V
MIN_LINE_WIDTH=0.25MM
MIN_NECK_WIDTH=0.25MM

PP0V9_S3M_MEM_NBVREFB — TRUE — =PP0V9_S3M_MEM_NBVREFB 7 16
VOLTAGE=0.9V
MIN_LINE_WIDTH=0.25MM
MIN_NECK_WIDTH=0.25MM

www.laptop-schematics.com

NB Graphics Decoupling

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 22 OF 118	



	HDA
HDA_BIT_CLK	24.000MHZ CLOCK W/INTERNAL WEAK PD
HDA_RST#	
HDA_SDIN[0-2]	INTEGRATED PDs
HDA_SDOUT	INTEGRATED PD
ACZ_SYNC	INTEGRATED PD

SB Enet, Disk, FSB, LPC

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 23 OF 118	

www.laptop-schematics.com

www.laptop-schematics.com

OMIT

U2300
ICH8M
BGA
(2 OF 6)

PCI_EXPRESS

Spares
(x2-capable, pull HDA_SYNC high for x2)

TP_PCIE_A_D2R_N	P27	PERN1	
TP_PCIE_A_D2R_P	P26	PERP1	
TP_PCIE_A_R2D_C_N	N29	PETN1	
TP_PCIE_A_R2D_C_P	N28	PETP1	

ExpressCard

TP_PCIE_B_D2R_N	M27	PERN2	
TP_PCIE_B_D2R_P	M26	PERP2	
TP_PCIE_B_R2D_C_N	L29	PETN2	
TP_PCIE_B_R2D_C_P	L28	PETP2	
TP_PCIE_EXCARD_D2R_N	K27	PERN3	
TP_PCIE_EXCARD_D2R_P	K26	PERP3	
TP_PCIE_EXCARD_R2D_C_N	J29	PETN3	
TP_PCIE_EXCARD_R2D_C_P	J28	PETP3	

FireWire

42 TP_PCIE_FW_D2R_N	H27	PERN4	
42 TP_PCIE_FW_D2R_P	H26	PERP4	
42 TP_PCIE_FW_R2D_C_N	G29	PETN4	
42 TP_PCIE_FW_R2D_C_P	G28	PETP4	

PCIe Mini Card (AirPort)

104 34 7 IN PCIE_MINI_D2R_N	F27	PERN5	
104 34 7 IN PCIE_MINI_D2R_P	F26	PERP5	
104 34 OUT PCIE_MINI_R2D_C_N	E29	PETP5	
104 34 OUT PCIE_MINI_R2D_C_P	E28	PETP5	

Ethernet Yukon-PCIE Nineveh-GLCI

104 37 7 IN PCIE_ENET_D2R_N	D27	PERN6/GLAN_RXN	
104 37 7 IN PCIE_ENET_D2R_P	D26	PERP6/GLAN_RXP	
104 37 OUT PCIE_ENET_R2D_C_N	C29	PETN6/GLAN_TXN	
104 37 OUT PCIE_ENET_R2D_C_P	C28	PETP6/GLAN_TXP	

SPI

103 61 B1 SPI_SCLK_R	C23	SPI_CLK	INT PU
103 61 B1 SPI_CE_R_L<0>	B23	SPI_CS0*	
TP_SPI_CE_R_L<1>	E22	SPI_CS1*	INT PU
103 61 B1 SPI_SI_R	D23	SPI_MOSI	INT PU
103 61 7 B1 SPI_SO	F21	SPI_MISO	INT PU

DIRECT MEDIA INTERFACE

DMI0RXN	V27	DMI_N2S_N<0>	IN 7 16 101
DMI0RXP	V26	DMI_N2S_P<0>	IN 7 16 101
DMI0TXN	U29	DMI_S2N_N<0>	OUT 7 16 101
DMI0TXP	U28	DMI_S2N_P<0>	OUT 7 16 101
DMI1RXN	Y27	DMI_N2S_N<1>	IN 16 101
DMI1RXP	Y26	DMI_N2S_P<1>	IN 16 101
DMI1TXN	W29	DMI_S2N_N<1>	OUT 16 101
DMI1TXP	W28	DMI_S2N_P<1>	OUT 16 101
DMI2RXN	AB26	DMI_N2S_N<2>	IN 16 101
DMI2RXP	AB25	DMI_N2S_P<2>	IN 16 101
DMI2TXN	AA29	DMI_S2N_N<2>	OUT 16 101
DMI2TXP	AA28	DMI_S2N_P<2>	OUT 16 101
DMI3RXN	AD27	DMI_N2S_N<3>	IN 16 101
DMI3RXP	AD26	DMI_N2S_P<3>	IN 16 101
DMI3TXN	AC29	DMI_S2N_N<3>	OUT 16 101
DMI3TXP	AC28	DMI_S2N_P<3>	OUT 16 101
DMI_CLKN	T26	SB_CLK100M_DMI_N	IN 7 30 105
DMI_CLKP	T25	SB_CLK100M_DMI_P	IN 7 30 105
DMI_ZCOMP	Y23		
DMI_IRCOMP	Y24	DMI_IRCOMP_R	

R2413 24.9 1% 1/10W MF-LF 402 — PP1V5_S0_SB_VCC1_5_B (23 26 27)

USB

EHCI0

INT PD USBP0N	G3	USB_EXTA_N	B1 46 103
INT PD USBP0P	G2	USB_EXTA_P	B1 46 103
INT PD USBP1N	H5	USB_MINI_N	B1 34 103
INT PD USBP1P	H4	USB_MINI_P	B1 34 103
INT PD USBP2N	H2	USB_EXTD_N	B1 46 103
INT PD USBP2P	H1	USB_EXTD_P	B1 46 103
INT PD USBP3N	J3	USB_CAMERA_N	B1 7 47 103
INT PD USBP3P	J2	USB_CAMERA_P	B1 7 47 103
INT PD USBP4N	K5	USB_IR_N	B1 7 47 103
INT PD USBP4P	K4	USB_IR_P	B1 7 47 103
INT PD USBP5N	K2	USB_TPAD_N	B1 47 103
INT PD USBP5P	K1	USB_TPAD_P	B1 47 103

EHCI1

INT PD USBP6N	L3	USB_BT_N	B1 7 47 103
INT PD USBP6P	L2	USB_BT_P	B1 7 47 103
INT PD USBP7N	M5	USB_EXTB_N	B1 46 103
INT PD USBP7P	M4	USB_EXTB_P	B1 46 103
INT PD USBP8N	M2	USB_EXCARD_N	B1 47 103
INT PD USBP8P	M1	USB_EXCARD_P	B1 47 103
INT PD USBP9N	N3	USB_EXTC_N	B1 46 103
INT PD USBP9P	N2	USB_EXTC_P	B1 46 103

USBRBIAS* F2
USBRBIAS F3 — 103 USB_RBIAS — R2414 22.6 1% 1/10W MF-LF 402

External A
AirPort (PCIe Mini-Card)
External D / WWAN
Camera
IR
Geyser Trackpad/Keyboard
Bluetooth
External B
ExpressCard
External C

NOTE: USBP[0-9]P/N have internal 15K pull-downs.

=PP3V3_S5_SB_USB

R2400 10K 5% 1/16W MF-LF 402
R2401 10K 5% 1/16W MF-LF 402
R2402 10K 5% 1/16W MF-LF 402
R2403 10K 5% 1/16W MF-LF 402
R2404 10K 5% 1/16W MF-LF 402
R2405 10K 5% 1/16W MF-LF 402
R2407 10K 5% 1/16W MF-LF 402
R2408 10K 5% 1/16W MF-LF 402
R2409 10K 5% 1/16W MF-LF 402

46 13 IN USB_EXTA_OC_L	AJ19	OC0*
13 OUT SB_GPIO40	AG16	OC1*/GPIO40
13 IN USB_EXTD_OC_L	AG15	OC2*/GPIO41
13 OUT WOW_EN	AE15	OC3*/GPIO42
13 OUT PM_LATRIGGER_L	AF15	OC4*/GPIO43
13 OUT EXTGPU_LVDS_EN	AG17	OC5*/GPIO29
13 OUT SB_GPIO30	AD12	OC6*/GPIO30
46 13 IN USB_EXTB_OC_L	AJ18	OC7*/GPIO31
IN EXCARD_OC_L	AD14	OC8*
46 IN USB_EXTC_OC_L	AH18	OC9*

R2406 10K 5% 1/16W MF-LF 402

NOTE: GNT[0-3]# have internal 20K pull-ups enabled only when PCIRST# = 0 and PWROK = 1

If used, ensure GNT2# is not low when PWROK rises, or PCIe ports 5 & 6 will be disabled.

OMIT

U2300
ICH8M
BGA
(3 OF 6)

PCI

104 28 B1 PCI_AD<0>	D20	AD0	REQ0* A4 PCI_FW_REQ_L IN 24 104
104 28 B1 PCI_AD<1>	E19	AD1	INT PU GNT0* D7 PCI_FW_GNT_L MAKE_BASE=TRUE OUT 104
104 28 B1 PCI_AD<2>	D19	AD2	REQ1*/GPIO50 E18 PCI_REQ1_L IN 7 24 104 — BOOT_LPC_SPI_L OUT 7 51
104 28 B1 PCI_AD<3>	A20	AD3	INT PU GNT1*/GPIO51 C18 TP_SB_GPIO51
104 28 B1 PCI_AD<4>	D17	AD4	REQ2*/GPIO52 B19 PCI_REQ2_L IN 7 24 104
104 28 B1 PCI_AD<5>	A21	AD5	INT PU GNT2*/GPIO53 E18 TP_SB_GPIO53
104 28 B1 PCI_AD<6>	A19	AD6	REQ3*/GPIO54 A11 ODD_RST_5VTOL_L OUT 44 103
104 28 B1 PCI_AD<7>	C19	AD7	INT PU GNT3*/GPIO55 E10 TP_SB_GPIO55
104 28 B1 PCI_AD<8>	A18	AD8	
104 28 B1 PCI_AD<9>	B16	AD9	C/BE0* C17 PCI_C_BE_L<0> B1 28 104
104 28 B1 PCI_AD<10>	A12	AD10	C/BE1* E15 PCI_C_BE_L<1> B1 28 104
104 28 B1 PCI_AD<11>	E16	AD11	C/BE2* F16 PCI_C_BE_L<2> B1 28 104
104 28 B1 PCI_AD<12>	A14	AD12	C/BE3* E17 PCI_C_BE_L<3> B1 28 104
104 28 B1 PCI_AD<13>	G16	AD13	
104 28 B1 PCI_AD<14>	A15	AD14	IRDY* C8 PCI_IRDY_L B1 24 104
104 28 B1 PCI_AD<15>	B6	AD15	PAR D9 PCI_PAR B1 28 104
104 28 B1 PCI_AD<16>	C11	AD16	PCIRST* G6 PCI_RST_L OUT 28
104 28 B1 PCI_AD<17>	A9	AD17	DEVSEL* D16 PCI_DEVSEL_L B1 24 104
104 28 B1 PCI_AD<18>	D11	AD18	PERR* A7 PCI_PERR_L B1 24 104
104 28 B1 PCI_AD<19>	B12	AD19	PLOCK* B7 PCI_LOCK_L B1 24 104
104 28 B1 PCI_AD<20>	C12	AD20	SERR* F10 PCI_SERR_L B1 24 28 104
104 28 B1 PCI_AD<21>	D10	AD21	STOP* C16 PCI_STOP_L B1 24 104
104 28 B1 PCI_AD<22>	C7	AD22	TRDY* C9 PCI_TRDY_L B1 24 104
104 28 B1 PCI_AD<23>	F13	AD23	FRAME* A17 PCI_FRAME_L B1 24 104
104 28 B1 PCI_AD<24>	E11	AD24	
104 28 B1 PCI_AD<25>	E13	AD25	PLTRST* AG24 PLT_RST_L OUT 28
104 28 B1 PCI_AD<26>	E12	AD26	PCICLK B10 PCI_CLK33M_SB IN 7 30 105
104 28 B1 PCI_AD<27>	D8	AD27	INT PU PME* G7 TP_PCI_PME_L
104 28 B1 PCI_AD<28>	A6	AD28	
104 28 B1 PCI_AD<29>	E8	AD29	
104 28 B1 PCI_AD<30>	D6	AD30	
104 28 B1 PCI_AD<31>	A3	AD31	

INTERRUPT I/F

104 24 B1 INT_PIRQA_L	F9	PIRQA*	PIRQE*/GPIO2 F8 INT_PIRQE_L B1 24 98 104
104 24 B1 INT_PIRQB_L	B5	PIRQB*	PIRQF*/GPIO3 G11 INT_PIRQF_L B1 24 104
104 24 B1 INT_PIRQC_L	C5	PIRQC*	PIRQG*/GPIO4 F12 DVI_HOTPLUG_DET IN 28
104 24 B1 INT_PIRQD_L	A10	PIRQD*	PIRQH*/GPIO5 B3 ODD_PWR_EN_L OUT 24

FireWire INT*

R2415 1K 5% 1/16W MF-LF 402

R2415 pull-down on GNT0# selects SPI ROM by default.

Provide a pull-down on this GPIO if not used.

SB BOOT BIOS SELECT

I/F	GNT0#
LPC	1
SPI	0

NOTE: GNT0# HAS INT PU; ENABLED ONLY WHEN PCIRST#=0 AND PWROK=H
SPI_CS1# HAS INT PU (NOMINAL=20K, SIMULATION=15K-35K)

=PP3V3_S0_SB_PCI

104 24 PCI_FRAME_L	R2423	8.2K
104 24 PCI_IRDY_L	R2424	8.2K
104 24 PCI_TRDY_L	R2425	8.2K
104 24 PCI_STOP_L	R2426	8.2K
104 28 24 PCI_SERR_L	R2427	8.2K
104 24 PCI_DEVSEL_L	R2428	8.2K
104 24 PCI_PERR_L	R2430	8.2K
104 24 PCI_LOCK_L	R2429	8.2K
104 24 PCI_FW_REQ_L	R2432	8.2K
104 24 7 PCI_REQ1_L	R2431	8.2K
104 24 7 PCI_REQ2_L	R2433	8.2K
104 24 INT_PIRQA_L	R2437	8.2K
104 24 INT_PIRQB_L	R2436	8.2K
104 24 INT_PIRQC_L	R2438	8.2K
104 24 INT_PIRQD_L	R2439	8.2K
104 98 24 INT_PIRQE_L	R2440	8.2K
104 24 INT_PIRQF_L	R2441	8.2K
24 ODD_PWR_EN_L	R2442	8.2K

SB PCI, PCIe, DMI, USB

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE
II NOT TO REPRODUCE OR COPY IT
III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 24 OF 118	

www.laptop-schematics.com

=PP3V3_S0_SB_GPIO
=PP3V3_S5_SB_GPIO
NO_REBOOT_MODE

R2500 1K 5% 1/16W MF-LF 402
R2551 8.2K 5% 1/16W MF-LF 402
R2553 8.2K 5% 1/16W MF-LF 402
R2504 10K 5% 1/16W MF-LF 402
R2506 10K 5% 1/16W MF-LF 402
R2510 1K 5% 1/16W MF-LF 402
R2502 10K 5% 1/16W MF-LF 402
R2550 10K 5% 1/16W MF-LF 402
R2552 10K 5% 1/16W MF-LF 402
R2547 10K 5% 1/16W MF-LF 402
R2505 8.2K 5% 1/16W MF-LF 402
R2507 8.2K 5% 1/16W MF-LF 402

OMIT
U2300
ICH8M
BGA
(4 OF 6)

SMB
SMB_CLK
SMB_DATA
TP_CLINK_WLAN_RESET_L
SMB_ME_CLK
SMB_ME_DATA

CLOCKS
PM_RI_L
PM_SUS_STAT_L
PM_SYSRST_L
PM_BMBUSY_L
LINDACARD_GPIO

SYS GPIO
PM_STPPCI_L
PM_STPCPU_L
PM_CLKRUN_L
PCIE_WAKE_L
INT_SERIRQ
PM_THRM_L
VR_PWRGD_CLKEN
TP_SB_TP7

GPIO
PCI_PME_FW_L
SB_GPIO6
SMC_RUNTIME_SCI_L
SMC_WAKE_SCI_L
LAN_PHYPC
EXTGPU_RST_L
SB_GPIO18
TP_SB_GPIO20
SB_SCLOCK
SATA_B_PWR_EN_L
FWH_MFG_MODE
SB_SATA_CLKREQ_L
SB_SLOAD
SB_SDATAOUT<0>
SB_SDATAOUT<1>

MISC
SB_SPKR
NB_SB_SYNC_L
TP_SB_TP3

Test access required
for XOR chain testing.

SATA GPIO
SATA0GP/GPIO21
SATA1GP/GPIO19
SATA2GP/GPIO36
SATA3GP/GPIO37

R2532 10K 5% 1/16W MF-LF 402
R2535 10K 5% 1/16W MF-LF 402
R2533 10K 5% 1/16W MF-LF 402
R2534 10K 5% 1/16W MF-LF 402

RSVD_EXTGPU_LVDS_EN
SATA_B_DET_L
SB_GPIO36
SB_CRT_TVOUT_MUX_L

POWER MGT
CLK14
CLK48
SUSCLK
SLP_S3*
SLP_S4*
SLP_S5*
S4_STATE*/GPIO26
PWROK
DPRSLPVR/GPIO16
BATLOW*
PWRBTN*
LAN_RST*
RSMRST*
CK_PWRGD
CLPWROK
SLP_M*

SB_CLK14P3M_TIMER
SB_CLK48M_USBCTLR
SUS_CLK_SB
PM_SLP_S3_L
TP_PM_SLP_S4_L
PM_SLP_S5_L
PM_S4_STATE_L
PM_SB_PWROK
PM_DPRSLPVR
PM_BATLOW_L
PM_PWRBTN_L
PM_LAN_ENABLE
PM_RSMRST_L
CLK_PWRGD
See note below
=SB_CLINK_MPWROK
TP_PM_SLP_M_L

NOTE: DPRSLPVR HAS INT 20K PD ENABLED
AT BOOT/RESET FOR STRAPPING FUNCTION

PM_LAN_ENABLE must remain deasseted
until VccCL3_3, VccLAN3_3 and VccLAN1_05
have been up for at least 1ms.

R2524 100K 5% 1/16W MF-LF 402
R2525 10K 5% 1/16W MF-LF 402

CONTROLLER LINK
CL_CLK0
CL_CLK1
CL_DATA0
CL_DATA1
CL_VREF0
CL_VREF1
CL_RST*
MEM_LED/GPIO24
ME_EC_ALERT/GPIO10
EC_ME_ALERT/GPIO14
WOL_EN/GPIO9

CLINK_NB_CLK
TP_CLINK_WLAN_CLK
CLINK_NB_DATA
TP_CLINK_WLAN_DATA
SB_CLINK_VREF0
SB_CLINK_VREF1
CLINK_NB_RESET_L
CPU_SET_SPEED
SB_GPIO10_CL1
SB_GPIO14_CL2
WOL_EN

=PP3V3_S0MWOL_SB_CLINK0
R2526 3.24K 1% 1/16W MF-LF 402
C2500 0.1uF 10% 16V X5R 402
R2527 453 1% 1/16W MF-LF 402

=PP3V3_S5_SB_CLINK1
R2528 3.24K 1% 1/16W MF-LF 402
C2501 0.1uF 10% 16V X5R 402
R2529 453 1% 1/16W MF-LF 402

R2523 100K 5% 1/16W MF-LF 402

NOTE: ICH CLPWROK input must be PWRGD signal for
PP3V3_S0M, PP3V3_S0MWOL, PP1V8_S3M, PP1V25_S0M,
PP1V05_S0M, PP0V9_S3M and PP0V9_S0M.
If ME/AMT is not used, short CLPWROK to PWROK.

=PP3V3_S5_SB
R2511 10K 5% 1/16W MF-LF 402
R2515 10K 5% 1/16W MF-LF 402
R2514 100K 5% 1/16W MF-LF 402
LINDACARD_GPIO
CPU_SET_SPEED
FWH_MFG_MODE
NOSTUFF
R2512 0 5% 1/16W MF-LF 402
NOSTUFF
R2516 10K 5% 1/16W MF-LF 402

SATA_B_PWR_EN_L
R2530 10K 1% 1/16W MF-LF 402
=PP3V3_S0_SB_GPIO
PCI_PME_FW_L
R2531 10K 1% 1/16W MF-LF 402
SB_GPIO6
R2596 10K 1% 1/16W MF-LF 402
EXTGPU_RST_L
R2597 10K 1% 1/16W MF-LF 402

PM_RI_L
R2536 10K 1% 1/16W MF-LF 402
=PP3V3_S5_SB
PM_BATLOW_L
R2544 8.2K 5% 1/16W MF-LF 402
LAN_PHYPC
R2545 10K 1% 1/16W MF-LF 402
SB_GPIO10_CL1
R2598 10K 1% 1/16W MF-LF 402
SB_GPIO14_CL2
R2546 10K 1% 1/16W MF-LF 402

www.laptop-schematics.com

SB Pwr Mgt, GPIO, Clink

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 25 OF 118	

www.laptop-schematics.com

U2300
ICH8M
BGA
(5 OF 6)
OMIT

VSS
VSS
VSS_NCTF

U2300
ICH8M
BGA
(6 OF 6)
OMIT

6 uA S0-G3
1 mA
1 mA S0-S5
657 mA
47 mA
1080 mA (VCC1_5_A total)
10 mA
19 mA S0, 63 mA M1 & WOL
23 mA
80 mA
1 mA

PP3V3_G3_SB_RTC	VCCRTC	
PP5V_S0_SB_V5REF	V5REF	
PP5V_S5_SB_V5REF_SUS	V5REF_SUS	
PP1V5_S0_SB_VCC1_5_B	VCC1_5_B	VCCA3GP
PP1V5_S0_SB_VCCSATAPLL	VCCSATAPLL	
=PP1V5_S0_SB_VCC1_5_A_ARX	VCC1_5_A	ARX
=PP1V5_S0_SB_VCC1_5_A_ATX	VCC1_5_A	ATX
=PP1V5_S0_SB_VCC1_5_A	VCC1_5_A	
=PP1V5_S0_SB_VCC1_5_A_USB_CORE	VCC1_5_A	USB CORE
=PP1V5_S0_SB_VCCUSBPLL	VCCUSBPLL	
	VCC1_5_A24	
TP_VCCLAN1_05_INTERNAL_REG1	VCCLAN1_05	
TP_VCCLAN1_05_INTERNAL_REG2		
=PP3V3_S0MWOL_SB_VCCCL3_3	VCCCL3_3	
PP1V5_S0_SB_VCCGLANPLL	VCCGLANPLL	
=PP1V5_S0_SB_VCCGLAN1_5	VCCGLAN1_5	GLAN POWER
=PP3V3_S0_SB_VCCGLAN3_3	VCCGLAN3_3	

=PPVCORE_S0_SB	VCC1_05	CORE	1130 mA
PP1V5_S0_SB_VCCDMIPLL	VCCDMIPLL		23 mA
=PP1V25_S0_SB_DMI	VCC_DMI		50 mA
=PP1V05_S0_SB_CPU_IO	V_CPU_IO		1 mA
=PP3V3_S0_SB_VCC3_3_DMI	VCC3_3		
=PP3V3_S0_SB_VCC3_3_SATA	VCC3_3		
=PP3V3_S0_SB_VCC3_3_VCCPCORE	VCC3_3	VCCPCORE	
=PP3V3_S0_SB_VCC3_3_IDE	VCC3_3	IDE	442 mA
=PP3V3_S0_SB_VCC3_3_PCI	VCC3_3	PCI	
=PP3V3R1V5_S0_SB_VCCHDA	VCCHDA		32 mA
=PP3V3_S5_SB_3V3_VCCSUSHDA	VCCSUSHDA		11 mA S0, 1 mA S3-S5
TP_VCCSUS1_05_INTERNAL_REG1	VCCSUS1_05		
TP_VCCSUS1_05_INTERNAL_REG2			
TP_VCCSUS1_5_INTERNAL_REG1	VCCSUS1_5		
TP_VCCSUS1_5_INTERNAL_REG2	VCCSUS1_5		
=PP3V3_S5_SB_VCCSUS3_3	VCCSUS3_3		
	VCCSUS3_3	VCCPSUS	117 mA S0, 44 mA S3-S5
=PP3V3_S5_SB_VCCSUS3_3_USB	VCCSUS3_3	VCCPUSB	
TP_VCCCL1_05_INTERNAL_REG	VCCCL1_05		
VCCCL1_5V	VCCCL1_5		
=PP3V3_S0MWOL_SB_VCCLAN3_3	VCCLAN3_3		19 mA S0, 51 mA M1 & WOL

(VCC3_3 total)
(VCCSUS3_3 total)

C2600 10uF 10% 6.3V CERM 402
C2601 0.1uF 20% 10V CERM 402

NOTE:
VccHDA and VccSusHDA can be 1.5V or 3.3V depending on VIO of HD Audio interface.

Current figures provided assume 1.5V.

Current numbers from ICH8M Max Power Estimates Rev 2.0, doc #610194.

SB Power & Ground

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 26 OF 118	



www.laptop-schematics.com

RTC Power Sources



SB RTC Crystal



CPU VCORE FORCEPSI UNUSED

PWROK = CLINK PWROK FOR NO ME

VRMPWRGD INVERTER



UNUSED PCI BUS

PCI_AD<0>	MAKE_BASE=TRUE	TP_PCI_AD_0	
PCI_AD<1>	MAKE_BASE=TRUE	TP_PCI_AD_1	
PCI_AD<2>	MAKE_BASE=TRUE	TP_PCI_AD_2	
PCI_AD<3>	MAKE_BASE=TRUE	TP_PCI_AD_3	
PCI_AD<4>	MAKE_BASE=TRUE	TP_PCI_AD_4	NO_TEST=TRUE
PCI_AD<5>	MAKE_BASE=TRUE	TP_PCI_AD_5	
PCI_AD<6>	MAKE_BASE=TRUE	TP_PCI_AD_6	
PCI_AD<7>	MAKE_BASE=TRUE	TP_PCI_AD_7	
PCI_AD<8>	MAKE_BASE=TRUE	TP_PCI_AD_8	
PCI_AD<9>	MAKE_BASE=TRUE	TP_PCI_AD_9	
PCI_AD<10>	MAKE_BASE=TRUE	TP_PCI_AD_10	
PCI_AD<11>	MAKE_BASE=TRUE	TP_PCI_AD_11	
PCI_AD<12>	MAKE_BASE=TRUE	TP_PCI_AD_12	
PCI_AD<13>	MAKE_BASE=TRUE	TP_PCI_AD_13	
PCI_AD<14>	MAKE_BASE=TRUE	TP_PCI_AD_14	
PCI_AD<15>	MAKE_BASE=TRUE	TP_PCI_AD_15	
PCI_AD<16>	MAKE_BASE=TRUE	TP_PCI_AD_16	
PCI_AD<17>	MAKE_BASE=TRUE	TP_PCI_AD_17	
PCI_AD<18>	MAKE_BASE=TRUE	TP_PCI_AD_18	
PCI_AD<19>	MAKE_BASE=TRUE	TP_PCI_AD_19	
PCI_AD<20>	MAKE_BASE=TRUE	TP_PCI_AD_20	
PCI_AD<21>	MAKE_BASE=TRUE	TP_PCI_AD_21	
PCI_AD<22>	MAKE_BASE=TRUE	TP_PCI_AD_22	
PCI_AD<23>	MAKE_BASE=TRUE	TP_PCI_AD_23	
PCI_AD<24>	MAKE_BASE=TRUE	TP_PCI_AD_24	
PCI_AD<25>	MAKE_BASE=TRUE	TP_PCI_AD_25	
PCI_AD<26>	MAKE_BASE=TRUE	TP_PCI_AD_26	
PCI_AD<27>	MAKE_BASE=TRUE	TP_PCI_AD_27	
PCI_AD<28>	MAKE_BASE=TRUE	TP_PCI_AD_28	
PCI_AD<29>	MAKE_BASE=TRUE	TP_PCI_AD_29	
PCI_AD<30>	MAKE_BASE=TRUE	TP_PCI_AD_30	
PCI_AD<31>	MAKE_BASE=TRUE	TP_PCI_AD_31	
PCI_C_BE_L<0>	MAKE_BASE=TRUE	TP_PCI_C_BE_L_0	
PCI_C_BE_L<1>	MAKE_BASE=TRUE	TP_PCI_C_BE_L_1	
PCI_C_BE_L<2>	MAKE_BASE=TRUE	TP_PCI_C_BE_L_2	
PCI_C_BE_L<3>	MAKE_BASE=TRUE	TP_PCI_C_BE_L_3	
PCI_RST_L	MAKE_BASE=TRUE	TP_PCI_RST_L	
PCI_PAR	MAKE_BASE=TRUE	TP_PCI_PAR	

NO TEST DUE TO ROUTING

TP_LAN_D2R<2>		NO_TEST=TRUE
TP_CLINK_WLAN_DATA		NO_TEST=TRUE
PCI_SERR_L		NO_TEST=TRUE

Platform Reset Connections

Unbuffered



RE-PURPOSED GPIOS

SB_GPIO6	MAKE_BASE=TRUE	GPU_PRESENT

20_INCH_LCD



UNUSED GPIOS





SB Misc

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 28 OF 118	

www.laptop-schematics.com



FS_C	FS_B	FS_A	CPU MHz
0	0	0	(266.6)
0	0	1	133.3
0	1	0	200.0
0	1	1	166.6
1	0	0	(333.3)
1	0	1	100.0
1	1	0	(400.0)
1	1	1	RSVD

(Only 100-200MHz supported by SLG8LP536 and CY28545-5)

FCT_SEL	PIN 6	PIN 7	PIN 10	PIN 11	
0	DOT_96+	DOT_96-	LCD_CLK+	LCD_CLK-	(For Internal Graphics)
1	27M	27M w/SS	SRC_0+	SRC_0-	(For External Graphics)

www.laptop-schematics.com

Clock (CK505)

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 29 OF 118	

CK505 Configuration Straps

FCT_SEL (GFX clock select)



NOT USING 27 MHZ CLOCK FOR GPU

FS_A, FS_B, FS_C (Host clock freq select)







FS_C	FS_B	FS_A	CPU MHz
0	0	0	(266.6)
0	0	1	133.3
0	1	0	200.0
0	1	1	166.6
1	0	0	(333.3)
1	0	1	100.0
1	1	0	(400.0)
1	1	1	RSVD

NO STUFF R3082, R3086 & R3090
for manual CPU clk frequency.

CLK Termination

(Note: HOST/SRC/GFX clock termination kept on T9 for Cypress CY28545-5 compatibility)

105 29 IN CK505_CPU0_P — MAKE_BASE=TRUE — FSB_CLK_CPU_P OUT 7 10 105
105 29 IN CK505_CPU0_N — MAKE_BASE=TRUE — FSB_CLK_CPU_N OUT 7 10 105
(CPU HOST 167/200MHZ)

105 29 IN CK505_CPU1_P — MAKE_BASE=TRUE — FSB_CLK_NB_P OUT 7 14 105
105 29 IN CK505_CPU1_N — MAKE_BASE=TRUE — FSB_CLK_NB_N OUT 7 14 105
(GMCH HOST 167/200MHZ)

105 29 IN CK505_CPU2_ITP_SRC10_P — MAKE_BASE=TRUE — XDP_CLK_P OUT 13 100 105
105 29 IN CK505_CPU2_ITP_SRC10_N — MAKE_BASE=TRUE — XDP_CLK_N OUT 13 100 105
(ITP HOST 167/200MHZ)

105 29 IN CK505_LVDS_P — MAKE_BASE=TRUE — TP_CK505_LVDS_P
105 29 IN CK505_LVDS_N — MAKE_BASE=TRUE — TP_CK505_LVDS_N
(INT GFX LVDS 100MHZ - NOT USED)

105 29 IN CK505_SRC1_P — MAKE_BASE=TRUE — GPU_CLK100M_PCIE_P OUT 85 105
105 29 IN CK505_SRC1_N — MAKE_BASE=TRUE — GPU_CLK100M_PCIE_N OUT 85 105
(MXM PCIE 100MHZ)

105 29 IN CK505_SRC2_P — MAKE_BASE=TRUE — SB_CLK100M_DMI_P OUT 7 24 105
105 29 IN CK505_SRC2_N — MAKE_BASE=TRUE — SB_CLK100M_DMI_N OUT 7 24 105
(ICH8M DMI 100MHZ)

105 29 IN CK505_SRC3_P — MAKE_BASE=TRUE — PCIE_CLK100M_FW_P OUT 7 40 105
105 29 IN CK505_SRC3_N — MAKE_BASE=TRUE — PCIE_CLK100M_FW_N OUT 7 40 105
(FW PCIE 100MHZ)

105 29 IN CK505_SRC4_P — MAKE_BASE=TRUE — SB_CLK100M_SATA_P OUT 7 23 105
105 29 IN CK505_SRC4_N — MAKE_BASE=TRUE — SB_CLK100M_SATA_N OUT 7 23 105
(ICH8M SATA 100MHZ)

105 29 IN CK505_SRC5_P — MAKE_BASE=TRUE — NB_CLK100M_PCIE_P OUT 7 16 105
105 29 IN CK505_SRC5_N — MAKE_BASE=TRUE — NB_CLK100M_PCIE_N OUT 7 16 105
(GMCH PEG/DMI 100MHZ)

105 29 IN CK505_SRC6_P — MAKE_BASE=TRUE — PCIE_CLK100M_MINI_P OUT 34 105
105 29 IN CK505_SRC6_N — MAKE_BASE=TRUE — PCIE_CLK100M_MINI_N OUT 34 105
(WIRELESS PCIe MINI 100MHZ)

NO STUFF R3098 0
105 29 IN CK505_SRC7_P
105 29 IN CK505_SRC7_N
(INT GFX DOT 100MHZ - USED FOR DEBUG)

105 29 IN CK505_SRC8_P — MAKE_BASE=TRUE — PCIE_CLK100M_ENET_P OUT 7 37 105
105 29 IN CK505_SRC8_N — MAKE_BASE=TRUE — PCIE_CLK100M_ENET_N OUT 7 37 105
(Yukon PCIe 100MHZ)

105 29 IN CK505_DOT96_27M_P — MAKE_BASE=TRUE — TP_CK505_27M_P
105 29 IN CK505_DOT96_27M_N — MAKE_BASE=TRUE — TP_CK505_27M_N
(INT GFX DOT 96MHZ - NOT USED)

R3026 33
105 29 IN CK505_PCIF0_CLK_ITPEN — PCI_CLK33M_LPCPLUS OUT 7 51 105
(LINDA/LPC+ LPC 33MHZ)

R3027 33
105 29 IN CK505_PCIF1_CLK — PCI_CLK33M_SB OUT 7 24 105
(ICH8M PCI 33MHZ)

105 29 IN CK505_PCI1_CLK — MAKE_BASE=TRUE — TP_CK505_PCI1_CLK 7
(SPARE PCI 33MHZ)

105 29 IN CK505_PCI2_CLK — MAKE_BASE=TRUE — TP_PCI_CLK33M_TPM OUT
(TPM PCI 33MHZ)

R3030 33
105 29 IN CK505_PCI3_CLK — PCI_CLK33M_SMC OUT 7 49 105
(SMC PCI 33MHZ)

105 29 IN CK505_PCI4_CLK — MAKE_BASE=TRUE — TP_CK505_PCI4_CLK
(SPARE PCI 33MHZ)

CLKREQ Controls

Silego SL8GLP537 has internal
PULL-UPS ON ALL CLKREQ# PINS?

29 6 =PP3V3_S0M_CK505

NO STUFF R3050 10K
85 29 OUT CK505_CLKREQ1_L

NO STUFF R3051 10K
40 29 OUT CK505_CLKREQ3_L

NO STUFF R3052 10K
29 25 BI SB_SATA_CLKREQ_L

NO STUFF R3053 10K
29 16 BI NB_CLKREQ_L

NO STUFF R3054 10K
34 IN MINI_CLKREQ_L (MAKE_BASE=TRUE)
29 OUT CK505_CLKREQ6_L

NO STUFF R3055 10K
37 IN ENET_CLKREQ_L (MAKE_BASE=TRUE)
29 OUT CK505_CLKREQ8_L

NO STUFF R3046 10K
29 25 OUT PM_STPPCI_L

NO STUFF R3047 10K
29 25 OUT PM_STPCPU_L

Unused Clocks

29 IN CK505_REF1 — MAKE_BASE=TRUE — TP_CK505_REF1 7
(Spare 14.318MHZ)

www.laptop-schematics.com

Clock Termination

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE
II NOT TO REPRODUCE OR COPY IT
III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 30 OF 118	

Page Notes

Power aliases required by this page:
- =PP1V8_S3_MEM
- =PP0V9_S3_MEM_VREF
- =PPSPD_S0_MEM (2.5V - 3.3V)

Signal aliases required by this page:
- =I2C_MEM_SCL
- =I2C_MEM_SDA

BOM options provided by this page:
(NONE)

NOTE: This page does not supply VREF.
The reference voltage must be provided
by another page.





DDR2 Bypass Caps

(For return current)

DDR2 SO-DIMM Connector A

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A

SCALE: NONE

SHT 31 OF 118

www.laptopschematics.com

Page Notes

Power aliases required by this page:
- =PP1V8_S3_MEM
- =PP0V9_S3_MEM_VREF
- =PPSPD_S0_MEM (2.5V - 3.3V)

Signal aliases required by this page:
- =I2C_MEM_SCL
- =I2C_MEM_SDA

BOM options provided by this page:
(NONE)

NOTE: This page does not supply VREF.
The reference voltage must be provided
by another page.



DDR2 Bypass Caps

(For return current)

DDR2 SO-DIMM Connector B

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A

SCALE: NONE SHT 32 OF 118

www.laptopschematics.com

One cap for each side of every RPAK, one cap for every two discrete resistors

Ensure CS_L and ODT resistors are close to SO-DIMM connector



www.laptop-schematics.com

Memory Active Termination

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A

SCALE NONE SHT 33 OF 118

www.laptop-schematics.com

3.3V_S3_CURRENT	D0-D2_D3HOT	D3COLD
MAX CONT.	1100MA	250MA
MAX PEAK	2750MA	2750MA
1.5V_CURRENT		
MAX CONT.	375MA	N/A
MAX PEAK	500MA	N/A

NOTE: CURRENT DATA PER 5/16/2005 PCIE MINI CEM ECN

NO STUFF
R3400
0
5%
1/16W
MF-LF
402

NO STUFF
R3401
0
5%
1/16W
MF-LF
402

CRITICAL
J3400
ASOB226-S80N-7F
F-RT-SM

=PP3V3_S3_MINI 6

C3410 0.1uF 20% 10V CERM 402
C3420 0.1uF 20% 10V CERM 402
C3421 10uF 20% 6.3V X5R 603

PP1V05_S0 6 7 73

=PP1V5_S0_MINI 6

C3400 0.1uF 20% 10V CERM 402
C3401 10uF 20% 6.3V X5R 603

37 25 OUT PCIE_WAKE_L
RSVD_MINI_WLAN_ACTIVE
RSVD_MINI_BT_ACTIVE
30 OUT MINI_CLKREQ_L
105 30 IN PCIE_CLK100M_MINI_N
105 30 IN PCIE_CLK100M_MINI_P

104 24 7 OUT PCIE_MINI_D2R_N
104 24 7 OUT PCIE_MINI_D2R_P

PLACEMENT_NOTE=Place close to U2300.
C3431
0.1uF
10%
16V
X5R
402

104 24 IN PCIE_MINI_R2D_C_N

PLACEMENT_NOTE=Place close to U2300.
C3430
0.1uF
10%
16V
X5R
402

104 24 IN PCIE_MINI_R2D_C_P

104 PCIE_MINI_R2D_N
104 PCIE_MINI_R2D_P

RESERVED
RESERVED

MINI_RESET_L IN 28

=SMBUS_MINI_SCL IN 52
=SMBUS_MINI_SDA BI 52

USB_MINI_N BI 24 103
USB_MINI_P BI 24 103

NC
NC
NC

Page Notes

Power aliases required by this page:
- =PP3V3_ENET_PHY (EC / Ultra)
- =PP1V9R2V5_ENET_PHY (2.5V / 1.8V)

- =PP1V2_ENET_PHY

Signal aliases required by this page:
- =ENET_CLKREQ_L (NC/TP for Yukon EC)
- =ENET_VMAIN_AVLBL (See note by pin)

38 =PP1V2_ENET_PHY

Yukon Ultra

No link: 130 mA
10 Mbps: 130 mA
100 Mbps: 150 mA
1000 Mbps: 290 mA

NOSTUFF C3700 4.7UF 20% 6.3V CERM 603; C3701 C3702 C3703 C3704 C3705 C3706 C3707 C3708 1UF 10% 10V X5R 402

38 =PP3V3_ENET_PHY

Yukon Ultra

No link: 60 mA
10 Mbps: 70 mA
100 Mbps: 70 mA
1000 Mbps: 80 mA

NOSTUFF C3710 4.7UF 20% 6.3V CERM 603; C3711 C3712 C3713 C3714 C3715 1UF 10% 10V X5R 402

39 38 PP1V9_S3_ENET — R3720 0 5% 1/10W MF-LF 402 — 104 PP1V9_ENET_PHY_AVDD
MIN_LINE_WIDTH=0.4 mm
MIN_NECK_WIDTH=0.2 MM
VOLTAGE=1.8V

Yukon Ultra (1.8V)

No link: 0 mA
10 Mbps: 30 mA
100 Mbps: 40 mA
1000 Mbps: 150 mA

C3720 4.7UF 20% 6.3V CERM 603; C3721 C3722 C3723 C3724 1UF 10% 10V X5R 402

NC NC NC

YUKON 1.9V SUPPLY



YUKON 1.2 RAIL SUPPLY



YUKON T9 ALIASES

37 TP_YUKON_CTRL18	=	ENET_CTRL19 MAKE_BASE=TRUE	38
37 TP_YUKON_CTRL12	=	ENET_CTRL12 MAKE_BASE=TRUE	38
37 =ENET_VMAIN_AVLBL	=	=PP3V3_S0_ENET	6

YUKON/ULTRA SUPPORT

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 38 OF 118	

www.laptop-schematics.com



www.laptop-schematics.com

ETHERNET CONNECTOR

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A

SCALE	SHT	OF
NONE	39	118

www.laptop-schematics.com

=PP3V3_S5_FW 6 40 42 43
PP3V3_S5_FW_AVDD1 42
PP1V0_S5_FW_AVDD 42
PP3V3_S5_FW_AVDD2 42
=PP3V3_S5_FW 6 40 42 43
42 PP1V0_S5_FW_DVDD

A1 B1 B12 C13 E2 E10 H2 H12 K2 L1 M12 N3 N11 C1 C12 F1 G12 J1 L3 L11 M2 A12 D5 D6 D8 L5 L10 L6 L9 K12
VDD10 VDD33 VDDH VP VP25 VREG_PWR

CRITICAL
U4000
FW643
BGA
OMIT PCI EXPRESS PHY

NC B13 ATBUSB
NC A13 ATBUSH
NC A11 ATBUSN
42 FW_PHY_DS0 F12 DS0 NAND TREE PIN
42 FW_PHY_DS1 E12 DS1 NAND TREE PIN
42 FW_PHY_DS2 E13 DS2 NAND TREE PIN
43 FW_P0_TPA_N B8 TPA0N
43 FW_P0_TPA_P A8 TPA0P
43 FW_P1_TPA_N B5 TPA1N
43 FW_P1_TPA_P A5 TPA1P
43 FW_P2_TPA_N B3 TPA2N
43 FW_P2_TPA_P A3 TPA2P
43 FW_P0_TPB_N B9 TPB0N
43 FW_P0_TPB_P A9 TPB0P
43 FW_P1_TPB_N B6 TPB1N
43 FW_P1_TPB_P A6 TPB1P
43 FW_P2_TPB_N B4 TPB2N
43 FW_P2_TPB_P A4 TPB2P
43 FW_P0_TPBIAS B7 TPBIAS0
43 FW_P1_TPBIAS C3 TPBIAS1
43 FW_P2_TPBIAS A2 TPBIAS2
FW_R0 B11 R0
FW_TPCPS B10 TPCPS
7 TP_FW_NAND_TREE K1 NAND_TREE
FW_REXT L8 REXT
FW_XO F13 XO
FW_XI G13 XI NAND TREE PIN
7 TP_FW_SE M13 SE NAND TREE PIN(NOT IN -04)
7 TP_FW_SM N13 SM NAND TREE PIN(NOT IN -04)
PD INTERNAL TP_FW_MODE_A J2 MODE_A NAND TREE PIN
7 TP_FW_CE L13 CE NAND TREE PIN(-02)
PU INTERNAL TP_FW_FW620_L D12 FW620* NAND TREE PIN(-02) MISCELLANEOUS
TP_FW_JASI_EN D1 JASI_EN NAND TREE PIN
TP_FW_AVREG A10 AVREG
TP_FW_VBUF H13 VBUF
FW_PU_RST_L K13 FW_RESET* NAND TREE PIN
42 FW_OCR10_CTL J12 OCR_CTL_V10
NC J13 OCR_CTL_V12

B2 D4 D7 D9 D10 E4 E5 E9 F4 F6 F7 F8 F10 G4 G6 G7 G8 G10 H4 H6 H7 H8 H10 J4 J5 J9 J10 K4 K5 K7 K8 K9 L7 K6 K10 L12
VSS VREG_VSS

PCIE_RXD0N N8 PCIE_FW_R2D_N
PCIE_RXD0P N7 PCIE_FW_R2D_P
PCIE_TXD0N N5 PCIE_FW_D2R_C_N
PCIE_TXD0P N6 PCIE_FW_D2R_C_P
REFCLKN N9 PCIE_CLK100M_FW_N 7 30 105
REFCLKP N10 PCIE_CLK100M_FW_P 7 30 105

LAYOUT NOTE: PLACE C4010,C4011 CLOSE TO SOUTHBRIDGE(U2300)
C4010 0.1UF 10% 16V X5R 402 PCIE_FW_R2D_C_N 42 104
C4011 0.1UF 10% 16V X5R 402 PCIE_FW_R2D_C_P 42 104
C4020 0.1UF 10% 16V X5R 402 PCIE_FW_D2R_N 7 42 104
C4021 0.1UF 10% 16V X5R 402 PCIE_FW_D2R_P 7 42 104
LAYOUT NOTE: PLACE C4020,C4021 CLOSE TO FW643(U4000)

TEST CONTROLLER
NAND TREE PIN TCK M4 TP_FW_TCK 7
NAND TREE PIN TDI N2 TP_FW_TDI 7
TDO M1 TP_FW_TDO 7
NAND TREE PIN TMS M3 TP_FW_TMS 7
NAND TREE PIN(-04)TRST* N1 FW_TRST_L

1394 PHY
NAND TREE PIN WAKE* C2 PCI_PME_FW_L 25
FIXME!!! - TYPO IN SYMBOL REGCTL REGCLT D13 FW643_REGCTL
POWER MANAGEMENT NAND TREE PIN VAUX_DETECT E1 FW_VAUX_DETECT
NAND TREE PIN VAUX_DISABLE D2 TP_FW_VAUX_DISABLE
CLKREQN L2 CK505_CLKREQ3_L 29 30

SCIF
NAND TREE PIN SCIFCLK G2 TP_FW_SCIFCLK
NAND TREE PIN SCIFDAIN G1 TP_FW_SCIFDAIN
NAND TREE PIN SCIFDOUT H1 TP_FW_SCIFDOUT
NAND TREE PIN SCIFMC F2 TP_FW_SCIFMC

SERIAL EEPROM CONTROLLER
NAND TREE PIN SCL N12 FW_SCL
NAND TREE PIN SDA M11 TP_FW_SDA

CHIP RESET
NAND TREE PIN PERST* N4 FW_RESET_L 7 28

43 FW_PORTS_VP_R
R4001 390K 5% 1/16W MF-LF 402
R4002 2.94K 1% 1/16W MF-LF 402
R4080 191 1% 1/16W MF-LF 402
C4000 22PF 5% 50V CERM 402
C4001 22PF 5% 50V CERM 402
CRITICAL Y4000 24.576M HC49-USMD
R4000 412 1% 1/16W MF-LF 402
LAYOUT NOTE: PLACE Y4000 WITHIN 1.27CM OF XO/XI PINS
C4090 0.33UF 10% 6.3V CERM-X5R 402
R4090 470K 5% 1/16W MF-LF 402

NOSTUFF
R4010 10K 5% 1/16W MF-LF 402
=PP3V3_S5_FW 6 40 42 43
R4013 10K 5% 1/16W MF-LF 402
R4011 10K 5% 1/16W MF-LF 402
R4012 10K 5% 1/16W MF-LF 402

FW: 1394B CONTROLLER

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 40 OF 118	

FW643 1.0V GENERATION

RF CHOKE TO KEEP DIGITAL NOISE OFF ANALOG SUPPLY RAIL

USING THE SAME TRICK FOR FW AS FOR ETHERNET. DERIVED FROM MARVELL SCHEMATICS



1394 PHY DATA/STROBE OPTIONS



THERE ARE THREE FIREWIRE PORTS, BUT ONLY TWO ARE USED. THE PULL-UPS ASSERT/ENABLE DATA STROBE ONLY MODE, WHICH IS SYNONYMOUS TO LEGACY OR 1394-A. NOT ASSERTING THIS MEANS THAT THE PORT WILL OPERATE IN BILINGUALLY, SUPPORTING BETA (1394-B) AND LEGACY MODES. PULLING-UP THE UNUSED PORT SAVES A BIT OF POWER AS BETA TONING USES A CLOCK.

FW643 DECOUPLING

NOTE: PLACE 1 CAP CLOSE TO EACH POWER PIN ON U4000



FW 3.3V FILTERING



FW PCIE ALIASES



FW: 1394B MISC

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 42 OF 118	

www.laptop-schematics.com

www.laptop-schematics.com

=PP12V_S5_FW

12 VOLTS
7 WATTS MAX PER PORT

DE4300 SM CRS08

FW_PORTS_VP
MIN_LINE_WIDTH=1.7MM
MIN_NECK_WIDTH=0.25MM
VOLTAGE=33V

R4300 1.00 NOSTUFF / CRITICAL
R4302 0
R4301 1.00 NOSTUFF / CRITICAL
10% 1W MF 2512
5% 1/8W MF-LF 805

FW_PORTS_VP_R

CRITICAL F4300 0.75AMP-30V SM

FW_PORT0_VP_F
MIN_LINE_WIDTH=1.7MM
MIN_NECK_WIDTH=0.25MM
VOLTAGE=33V

CRITICAL L4300 FERR-250-OHM SM

SHOULD BE DONE AS A POWER STRIP(SUBPLANE)

FW_PORT0_VP
MIN_LINE_WIDTH=1.7MM
MIN_NECK_WIDTH=0.25MM
VOLTAGE=33V

C4300 0.01UF 10% 50V X7R 603-1

GND_CHASSIS_FIREWIRE

Termination
Place close to FireWire PHY

FW_P1_TPBIAS
VOLTAGE=1.86V
MIN_LINE_WIDTH=0.1MM
MIN_NECK_WIDTH=0.08MM

FW_P0_TPBIAS
VOLTAGE=1.86V
MIN_LINE_WIDTH=0.1MM
MIN_NECK_WIDTH=0.08MM

C4360 0.33UF 10% 6.3V CERM-X5R 402

C4350 0.33UF 10% 6.3V CERM-X5R 402

R4350 56.2 1% 1/10W MF-LF 402
R4351 56.2 1% 1/16W MF-LF 402
R4360 56.2 1% 1/16W MF-LF 402
R4361 56.2 1% 1/16W MF-LF 402

FW_P0_TPA_P — FW_PORT0_TPA_P
FW_P0_TPA_N — FW_PORT0_TPA_N
FW_P0_TPB_P — FW_PORT0_TPB_P
FW_P0_TPB_N — FW_PORT0_TPB_N
FW_P1_TPA_P — FW_PORT1_TPA_P
FW_P1_TPA_N — FW_PORT1_TPA_N
FW_P1_TPB_P — FW_PORT1_TPB_P
FW_P1_TPB_N — FW_PORT1_TPB_N
MAKE_BASE=TRUE

R4362 56.2 1% 1/16W MF-LF 402
R4363 56.2 1% 1/16W MF-LF 402

R4352 56.2 1% 1/16W MF-LF 402
R4353 56.2 1% 1/16W MF-LF 402

FW_P0_TPA_C
C4354 220PF 10% 25V CERM 402
R4354 4.99K 1% 1/16W MF-LF 402

FW_P1_TPA_C
C4364 220PF 10% 25V CERM 402
R4364 4.99K 1% 1/16W MF-LF 402

3rd TPA/TPB pair unused

FW_P2_TPBIAS — NC_FW_PORT2_TPBIAS
FW_P2_TPA_P — NC_FW_PORT2_TPA_P
FW_P2_TPA_N — NC_FW_PORT2_TPA_N
FW_P2_TPB_P — NC_FW_PORT2_TPB_P
FW_P2_TPB_N — NC_FW_PORT2_TPB_N
MAKE_BASE=TRUE
NO_TEST=TRUE

NOTE: AGERE'S RECOMMENDATION FOR UNUSED PORTS

ESD Rail

=PP3V3_S5_FW — R4390 332 1% 1/16W MF-LF 402 — PP3V3_FW_ESD
VOLTAGE=3.3V
MIN_LINE_WIDTH=0.38 mm
MIN_NECK_WIDTH=0.25 mm

CRITICAL D4390 SOT23 MMBZ5227B

[LATE VG NOTES]
CURRENT THROUGH THE BIAS RESISTOR SHOULD BE 5MA FOR A VOLTAGE DROP TO 2.2V
IT IS 2.2V INSTEAD OF 2.7V BECAUSE THE SNAPBACK ESD DIODES HAVE A .5V DROP

"Snapback" & "Late VG" Protection

PP3V3_FW_ESD

CRITICAL DP4310 BAV99DW-X-F SOT-363
C4310 0.01UF 10% 50V X7R 402
C4311 0.01UF 10% 50V X7R 402

CRITICAL DP4311 BAV99DW-X-F SOT-363
C4312 0.01UF 10% 50V X7R 402
C4313 0.01UF 10% 50V X7R 402

CRITICAL DP4320 BAV99DW-X-F SOT-363
C4320 0.01UF 10% 50V X7R 402
C4321 0.01UF 10% 50V X7R 402

CRITICAL DP4321 BAV99DW-X-F SOT-363
C4322 0.01UF 10% 50V X7R 402
C4323 0.01UF 10% 50V X7R 402

FW_PORT0_TPB_N
FW_PORT0_TPB_P
FW_PORT0_TPA_N
FW_PORT0_TPA_P
FW_PORT1_TPA_P
FW_PORT1_TPA_N
FW_PORT1_TPB_P
FW_PORT1_TPB_N

CRITICAL L4301 FERR-250-OHM SM

SHOULD BE DONE AS A POWER STRIP(SUBPLANE)

FW_PORT1_VP
MIN_LINE_WIDTH=1.7MM
MIN_NECK_WIDTH=0.25MM
VOLTAGE=33V

C4301 0.01UF 10% 50V X7R 603-1

GND_CHASSIS_FIREWIRE

CRITICAL FL4300 120-OHM L701-SM SYM_VER-1
CRITICAL FL4310 120-OHM L701-SM SYM_VER-1

FW_PORT1_TPA_FL_P
FW_PORT1_TPA_FL_N
FW_PORT1_TPB_FL_P
FW_PORT1_TPB_FL_N

PORT 0
1394B

CRITICAL J4300 1394B-M72 F-ANG-TH
514-0438

TPB-
TPB<R>
TPB+
VP
NC
VG
TPA-
TPA<R>
TPA+

FW_PORT0_TPA_R

NOSTUFF C4332 0.001UF 10% 16V CERM 402

R4335 1M 1% 1/16W MF-LF 402
C4335 0.1UF 10% 16V X7R 603-1

PORT 1
1394A

CRITICAL J4301 1394A-M72 F-ANG-TH
514-0398

TPA+
TPA-
TPB+
TPB-
VP
VGND

PART NUMBER	ALTERNATE FOR PART NUMBER	BOM OPTION	REF DES	COMMENTS:
155S0232	155S0289		FL4300,FL4310	ORIGINAL TOKO CHOKE

FIREWIRE CONNECTORS

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 43 OF 118	

CRITICAL
SDF4400
STDOFF-3.0OD4.0H-1.35-2.4-TH

IDE (ODD) Connector

www.laptop-schematics.com

44 6 =PP5V_S0_PATA
6 =PP3V3_S0_PATA

CRITICAL
J4401
804PVS-0502S5RG
M-ST-SM

R4403 100K 5% 1/16W MF-LF 402
R4451 4.7K Per ATA Spec
R4453 1K Obsolete
R4454 33K 5% 1/16W MF-LF 402

NC	1	2	NC
	3	4	NC
103 24 ODD_RST_5VTOL_L	5	6	IDE_PDD<8> 23 103
103 23 IDE_PDD<7>	7	8	IDE_PDD<9> 7 23 103
103 23 IDE_PDD<6>	9	10	IDE_PDD<10> 23 103
103 23 IDE_PDD<5>	11	12	IDE_PDD<11> 23 103
103 23 IDE_PDD<4>	13	14	IDE_PDD<12> 23 103
103 23 IDE_PDD<3>	15	16	IDE_PDD<13> 23 103
103 23 IDE_PDD<2>	17	18	IDE_PDD<14> 23 103
103 23 IDE_PDD<1>	19	20	IDE_PDD<15> 23 103
103 23 IDE_PDD<0>	21	22	
(UATA_STOP) 23 103 IDE_PDIOW_L	23	24	IDE_PDIOR_L 7 23 103 (UATA_HSTROBE)
(UATA_DSTROBE) 23 7 101 IDE_PDIORDY	25	26	IDE_PDDACK_L 23 103
103 23 IDE_IRQ14	27	28	IDE_IOCS16_PU NOTE: ATA-2, NOW OBSOLETE
103 23 IDE_PDA<1>	29	30	
103 23 IDE_PDA<0>	31	32	NC
(UATA_CS0*) 23 103 IDE_PDCS1_L	33	34	IDE_PDA<2> 23 103
IDE_DASP_L	35	36	IDE_PDCS3_L 23 103 (UATA_CS1*)
	37	38	
	39	40	
	41	42	
	43	44	
	45	46	
	47	48	
IDE_CSEL NC	49	50	SMC_ODD_DETECT 49
		52	

516S0583

NO STUFF
C4404 10pF 5% 50V CERM 402

C4405 0.1uF 20% 10V CERM 402
C4406 10UF 20% 10V 25R 805

103 23 IDE_PDDREQ

PLACE C4405-06 CLOSE TO J4401 FOR PP5V_S0_PATA.
APPLY A WIDE TRACE SHAPE FROM J4401 TO C4405-06.
MIN NECK & MIN LINE WIDTH ARE CONTROLLED BY PP5V_S0 1MM / 0.6MM.

44 6 =PP5V_S0_PATA

DEVELOPMENT
R4457 499 1% 1/16W 402 MF-LF

R4458 0 5% 1/16W MF-LF 402
R4459 6.2K 5% 1/16W MF-LF 402 PER ATA7 SPEC STUFFED PER LARRY

DEVELOPMENT
LED4400
GREEN-3.6MCD
2.0X1.25MM-SM
"IDE ACTIVE"

IDE_DASP_L_DS

CRITICAL
SDF4401
STDOFF-3.0OD4.0H-1.35-2.4-TH

www.laptop-schematics.com

PATA Connector

SYNC_MASTER=K3_MASTER SYNC_DATE=N/A

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE NONE	SHT 44 OF 118	

SATA Port A

CRITICAL
J4510
EP00-081-91
M-ST-SM

518S0251

SATA_A_R2D_P 103
SATA_A_R2D_N 103
SATA_A_D2R_C_N 103
SATA_A_D2R_C_P 103

C4510 0.0047uF 10% 25V CERM 402 — SATA_A_R2D_C_P — IN 23 103
C4511 0.0047uF 10% 25V CERM 402 — SATA_A_R2D_C_N — IN 23 103
C4515 0.0047uF 10% 25V CERM 402 — SATA_A_D2R_N — OUT 7 23 103
C4516 0.0047uF 10% 25V CERM 402 — SATA_A_D2R_P — OUT 7 23 103

SATA Activity LED

6 =PP3V3_S0_SATALED

DEVELOPMENT
R4599 1
330
5%
1/10W
MF-LF
603 2

SB_SATALED_R_L

DEVELOPMENT
DS4599 1
GREEN-3.6MCD
2.6X1.25MM-SM 2

SILK_PART=SATA ACTIVE

23 TP_SB_SATALED_L — SB_SATALED_L MAKE_BASE=TRUE
50 49 SMC_EXCARD_OC_L

UNUSED SATA PORTS

TP_SATA_B_R2D_P MAKE_BASE=TRUE — SATA_B_R2D_C_P 23 103
TP_SATA_B_R2D_N MAKE_BASE=TRUE — SATA_B_R2D_C_N 23 103

103 23 SATA_B_D2R_P — TP_SATA_B_D2R_P MAKE_BASE=TRUE
103 23 SATA_B_D2R_N — TP_SATA_B_D2R_N MAKE_BASE=TRUE

TP_SATA_C_R2D_P MAKE_BASE=TRUE — SATA_C_R2D_C_P 23
TP_SATA_C_R2D_N MAKE_BASE=TRUE — SATA_C_R2D_C_N 23

23 SATA_C_D2R_P — TP_SATA_C_D2R_P MAKE_BASE=TRUE
23 SATA_C_D2R_N — TP_SATA_C_D2R_N MAKE_BASE=TRUE

ICH SATA Support

23 SATA_RBIAS_P
23 SATA_RBIAS_N
— 103 SATA_RBIAS MAKE_BASE=TRUE

PLACEMENT_NOTE=Place R4590 within 12.7mm of U2300 pins AG1 & AG2

1 R4590
24.9
1%
1/16W
MF-LF
2 402

www.laptop-schematics.com

SATA Connectors

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE
II NOT TO REPRODUCE OR COPY IT
III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A

SCALE NONE — SHT 45 OF 118

USB/SMC DEBUG MUX



UNUSED EXTERNAL USB PORT(S)

PART NUMBER	ALTERNATE FOR PART NUMBER	BOM OPTION	REF DES	COMMENTS:
155S0232	155S0289		ALL	ORIGINAL TOKO CHOKE

EXTERNAL USB CONNECTORS

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 46 OF 118	

www.laptop-schematics.com

www.laptop-schematics.com

CAMERA POWER FILTERING

47 6 =PP5V_S3_BNDI

C4700 10UF 20% 6.3V CERM 805-1

CRITICAL
L4700 FERR-250-OHM SM

PP5V_S3_BNDI
VOLTAGE=5V
MIN_LINE_WIDTH=0.6MM
MIN_NECK_WIDTH=0.2MM
47

C4701 0.1UF 20% 10V CERM 402

LAYOUT NOTE:
PLACE C4700, C4701 & L4700
NEAR J4700 PINS 4 AND 5 IN THE
ORDER LISTED, AND NOT ON
BOTH SIDES OF THE PIN.

K37L (BLUETOOTH) CONNECTOR

CRITICAL
J4720 88262-0401 M-ST-SM

SB HAS INTERNAL 15K PULL-DOWNS

103 24 7 USB_BT_N
103 24 7 USB_BT_P
6 =PP3V3_S3_BT

C4720 10UF 20% 6.3V CERM 805-1

C4721 0.1UF 20% 10V CERM 402

CRITICAL
SDF4721 STDOFF-4.00D6.5H-1.35-2.4-TH

SDF4721_1

R4721 0 5% 1/16W MF-LF 402

CAMERA CONNECTOR

R4701 0 402
L4701 CRITICAL 120-OHM L701-SM
R4702 0 402

103 24 7 USB_CAMERA_P
103 24 7 USB_CAMERA_N

SB HAS INTERNAL 15K PULL-DOWNS
NOSTUFF

108 USB_CAMERA_L_P
108 USB_CAMERA_L_N
47 PP5V_S3_BNDI

FIXME!!! - THIS IS REISTECH CHOKE, T9 USES TOKO(155S0232)

R4710 0 402
L4710 CRITICAL 120-OHM L701-SM
R4711 0 402

103 24 7 USB_IR_N
103 24 7 USB_IR_P

SB HAS INTERNAL 15K PULL-DOWNS
NOSTUFF

USB_IR_L_N 47 108
USB_IR_L_P 47 108

CRITICAL
J4700 88262-0501 M-ST-SM

518S0553

47 CHASSIS_GND_BNDI

47 CHASSIS_GND_BNDI — MAKE_BASE=TRUE

UNUSED INTERNAL USB PORTS

103 24 USB_TPAD_N — TP_USB_TPAD_N MAKE_BASE=TRUE
103 24 USB_TPAD_P — TP_USB_TPAD_P MAKE_BASE=TRUE

SB HAS INTERNAL 15K PULL-DOWNS

103 24 USB_EXCARD_N — TP_USB_EXCARD_N MAKE_BASE=TRUE
103 24 USB_EXCARD_P — TP_USB_EXCARD_P MAKE_BASE=TRUE

SB HAS INTERNAL 15K PULL-DOWNS

IR RECEIVER

CRITICAL
J4780 88262-0401 M-ST-SM

108 47 USB_IR_L_N
108 47 USB_IR_L_P
47 6 =PP5V_S3_BNDI

C4781 1UF 10% 6.3V CERM 402

Internal USB Connections

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE
II NOT TO REPRODUCE OR COPY IT
III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 47 OF 118	

NOTE: Unused pins have "SMC_Pxx" names. Unused pins designed as outputs can be left floating, those designated as inputs require pull-ups.





NOTE: SMS Interrupt can be active high or low, rename net accordingly.
If SMS interrupt is not used, pull up to SMC rail.



SMC

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING
I TO MAINTAIN THE DOCUMENT IN CONFIDENCE
II NOT TO REPRODUCE OR COPY IT
III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 49 OF 118	

www.laptopschematics.com

SMC Reset Button / Brownout Detect



SMC Crystal Circuit



POWER BUTTON

SILK_PART=PWR BTN



SMC AVREF Supply



PART NUMBER	ALTERNATE FOR PART NUMBER	BOM OPTION	REF DES	COMMENTS:
353S1381	353S1278		ALL	Intersil ISL60002-33

UNUSED TP/NC ALIASES

SMC_BATT_ISET	NC_SMC_BATT_ISET	MAKE_BASE=TRUE	NO_TEST=TRUE
SMC_SYS_ISET	NC_SMC_SYS_ISET	MAKE_BASE=TRUE	NO_TEST=TRUE
SMC_BATT_VSET	NC_SMC_BATT_VSET	MAKE_BASE=TRUE	NO_TEST=TRUE
SMC_SYS_VSET	NC_SMC_SYS_VSET	MAKE_BASE=TRUE	NO_TEST=TRUE
SMC_BATT_TRICKLE_EN_L	NC_SMC_BATT_TRICKLE_EN_L	MAKE_BASE=TRUE	NO_TEST=TRUE
SMC_BATT_CHG_EN	NC_SMC_BATT_CHG_EN	MAKE_BASE=TRUE	NO_TEST=TRUE
SMS_X_AXIS	NC_SMS_X_AXIS	MAKE_BASE=TRUE	NO_TEST=TRUE
SMS_Y_AXIS	NC_SMS_Y_AXIS	MAKE_BASE=TRUE	NO_TEST=TRUE
SMS_Z_AXIS	NC_SMS_Z_AXIS	MAKE_BASE=TRUE	NO_TEST=TRUE
ALS_GAIN	NC_ALS_GAIN	MAKE_BASE=TRUE	NO_TEST=TRUE
ALS_LEFT	TP_ALS_LEFT	MAKE_BASE=TRUE	
ALS_RIGHT	TP_ALS_RIGHT	MAKE_BASE=TRUE	
SMC_P14	TP_SMC_P14	MAKE_BASE=TRUE	
SMC_P20	TP_SMC_P20	MAKE_BASE=TRUE	
SMC_P21	TP_SMC_P21	MAKE_BASE=TRUE	
SMC_P22	TP_SMC_P22	MAKE_BASE=TRUE	
SMC_P23	TP_SMC_P23	MAKE_BASE=TRUE	
SMC_P26	TP_SMC_P26	MAKE_BASE=TRUE	
SMC_P27	TP_SMC_P27	MAKE_BASE=TRUE	
SMC_P43	TP_SMC_P43	MAKE_BASE=TRUE	
SMC_P44	TP_SMC_P44	MAKE_BASE=TRUE	
SMC_P45	TP_SMC_P45	MAKE_BASE=TRUE	
SMC_P62	TP_SMC_P62	MAKE_BASE=TRUE	
SMC_P63	TP_SMC_P63	MAKE_BASE=TRUE	
SMC_P64	TP_SMC_P64	MAKE_BASE=TRUE	
SMC_P81	TP_SMC_P81	MAKE_BASE=TRUE	
SMC_PF0	TP_SMC_PF0	MAKE_BASE=TRUE	
SMC_PF1	TP_SMC_PF1	MAKE_BASE=TRUE	
SMC_FAN_3_CTL	TP_SMC_FAN_3_CTL	MAKE_BASE=TRUE	
SMC_FAN_3_TACH	TP_SMC_FAN_3_TACH	MAKE_BASE=TRUE	
SMC_PM_G2_EN	TP_SMC_PM_G2_EN	MAKE_BASE=TRUE	
SMC_ADAPTER_EN	TP_SMC_ADAPTER_EN	MAKE_BASE=TRUE	
SMC_SYS_KBDLED	TP_SMC_SYS_KBDLED	MAKE_BASE=TRUE	
SMC_SYS_LED	TP_SMC_SYS_LED	MAKE_BASE=TRUE	
SMC_EXCARD_PWR_EN	TP_SMC_EXCARD_PWR_EN	MAKE_BASE=TRUE	
SMC_RSTGATE_L	TP_SMC_RSTGATE_L	MAKE_BASE=TRUE	
SMS_ONOFF_L	TP_SMS_ONOFF_L	MAKE_BASE=TRUE	
SMC_P46	TP_SMC_P46	MAKE_BASE=TRUE	

ANALOG SENSORS

SMC_NB_1V8_ISENSE	NC_SMC_NB_1V8_ISENSE	MAKE_BASE=TRUE	NO_TEST=TRUE
SMC_NB_CORE_ISENSE	NC_SMC_NB_CORE_ISENSE	MAKE_BASE=TRUE	NO_TEST=TRUE
SMC_DCIN_ISENSE	SMC_12V_S0_ISENSE	MAKE_BASE=TRUE	53
SMC_PBUS_VSENSE	SMC_12V_S0_VSENSE	MAKE_BASE=TRUE	53
SMC_BATT_ISENSE	SMC_12V_S5_ISENSE	MAKE_BASE=TRUE	53
SMC_NB_1V25_ISENSE	SMC_12V_S5_VSENSE	MAKE_BASE=TRUE	53

SMC FSB to 3.3V Level Shifting



MISC. SIGNAL ALIASES

SMC_ANALOG_ID	ACDC_TEMP	MAKE_BASE=TRUE	6
SMC_SUS_CLK	SUS_CLK_SB	MAKE_BASE=TRUE	25
PM_LAN_PWRGD	ALL_SYS_PWRGD	MAKE_BASE=TRUE	7 49 70 84

=PP3V3_S5_SMC

SMC_ONOFF_L	R5032	10K	5%	1/16W	MF-LF	402		
SMC_LID	R5033	100K	5%	1/16W	MF-LF	402		
SMC_FWE	R5034	10K	5%	1/16W	MF-LF	402		
SMC_TX_L	R5035	10K	5%	1/16W	MF-LF	402		
SMC_RX_L	R5036	100K	5%	1/16W	MF-LF	402		
SYS_ONEWIRE	R5037	2.0K	5%	1/16W	MF-LF	402		
SMC_BS_ALRT_L	R5038	100K	5%	1/16W	MF-LF	402		
SMC_TMS	R5039	10K	5%	1/16W	MF-LF	402		
SMC_TDO	R5040	10K	5%	1/16W	MF-LF	402		
SMC_TDI	R5041	10K	5%	1/16W	MF-LF	402		
SMC_TCK	R5042	10K	5%	1/16W	MF-LF	402		
SMC_EXCARD_OC_L	R5043	10K	5%	1/16W	MF-LF	402	NO STUFF	
SMC_PF3	R5080	10K	5%	1/16W	MF-LF	402		
SMC_PH4	R5082	10K	5%	1/16W	MF-LF	402		
SMC_BC_ACOK	R5047	10K	5%	1/16W	MF-LF	402		
SMC_PA0	R5096	10K	5%	1/16W	MF-LF	402		
SMC_PA1	R5090	10K	5%	1/16W	MF-LF	402		
SMC_PB0	R5091	10K	5%	1/16W	MF-LF	402		
=SMC_SMS_INT — SMC_SMS_INT	R5092	10K	5%	1/16W	MF-LF	402		
SMC_P67	R5093	10K	5%	1/16W	MF-LF	402		
SMC_PG0	R5094	10K	5%	1/16W	MF-LF	402		
SMC_CASE_OPEN	R5046	10K	5%	1/16W	MF-LF	402		
SMC_EXCARD_CP	R5048	10K	5%	1/16W	MF-LF	402		
PM_SUS_STAT_L	R5083	100K	5%	1/16W	MF-LF	402		
PM_SLP_S5_L	R5084	100K	5%	1/16W	MF-LF	402		
ISENSE_CAL_EN	R5088	100K	5%	1/16W	MF-LF	402	NO STUFF	

www.laptop-schematics.com

SMC Support

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 50 OF 118	

www.laptop-schematics.com

LPC+ Connector



FWH_INIT_L Generation



www.laptop-schematics.com

LPC+ Debug Connector

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 51 OF 118	

ICH8-M SMBus Connections



SMC "0" SMBus Connections



SMC "A" SMBus Connections

NOTE: SMC RMT BUS REMAINS POWERED AND MAY BE ACTIVE IN S5 STATE



SMC "B" SMBus Connections



LM95214 QUAD DIODE SENSOR

DIODE	FUNCTION
1	HDD TEMP
2	ODD TEMP
3	CPU HEATSINK
4	GPU HEATSINK

UNUSED SMC "BATTERY A" SMBUS CONNECTIONS

UNUSED SMC "MANAGEMENT" SMBUS CONNECTIONS



UNUSED ICH8-M ME SMBUS CONNECTIONS



SMBUS CONNECTIONS

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 52 OF 118	

www.laptop-schematics.com

CPU POWER SENSE CALIBRATION CIRCUIT

Switches in fixed load on power supplies to calibrate current sense circuits

CPU Voltage Sense / Filter



CPU SUPPLY POWER SENSE FILTER



PCPU = VPMON / (17.5 * .0021)

MXM PWRSRC VOLTAGE SENSE

(SCALING 12V INPUT VOLTAGE TO SMC)



MXM PWRSRC (GPU CORE & MEM) CURRENT SENSE



K2 SET FOR APPROX 2V AT 4A ON PWRSRC

SCALE COUNT
2 A/V .0064453 A/COUNT
ADC IS 10BIT 0 TO 1023
0 TO 3.3V

K3 SET FOR APPROX 1.98V AT 5.5A ON PWRSRC

SCALE COUNT
2.778 A/V .0087518 A/COUNT
ADC IS 10BIT 0 TO 1023
0 TO 3.3V

PART#	QTY	DESCRIPTION	REFERENCE DESIGNATOR(S)	CRITICAL	BOM OPTION
107S0063	1	25 MILLIOHM	R5380	CRITICAL	20_INCH_LCD
107S0111	1	18 MILLIOHM	R5380	CRITICAL	24_INCH_LCD

12V RAILS CURRENT/VOLTAGE SENSE



ISENSE_CAL_EN_LS12V



PART#	QTY	DESCRIPTION	REFERENCE DESIGNATOR(S)	CRITICAL	BOM OPTION
107S0069	1	10 MILLIOHM	R5382	CRITICAL	K2_BETTER
107S0112	1	8 MILLIOHM	R5382	CRITICAL	24_INCH_LCD
107S0070	1	RES,0 OHM,2512	R5382	CRITICAL	K2_GOOD
107S0063	1	25 MILLIOHM	R5381	CRITICAL	12V_PWR_SENSE
107S0070	1	RES,0 OHM,2512	R5381	CRITICAL	K2_GOOD
116S0090	4	RES,10K0HM,5%,402	C5383,C5384,C5386,C5388		K2_GOOD
132S0080	4	CAP,22UF,20%,6.3V,X5R,402	C5383,C5384,C5386,C5388		12V_PWR_SENSE

12V_PWR_SENSE SHOULD BE STUFFED FOR K2 BETTER AND K3 (BEST/CTO)
K2 GOOD WILL NOT HAVE THE SENSORS, SO CAPS FROM THE RC FILTER BECOME RESISTORS TO GROUND (SO SMC READS 0)

K2 GOOD DOES NOT NEED 12V POWER SENSE BECAUSE THE CONFIGURATION DOES NOT DRAW CURRENT WHICH APPROACHES THE ACDC SPEC

Current & Voltage Sensing

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 53 OF 118	

www.laptop-schematics.com

www.laptop-schematics.com

AMBIENT TEMP SENSOR



LCD TEMP SENSOR



CPU T-Diode Thermal Sensor



UNUSED NB THERMAL SENSORS



REMOTE THERMAL SENSORS (HEATSINKS AND DISKS)

PLACE ALL CAPS NEAR U5500

PLACE DISK SENSOR CONNS BOTTOM SIDE

SILK_PART=HDD TEMP



SILK_PART=ODD TEMP



PLACE HSK SENSOR CONN. TOP SIDE NEAR GPU OR CPU

SILK_PART=CPU HSK



SILK_PART=GPU HSK



TO HELP POWER DELIVERY

74 73 7 6 PPMCH_CORE_S0

55 6 =PP3V3_S0_TSENS

BYPASS PER NATIONAL

PLACE C5503 CLOSEST TO U5500 PIN 2





PLACE ALL SHORTS AS CLOSE TO U5500 AS POSSIBLE

ROUTE DIODE SIGNALS AS DIFF PAIRS

Thermal Sensors		
SYNC_MASTER=K2_MLB	SYNC_DATE=01/08/2008	

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.	SIZE	DRAWING NUMBER	REV.
	D	051-7484	A
	SCALE: NONE	SHT 55 OF 118	

FAN 0



NOTE: ADDED TO PROTECT SMC

FAN 1



www.laptop-schematics.com

HD AND OD FAN

SYNC_MASTER=K3_MASTER SYNC_DATE=N/A

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A

SCALE	SHT	OF
NONE	56	118

FAN 2



www.laptop-schematics.com

www.laptop-schematics.com

www.laptop-schematics.com

CPU FAN

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 57 OF 118	

www.laptop-schematics.com



www.laptop-schematics.com

www.laptop-schematics.com

SPI BootROM

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 61 OF 118	

S5 POWER RAIL SEQUENCING



S3 POWER RAIL SEQUENCING



S0 POWER RAIL SEQUENCING



STARTUP (BOOT OR WAKE) TIMING



SHUT DOWN (SHUTDOWN OR SLEEP) TIMING



POWER SEQUENCING BLOCK DIAGRAM

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A

SCALE: NONE

SHT 69 OF 118

www.laptop-schematics.com

PGOOD Comparators

PP12V_S5 (76 75 53 7 6)
PP5V_S5 (78 77 76 70 7 6)
PP3V3_S0 (78 77 70 53 13 7 6)
PP1V8_S0 (78 7 6)
PP5V_S0 (94 78 74 73 72 71 7 6)
PP0V9_S0 (75 7 6)

C7010 0.1UF 20% 16V CERM 603

R7010 2.21K 1% 1/16W MF-LF 402
R7013 7.5K 1% 1/16W MF-LF 402
R7018 5.62K 1% 1/16W MF-LF 402
R7020 1.62K 1% 1/16W MF-LF 402
R7000 2.74K 1% 1/16W MF-LF 402
R7001 1.43K 1% 1/16W MF-LF 402
R7002 3.92K 1% 1/16W MF-LF 402
R7003 715 1% 1/16W MF-LF 402
R7011 1K 1% 1/16W MF-LF 402
R7014 10K 1% 1/16W MF-LF 402
R7019 1K 1% 1/16W MF-LF 402
R7021 10K 1% 1/16W MF-LF 402

CRITICAL
U7010 LM339A SOI-LF
V+ GND

(2.94V/2.61V; 330MV HYSTERESIS)
(1.58V/1.41V; 172MV HYSTERESIS)
(4.47V/4.00V; 470MV HYSTERESIS)
(0.76V/0.67V; 85MV HYSTERESIS)

-1 +1 5VS5_2V80_REF
-2 +2 3V3S0_COMP_REF
-3 +3 5VS5_1V53_REF
-4 +4 1V8S0_COMP_REF
5VS5_4V24_REF1
5VS0_COMP_REF
5VS5_0V76_REF
0V9S0_COMP_REF

R7005 100K 1% 1/16W MF-LF 402
R7006 100K 1% 1/16W MF-LF 402
R7007 100K 1% 1/16W MF-LF 402
R7008 100K 1% 1/16W MF-LF 402

PGOOD_3V3_S0 OUT (70)
PGOOD_1V8_S0 OUT (70)
PGOOD_5V_S0 OUT (70)
PGOOD_0V9_S0 OUT (70)

(PULLUPS ARE NEAR LOADS)

NOSTUFF C7000 0.1uF 20% 10V CERM 402
NOSTUFF C7001 0.1uF 20% 10V CERM 402
NOSTUFF C7002 0.1uF 20% 10V CERM 402
NOSTUFF C7003 0.1uF 20% 10V CERM 402

(HYSTERESIS)
(R7000: 20.5K; R7001: 17.4K; R7002: 24.9K; R7003: 8.25K) (200MV; 150MV; 300MV; 100MV HYSTERESIS)
(R7010: 21.5K; R7013: 7.15K; R7018: 52.3K; R7020: 1.37K) (200MV; 150MV; 300MV; 100MV HYSTERESIS)

1.05V/MCH_CORE S0 RUN/SS CONTROL

PP3V3_S5 (77 75 70 7 6)

R7070 5.1K 5% 1/16W MF-LF 402
R7040 0 5% 1/16W MF-LF 402
R7041 0 5% 1/16W MF-LF 402
R7065 100K 5% 1/16W MF-LF 402
R7066 330 5% 1/16W MF-LF 402

PGOOD_3V3_S0 IN (78)
PGOOD_CR_S0
PGOOD_12V_S0 IN (76)
1V05S0_RUNSS_BUF
1V05S0_RUNSS OUT (73 74)

Q7007 SSM6N15FE SOT563
RUNSS_GATE_D_L (70)

C7062 0.01UF 10% 16V CERM 402

1.25V S0 RUN/SS CONTROL

R7063 51K 5% 1/16W MF-LF 402
R7064 680 5% 1/16W MF-LF 402

1V25S0_RUNSS_BUF
1V25S0_RUNSS OUT (74)

Q7006 SSM6N15FE SOT563
RUNSS_GATE_D_L (70)

C7061 0.01UF 10% 16V CERM 402

1.5V S0 RUN/SS CONTROL

R7061 10K 5% 1/16W MF-LF 402
R7062 1K 5% 1/16W MF-LF 402

1V5S0_RUNSS_BUF
1V5S0_RUNSS OUT (73)

PP5V_S5 (78 77 76 70 7 6)
R7060 470K 5% 1/16W MF-LF 402
CRITICAL Q7007 SSM6N15FE SOT563
RUNSS_GATE_D_L (70)

CRITICAL Q7006 SSM6N15FE SOT563
PM_SLP_S3_L IN (78 75 49 25 7 6)

C7060 0.01UF 10% 16V CERM 402

(SUPPLY CHANGED FOR ROUTING)

PP5V_S3 (78 76 75 7 6)
PP3V3_S3 (78 76 75 7 6)

(REMOVE AFTER DEVELOPMENT, MAKE INTO TP)

R7080 100K 5% 1/16W MF-LF 402
R7081 100K 5% 1/16W MF-LF 402

PGOOD_1V8_S3 IN (75)
PGOOD_3V3_S3 IN (76)

PWROK Sequencing

PP3V3_S0 (78 77 70 53 13 7 6)
PP3V3_S5 (77 75 70 7 6)

R7034 5.1K 5% 1/16W MF-LF 402

(MC74VHC1G08 HAS 100NS/V MAX SLEW RATE)
(10PF MAX CIN)

C7052 0.1UF 20% 10V CERM 402
C7056 0.1UF 20% 10V CERM 402

R7030 100 5% 1/16W MF-LF 402
R7031 100 5% 1/16W MF-LF 402
R7032 100 5% 1/16W MF-LF 402

PGOOD_0V9_S0 IN (70)
PGOOD_5V_S0 IN (70)
PGOOD_1V8_S0 IN (70)

PGOOD_S0_OUT1

U7052 MC74VHC1G08 SOT23-5-LF
ALL_SYS_PWRGD OUT (7 49 50 84)

U7056 MC74VHC1G08 SOT23-5-LF
VR_PWRGOOD_DELAY IN (71 22 16 7)
PM_SB_PWROK OUT (7 25 28)

(NOT ALL PGOODS ARE NEEDED HERE SINCE
(SOME REGULATORS ARE DAISY CHAIN ENABLED)

R7039 5.1K 5% 1/16W MF-LF 402
R7035 100 5% 1/16W MF-LF 402
R7036 100 5% 1/16W MF-LF 402
R7037 100 5% 1/16W MF-LF 402
R7038 100 5% 1/16W MF-LF 402

PGOOD_MCH_CORE_S0 IN (74)
PGOOD_1V05_S0 IN (73)
PGOOD_1V25_S0 IN (74)
PGOOD_1V5_S0 IN (73)

IMVP_PGD_IN

R7092 10K 5% 1/16W MF-LF 402

(3.3V WILL NOT BE UP UNTIL 5V IS IN REGULATION)
(SMC CAN HANDLE SLOW RISE TIME OF RSMRST_PWRGD)

PGOOD_3V3_S5 IN (77)
RSMRST_PWRGD OUT (49)
MAKE_BASE=TRUE

NOSTUFF C7090 220PF 5% 25V CERM 402

www.laptop-schematics.com

PGOOD and Power Sequencing

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE
II NOT TO REPRODUCE OR COPY IT
III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 70 OF 118	



DPRSLPVR	DPRSTP*	PSI*	Operation	Mode
0	1	1	3/2-PHASE	CCM
0	1	0	2/1-PHASE	CCM
1	0	1	3/2-PHASE	DCM
1	0	0	2/1-PHASE	DCM

SYNC_MASTER=K2_MLB	SYNC_DATE=01/08/2008
SIZE	D
DRAWING NUMBER	051-7484
REV.	A
SCALE	NONE
SHT	71
OF	118

www.laptop-schematics.com

IMVP6 CPU VCORE REGULATOR



www.laptop-schematics.com

NO TEST FOR CPU VREG, ADDED K2/K3

IMVP6_VO1	NO_TEST=TRUE	
IMVP6_VO2	NO_TEST=TRUE	
IMVP6_VO3	NO_TEST=TRUE	
IMVP6_VSUM1	NO_TEST=TRUE	
IMVP6_VSUM2	NO_TEST=TRUE	
IMVP6_VSUM3	NO_TEST=TRUE	

IMVP6_PWM3	MIN_LINE_WIDTH=0.25 MM	MIN_NECK_WIDTH=0.23 MM	T51
IMVP6_PHASE3	MIN_LINE_WIDTH=1.5 MM	MIN_NECK_WIDTH=0.25 MM	T45
IMVP6_BOOT3	MIN_LINE_WIDTH=0.25 MM	MIN_NECK_WIDTH=0.25 MM	T44
IMVP6_UGATE3	MIN_LINE_WIDTH=0.5 MM	MIN_NECK_WIDTH=0.25 MM	T46
IMVP6_LGATE3	MIN_LINE_WIDTH=0.5 MM	MIN_NECK_WIDTH=0.25 MM	T48
IMVP6_ISEN3	MIN_LINE_WIDTH=0.25 MM	MIN_NECK_WIDTH=0.23 MM	T49
IMVP6_FET_RC3	MIN_LINE_WIDTH=0.25 MM	MIN_NECK_WIDTH=0.25 MM	T47
IMVP6_VSUM3	MIN_LINE_WIDTH=0.25 MM	MIN_NECK_WIDTH=0.25 MM	T43
IMVP6_VO3	MIN_LINE_WIDTH=0.25 MM	MIN_NECK_WIDTH=0.25 MM	T50
IMVP6_BOOT3_RC	MIN_LINE_WIDTH=0.25 MM	MIN_NECK_WIDTH=0.25 MM	T52

IMVP6 3RD PHASE

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 72 OF 118	

1.5V S0 & 1.05V SO RAILS

www.laptop-schematics.com

PP12V_S0
PP5V_S0
PP1V5_S0 (1.512V NOMINAL)
1.5V S0 M72778 POWER BUDGET PEAK=2.77A AVE=2.45A
1.05V S0 M72/M78 POWER BUDGET PEAK=3.43A AVE=3.03A
1.05V NOMINAL PP1V05_S0
VCC U7300 ISL6539 SSOP (300KHZ) CRITICAL
1V5REG_SOFT
1V5REG_BOOT
1V5REG_UGATE
1V5REG_ISEN
1V5REG_LGATE
1V5REG_SWITCHNODE
1V5REG_SNUBBER_R
1V5REG_OCSET
1V5S0_RUNSS (200MV HYSTERESIS)
PGOOD_1V5_S0 (3MS NOISE FILTER)
1V05REG_BOOT_R
1V05REG_SOFT
1V05REG_UGATE
1V05REG_ISEN
1V05REG_LGATE
1V05REG_SWITCHNODE
1V05S0_RUNSS (200MV HYSTERESIS)
PGOOD_1V05_S0 (3MS NOISE FILTER)
1V05REG_OCSET
1V05S0_EN
1V5REG_VSEN
1V05REG_VSEN
GND_PP1V5REG_SGND
VOUT = 0.9V * (RA + RB) / RB
PLANE SHORTING RESISTORS
PP1V05_S0
PPMCH_CORE_S0

www.laptop-schematics.com

1.5V / 1.05V SUPPLIES

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 73 OF 118	

1.25V S0 & MCH CORE RAILS



PART NUMBER	QTY	DESCRIPTION	REFERENCE DES	CRITICAL	BOM OPTION
114S0342	1	RES,MTL FILM,1/16W,19.6K,1,0402,SMD,LF	R7491		CR_STD
114S0309	1	RES,MTL FILM,1/16W,8.66K,1,0402,SMD,LF	R7491		CR_E

www.laptop-schematics.com

1.25V / MCH CORE SUPPLIES

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A

SCALE: NONE

SHT 74 OF 118

1.8V S3 / MEM VTT RAILS

PP12V_S5
C7547 1000PF 10% 25V X7R 402
C7501 1UF 10% 10V X5R 603
CRITICAL C7532 470UF 20% 16V POLY TH
CRITICAL C7530 470UF 20% 16V POLY TH
C7533 10UF 10% 25V X5R 1206-1
C7534 10UF 10% 25V X5R 1206-1
C7531 1UF 10% 10V X5R 603

PP5V_S3
PP3V3_S5
C7560 0.1UF 20% 10V CERM 402
CRITICAL U7501 74LVC1G07 SC70
NOSTUFF R7504 0 5% 1/16W MF-LF 402
PP3V3_S3 R7539 10K 5% 1/16W MF-LF 402
PM_S4_STATE_L (OPEN_DRAIN)
(FOR POWER DOWN SEQUENCING)
(NC)

1V8S3_VCC
C7502 2.2UF 20% 6.3V CERM1 603
NOSTUFF R7507 0 5% 1/16W MF-LF 402
C7500 2.2UF 20% 6.3V CERM1 603

GND_PP1V8REG_SGND

CRITICAL U7500 ISL6269 QFN
VIN, FSET, EN, FCCM, PGOOD, COMP, FB, VO, PVCC, VCC, UG, BOOT, PHASE, ISEN, LG, PGND, THRML PAD 17

1V8S3_FSET
(200MV_HYSTERESIS) 1V8S3_EN
1V8S3_FCCM
PGOOD_1V8_S3
(2.75MS BETWEEN ENABLE GOING HIGH AND PGOOD GOING HIGH)
1V8S3_COMP
1V8S3_FB
1V8S3_UG
1V8S3_BOOT
1V8S3_PHASE
1V8S3_ISEN
1V8S3_LG

R7505 0 5% 1/16W MF-LF 402
R7508 90.9K 1% 1/16W MF-LF 402
1V8S3_COMP_R
C7506 0.01UF 10% 16V CERM 402
R7506 57.6K 1% 1/16W MF-LF 402
C7508 4700PF 10% 50V CERM 603
C7507 22PF 5% 50V CERM 402

OMIT XW7500 SM
NOSTUFF C7510 0.001UF 10% 50V CERM 402

R7500 2.2 5% 1/16W MF-LF 402
1V8S3_BOOT_RC
C7509 0.1UF 10% 25V X5R 402

CRITICAL Q7520 FDMS8690-RJK0305DPB MLP5X6-LFPAK
CRITICAL Q7521 FDSM8660S-RJK0301DPB MLP5X6-LFPAK

R7510 3.92K 1% 1/16W MF-LF 402

D7520 CTLSH3-30M833 TLM833
NOSTUFF

CRITICAL L7580 1.5UH-19A-5.5MOHM DCR=5.5 MOHM IHLP5050-MMD12CE-SM
NOSTUFF R7556 5.11 1% 1/4W MF-LF 1206
1V8S3_SNUBBER_R
NOSTUFF C7564 1000PF 10% 25V X7R 402

C7545 1000PF 10% 25V X7R 402
C7540 22UF 20% 6.3V CERM 805
C7541 22UF 20% 6.3V CERM 805
CRITICAL C7543 330UF 20% 2V POLY CASE-D2-SM
CRITICAL C7542 330UF 20% 2V POLY CASE-D2-SM
CRITICAL C7544 330UF 20% 2V POLY CASE-D2-SM

1.8V S3
M727/M78
POWER BUDGET
PEAK=13.6A
AVE=5.17A

(1.8V_S3 MUST RAMP UP IN < 2 MS)

NOSTUFF R7501 0 5% 1/16W MF-LF 402
PP1V8_S3_R
<Ra> R7521 4.02K 1% 1/16W MF-LF 402
NOSTUFF C7503 0.0047UF 10% 16V CERM 402
<Rb> R7522 2.0K 1% 1/16W MF-LF 402
PP1V8_S3

Vout = 0.6V * (1 + Ra / Rb)

DDR2 Vtt Regulator

=PP5V_S3_MEMVTT
C7550 1uF 10% 6.3V CERM 402
=PP1V8_S3_MEMVTT
R7551 220 5% 1/10W MF-LF 402
U7550_VDDQ
C7559 2.2UF 10% 6.3V CERM1 603
VOLTAGE=1.8V MIN_LINE_WIDTH=0.25 MM MIN_NECK_WIDTH=0.25 mm
CRITICAL U7550 BD3533FVM MSOP-8
VDDQ, VCC, VTT_IN, VREF, EN, VTTS, GND
MEMVTT_VREF
PM_SLP_S3_L
C7551 10UF 20% 6.3V CERM 805-1
C7553 0.1UF 20% 10V CERM 402
C7552 10UF 20% 6.3V CERM 805-1
If power inputs are not S0, MEMVTT_EN can be used to disable MEMVTT in sleep.
?Can 5V be S0 if 1V8 is S3?
PP0V9_S0
CRITICAL C7555 150UF 20% 6.3V POLY CASE-C3

EMC REQUESTED CAPS

PP1V8_S3
C7595 0.01UF 10% 50V X7R 402
C7596 0.01UF 10% 50V X7R 402
C7597 0.01UF 10% 50V X7R 402
C7598 0.01UF 10% 50V X7R 402
C7599 0.01UF 10% 50V X7R 402
C7590 0.01UF 10% 50V X7R 402
C7591 0.01UF 10% 50V X7R 402
C7592 0.01UF 10% 50V X7R 402
C7593 0.01UF 10% 50V X7R 402
C7594 0.01UF 10% 50V X7R 402
C7585 0.01UF 10% 50V X7R 402
C7586 0.01UF 10% 50V X7R 402
C7587 0.01UF 10% 50V X7R 402
C7588 0.01UF 10% 50V X7R 402
C7589 0.01UF 10% 50V X7R 402

www.laptop-schematics.com

1.8V S3 /0.9V S0 SUPPLIES
SYNC_MASTER=K3_MASTER SYNC_DATE=N/A

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING
I TO MAINTAIN THE DOCUMENT IN CONFIDENCE
II NOT TO REPRODUCE OR COPY IT
III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.
SIZE D | DRAWING NUMBER 051-7484 | REV. A
SCALE NONE | SHT 75 OF 118

5V S5 & 3.3V S3 RAILS

www.laptop-schematics.com

5V S5 / 3.3V S3 SUPPLIES

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 76 OF 118	

5V S5
M72/M78
POWER BUDGET
M72 PEAK=12.0A
M72 AVE=6.83A
M78 PEAK=8.91A
M78 AVE=5.33A

3.3V S3
M72/78
POWER BUDGET
PEAK=6.06A
AVE=3.06A

3.3V S5 RAIL



2.5V S0 RAIL (LDO)



State	Manageability	SMC_PM_G2_ENABLE	PM_S4_STATE_L	PM_SLP_S3_L	PM_SLP_S4_L	PM_SLP_M_L
Run (S0/M0)	N/A	1	1	1	1	1
Sleep (S3/M1)	On	1	1	0	1	1
Soft-Off (S5/M1)	On	1	0	0	1	1
Sleep (S3/M-Off)	Off	1	1	0	1	0
Soft-Off (S5/M-Off)	Off	1	0	0	0	0
Battery Off (G3Hot)	N/A	0	0	0	0	0

3.3V / 2.5V POWER SUPPLIES

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 77 OF 118	

www.laptop-schematics.com









	I	Rds(on)	Vgs +/-
IRF7410	13A	7mOHM	8V
IRF7413	9.6A	18mOHM	20V
FDS4435	8.8A	35mOHM	25V
IRF7406	5.8A	70mOHM	20V
IRF6402	3.7A	65mOHM	12V
SI2302	1.6A	115mOHM	8V

S3 & S0 FETs

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 78 OF 118	

www.laptop-schematics.com

Page Notes

Power aliases required by this page:
- =PP12V_S0_MXM
- =PP5V_S0_MXM
- =PP1V8_S0_MXM

Signal aliases required by this page:
(NONE)

BOM options provided by this page:
(NONE)

Note: PCI-E Lanes are reversed to untangle routes
Need to stuff config strap using BOM option NBCFG_PEG_REVERSE
Polarity is also inverted (Tx+ goes to Rx-) to untangle routes

MXM SPEC POWER REQUIREMENTS
(NOT NECESSARILY THE SAME FOR EVERY MODULE)

VOLTAGE	CURRENT	POWER
3V3	1.5 A	4.95 W
5V	0.5 A	2.5 W
2V5	0.5 A	1.25 W
1V8	3.5 A	6.3 W
PWR (12V)	UP TO 4 A	PLATFORM DEPENDENT

www.laptop-schematics.com

APPLE P/N: 516S0562

J8400
AS0B52X-S43E-XF
F-RT-SM
(1 OF 2)
CRITICAL

6 =PP1V8_S0_MXM
6 =PP5V_S0_MXM
70 50 49 7 ALL_SYS_PWRGD

C8410 1000PF 10% 25V X7R 402
C8401 22UF 20% 6.3V CERM 805
C8411 1000PF 10% 25V X7R 402
C8400 22UF 20% 35V ELEC SM-LF
C8412 1000PF 10% 25V X7R 402
C8413 1000PF 10% 25V X7R 402
C8414 1000PF 10% 25V X7R 402
C8415 1000PF 10% 25V X7R 402
C8416 1000PF 10% 25V X7R 402

PPV_S0_MXM_PWRSRC 53
VOLTAGE=12V
MIN_LINE_WIDTH=0.60MM
MIN_NECK_WIDTH=0.25MM

(FOR ROUTING EASE ON M72/M78
(POLARITY REVERSED FOR LANES 4,7,14)

PLACE CAPS NEAR NB

PRSNT2_L: RESERVED FOR FUTURE USE

2	1V8RUN0	PWR_SRC0	1				
4	1V8RUN1	PWR_SRC1	3				
6	1V8RUN2	PWR_SRC2	5				
8	1V8RUN3	PWR_SRC3	7				
10	1V8RUN4	PWR_SRC4	9				
12	1V8RUN5	PWR_SRC5	11				
14	1V8RUN6	PWR_SRC6	13				
16	RUNPWROK	PWR_SRC7	15				
18	5VRUN	GND0	17				
20	GND20	GND1	19				
22	GND21	GND2	21				
24	GND22	GND3	23				
	KEY						
38	PRSNT2_L	PEX_RX15_L	37	PEG_R2D_C_P<0>	C8420	0.1uF	PEG_D2R_N<0>
40	PEX_TX15_L	PEX_RX15	39	PEG_R2D_C_N<0>	C8421	0.1uF	PEG_D2R_P<0>
42	PEX_TX15	GND4	41				
44	GND23	PEX_RX14_L	43	PEG_R2D_C_P<1>	C8422	0.1uF	PEG_D2R_N<1>
46	PEX_TX14_L	PEX_RX14	45	PEG_R2D_C_N<1>	C8423	0.1uF	PEG_D2R_P<1>
48	PEX_TX14	GND5	47				
50	GND24	PEX_RX13_L	49	PEG_R2D_C_P<2>	C8424	0.1uF	PEG_D2R_N<2>
52	PEX_TX13_L	PEX_RX13	51	PEG_R2D_C_N<2>	C8425	0.1uF	PEG_D2R_P<2>
54	PEX_TX13	GND6	53				
56	GND25	PEX_RX12_L	55	PEG_R2D_C_P<3>	C8426	0.1uF	PEG_D2R_P<3>
58	PEX_TX12_L	PEX_RX12	57	PEG_R2D_C_N<3>	C8427	0.1uF	PEG_D2R_N<3>
60	PEX_TX12	GND7	59				
62	GND26	PEX_RX11_L	61	PEG_R2D_C_N<4>	C8428	0.1uF	PEG_D2R_P<4>
64	PEX_TX11_L	PEX_RX11	63	PEG_R2D_C_P<4>	C8429	0.1uF	PEG_D2R_N<4>
66	PEX_TX11	GND8	65				
68	GND27	PEX_RX10_L	67	PEG_R2D_C_P<5>	C8430	0.1uF	PEG_D2R_P<5>
70	PEX_TX10_L	PEX_RX10	69	PEG_R2D_C_N<5>	C8431	0.1uF	PEG_D2R_N<5>
72	PEX_TX10	GND9	71				
74	GND28	PEX_RX9_L	73	PEG_R2D_C_P<6>	C8432	0.1uF	PEG_D2R_P<6>
76	PEX_TX9_L	PEX_RX9	75	PEG_R2D_C_N<6>	C8433	0.1uF	PEG_D2R_N<6>
78	PEX_TX9	GND10	77				
80	GND29	PEX_RX8_L	79	PEG_R2D_C_N<7>	C8434	0.1uF	PEG_D2R_P<7>
82	PEX_TX8_L	PEX_RX8	81	PEG_R2D_C_P<7>	C8435	0.1uF	PEG_D2R_N<7>
84	PEX_TX8	GND11	83				
86	GND30	PEX_RX7_L	85	PEG_R2D_C_P<8>	C8436	0.1uF	PEG_D2R_P<8>
88	PEX_TX7_L	PEX_RX7	87	PEG_R2D_C_N<8>	C8437	0.1uF	PEG_D2R_N<8>
90	PEX_TX7	GND12	89				
92	GND31	PEX_RX6_L	91	PEG_R2D_C_P<9>	C8438	0.1uF	PEG_D2R_P<9>
94	PEX_TX6_L	PEX_RX6	93	PEG_R2D_C_N<9>	C8439	0.1uF	PEG_D2R_N<9>
96	PEX_TX6	GND13	95				
98	GND32	PEX_RX5_L	97	PEG_R2D_C_P<10>	C8440	0.1uF	PEG_D2R_P<10>
100	PEX_TX5_L	PEX_RX5	99	PEG_R2D_C_N<10>	C8441	0.1uF	PEG_D2R_N<10>
102	PEX_TX5	GND14	101				
104	GND33	PEX_RX4_L	103	PEG_R2D_C_P<11>	C8442	0.1uF	PEG_D2R_P<11>
106	PEX_TX4_L	PEX_RX4	105	PEG_R2D_C_N<11>	C8443	0.1uF	PEG_D2R_N<11>
108	PEX_TX4	GND15	107				
110	GND34	PEX_RX3_L	109	PEG_R2D_C_P<12>	C8444	0.1uF	PEG_D2R_P<12>
112	PEX_TX3_L	PEX_RX3	111	PEG_R2D_C_N<12>	C8445	0.1uF	PEG_D2R_N<12>
114	PEX_TX3	GND16	113				
116	GND35	PEX_RX2_L	115	PEG_R2D_C_P<13>	C8446	0.1uF	PEG_D2R_P<13>
118	PEX_TX2_L	PEX_RX2	117	PEG_R2D_C_N<13>	C8447	0.1uF	PEG_D2R_N<13>
120	PEX_TX2	GND17	119				
122	GND36	PEX_RX1_L	121	PEG_R2D_C_N<14>	C8448	0.1uF	PEG_D2R_P<14>
124	PEX_TX1_L	PEX_RX1	123	PEG_R2D_C_P<14>	C8449	0.1uF	PEG_D2R_N<14>
126	PEX_TX1	GND18	125				
128	GND37	PEX_RX0_L	127	PEG_R2D_C_P<15>	C8450	0.1uF	PEG_D2R_P<15>
130	PEX_TX0_L	PEX_RX0	129	PEG_R2D_C_N<15>	C8451	0.1uF	PEG_D2R_N<15>
132	PEX_TX0	GND19	131				

(FOR ROUTING EASE ON M72/M78
(POLARITY REVERSED FOR LANES 0-2)

www.laptop-schematics.com

MXM PCI-E & PWR

SYNC_MASTER=K3_MASTER SYNC_DATE=N/A

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING
I TO MAINTAIN THE DOCUMENT IN CONFIDENCE
II NOT TO REPRODUCE OR COPY IT
III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 84 OF 118	

Page Notes

Power aliases required by this page:
- =PP3V3_S0_MXM
- =PP2V5_S0_MXM

Signal aliases required by this page:
- =SMB_GPU_THRM_DATA
- =SMB_GPU_THRM_CLK

BOM options provided by this page:
24_INCH_LCD

MXM SPEC POWER REQUIREMENTS

(NOT NECESSARILY THE SAME FOR EVERY MODULE)

VOLTAGE	CURRENT	POWER
3V3	1.5 A	4.95 W
5V	0.5 A	2.5 W
2V5	0.5 A	1.25 W
1V8	3.5 A	6.3 W
PWR (12V)	UP TO 4 A	PLATFORM DEPENDENT

MXM SYSTEM INFORMATION ROM

PLACE CLOSE TO J8400

=PP3V3_S0_MXM 6 85

MXM_ROM
C8570
0.1UF
20%
10V
CERM
402

STUFF FOR WRITE PROTECT
NOSTUFF
R8570
0
5%
1/16W
MF-LF
402

I2C ADDRESS: AC

U8570
M24C02-WMN6
S08

VCC
E2/NC2
E1/NC1 CRITICAL
E0/NC0 OMIT
WC*
SDA
SCL
VSS

MXM_ROM_WP

GPU_DDC_C_DATA 85 90
GPU_DDC_C_CLK 85 90

J8400
AS0B52X-S43E-XF
F-RT-SM
(2 OF 2)

85 6 =PP3V3_S0_MXM
NOSTUFF
R8500
100K
5%
1/16W
MF-LF
402

30 29 CK505_CLKREQ1_L
28 PEG_RESET_L

85 6 =PP3V3_S0_MXM
R8502
100K
5%
1/16W
49 SMC_GFX_OVERTEMP_L

52 =SMB_GPU_THRM_SDA
52 =SMB_GPU_THRM_SCL

108 91 GPU_H2SYNC
108 91 GPU_V2SYNC
94 GPU_DDC_A_CLK
94 GPU_DDC_A_DATA
EXT. DVI/VGA

49 SMC_GFX_THROTTLE_L
10K PD ON MXM

94 GPU_HPD
108 94 TMDS_CLK_N
108 94 TMDS_CLK_P
108 94 TMDS_DATA_N<2>
108 94 TMDS_DATA_P<2>
108 94 TMDS_DATA_N<1>
108 94 TMDS_DATA_P<1>
108 94 TMDS_DATA_N<0>
108 94 TMDS_DATA_P<0>

105 30 GPU_CLK100M_PCIE_N	133	PEX_REFCLK_L	
105 30 GPU_CLK100M_PCIE_P	135	PEX_REFCLK	
	137	CLK_REQ_L	
	139	PEX_RST_L	
	141	RSVD0	
	143	RSVD1	
	145	SMB_DAT	
	147	SMB_CLK	
	149	THERM_L	
	151	VGA_HSYNC	
	153	VGA_VSYNC	
	155	DDCA_CLK	
	157	DDCA_DAT	
	159	IGP0	
	161	IGP1	
	163	IGP2	
	165	RSVD2	
	167	RSVD3	
	169	AC_BATT_L	
	171	IGP3	
	173	IGP4	
	175	IGP5	
	177	IGP6	
	179	IGP7	
	181	IGP8	
	183	IGP9	
	185	IGP10	
	187	GND38	
	189	IGP_DVI_B_CLK_L	
	191	IGP_DVI_B_CLK	
	193	DVI_B_HPD_GND	
	195	RSVD4	
	197	RSVD5	
	199	GND39	
	201	IGP_DVI_B_TX2_L	
	203	IGP_DVI_B_TX2	
	205	GND40	
	207	IGP_DVI_B_TX1_L	
	209	IGP_DVI_B_TX1	
	211	GND41	
	213	IGP_DVI_B_TX0_L	
	215	IGP_DVI_B_TX0	
	217	DVI_A_HPD	
	219	DVI_A_CLK_L	
	221	DVI_A_CLK	
	223	GND42	
	225	DVI_A_TX2_L	
	227	DVI_A_TX2	
	229	GND43	
	231	DVI_A_TX1_L	
	233	DVI_A_TX1	
	235	GND44	
	237	DVI_A_TX0_L	
	239	DVI_A_TX0	
	241	GND45	

	134	PRSNT1_L	
	136	TV_C_HDTV_PR	GPU_TV_C 91 108
	138	GND46	
	140	TV_Y_HDTV_Y_TV_CVBS	GPU_TV_Y 91 108
	142	GND47	
	144	TV_CVBS_HDTV_PB	GPU_TV_COMP 91 108
	146	GND48	
	148	VGA_RED	GPU_RED 91 108
	150	GND49	
	152	VGA_GRN	GPU_GRN 91 108
	154	GND50	
	156	VGA_BLU	GPU_BLU 91 108
	158	GND51	
	160	LVDS_UCLK_L	LVDS_U_CLK_N 90 108
	162	LVDS_UCLK	LVDS_U_CLK_P 90 108
	164	GND52	
	166	LVDS_UTX3_L	LVDS_U_DATA_N<3> 90 108
	168	LVDS_UTX3	LVDS_U_DATA_P<3> 90 108
	170	GND53	MXM_PIN170
	172	LVDS_UTX2_L	LVDS_U_DATA_N<2> 90 108
	174	LVDS_UTX2	LVDS_U_DATA_P<2> 90 108
	176	GND54	
	178	LVDS_UTX1_L	LVDS_U_DATA_N<1> 90 108
	180	LVDS_UTX1	LVDS_U_DATA_P<1> 90 108
	182	GND55	
	184	LVDS_UTX0_L	LVDS_U_DATA_N<0> 90 108
	186	LVDS_UTX0	LVDS_U_DATA_P<0> 90 108
	188	GND56	
	190	LVDS_LCLK_L	LVDS_L_CLK_N 90 108
	192	LVDS_LCLK	LVDS_L_CLK_P 90 108
	194	GND57	
	196	LVDS_LTX3_L	LVDS_L_DATA_N<3> 90 108
	198	LVDS_LTX3	LVDS_L_DATA_P<3> 90 108
	200	GND58	
	202	LVDS_LTX2_L	LVDS_L_DATA_N<2> 90 108
	204	LVDS_LTX2	LVDS_L_DATA_P<2> 90 108
	206	GND59	
	208	LVDS_LTX1_L	LVDS_L_DATA_N<1> 90 108
	210	LVDS_LTX1	LVDS_L_DATA_P<1> 90 108
	212	GND60	
	214	LVDS_LTX0_L	LVDS_L_DATA_N<0> 90 108
	216	LVDS_LTX0	LVDS_L_DATA_P<0> 90 108
	218	GND61	
	220	DDCC_DAT	GPU_DDC_C_DATA 85 90
	222	DDCC_CLK	GPU_DDC_C_CLK 85 90
	224	LVDS_PPEN	GPU_DIGON 90
	226	LVDS_BL_BRGHT	GPU_VARY_BL 90 PWM
	228	LVDS_BLEN	GPU_ENABLE_BL
	230	DDCB_DAT	TP_GPU_DDC_B_DATA
	232	DDCB_CLK	TP_GPU_DDC_B_CLK UNCONNECTED. USE DDC_A FOR EXT. TMDS
	234	2V5RUN	
	236	GND62	
	238	3V3RUN0	
	240	3V3RUN1	
	242	3V3RUN2	

=PP3V3_S0_MXM 6 85
R8501
100K
5%
1/16W
MF-LF
402
PULLED TO GROUND ON MXM
MXM_DETECT_L

INPUT ENABLES HDMI FOR NVIDIA CARDS

REMOVE THESE RESISTORS IN PROTO 2
IF THIS PIN CONFIRMED TO BE USED
FOR MXM_SPDIF IN

R8505
0
5%
1/16W
MF-LF
402

24_INCH_LCD
R8503
0
5%
1/16W
MF-LF
402
INV_EN_BL_OR_PANEL_ID 6 28

TO INTERNAL PANEL

=PP2V5_S0_MXM 6
=PP3V3_S0_MXM 6 85

C8500
22uF
20%
6.3V
X5R
805

C8511
1000PF
10%
25V
X7R
402
EMC: C8511

C8510
1000PF
10%
25V
X7R
402
EMC: C8510

MXM I/O

SYNC_MASTER=K3_MASTER SYNC_DATE=N/A

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 85 OF 118	

www.laptop-schematics.com

Page Notes

Power aliases required by this page:
- =PPV_S0_LCD_24INCH
- =PPV_S0_LCD_20INCH
- =PP3V3_S0_VIDEO

Signal aliases required by this page:
(NONE)

BOM options provided by this page:
20_INCH_LCD, 24_INCH_LCD

94 91 6 =PP3V3_S0_VIDEO — I20 — =PP3V3_DDC_LCD 90

www.laptop-schematics.com

LCD (LVDS) INTERFACE

6 =PPV_S0_LCD_24INCH — 24_INCH_LCD R9002 0 5% 1/8W MF-LF 805

6 =PPV_S0_LCD_20INCH — 20_INCH_LCD R9003 0 5% 1/8W MF-LF 805

PANEL POWER SEQUENCING

PPV_S0_LCD
VOLTAGE=12V
MIN_LINE_WIDTH=0.5 mm
MIN_NECK_WIDTH=0.25 mm

R9000 100K 5% 1/10W MF-LF 402

C9000 0.1UF 10% 50V X7R 603-1

NOSTUFF R9090 0 5% 1/8W MF-LF 805

PLACE NEAR J9002

CRITICAL

R9001 29.4K 1% 1/10W MF-LF 402

LCD_PWREN_DIV

LCD_PWREN_L_RC

Q9000 SI3443DV TSOP-LF

PPV_LCD_SW
VOLTAGE=12V
MIN_LINE_WIDTH=0.5 mm
MIN_NECK_WIDTH=0.25 mm

L9000 FERR-250-OHM SM

VOLTAGE=12V
MIN_LINE_WIDTH=0.5 mm
MIN_NECK_WIDTH=0.25 mm

C9020 10UF 10% 16V X5R-CERM 1210

C9001 0.001uF 20% 50V CERM 402

PPV_LCD_CONN 6 90

5V FOR 20 INCH LCD
12V FOR 24 INCH LCD

OMIT R9099 100K 5% 1/10W MF-LF 402

LCD_PWREN_L

Q9001 2N7002 SOT23-LF

85 GPU_DIGON

R9070 100K 5% 1/16W MF-LF 402

PART#	QTY	DESCRIPTION	REFERENCE DESIGNATOR(S)	CRITICAL	BOM OPTION
116S0114	1	RES,100K,5%,0402	R9099		24_INCH_LCD
116S0004	1	RES,0,5%,0402	R9099		20_INCH_LCD

CRITICAL
SDF9000
STDOFF-4.0OD4.6H-1.35-2.4-TH

516S0241
CRITICAL
J9002
53307-3052
F-ST-SM

108 85 LVDS_U_DATA_N<0>	1	2	LVDS_U_DATA_P<0>	85 108
108 85 LVDS_U_DATA_N<1>	3	4	LVDS_U_DATA_P<1>	85 108
108 85 LVDS_U_DATA_N<2>	5	6	LVDS_U_DATA_P<2>	85 108
	7	8	LVDS_U_CLK_N	85 108
108 85 LVDS_U_CLK_P	9	10	LVDS_U_DATA_N<3>	85 108
108 85 LVDS_U_DATA_P<3>	11	12	LVDS_L_DATA_N<0>	85 108
108 85 LVDS_L_DATA_P<0>	13	14		
108 85 LVDS_L_DATA_N<1>	15	16	LVDS_L_DATA_P<1>	85 108
	17	18	LVDS_L_DATA_N<2>	85 108
108 85 LVDS_L_DATA_P<2>	19	20	LVDS_L_CLK_N	85 108
108 85 LVDS_L_CLK_P	21	22	LVDS_L_DATA_N<3>	85 108
108 85 LVDS_L_DATA_P<3>	23	24		
90 =PP3V3_DDC_LCD	25	26	GPU_DDC_C_DATA 85	
90 6 PPV_LCD_CONN	27	28	PPV_LCD_CONN 6 90	
	29	30		

Panel has 4.7K DDC pull-ups
MXM also has 2.2K pull-ups

C9010 0.001uF 20% 50V CERM 402

CRITICAL
SDF9001
STDOFF-4.0OD4.6H-1.35-2.4-TH

INVERTER INTERFACE

INVERTER CONNECTOR INCORPORATED INTO AC/DC CONNECTOR

85 GPU_VARY_BL — R9075 47 5% 1/10W MF-LF 402 — LCD_PWM 6

NOSTUFF R9074 10K 5% 1/10W MF-LF 402

www.laptop-schematics.com

INTERNAL DISPLAY CONNS

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 90 OF 118	

www.laptop-schematics.com

ANALOG FILTERING
PLACE CLOSE TO CONNECTOR



VIDEO_MUX_SEL	OUT
1	CRT
0	TV

PLACE U9120 NEAR GMCH

PART#	QTY	DESCRIPTION	REFERENCE DESIGNATOR(S)	CRITICAL	BOM OPTION
353S1700	1	QUAD SPDT HIGH-BANDWITDH VIDEO SWITCH,LOW ON-RES	U9130	CRITICAL	

PLACE R9760 & R9761 CLOSE TO DVI CONNECTOR



Analog Video Support

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 91 OF 118	

DVI INTERFACE

TMDS TERMINATION, IF ANY, IS ON MXM CARD

PLACE FILTER CLOSE TO MINI-DVI CONNECTOR



DVI DDC CURRENT LIMIT

(55mA requirement per DVI spec)



DON'T USE M51 SPECIFIC: 514S0129
APPLE PN: 514S0204



FOR IMAGE PLANE, THE SHELL PINS OF THE CONNECTOR ARE ALIASED DIRECTLY TO DIGITAL GROUND. IF CAPS ARE NECESSARY LATER, THEY SHOULD BE ADDED TO THE PAGE WHERE =SIGNAL =GND_CHASSIS_DVI IS CONNECTED

=GND_CHASSIS_DVI 9

PLACE CLOSE TO MINI-DVI CONNECTOR

3V LEVEL SHIFTERS



PART#	QTY	DESCRIPTION	REFERENCE DESIGNATOR(S)	CRITICAL	BOM OPTION
514S0204	1	CONN,RCPT,MINI_DVI,SMT,14 DGE,32P	J9410	CRITICAL	

www.laptop-schematics.com

External Display Conns

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 94 OF 118	

CRITICAL
SDF9800
STDOFF-4.0OD3.5H-1.35-TH

CRITICAL
SDF9801
STDOFF-4.0OD3.5H-1.35-TH

518S0586

CRITICAL
J9800
52893-2298
F-RT-SM

9 GND_AUDIO_SPKRAMP

C9800 1UF 10V 25V X7R 0805

6 =PP12V_S0_AUDIO_SPKRAMP

98 6 =PP5V_S0_AUDIO

103 23 HDA_SDIN0

103 23 HDA_SDOUT

103 23 HDA_BIT_CLK

103 23 HDA_RST_L

103 23 HDA_SYNC

98 6 =PP3V3_S0_AUDIO

NOSTUFF
R9800
0
5% 1/10W MF-LF 402

25 SB_SLOAD

IPHS_SW_SUPBIAS_EN_L

IPHS_SW_INT_TO_SB

NOSTUFF
R9801
0
5% 1/16W MF-LF 402

104 24 INT_PIRQE_L

=PP5V_S0_AUDIO 6 98

=PP3V3_S0_AUDIO 6 98

NOSTUFF
C9801
0.1UF
20% 10V CERM 402

NOSTUFF
C9802
0.1UF
20% 10V CERM 402

CRITICAL
SDF9803
STDOFF-4.0OD3.5H-1.35-TH

CRITICAL
SDF9804
STDOFF-4.0OD3.5H-1.35-TH

STANDOFFS ARE 860-0893

www.laptop-schematics.com

MLB: AUDIO CONNECTOR

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A

SCALE	SHT	OF
NONE	98	118

FSB (Front-Side Bus) Constraints

PHYSICAL_RULE_SET	LAYER	ALLOW ROUTE ON LAYER?	MINIMUM LINE WIDTH	MINIMUM NECK WIDTH	MAXIMUM NECK LENGTH	DIFFPAIR PRIMARY GAP	DIFFPAIR NECK GAP
FSB_DSTB_55S	*	=1:1_DIFFPAIR	=55_OHM_SE	=55_OHM_SE	=55_OHM_SE	=1:1_DIFFPAIR	=1:1_DIFFPAIR

NET_PHYSICAL_TYPE	AREA_TYPE	PHYSICAL_RULE_SET
FSB_55S	*	55_OHM_SE

NET_SPACING_TYPE1	NET_SPACING_TYPE2	AREA_TYPE	SPACING_RULE_SET
FSB_ADDR	*	*	SPACING_0.2MM
FSB_ADSTB	*	*	SPACING_0.3MM
FSB_DATA	*	*	SPACING_0.2MM
FSB_DSTB	*	*	SPACING_0.3MM
FSB_COMMON	*	*	SPACING_0.2MM

All FSB signals with impedance requirements are 55-ohm single-ended.
Worst-case spacing is 2:1 within Addr bus, with 3:1 spacing to the ADSTBs.
Worst-case spacing is 2:1 within Data bus, with 3:1 spacing to the DSTBs.
DSTB complementary pairs are spaced 1:1 and routed as differential pairs.

Design Guide recommends each strobe/signal group is routed on the same layer.
Design Guide recommends FSB signals be routed only on internal layers.

NOTE: Design Guide does not indicate FSB spacing to other signals, assumed 3:1.
NOTE: Design Guide allows closer spacing if signal lengths can be shortened.

SOURCE: Santa Rosa Platform DG, Rev 0.9 (#20517), Sections 4.2 & 4.3

CPU Signal Constraints

NET_PHYSICAL_TYPE	AREA_TYPE	PHYSICAL_RULE_SET
CPU_55S	*	55_OHM_SE
CPU_27P4S	*	27P4_OHM_SE

NET_SPACING_TYPE1	NET_SPACING_TYPE2	AREA_TYPE	SPACING_RULE_SET
CPU_2TO1	*	*	SPACING_0.2MM
CPU_COMP	*	*	SPACING_0.6MM
CPU_GTLREF	*	*	SPACING_0.6MM
CPU_ITP	*	*	SPACING_0.2MM
CPU_VCCSENSE	*	*	SPACING_0.6MM

NOTE: 7 mil gap is for VCCSense pair, which Intel says to route with 7 mil spacing without specifying a target differential impedance.

DG recommends at least 25 mils, >50 mils preferred

Most CPU signals with impedance requirements are 55-ohm single-ended.
Some signals require 27.4-ohm single-ended impedance.

SOURCE: Santa Rosa Platform DG, Rev 0.9 (#20517), Sections 4.4 & 5.8.2.4

CPU / FSB Net Properties

ELECTRICAL_CONSTRAINT_SET	NET_TYPE PHYSICAL	NET_TYPE SPACING		
FSB_COMMON	FSB_55S	FSB_COMMON	FSB_ADS_L	10 14
FSB_COMMON_PP	FSB_55S	FSB_COMMON	FSB_BNR_L	7 10 14
FSB_COMMON	FSB_55S	FSB_COMMON	FSB_BPRI_L	10 14
FSB_COMMON_PP	FSB_55S	FSB_COMMON	FSB_BREQ0_L	7 10 14
FSB_COMMON_PP	FSB_55S	FSB_COMMON	FSB_DBSY_L	7 10 14
FSB_COMMON	FSB_55S	FSB_COMMON	FSB_DEFER_L	10 14
FSB_COMMON_PP	FSB_55S	FSB_COMMON	FSB_DPWR_L	7 10 14
FSB_COMMON	FSB_55S	FSB_COMMON	FSB_DRDY_L	10 14
FSB_COMMON_PP	FSB_55S	FSB_COMMON	FSB_HIT_L	7 10 14
FSB_COMMON_PP	FSB_55S	FSB_COMMON	FSB_HITM_L	7 10 14
FSB_COMMON_2PP	FSB_55S	FSB_COMMON	FSB_LOCK_L	7 10 14
FSB_COMMON	FSB_55S	FSB_COMMON	FSB_RS_L<2..0>	10 14
FSB_COMMON	FSB_55S	FSB_COMMON	FSB_TRDY_L	10 14
FSB_CPURST_L	FSB_55S	FSB_COMMON	FSB_CPURST_L	7 10 13 14
FSB_DATA_GROUP0	FSB_55S	FSB_DATA	FSB_D_L<15..1>	10 14
FSB_DATA_GROUP0_PP	FSB_55S	FSB_DATA	FSB_D_L<0>	7 10 14
FSB_DATA_GROUP0_PP	FSB_55S	FSB_DATA	FSB_DINV_L<0>	7 10 14
FSB_DSTB0	FSB_DSTB_55S	FSB_DSTB	FSB_DSTB_L_P<0>	7 10 14
	FSB_DSTB_55S	FSB_DSTB	FSB_DSTB_L_N<0>	7 10 14
FSB_DATA_GROUP1	FSB_55S	FSB_DATA	FSB_D_L<31..17>	10 14
FSB_DATA_GROUP1_PP	FSB_55S	FSB_DATA	FSB_D_L<16>	7 10 14
FSB_DATA_GROUP1_PP	FSB_55S	FSB_DATA	FSB_DINV_L<1>	7 10 14
FSB_DSTB1	FSB_DSTB_55S	FSB_DSTB	FSB_DSTB_L_P<1>	7 10 14
	FSB_DSTB_55S	FSB_DSTB	FSB_DSTB_L_N<1>	7 10 14
FSB_DATA_GROUP2	FSB_55S	FSB_DATA	FSB_D_L<47..42>	10 14
FSB_DATA_GROUP2_PP	FSB_55S	FSB_DATA	FSB_D_L<41>	7 10 14
FSB_DATA_GROUP2	FSB_55S	FSB_DATA	FSB_D_L<40..32>	10 14
FSB_DATA_GROUP2_PP	FSB_55S	FSB_DATA	FSB_DINV_L<2>	7 10 14
FSB_DSTB2	FSB_DSTB_55S	FSB_DSTB	FSB_DSTB_L_P<2>	7 10 14
	FSB_DSTB_55S	FSB_DSTB	FSB_DSTB_L_N<2>	7 10 14
FSB_DATA_GROUP3	FSB_55S	FSB_DATA	FSB_D_L<63..60>	10 14
FSB_DATA_GROUP3_PP	FSB_55S	FSB_DATA	FSB_D_L<59>	7 10 14
FSB_DATA_GROUP3	FSB_55S	FSB_DATA	FSB_D_L<58..48>	10 14
FSB_DATA_GROUP3_PP	FSB_55S	FSB_DATA	FSB_DINV_L<3>	7 10 14
FSB_DSTB3	FSB_DSTB_55S	FSB_DSTB	FSB_DSTB_L_P<3>	7 10 14
	FSB_DSTB_55S	FSB_DSTB	FSB_DSTB_L_N<3>	7 10 14
FSB_ADDR_GROUP0	FSB_55S	FSB_ADDR	FSB_A_L<16..7>	10 14
FSB_ADDR_GROUP0	FSB_55S	FSB_ADDR	FSB_A_L<5..3>	10 14
FSB_ADDR_GROUP0_PP	FSB_55S	FSB_ADDR	FSB_A_L<6>	7 10 14
FSB_ADDR_GROUP0_PP	FSB_55S	FSB_ADDR	FSB_REQ_L<4..0>	7 10 14
FSB_ADSTB0	FSB_55S	FSB_ADSTB	FSB_ADSTB_L<0>	7 10 14
FSB_ADDR_GROUP1	FSB_55S	FSB_ADDR	FSB_A_L<35..28>	10 14
FSB_ADDR_GROUP1	FSB_55S	FSB_ADDR	FSB_A_L<26..17>	10 14
FSB_ADDR_GROUP1_PP	FSB_55S	FSB_ADDR	FSB_A_L<27>	7 10 14
FSB_ADSTB1	FSB_55S	FSB_ADSTB	FSB_ADSTB_L<1>	7 10 14
CPU_IERR_L	CPU_55S		CPU_IERR_L	10
CPU_FERR_L	CPU_55S		CPU_FERR_L	10 23
CPU_PROCHOT_L	CPU_55S	CPU_2TO1	CPU_PROCHOT_L	10 50 55
CPU_PWRGD	CPU_55S		CPU_PWRGD	7 10 13 23
CPU_FROM_SB_PP	CPU_55S		CPU_INTR	7 10 23
CPU_FROM_SB_PP	CPU_55S		CPU_NMI	7 10 23
CPU_FROM_SB_PP	CPU_55S		CPU_A20M_L	7 10 23
CPU_FROM_SB	CPU_55S		CPU_DPSLP_L	10 23
CPU_FROM_SB_PP	CPU_55S		CPU_IGNNE_L	7 10 23
CPU_INIT_L	CPU_55S		CPU_INIT_L	7 10 23 51
CPU_FROM_SB_PP	CPU_55S		CPU_SMI_L	7 10 23
CPU_FROM_SB_PP	CPU_55S		CPU_STPCLK_L	7 10 23
PM_THRMTRIP_L	CPU_55S	CPU_2TO1	PM_THRMTRIP_L	10 16 23 50
FSB_CPUSLP_L	CPU_55S		FSB_CPUSLP_L	10 14
PM_DPRSLPVR	CPU_55S	CPU_2TO1	PM_DPRSLPVR	16 25 71
	CPU_55S	CPU_2TO1	IMVP_DPRSLPVR	71
CPU_BSEL0	CPU_55S	CPU_2TO1	CPU_BSEL<0>	10 30
	CPU_55S	CPU_2TO1	NB_BSEL<0>	13 16 30
CPU_BSEL1	CPU_55S	CPU_2TO1	CPU_BSEL<1>	10 30
	CPU_55S	CPU_2TO1	NB_BSEL<1>	13 16 30
CPU_BSEL2	CPU_55S	CPU_2TO1	CPU_BSEL<2>	10 30
	CPU_55S	CPU_2TO1	NB_BSEL<2>	13 16 30
CPU_DPRSTP_L	CPU_55S	CPU_2TO1	CPU_DPRSTP_L	10 16 23 71
CPU_GTLREF	CPU_55S	CPU_GTLREF	CPU_GTLREF	10
CPU_COMP	CPU_55S	CPU_COMP	CPU_COMP<3>	10
CPU_COMP	CPU_27P4S	CPU_COMP	CPU_COMP<2>	10
CPU_COMP	CPU_55S	CPU_COMP	CPU_COMP<1>	10
CPU_COMP	CPU_27P4S	CPU_COMP	CPU_COMP<0>	10
XDP_TDI	CPU_55S	CPU_ITP	XDP_TDI	10 13
XDP_TDO	CPU_55S	CPU_ITP	XDP_TDO	10 13
XDP_TMS	CPU_55S	CPU_ITP	XDP_TMS	10 13
XDP_TCK	CPU_55S	CPU_ITP	XDP_TCK	10 13
XDP_TRST_L	CPU_55S	CPU_ITP	XDP_TRST_L	10 13
XDP_BPM_L	CPU_55S	CPU_ITP	XDP_BPM_L<4..0>	10 13
XDP_BPM_L5	CPU_55S	CPU_ITP	XDP_BPM_L<5>	10 13
	CLK_FSB_100D	CLK_FSB	XDP_CLK_P	13 30 105
	CLK_FSB_100D	CLK_FSB	XDP_CLK_N	13 30 105
(FSB_CPURST_L)	CPU_55S	CPU_ITP	ITP_CPURST_L	
	CPU_55S	CPU_2TO1	CPU_VID<6..0>	11 12
	CPU_55S	CPU_2TO1	IMVP6_VID<6..0>	12 71
CPU_VCCSENSE	CPU_27P4S	CPU_VCCSENSE	CPU_VCCSENSE_P	11 71
CPU_VCCSENSE	CPU_27P4S	CPU_VCCSENSE	CPU_VCCSENSE_N	11 71
	CPU_27P4S	CPU_VCCSENSE	IMVP6_VSEN_P	71
	CPU_27P4S	CPU_VCCSENSE	IMVP6_VSEN_N	71

www.laptop-schematic.com

CPU/FSB Constraints

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 100 OF 118	

PCI-Express / DMI Bus Constraints

NET_PHYSICAL_TYPE	AREA_TYPE	PHYSICAL_RULE_SET
PCIE_100D	*	100_OHM_DIFF
DMI_100D	*	100_OHM_DIFF

NET_SPACING_TYPE1	NET_SPACING_TYPE2	AREA_TYPE	SPACING_RULE_SET
PCIE	*	*	SPACING_0.5MM
DMI	*	*	SPACING_0.5MM

SOURCE: Santa Rosa Platform DG, Rev 1.0 (#21112), Sections 7.2, 9.2 & 10.5



Video Signal Constraints

NET_PHYSICAL_TYPE	AREA_TYPE	PHYSICAL_RULE_SET
LVDS_100D	*	100_OHM_DIFF
CRT_55S	*	55_OHM_SE
CRT_50S	*	50_OHM_SE
TMDS_100D	*	100_OHM_DIFF

NET_SPACING_TYPE1	NET_SPACING_TYPE2	AREA_TYPE	SPACING_RULE_SET	
LVDS	*	*	SPACING_0.5MM	
CRT	*	*	SPACING_0.6MM	DG Says 40 mil spacing minimum
CRT	CRT	*	SPACING_0.5MM	
TVDAC				DG Says 30 mil spacing minimum
CRT_SYNC	*	*	SPACING_0.6MM	
CRT_SYNC	CRT_SYNC	*	SPACING_0.5MM	DG Says 40 mil spacing minimum
TMDS	*	*	SPACING_0.5MM	

LVDS signals are 100-ohm +/- 20% differential impedence.
CRT & TVDAC signal single-ended impedence varies by location:
- 37.5-ohm +/- 15% from GMCH to first termination resistor.
- 50-ohm +/- 15% from first to second termination resistor.
- 55-ohm +/- 15% from second termination resistor to connector.

CRT_HSYNC/CRT_VSYNC signals are 55-ohm +/- 15% single-ended impedence.

SOURCE: Santa Rosa Platform DG, Rev 1.0 (#21112), Sections 8.1 - 8.3.

www.laptop-schematics.com

NB Constraints

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A

SCALE NONE SHT 101 OF 118

DDR2 Memory Bus Constraints

NET_PHYSICAL_TYPE	AREA_TYPE	PHYSICAL_RULE_SET
MEM_45S	*	45_OHM_SE
MEM_55S	*	55_OHM_SE
MEM_70D	*	70_OHM_DIFF
MEM_85D	*	85_OHM_DIFF

NET_SPACING_TYPE1	NET_SPACING_TYPE2	AREA_TYPE	SPACING_RULE_SET
MEM_CLK	*	*	SPACING_0.6MM
MEM_CMD	*	*	SPACING_0.15MM
MEM_CTRL	*	*	SPACING_0.6MM
MEM_DATA	*	*	SPACING_0.6MM
MEM_DQS	*	*	SPACING_0.6MM
MEM_CLK	MEM_CLK	*	SPACING_0.4MM
MEM_CLK	MEM_CTRL	*	SPACING_0.4MM
MEM_CLK	MEM_CMD	*	SPACING_0.4MM
MEM_CLK	MEM_DATA	*	SPACING_0.4MM
MEM_CLK	MEM_DQS	*	SPACING_0.4MM
MEM_CTRL	MEM_CTRL	*	SPACING_0.2MM
MEM_CTRL	MEM_CMD	*	SPACING_0.3MM
MEM_CTRL	MEM_DATA	*	SPACING_0.3MM
MEM_CTRL	MEM_DQS	*	SPACING_0.3MM
MEM_CMD	MEM_CMD	*	SPACING_0.15MM
MEM_CMD	MEM_DATA	*	SPACING_0.3MM
MEM_CMD	MEM_DQS	*	SPACING_0.3MM
MEM_DATA	MEM_DATA	*	SPACING_0.15MM
MEM_DATA	MEM_DQS	*	SPACING_0.3MM
MEM_DQS	MEM_DQS	*	SPACING_0.3MM

SOURCE: Santa Rosa Platform DG, Rev 1.0 (#21112), Section 6.2

Memory Net Properties

ELECTRICAL_CONSTRAINT_SET	NET_TYPE PHYSICAL	NET_TYPE SPACING		
MEM_A_CLK	MEM_70D	MEM_CLK	MEM_CLK_P<1..0>	16 31
	MEM_70D	MEM_CLK	MEM_CLK_N<1..0>	16 31
MEM_A_CNTL	MEM_45S	MEM_CTRL	MEM_CKE<1..0>	16 31 33
MEM_A_CNTL	MEM_45S	MEM_CTRL	MEM_CS_L<1..0>	16 31 33
MEM_A_CNTL	MEM_45S	MEM_CTRL	MEM_ODT<1..0>	16 31 33
MEM_A_CMD	MEM_55S	MEM_CMD	MEM_A_A<14..0>	16 17 31 33
MEM_A_CMD	MEM_55S	MEM_CMD	MEM_A_BS<2..0>	17 31 33
MEM_A_CMD	MEM_55S	MEM_CMD	MEM_A_RAS_L	17 31 33
MEM_A_CMD	MEM_55S	MEM_CMD	MEM_A_CAS_L	17 31 33
MEM_A_CMD	MEM_55S	MEM_CMD	MEM_A_WE_L	17 31 33
MEM_A_DQ_BYTE0	MEM_55S	MEM_DATA	MEM_A_DQ<6..0>	17 31
MEM_A_DQ_BYTE0_PP	MEM_55S	MEM_DATA	MEM_A_DQ<7>	7 17 31
MEM_A_DQ_BYTE1	MEM_55S	MEM_DATA	MEM_A_DQ<13..8>	17 31
MEM_A_DQ_BYTE1_PP	MEM_55S	MEM_DATA	MEM_A_DQ<14>	7 17 31
MEM_A_DQ_BYTE1	MEM_55S	MEM_DATA	MEM_A_DQ<15>	17 31
MEM_A_DQ_BYTE2_PP	MEM_55S	MEM_DATA	MEM_A_DQ<16>	7 17 31
MEM_A_DQ_BYTE2	MEM_55S	MEM_DATA	MEM_A_DQ<23..17>	17 31
MEM_A_DQ_BYTE3	MEM_55S	MEM_DATA	MEM_A_DQ<24>	17 31
MEM_A_DQ_BYTE3_PP	MEM_55S	MEM_DATA	MEM_A_DQ<25>	7 17 31
MEM_A_DQ_BYTE3	MEM_55S	MEM_DATA	MEM_A_DQ<31..26>	17 31
MEM_A_DQ_BYTE4	MEM_55S	MEM_DATA	MEM_A_DQ<38..32>	17 31
MEM_A_DQ_BYTE4_PP	MEM_55S	MEM_DATA	MEM_A_DQ<39>	7 17 31
MEM_A_DQ_BYTE5	MEM_55S	MEM_DATA	MEM_A_DQ<46..40>	17 31
MEM_A_DQ_BYTE5_PP	MEM_55S	MEM_DATA	MEM_A_DQ<47>	7 17 31
MEM_A_DQ_BYTE6	MEM_55S	MEM_DATA	MEM_A_DQ<53..48>	17 31
MEM_A_DQ_BYTE6_PP	MEM_55S	MEM_DATA	MEM_A_DQ<54>	7 17 31
MEM_A_DQ_BYTE6	MEM_55S	MEM_DATA	MEM_A_DQ<55>	17 31
MEM_A_DQ_BYTE7	MEM_55S	MEM_DATA	MEM_A_DQ<58..56>	17 31
MEM_A_DQ_BYTE7_PP	MEM_55S	MEM_DATA	MEM_A_DQ<59>	7 17 31
MEM_A_DQ_BYTE7	MEM_55S	MEM_DATA	MEM_A_DQ<63..60>	17 31
MEM_A_DM0	MEM_55S	MEM_DATA	MEM_A_DM<0>	17 31
MEM_A_DM1	MEM_55S	MEM_DATA	MEM_A_DM<1>	17 31
MEM_A_DM2	MEM_55S	MEM_DATA	MEM_A_DM<2>	17 31
MEM_A_DM3	MEM_55S	MEM_DATA	MEM_A_DM<3>	17 31
MEM_A_DM4	MEM_55S	MEM_DATA	MEM_A_DM<4>	17 31
MEM_A_DM5	MEM_55S	MEM_DATA	MEM_A_DM<5>	17 31
MEM_A_DM6	MEM_55S	MEM_DATA	MEM_A_DM<6>	17 31
MEM_A_DM7	MEM_55S	MEM_DATA	MEM_A_DM<7>	17 31
MEM_A_DQS0	MEM_85D	MEM_DQS	MEM_A_DQS_P<0>	7 17 31
	MEM_85D	MEM_DQS	MEM_A_DQS_N<0>	7 17 31
MEM_A_DQS1	MEM_85D	MEM_DQS	MEM_A_DQS_P<1>	7 17 31
	MEM_85D	MEM_DQS	MEM_A_DQS_N<1>	7 17 31
MEM_A_DQS2	MEM_85D	MEM_DQS	MEM_A_DQS_P<2>	7 17 31
	MEM_85D	MEM_DQS	MEM_A_DQS_N<2>	7 17 31
MEM_A_DQS3	MEM_85D	MEM_DQS	MEM_A_DQS_P<3>	7 17 31
	MEM_85D	MEM_DQS	MEM_A_DQS_N<3>	7 17 31
MEM_A_DQS4	MEM_85D	MEM_DQS	MEM_A_DQS_P<4>	7 17 31
	MEM_85D	MEM_DQS	MEM_A_DQS_N<4>	7 17 31
MEM_A_DQS5	MEM_85D	MEM_DQS	MEM_A_DQS_P<5>	7 17 31
	MEM_85D	MEM_DQS	MEM_A_DQS_N<5>	7 17 31
MEM_A_DQS6	MEM_85D	MEM_DQS	MEM_A_DQS_P<6>	7 17 31
	MEM_85D	MEM_DQS	MEM_A_DQS_N<6>	7 17 31
MEM_A_DQS7	MEM_85D	MEM_DQS	MEM_A_DQS_P<7>	7 17 31
	MEM_85D	MEM_DQS	MEM_A_DQS_N<7>	7 17 31

ELECTRICAL_CONSTRAINT_SET	NET_TYPE PHYSICAL	NET_TYPE SPACING		
MEM_B_CLK	MEM_70D	MEM_CLK	MEM_CLK_P<4..3>	16 32
	MEM_70D	MEM_CLK	MEM_CLK_N<4..3>	16 32
MEM_B_CNTL	MEM_45S	MEM_CTRL	MEM_CKE<4..3>	16 32 33
MEM_B_CNTL	MEM_45S	MEM_CTRL	MEM_CS_L<3..2>	16 32 33
MEM_B_CNTL	MEM_45S	MEM_CTRL	MEM_ODT<3..2>	16 32 33
MEM_B_CMD	MEM_55S	MEM_CMD	MEM_B_A<14..0>	16 17 32 33
MEM_B_CMD	MEM_55S	MEM_CMD	MEM_B_BS<2..0>	17 32 33
MEM_B_CMD	MEM_55S	MEM_CMD	MEM_B_RAS_L	17 32 33
MEM_B_CMD	MEM_55S	MEM_CMD	MEM_B_CAS_L	17 32 33
MEM_B_CMD	MEM_55S	MEM_CMD	MEM_B_WE_L	17 32 33
MEM_B_DQ_BYTE0	MEM_55S	MEM_DATA	MEM_B_DQ<5..0>	17 32
MEM_B_DQ_BYTE0_PP	MEM_55S	MEM_DATA	MEM_B_DQ<6>	7 17 32
MEM_B_DQ_BYTE0	MEM_55S	MEM_DATA	MEM_B_DQ<7>	17 32
MEM_B_DQ_BYTE1_PP	MEM_55S	MEM_DATA	MEM_B_DQ<8>	7 17 32
MEM_B_DQ_BYTE1	MEM_55S	MEM_DATA	MEM_B_DQ<15..9>	17 32
MEM_B_DQ_BYTE2	MEM_55S	MEM_DATA	MEM_B_DQ<22..16>	17 32
MEM_B_DQ_BYTE2_PP	MEM_55S	MEM_DATA	MEM_B_DQ<23>	7 17 32
MEM_B_DQ_BYTE3	MEM_55S	MEM_DATA	MEM_B_DQ<24>	17 32
MEM_B_DQ_BYTE3_PP	MEM_55S	MEM_DATA	MEM_B_DQ<25>	7 17 32
MEM_B_DQ_BYTE3	MEM_55S	MEM_DATA	MEM_B_DQ<31..26>	17 32
MEM_B_DQ_BYTE4	MEM_55S	MEM_DATA	MEM_B_DQ<37..32>	17 32
MEM_B_DQ_BYTE4_PP	MEM_55S	MEM_DATA	MEM_B_DQ<38>	7 17 32
MEM_B_DQ_BYTE4	MEM_55S	MEM_DATA	MEM_B_DQ<39>	17 32
MEM_B_DQ_BYTE5	MEM_55S	MEM_DATA	MEM_B_DQ<43..40>	17 32
MEM_B_DQ_BYTE5_PP	MEM_55S	MEM_DATA	MEM_B_DQ<44>	7 17 32
MEM_B_DQ_BYTE5	MEM_55S	MEM_DATA	MEM_B_DQ<47..45>	17 32
MEM_B_DQ_BYTE6_PP	MEM_55S	MEM_DATA	MEM_B_DQ<48>	7 17 32
MEM_B_DQ_BYTE6	MEM_55S	MEM_DATA	MEM_B_DQ<55..49>	17 32
MEM_B_DQ_BYTE7	MEM_55S	MEM_DATA	MEM_B_DQ<61..56>	17 32
MEM_B_DQ_BYTE7_PP	MEM_55S	MEM_DATA	MEM_B_DQ<62>	7 17 32
MEM_B_DQ_BYTE7	MEM_55S	MEM_DATA	MEM_B_DQ<63>	17 32
MEM_B_DM0	MEM_55S	MEM_DATA	MEM_B_DM<0>	17 32
MEM_B_DM1	MEM_55S	MEM_DATA	MEM_B_DM<1>	17 32
MEM_B_DM2	MEM_55S	MEM_DATA	MEM_B_DM<2>	17 32
MEM_B_DM3	MEM_55S	MEM_DATA	MEM_B_DM<3>	17 32
MEM_B_DM4	MEM_55S	MEM_DATA	MEM_B_DM<4>	17 32
MEM_B_DM5	MEM_55S	MEM_DATA	MEM_B_DM<5>	17 32
MEM_B_DM6	MEM_55S	MEM_DATA	MEM_B_DM<6>	17 32
MEM_B_DM7	MEM_55S	MEM_DATA	MEM_B_DM<7>	17 32
MEM_B_DQS0	MEM_85D	MEM_DQS	MEM_B_DQS_P<0>	7 17 32
	MEM_85D	MEM_DQS	MEM_B_DQS_N<0>	7 17 32
MEM_B_DQS1	MEM_85D	MEM_DQS	MEM_B_DQS_P<1>	7 17 32
	MEM_85D	MEM_DQS	MEM_B_DQS_N<1>	7 17 32
MEM_B_DQS2	MEM_85D	MEM_DQS	MEM_B_DQS_P<2>	7 17 32
	MEM_85D	MEM_DQS	MEM_B_DQS_N<2>	7 17 32
MEM_B_DQS3	MEM_85D	MEM_DQS	MEM_B_DQS_P<3>	7 17 32
	MEM_85D	MEM_DQS	MEM_B_DQS_N<3>	7 17 32
MEM_B_DQS4	MEM_85D	MEM_DQS	MEM_B_DQS_P<4>	7 17 32
	MEM_85D	MEM_DQS	MEM_B_DQS_N<4>	7 17 32
MEM_B_DQS5	MEM_85D	MEM_DQS	MEM_B_DQS_P<5>	7 17 32
	MEM_85D	MEM_DQS	MEM_B_DQS_N<5>	7 17 32
MEM_B_DQS6	MEM_85D	MEM_DQS	MEM_B_DQS_P<6>	7 17 32
	MEM_85D	MEM_DQS	MEM_B_DQS_N<6>	7 17 32
MEM_B_DQS7	MEM_85D	MEM_DQS	MEM_B_DQS_P<7>	7 17 32
	MEM_85D	MEM_DQS	MEM_B_DQS_N<7>	7 17 32

www.laptop-schematics.com

Memory Constraints

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A

SCALE: NONE SHT 102 OF 118

Disk Interface Constraints

NET_PHYSICAL_TYPE	AREA_TYPE	PHYSICAL_RULE_SET
IDE_55S	*	55_OHM_SE
SATA_55S	*	55_OHM_SE
SATA_100D	*	100_OHM_DIFF

NET_SPACING_TYPE1	NET_SPACING_TYPE2	AREA_TYPE	SPACING_RULE_SET
IDE	*	*	SPACING_0.18MM
SATA	*	*	SPACING_0.5MM

SOURCE: Santa Rosa Platform DG, Rev 1.0 (#21112), Sections 10.7 & 10.9

HD Audio Interface Constraints

NET_PHYSICAL_TYPE	AREA_TYPE	PHYSICAL_RULE_SET
HDA_55S	*	55_OHM_SE

NET_SPACING_TYPE1	NET_SPACING_TYPE2	AREA_TYPE	SPACING_RULE_SET
HDA	*	*	SPACING_0.18MM

SOURCE: Napa Platform DG, Rev 0.9 (#17978), Section 10.9.1

USB 2.0 Interface Constraints

NET_PHYSICAL_TYPE	AREA_TYPE	PHYSICAL_RULE_SET
USB_60S	*	55_OHM_SE
USB_90D	*	90_OHM_DIFF

NET_SPACING_TYPE1	NET_SPACING_TYPE2	AREA_TYPE	SPACING_RULE_SET
USB	*	*	SPACING_0.5MM

DG SAYS MINIMUM SPACING 50 MILS FROM USB TO CLOCKS

SOURCE: Santa Rosa Platform DG, Rev 1.0 (#21112), Section 10.13.2

Internal Interface Constraints

NET_PHYSICAL_TYPE	AREA_TYPE	PHYSICAL_RULE_SET
SMB_55S	*	55_OHM_SE
SPI_55S	*	55_OHM_SE

NET_SPACING_TYPE1	NET_SPACING_TYPE2	AREA_TYPE	SPACING_RULE_SET
SMB	*	*	SPACING_0.3MM
SPI	*	*	SPACING_0.18MM

SOURCE: Santa Platform DG, Rev 1.0 (#21112), Section 10.17

NET_TYPE			
ELECTRICAL_CONSTRAINT_SET	PHYSICAL	SPACING	
IDE_PDD	IDE_55S	IDE	IDE_PDD<15..10> 23 44
IDE_PDD_PP	IDE_55S	IDE	IDE_PDD<9> 7 23 44
IDE_PDD	IDE_55S	IDE	IDE_PDD<8..0> 23 44
IDE_PDA	IDE_55S	IDE	IDE_PDA<2..0> 23 44
IDE_PDCS	IDE_55S	IDE	IDE_PDCS1_L 23 44
IDE_PDCS	IDE_55S	IDE	IDE_PDCS3_L 23 44
IDE_CNTL	IDE_55S	IDE	IDE_PDIOW_L 23 44
IDE_PDIOR_L	IDE_55S	IDE	IDE_PDIOR_L 7 23 44
IDE_CNTL	IDE_55S	IDE	IDE_PDDACK_L 23 44
IDE_CNTL	IDE_55S	IDE	IDE_PDDREQ 23 44
IDE_PDIORDY	IDE_55S	IDE	IDE_PDIORDY 7 23 44
IDE_IRQ14	IDE_55S	IDE	IDE_IRQ14 23 44
IDE_RST_L	IDE_55S	IDE	ODD_RST_5VTOL_L 24 44
SATA_A_R2D	SATA_100D	SATA	SATA_A_R2D_C_P 23 45
	SATA_100D	SATA	SATA_A_R2D_C_N 23 45
	SATA_100D	SATA	SATA_A_R2D_P 45
	SATA_100D	SATA	SATA_A_R2D_N 45
SATA_A_D2R	SATA_100D	SATA	SATA_A_D2R_P 7 23 45
	SATA_100D	SATA	SATA_A_D2R_N 7 23 45
	SATA_100D	SATA	SATA_A_D2R_C_P 45
	SATA_100D	SATA	SATA_A_D2R_C_N 45
	SATA_100D	SATA	SATA_B_R2D_C_P 23 45
	SATA_100D	SATA	SATA_B_R2D_C_N 23 45
	SATA_100D	SATA	SATA_B_D2R_P 23 45
	SATA_100D	SATA	SATA_B_D2R_N 23 45
SATA_RBIAS	SATA_55S		SATA_RBIAS 45
HDA_BIT_CLK	HDA_55S	HDA	HDA_BIT_CLK 23 98
	HDA_55S	HDA	HDA_BIT_CLK_R 23
HDA_SYNC	HDA_55S	HDA	HDA_SYNC 23 98
	HDA_55S	HDA	HDA_SYNC_R 23
HDA_RST_L	HDA_55S	HDA	HDA_RST_L 23 98
	HDA_55S	HDA	HDA_RST_L_R 23
HDA_SDIN0	HDA_55S	HDA	HDA_SDIN0 23 98
	HDA_55S	HDA	HDA_SDIN_CODEC
HDA_SDOUT	HDA_55S	HDA	HDA_SDOUT 23 98
	HDA_55S	HDA	HDA_SDOUT_R 23
USB_EXTA	USB_90D	USB	USB_EXTA_P 24 46
	USB_90D	USB	USB_EXTA_N 24 46
	USB_90D	USB	USB_EXTA_MUXED_P
	USB_90D	USB	USB_EXTA_MUXED_N
USB_MINI	USB_90D	USB	USB_MINI_P 24 34
	USB_90D	USB	USB_MINI_N 24 34
	USB_90D	USB	USB_EXTD_P 24 46
	USB_90D	USB	USB_EXTD_N 24 46
USB_CAMERA	USB_90D	USB	USB_CAMERA_P 7 24 47
	USB_90D	USB	USB_CAMERA_N 7 24 47
USB_BT	USB_90D	USB	USB_BT_P 7 24 47
	USB_90D	USB	USB_BT_N 7 24 47
	USB_90D	USB	USB_TPAD_P 24 47
	USB_90D	USB	USB_TPAD_N 24 47
USB_IR	USB_90D	USB	USB_IR_P 7 24 47
	USB_90D	USB	USB_IR_N 7 24 47
USB_EXTB	USB_90D	USB	USB_EXTB_P 24 46
	USB_90D	USB	USB_EXTB_N 24 46
	USB_90D	USB	USB_EXCARD_P 24 47
	USB_90D	USB	USB_EXCARD_N 24 47
USB_EXTC	USB_90D	USB	USB_EXTC_P 24 46
	USB_90D	USB	USB_EXTC_N 24 46
USB_RBIAS	USB_60S		USB_RBIAS 24
SMB_SB_SCL	SMB_55S	SMB	SMB_CLK 25 52
SMB_SB_SDA	SMB_55S	SMB	SMB_DATA 25 52
SMB_SB_ME_SCL	SMB_55S	SMB	SMB_ME_CLK 25 52
SMB_SB_ME_SDA	SMB_55S	SMB	SMB_ME_DATA 25 52
SPI_SCLK	SPI_55S	SPI	SPI_SCLK_R 24 61
	SPI_55S	SPI	SPI_SCLK 7 61
	SPI_55S	SPI	SPI_A_SCLK_R
	SPI_55S	SPI	SPI_B_SCLK_R
SPI_SI	SPI_55S	SPI	SPI_SI_R 24 61
	SPI_55S	SPI	SPI_SI
	SPI_55S	SPI	SPI_A_SI_R 61
	SPI_55S	SPI	SPI_B_SI_R
SPI_SO	SPI_55S	SPI	SPI_SO 7 24 61
	SPI_55S	SPI	SPI_A_SO_R 7 61
	SPI_55S	SPI	SPI_B_SO
	SPI_55S	SPI	SPI_B_SO_R
SPI_CE_L0	SPI_55S	SPI	SPI_CE_R_L<0> 24 61
	SPI_55S	SPI	SPI_CE_L<0> 7 61
SPI_CE_L1	SPI_55S	SPI	SPI_CE_R_L<1>
	SPI_55S	SPI	SPI_CE_L<1>

SB Constraints (1 of 2)

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A
SCALE: NONE	SHT 103 OF 118	

www.laptop-schematics.com

PCI Bus Constraints

NET_PHYSICAL_TYPE	AREA_TYPE	PHYSICAL_RULE_SET
PCI_55S	*	55_OHM_SE

NET_SPACING_TYPE1	NET_SPACING_TYPE2	AREA_TYPE	SPACING_RULE_SET
PCI	*	*	STANDARD

CHANGED TO 0.1MM SPACING AS THERE ARE NO PCI DEVICES

SOURCE: Santa Rosa Platform DG, Rev 1.0 (#21112), Sections 10.18.1 & 10.19

Controller Link (AMT) Constraints

NET_PHYSICAL_TYPE	AREA_TYPE	PHYSICAL_RULE_SET
CLINK_55S	*	55_OHM_SE

NET_SPACING_TYPE1	NET_SPACING_TYPE2	AREA_TYPE	SPACING_RULE_SET
CLINK	*	*	SPACING_0.18MM
CLINK_VREF	*	*	SPACING_0.3MM

PHYSICAL_RULE_SET	LAYER	ALLOW ROUTE ON LAYER?	MINIMUM LINE WIDTH	MINIMUM NECK WIDTH	MAXIMUM NECK LENGTH	DIFFPAIR PRIMARY GAP	DIFFPAIR NECK GAP
CLINK_12MIL	*	=STANDARD	0.3 MM	0.125 MM	7.5 MM	=STANDARD	=STANDARD

SOURCE: Santa Rosa Platform DG, Rev 1.0 (#21112), Sections 10.27.1.5-7, 10.29 & 10.30

Ethernet (Yukon) Constraints

NET_PHYSICAL_TYPE	AREA_TYPE	PHYSICAL_RULE_SET
ENET_100D	*	100_OHM_DIFF

NET_SPACING_TYPE1	NET_SPACING_TYPE2	AREA_TYPE	SPACING_RULE_SET
ENET_MDI	*	*	SPACING_0.5MM
ENET_MDI	ENET_MDI_TERM	*	SPACING_0.2MM

SOURCE: Based on Santa Rosa Platform DG, Rev 1.0 (#21112), Sections 10.27.1.5-7, 10.29 & 10.30

NET_TYPE				
ELECTRICAL_CONSTRAINT_SET	PHYSICAL	SPACING		
	PCI_55S	PCI	PCI_AD<18..0>	24 28
	PCI_55S	PCI	PCI_AD<19>	24 28
	PCI_55S	PCI	PCI_AD<20>	24 28
	PCI_55S	PCI	PCI_AD<31..21>	24 28
	PCI_55S	PCI	PCI_PAR	24 28
	PCI_55S	PCI	PCI_C_BE_L<3..0>	24 28
	PCI_55S	PCI	PCI_IRDY_L	24
	PCI_55S	PCI	PCI_DEVSEL_L	24
	PCI_55S	PCI	PCI_PERR_L	24
	PCI_55S	PCI	PCI_LOCK_L	24
	PCI_55S	PCI	PCI_SERR_L	24 28
	PCI_55S	PCI	PCI_STOP_L	24
	PCI_55S	PCI	PCI_TRDY_L	24
	PCI_55S	PCI	PCI_FRAME_L	24
	PCI_55S	PCI	PCI_FW_REQ_L	24
	PCI_55S	PCI	PCI_FW_GNT_L	24
	PCI_55S	PCI	PCI_REQ1_L	7 24
	PCI_55S	PCI	PCI_GNT1_L	
	PCI_55S	PCI	PCI_REQ2_L	7 24
	PCI_55S	PCI	PCI_GNT2_L	
INT_PIRQA_L	PCI_55S	PCI	INT_PIRQA_L	24
INT_PIRQB_L	PCI_55S	PCI	INT_PIRQB_L	24
INT_PIRQC_L	PCI_55S	PCI	INT_PIRQC_L	24
INT_PIRQD_L	PCI_55S	PCI	INT_PIRQD_L	24
INT_PIRQE_L	PCI_55S	PCI	INT_PIRQE_L	24 98
INT_PIRQF_L	PCI_55S	PCI	INT_PIRQF_L	24
PCIE_A_R2D	PCIE_100D	PCIE	PCIE_MINI_R2D_C_P	24 34
	PCIE_100D	PCIE	PCIE_MINI_R2D_C_N	24 34
PCIE_A_D2R	PCIE_100D	PCIE	PCIE_MINI_D2R_P	7 24 34
	PCIE_100D	PCIE	PCIE_MINI_D2R_N	7 24 34
PCIE_B_R2D	PCIE_100D	PCIE	PCIE_ENET_R2D_C_P	24 37
	PCIE_100D	PCIE	PCIE_ENET_R2D_C_N	24 37
PCIE_B_D2R	PCIE_100D	PCIE	PCIE_ENET_D2R_P	7 24 37
	PCIE_100D	PCIE	PCIE_ENET_D2R_N	7 24 37
PCIE_B_R2D	PCIE_100D	PCIE	PCIE_FW_R2D_C_P	40 42
	PCIE_100D	PCIE	PCIE_FW_R2D_C_N	40 42
PCIE_B_D2R	PCIE_100D	PCIE	PCIE_FW_D2R_P	7 40 42
	PCIE_100D	PCIE	PCIE_FW_D2R_N	7 40 42
GLAN_COMP			GLAN_COMP	23
CLINK_NB	CLINK_55S	CLINK	CLINK_NB_CLK	7 16 25
CLINK_NB	CLINK_55S	CLINK	CLINK_NB_DATA	7 16 25
CLINK_NB_RESET_L	CLINK_55S	CLINK	CLINK_NB_RESET_L	16 25
NB_CLINK_VREF	CLINK_12MIL	CLINK_VREF	NB_CLINK_VREF	16
SB_CLINK_VREF0	CLINK_12MIL	CLINK_VREF	SB_CLINK_VREF0	25
SB_CLINK_VREF1	CLINK_12MIL	CLINK_VREF	SB_CLINK_VREF1	25
I149		PWR	PP1V9_ENET_PHY_AVDD	37
I147		ENET_MDI_TERM	ENET_MDI0	37
I148		ENET_MDI_TERM	ENET_MDI1	37
I149		ENET_MDI_TERM	ENET_MDI2	37
I149		ENET_MDI_TERM	ENET_MDI3	37
ENET_MDI0	ENET_100D	ENET_MDI	ENET_MDI_P<0>	37 39
	ENET_100D	ENET_MDI	ENET_MDI_N<0>	37 39
ENET_MDI1	ENET_100D	ENET_MDI	ENET_MDI_P<1>	37 39
	ENET_100D	ENET_MDI	ENET_MDI_N<1>	37 39
ENET_MDI2	ENET_100D	ENET_MDI	ENET_MDI_P<2>	37 39
	ENET_100D	ENET_MDI	ENET_MDI_N<2>	37 39
ENET_MDI3	ENET_100D	ENET_MDI	ENET_MDI_P<3>	37 39
	ENET_100D	ENET_MDI	ENET_MDI_N<3>	37 39

SB Constraints (2 of 2)

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A

SCALE: NONE SHT 104 OF 118

www.laptop-schematics.com

Clock Signal Constraints

NET_PHYSICAL_TYPE	AREA_TYPE	PHYSICAL_RULE_SET
CLK_FSB_100D	*	100_OHM_DIFF
CLK_PCIE_100D	*	100_OHM_DIFF
CLK_MED_55S	*	55_OHM_SE

NET_SPACING_TYPE1	NET_SPACING_TYPE2	AREA_TYPE	SPACING_RULE_SET
CLK_FSB	*	*	CLK_SPACING_0.6MM
CLK_PCIE	*	*	CLK_SPACING_0.5MM
CLK_MED	*	*	CLK_SPACING_0.5MM

SOURCE: Santa Rosa Platform DG, Rev 1.0 (#21112), Sections 14.1 - 14.6

Clock Net Properties

ELECTRICAL_CONSTRAINT_SET	NET_TYPE: PHYSICAL	NET_TYPE: SPACING		
CK505_CPU	CLK_FSB_100D	CLK_FSB	CK505_CPU0_P	29 30
CK505_CPU	CLK_FSB_100D	CLK_FSB	CK505_CPU0_N	29 30
CK505_NB	CLK_FSB_100D	CLK_FSB	CK505_CPU1_P	29 30
CK505_NB	CLK_FSB_100D	CLK_FSB	CK505_CPU1_N	29 30
CK505_ITP	CLK_FSB_100D	CLK_FSB	CK505_CPU2_ITP_SRC10_P	29 30
CK505_ITP	CLK_FSB_100D	CLK_FSB	CK505_CPU2_ITP_SRC10_N	29 30
CK505_PCIF0	CLK_MED_55S	CLK_MED	CK505_PCIF0_CLK_ITPEN	29 30
CK505_PCIF1	CLK_MED_55S	CLK_MED	CK505_PCIF1_CLK	29 30
	CLK_MED_55S	CLK_MED	CK505_PCI1_CLK	29 30
	CLK_MED_55S	CLK_MED	CK505_PCI2_CLK	29 30
CK505_PCI3	CLK_MED_55S	CLK_MED	CK505_PCI3_CLK	29 30
	CLK_MED_55S	CLK_MED	CK505_PCI4_CLK	29 30
CK505_PCI5	CLK_MED_55S	CLK_MED	CK505_PCI5_CLK_FCTSEL	29 30
(CPU_BSEL0)	CLK_MED_55S	CLK_MED	CK505_48M_FSA	29 30
(CPU_BSEL2)	CLK_MED_55S	CLK_MED	CK505_REF0_FSC	29 30
	CLK_PCIE_100D	CLK_PCIE	CK505_DOT96_27M_P	29 30
	CLK_PCIE_100D	CLK_PCIE	CK505_DOT96_27M_N	29 30
	CLK_PCIE_100D	CLK_PCIE	CK505_LVDS_P	29 30
	CLK_PCIE_100D	CLK_PCIE	CK505_LVDS_N	29 30
CK505_SRC1	CLK_PCIE_100D	CLK_PCIE	CK505_SRC1_P	29 30
	CLK_PCIE_100D	CLK_PCIE	CK505_SRC1_N	29 30
CK505_SRC2	CLK_PCIE_100D	CLK_PCIE	CK505_SRC2_P	29 30
	CLK_PCIE_100D	CLK_PCIE	CK505_SRC2_N	29 30
CK505_SRC3	CLK_PCIE_100D	CLK_PCIE	CK505_SRC3_P	29 30
	CLK_PCIE_100D	CLK_PCIE	CK505_SRC3_N	29 30
CK505_SRC4	CLK_PCIE_100D	CLK_PCIE	CK505_SRC4_P	29 30
	CLK_PCIE_100D	CLK_PCIE	CK505_SRC4_N	29 30
CK505_SRC5	CLK_PCIE_100D	CLK_PCIE	CK505_SRC5_P	29 30
	CLK_PCIE_100D	CLK_PCIE	CK505_SRC5_N	29 30
CK505_SRC6	CLK_PCIE_100D	CLK_PCIE	CK505_SRC6_P	29 30
	CLK_PCIE_100D	CLK_PCIE	CK505_SRC6_N	29 30
CK505_SRC7	CLK_PCIE_100D	CLK_PCIE	CK505_SRC7_P	29 30
	CLK_PCIE_100D	CLK_PCIE	CK505_SRC7_N	29 30
CK505_SRC8	CLK_PCIE_100D	CLK_PCIE	CK505_SRC8_P	29 30
	CLK_PCIE_100D	CLK_PCIE	CK505_SRC8_N	29 30
(CK505_CPU)	CLK_FSB_100D	CLK_FSB	FSB_CLK_CPU_P	7 10 30
(CK505_CPU)	CLK_FSB_100D	CLK_FSB	FSB_CLK_CPU_N	7 10 30
(CK505_NB)	CLK_FSB_100D	CLK_FSB	FSB_CLK_NB_P	7 14 30
(CK505_NB)	CLK_FSB_100D	CLK_FSB	FSB_CLK_NB_N	7 14 30
(CK505_ITP)	CLK_FSB_100D	CLK_FSB	XDP_CLK_P	13 30 100
(CK505_ITP)	CLK_FSB_100D	CLK_FSB	XDP_CLK_N	13 30 100
(CK505_PCIF0)	CLK_MED_55S	CLK_MED	PCI_CLK33M_LPCPLUS	7 30 51
(CK505_PCIF1)	CLK_MED_55S	CLK_MED	PCI_CLK33M_SB	7 24 30
(CK505_PCI2)	CLK_MED_55S	CLK_MED	PCI_CLK33M_TPM	
(CK505_PCI3)	CLK_MED_55S	CLK_MED	PCI_CLK33M_SMC	7 30 49
			CK505 PCI4 is project-specific	
			CK505 PCI5 is project-specific	
(CPU_BSEL0)	CLK_MED_55S	CLK_MED	SB_CLK48M_USBCTLR	7 25 30
(CPU_BSEL2)	CLK_MED_55S	CLK_MED	SB_CLK14P3M_TIMER	7 25 30
(CPU_BSEL0)	CLK_MED_55S	CLK_MED	CK505_FSA	30
(CPU_BSEL2)	CLK_MED_55S	CLK_MED	CK505_FSC	30
(CK505_SRC1)	CLK_PCIE_100D	CLK_PCIE	GPU_CLK100M_PCIE_P	30 85
(CK505_SRC1)	CLK_PCIE_100D	CLK_PCIE	GPU_CLK100M_PCIE_N	30 85
(CK505_SRC2)	CLK_PCIE_100D	CLK_PCIE	SB_CLK100M_DMI_P	7 24 30
(CK505_SRC2)	CLK_PCIE_100D	CLK_PCIE	SB_CLK100M_DMI_N	7 24 30
(CK505_SRC3)	CLK_PCIE_100D	CLK_PCIE	PCIE_CLK100M_FW_P	7 30 40
(CK505_SRC3)	CLK_PCIE_100D	CLK_PCIE	PCIE_CLK100M_FW_N	7 30 40
(CK505_SRC4)	CLK_PCIE_100D	CLK_PCIE	SB_CLK100M_SATA_P	7 23 30
(CK505_SRC4)	CLK_PCIE_100D	CLK_PCIE	SB_CLK100M_SATA_N	7 23 30
(CK505_SRC5)	CLK_PCIE_100D	CLK_PCIE	NB_CLK100M_PCIE_P	7 16 30
(CK505_SRC5)	CLK_PCIE_100D	CLK_PCIE	NB_CLK100M_PCIE_N	7 16 30
(CK505_SRC6)	CLK_PCIE_100D	CLK_PCIE	PCIE_CLK100M_MINI_P	30 34
(CK505_SRC6)	CLK_PCIE_100D	CLK_PCIE	PCIE_CLK100M_MINI_N	30 34
(CK505_SRC8)	CLK_PCIE_100D	CLK_PCIE	PCIE_CLK100M_ENET_P	7 30 37
(CK505_SRC8)	CLK_PCIE_100D	CLK_PCIE	PCIE_CLK100M_ENET_N	7 30 37

www.laptop-schematics.com

Clock Constraints

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A

SCALE: NONE SHT 105 OF 118

FireWire Interface Constraints

NET_PHYSICAL_TYPE	AREA_TYPE	PHYSICAL_RULE_SET
FW_110D	*	110_OHM_DIFF
FW_110D	BGA_P1MM	110_OHM_DIFF_ESCAPE

NET_SPACING_TYPE1	NET_SPACING_TYPE2	AREA_TYPE	SPACING_RULE_SET
FW_TP	*	*	SPACING_0.3MM

FireWire Net Properties

ELECTRICAL_CONSTRAINT_SET	NET_TYPE PHYSICAL	NET_TYPE SPACING		
FW_0_TPA	FW_110D	FW_TP	FW_PORT0_TPA_P	43
	FW_110D	FW_TP	FW_PORT0_TPA_N	43
FW_0_TPB	FW_110D	FW_TP	FW_PORT0_TPB_P	43
	FW_110D	FW_TP	FW_PORT0_TPB_N	43
FW_1_TPA	FW_110D	FW_TP	FW_PORT1_TPA_P	43
	FW_110D	FW_TP	FW_PORT1_TPA_N	43
FW_1_TPB	FW_110D	FW_TP	FW_PORT1_TPB_P	43
	FW_110D	FW_TP	FW_PORT1_TPB_N	43
	FW_110D	FW_TP	FW_PORT1_TPA_FL_P	43
	FW_110D	FW_TP	FW_PORT1_TPA_FL_N	43
	FW_110D	FW_TP	FW_PORT1_TPB_FL_P	43
	FW_110D	FW_TP	FW_PORT1_TPB_FL_N	43

Port 2 Not Used

SMC SMBus Net Properties

ELECTRICAL_CONSTRAINT_SET	NET_TYPE PHYSICAL	NET_TYPE SPACING		
SMBUS_SMC_A_S3_SCL	SMB_5SS	SMB	SMBUS_SMC_A_S3_SCL	
SMBUS_SMC_A_S3_SDA	SMB_5SS	SMB	SMBUS_SMC_A_S3_SDA	
SMBUS_SMC_B_S0_SCL	SMB_5SS	SMB	SMBUS_SMC_B_S0_SCL	52
SMBUS_SMC_B_S0_SDA	SMB_5SS	SMB	SMBUS_SMC_B_S0_SDA	52
SMBUS_SMC_0_S0_SCL	SMB_5SS	SMB	SMBUS_SMC_0_S0_SCL	52
SMBUS_SMC_0_S0_SDA	SMB_5SS	SMB	SMBUS_SMC_0_S0_SDA	52
SMBUS_SMC_BSA_SCL	SMB_5SS	SMB	SMBUS_SMC_BSA_SCL	52
SMBUS_SMC_BSA_SDA	SMB_5SS	SMB	SMBUS_SMC_BSA_SDA	52
SMBUS_SMC_MGMT_SCL	SMB_5SS	SMB	SMBUS_SMC_MGMT_SCL	52
SMBUS_SMC_MGMT_SDA	SMB_5SS	SMB	SMBUS_SMC_MGMT_SDA	52

www.laptop-schematics.com

FireWire & SMC Constraints

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

SPACING_RULE_SET	LAYER	LINE-TO-LINE SPACING	WEIGHT
GND	*	=STANDARD	900
PWR	*	=STANDARD	900

SPACING_RULE_SET	LAYER	LINE-TO-LINE SPACING	WEIGHT
GND_P2MM	*	0.20 MM	1000
PWR_P2MM	*	0.20 MM	1000

NET_SPACING_TYPE1	NET_SPACING_TYPE2	AREA_TYPE	SPACING_RULE_SET
MEM_CLK	GND	*	GND_P2MM
MEM_CMD	GND	*	GND_P2MM
MEM_CTRL	GND	*	GND_P2MM
MEM_DATA	GND	*	GND_P2MM
MEM_DQS	GND	*	GND_P2MM
MEM_CLK	PWR	*	PWR_P2MM
MEM_CMD	PWR	*	PWR_P2MM
MEM_CTRL	PWR	*	PWR_P2MM
MEM_DATA	PWR	*	PWR_P2MM
MEM_DQS	PWR	*	PWR_P2MM

NET_SPACING_TYPE1	NET_SPACING_TYPE2	AREA_TYPE	SPACING_RULE_SET
CLINK_VREF	GND	*	GND_P2MM
CLK_MED	GND	*	GND_P2MM
CLK_PCIE	GND	*	GND_P2MM
DMI	GND	*	GND_P2MM
PCIE	GND	*	GND_P2MM
SATA	GND	*	GND_P2MM
USB	GND	*	GND_P2MM
CLK_PCIE	PWR	*	PWR_P2MM
DMI	PWR	*	PWR_P2MM
SATA	PWR	*	PWR_P2MM
USB	PWR	*	PWR_P2MM

NET_SPACING_TYPE1	NET_SPACING_TYPE2	AREA_TYPE	SPACING_RULE_SET
LVDS	GND	*	GND_P2MM

NET_SPACING_TYPE1	NET_SPACING_TYPE2	AREA_TYPE	SPACING_RULE_SET
CLK_PCIE	PWR	*	PWR_P2MM

NET_SPACING_TYPE1	NET_SPACING_TYPE2	AREA_TYPE	SPACING_RULE_SET
CLK_FSB	GND	*	GND_P2MM
CPU_COMP	GND	*	GND_P2MM
CPU_GTLREF	GND	*	GND_P2MM
CPU_VCCSENSE	GND	*	GND_P2MM
FSB_DSTB	GND	*	GND_P2MM

NET_SPACING_TYPE1	NET_SPACING_TYPE2	AREA_TYPE	SPACING_RULE_SET
ENET_MDI	GND	*	GND_P2MM
ENET_MDI	PWR	*	PWR_P2MM

NET_SPACING_TYPE1	NET_SPACING_TYPE2	AREA_TYPE	SPACING_RULE_SET
CLK_MED	PWR	*	GND_P2MM

NET_PHYSICAL_TYPE	AREA_TYPE	PHYSICAL_RULE_SET
THERM_DIFF	*	1:1_DIFFPAIR

NET_SPACING_TYPE1	NET_SPACING_TYPE2	AREA_TYPE	SPACING_RULE_SET
THERMAL	*	*	SPACING_0.4MM
SWITCHNODE	*	*	SWITCHNODE
THERMAL	PWR	*	PWR_P2MM
THERMAL	GND	*	GND_P2MM
SMS	*	*	SPACING_0.3MM

M72/M78 SPECIFIC NET PROPERTIES

ELECTRICAL_CONSTRAINT_SET	NET_TYPE PHYSICAL	NET_TYPE SPACING		
TMDS_DATA	TMDS_100D	TMDS	TMDS_DATA_P<3..0>	85 94
	TMDS_100D	TMDS	TMDS_DATA_N<3..0>	85 94
TMDS_CLK	TMDS_100D	TMDS	TMDS_CLK_P	85 94
	TMDS_100D	TMDS	TMDS_CLK_N	85 94
	TMDS_100D	TMDS	TMDS_CONN_DP<3..0>	94
	TMDS_100D	TMDS	TMDS_CONN_DN<3..0>	94
	TMDS_100D	TMDS	TMDS_CONN_CLKP	94
	TMDS_100D	TMDS	TMDS_CONN_CLKN	94
(USB_EXTA)	USB_90D	USB	USB_PORT0_P	46
(USB_EXTA)	USB_90D	USB	USB_PORT0_N	46
(USB_EXTB)	USB_90D	USB	USB_PORT1_P	46
(USB_EXTB)	USB_90D	USB	USB_PORT1_N	46
(USB_EXTC)	USB_90D	USB	USB_PORT2_P	46
(USB_EXTC)	USB_90D	USB	USB_PORT2_N	46
(USB_EXTD)	USB_90D	USB	USB_C_MUXED_P	46
(USB_EXTD)	USB_90D	USB	USB_C_MUXED_N	46
(USB_CAMERA)	USB_90D	USB	USB_CAMERA_L_P	47
(USB_CAMERA)	USB_90D	USB	USB_CAMERA_L_N	47
(USB_IR)	USB_90D	USB	USB_IR_L_P	47
(USB_IR)	USB_90D	USB	USB_IR_L_N	47
LVDS_A_CLK	LVDS_100D	LVDS	LVDS_L_CLK_P	85 90
LVDS_A_CLK	LVDS_100D	LVDS	LVDS_L_CLK_N	85 90
LVDS_A_DATA	LVDS_100D	LVDS	LVDS_L_DATA_P<3..0>	85 90
LVDS_A_DATA	LVDS_100D	LVDS	LVDS_L_DATA_N<3..0>	85 90
LVDS_B_CLK	LVDS_100D	LVDS	LVDS_U_CLK_P	85 90
LVDS_B_CLK	LVDS_100D	LVDS	LVDS_U_CLK_N	85 90
LVDS_B_DATA	LVDS_100D	LVDS	LVDS_U_DATA_P<3..0>	85 90
LVDS_B_DATA	LVDS_100D	LVDS	LVDS_U_DATA_N<3..0>	85 90
	PCIE_100D	PCIE	PCIE_FW_R2D_N	7 40
	PCIE_100D	PCIE	PCIE_FW_R2D_P	7 40
	PCIE_100D	PCIE	PCIE_FW_D2R_C_N	40
	PCIE_100D	PCIE	PCIE_FW_D2R_C_P	40
	PCIE_100D	PCIE	PCIE_ENET_R2D_P	7 37
	PCIE_100D	PCIE	PCIE_ENET_R2D_N	7 37
	PCIE_100D	PCIE	PCIE_ENET_D2R_C_P	37
	PCIE_100D	PCIE	PCIE_ENET_D2R_C_N	37
	PCIE_100D	PCIE	PCIE_MINI_R2D_N	34
	PCIE_100D	PCIE	PCIE_MINI_R2D_P	34
ENET_MDI_T	ENET_100D	ENET_MDI	ENET_MDI_T_P<0>	39
	ENET_100D	ENET_MDI	ENET_MDI_T_N<0>	39
ENET_MDI_T	ENET_100D	ENET_MDI	ENET_MDI_T_P<1>	39
	ENET_100D	ENET_MDI	ENET_MDI_T_N<1>	39
ENET_MDI_T	ENET_100D	ENET_MDI	ENET_MDI_T_P<2>	39
	ENET_100D	ENET_MDI	ENET_MDI_T_N<2>	39
ENET_MDI_T	ENET_100D	ENET_MDI	ENET_MDI_T_P<3>	39
	ENET_100D	ENET_MDI	ENET_MDI_T_N<3>	39
	ENET_100D	ENET_MDI	ENET_MDI_R_P<0>	
	ENET_100D	ENET_MDI	ENET_MDI_R_N<0>	
	ENET_100D	ENET_MDI	ENET_MDI_R_P<1>	
	ENET_100D	ENET_MDI	ENET_MDI_R_N<1>	
	ENET_100D	ENET_MDI	ENET_MDI_R_P<2>	
	ENET_100D	ENET_MDI	ENET_MDI_R_N<2>	
	ENET_100D	ENET_MDI	ENET_MDI_R_P<3>	
	ENET_100D	ENET_MDI	ENET_MDI_R_N<3>	
	CRT_50S	CRT	GPU_TV_COMP	85 91
	CRT_50S	CRT	GPU_TV_C	85 91
	CRT_50S	CRT	GPU_TV_Y	85 91
CRT_RED	CRT_50S	CRT	GPU_RED	85 91
CRT_GREEN	CRT_50S	CRT	GPU_GRN	85 91
CRT_BLUE	CRT_50S	CRT	GPU_BLU	85 91
(CRT_SYNC)	CRT_55S	CRT_SYNC	GPU_H2SYNC	85 91
(CRT_SYNC)	CRT_55S	CRT_SYNC	GPU_V2SYNC	85 91
CRT_SYNC	CRT_55S	CRT_SYNC	VGA_HSYNC	91 94
CRT_SYNC	CRT_55S	CRT_SYNC	VGA_VSYNC	91 94
(CRT_SYNC)	CRT_55S	CRT_SYNC	GPU_BUF_HSYNC	
(CRT_SYNC)	CRT_55S	CRT_SYNC	GPU_BUF_VSYNC	
	CRT_50S	CRT	VIDEO_MUX_RED	91
	CRT_50S	CRT	VIDEO_MUX_GRN	91
	CRT_50S	CRT	VIDEO_MUX_BLU	91
	CRT_55S	CRT	VGA_RED	91 94
	CRT_55S	CRT	VGA_GRN	91 94
	CRT_55S	CRT	VGA_BLU	91 94
THERM_DIFF	THERM_DIFF	THERMAL	HDD_THRMD_P	55
	THERM_DIFF	THERMAL	HDD_THRMD_N	55
THERM_DIFF	THERM_DIFF	THERMAL	ODD_THRMD_P	55
	THERM_DIFF	THERMAL	ODD_THRMD_N	55
THERM_DIFF	THERM_DIFF	THERMAL	CPU_THERMD_P	10 55
	THERM_DIFF	THERMAL	CPU_THERMD_N	10 55
THERM_DIFF	THERM_DIFF	THERMAL	GPU_HSK_THRMD_P	55
	THERM_DIFF	THERMAL	GPU_HSK_THRMD_N	55
THERM_DIFF	THERM_DIFF	THERMAL	CPU_HSK_THRMD_P	55
	THERM_DIFF	THERMAL	CPU_HSK_THRMD_N	55

M72/M78 SPECIFIC NET PROPERTIES

ELECTRICAL_CONSTRAINT_SET	NET_TYPE PHYSICAL	NET_TYPE SPACING		
		SWITCHNODE	IMVP6_PHASE1	71
		SWITCHNODE	IMVP6_PHASE2	71
		SWITCHNODE	IMVP6_PHASE3	72
		SWITCHNODE	1V05REG_SWITCHNODE	73
		SWITCHNODE	1V5REG_SWITCHNODE	73
		SWITCHNODE	MCH_CORES0_SWITCHNODE	74
		SWITCHNODE	1V25REG_SWITCHNODE	74
		SWITCHNODE	1V8S3_PHASE	75
		SWITCHNODE	5VS5_SW	76
		SWITCHNODE	3V3S3_SW	76
		SWITCHNODE	P3V3S5_SW	77
		SWITCHNODE	P2V5S0_SW	
		SMS	SMS_X_AXIS	49 50
		SMS	SMS_Y_AXIS	49 50
		SMS	SMS_Z_AXIS	49 50

M72/M78 SPECIFIC CONSTRAINTS

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A

SCALE: NONE

SHT 108 OF 118

www.laptopschematics.com

M72/M78 BOARD-SPECIFIC SPACING & PHYSICAL CONSTRAINTS

BOARD LAYERS	BOARD AREAS	BOARD UNITS (MIL or MM)	ALLEGRO VERSION
TOP,ISL2,ISL3,ISL4,ISL5,ISL6,ISL7,BOTTOM	NO_TYPE,BGA_P1MM	MM	15.5.1

PHYSICAL_RULE_SET	LAYER	ALLOW ROUTE ON LAYER?	MINIMUM LINE WIDTH	MINIMUM NECK WIDTH	MAXIMUM NECK LENGTH	DIFFPAIR PRIMARY GAP	DIFFPAIR NECK GAP
DEFAULT	*	Y	=55_OHM_SE	=55_OHM_SE	4 MM	0 MM	0 MM
STANDARD	*	Y	=DEFAULT	=DEFAULT	12.7 MM	=DEFAULT	=DEFAULT
DEFAULT	TOP,BOTTOM	Y	=55_OHM_SE	0.100 MM	3 MM	0 MM	0 MM

PHYSICAL_RULE_SET	LAYER	ALLOW ROUTE ON LAYER?	MINIMUM LINE WIDTH	MINIMUM NECK WIDTH	MAXIMUM NECK LENGTH	DIFFPAIR PRIMARY GAP	DIFFPAIR NECK GAP
55_OHM_SE	TOP,BOTTOM	Y	0.125 MM	0.125 MM			
55_OHM_SE	*	Y	0.100 MM	0.100 MM	=STANDARD	=STANDARD	=STANDARD

PHYSICAL_RULE_SET	LAYER	ALLOW ROUTE ON LAYER?	MINIMUM LINE WIDTH	MINIMUM NECK WIDTH	MAXIMUM NECK LENGTH	DIFFPAIR PRIMARY GAP	DIFFPAIR NECK GAP
40_OHM_SE	TOP,BOTTOM	Y	0.225 MM	0.225 MM			
40_OHM_SE	*	Y	0.185 MM	0.185 MM	=STANDARD	=STANDARD	=STANDARD

PHYSICAL_RULE_SET	LAYER	ALLOW ROUTE ON LAYER?	MINIMUM LINE WIDTH	MINIMUM NECK WIDTH	MAXIMUM NECK LENGTH	DIFFPAIR PRIMARY GAP	DIFFPAIR NECK GAP
45_OHM_SE	TOP,BOTTOM	Y	0.185 MM	0.185 MM			
45_OHM_SE	*	Y	0.150 MM	0.150 MM	=STANDARD	=STANDARD	=STANDARD

PHYSICAL_RULE_SET	LAYER	ALLOW ROUTE ON LAYER?	MINIMUM LINE WIDTH	MINIMUM NECK WIDTH	MAXIMUM NECK LENGTH	DIFFPAIR PRIMARY GAP	DIFFPAIR NECK GAP
27P4_OHM_SE	TOP,BOTTOM	Y	0.340 MM	0.340 MM			
27P4_OHM_SE	*	Y	0.265 MM	0.265 MM	=STANDARD	=STANDARD	=STANDARD

PHYSICAL_RULE_SET	LAYER	ALLOW ROUTE ON LAYER?	MINIMUM LINE WIDTH	MINIMUM NECK WIDTH	MAXIMUM NECK LENGTH	DIFFPAIR PRIMARY GAP	DIFFPAIR NECK GAP
70_OHM_DIFF	*	N	=STANDARD	=STANDARD	=STANDARD	=STANDARD	=STANDARD
70_OHM_DIFF	ISL3,ISL6	Y	0.180 MM	0.180 MM		0.120 MM	0.120 MM
70_OHM_DIFF	TOP,BOTTOM	Y	0.215 MM	0.215 MM		0.125 MM	0.125 MM

PHYSICAL_RULE_SET	LAYER	ALLOW ROUTE ON LAYER?	MINIMUM LINE WIDTH	MINIMUM NECK WIDTH	MAXIMUM NECK LENGTH	DIFFPAIR PRIMARY GAP	DIFFPAIR NECK GAP
85_OHM_DIFF	*	N	=STANDARD	=STANDARD	=STANDARD	=STANDARD	=STANDARD
85_OHM_DIFF	ISL3,ISL6	Y	0.120 MM	0.120 MM		0.130 MM	0.130 MM
85_OHM_DIFF	TOP,BOTTOM	Y	0.145 MM	0.145 MM		0.125 MM	0.125 MM

PHYSICAL_RULE_SET	LAYER	ALLOW ROUTE ON LAYER?	MINIMUM LINE WIDTH	MINIMUM NECK WIDTH	MAXIMUM NECK LENGTH	DIFFPAIR PRIMARY GAP	DIFFPAIR NECK GAP
90_OHM_DIFF	*	N	=STANDARD	=STANDARD	=STANDARD	=STANDARD	=STANDARD
90_OHM_DIFF	ISL3,ISL6	Y	0.125 MM	0.125 MM		0.200 MM	0.200 MM
90_OHM_DIFF	TOP,BOTTOM	Y	0.145 MM	0.145 MM		0.175 MM	0.175 MM

PHYSICAL_RULE_SET	LAYER	ALLOW ROUTE ON LAYER?	MINIMUM LINE WIDTH	MINIMUM NECK WIDTH	MAXIMUM NECK LENGTH	DIFFPAIR PRIMARY GAP	DIFFPAIR NECK GAP
100_OHM_DIFF	*	N	=STANDARD	=STANDARD	=STANDARD	=STANDARD	=STANDARD
100_OHM_DIFF	ISL3,ISL6	Y	0.095 MM	0.095 MM		0.205 MM	0.205 MM
100_OHM_DIFF	TOP,BOTTOM	Y	0.115 MM	0.115 MM		0.180 MM	0.180 MM

PHYSICAL_RULE_SET	LAYER	ALLOW ROUTE ON LAYER?	MINIMUM LINE WIDTH	MINIMUM NECK WIDTH	MAXIMUM NECK LENGTH	DIFFPAIR PRIMARY GAP	DIFFPAIR NECK GAP
110_OHM_DIFF	*	N	=STANDARD	=STANDARD	=STANDARD	=STANDARD	=STANDARD
110_OHM_DIFF	ISL3,ISL6	Y	0.085 MM	0.085 MM		0.330 MM	0.330 MM
110_OHM_DIFF	TOP,BOTTOM	Y	0.105 MM	0.100 MM		0.280 MM	0.280 MM

PHYSICAL_RULE_SET	LAYER	ALLOW ROUTE ON LAYER?	MINIMUM LINE WIDTH	MINIMUM NECK WIDTH	MAXIMUM NECK LENGTH	DIFFPAIR PRIMARY GAP	DIFFPAIR NECK GAP
1:1_DIFFPAIR	*	Y	=STANDARD	=STANDARD	=STANDARD	0.1 MM	0.1 MM

PHYSICAL_RULE_SET	LAYER	ALLOW ROUTE ON LAYER?	MINIMUM LINE WIDTH	MINIMUM NECK WIDTH	MAXIMUM NECK LENGTH	DIFFPAIR PRIMARY GAP	DIFFPAIR NECK GAP
110_OHM_DIFF_ESCAPE	*	N	=STANDARD	=STANDARD	=STANDARD	=STANDARD	=STANDARD
110_OHM_DIFF_ESCAPE	TOP,BOTTOM	Y	0.105 MM	0.100 MM		0.250 MM	0.250 MM
110_OHM_DIFF_ESCAPE	ISL3,ISL6	Y	0.085 MM	0.085 MM		0.330 MM	0.330 MM

PHYSICAL_RULE_SET	LAYER	ALLOW ROUTE ON LAYER?	MINIMUM LINE WIDTH	MINIMUM NECK WIDTH	MAXIMUM NECK LENGTH	DIFFPAIR PRIMARY GAP	DIFFPAIR NECK GAP
50_OHM_SE	TOP,BOTTOM	Y	0.15 MM	0.15 MM			
50_OHM_SE	*	Y	0.120 MM	0.120 MM	=STANDARD	=STANDARD	=STANDARD

SPACING_RULE_SET	LAYER	LINE-TO-LINE SPACING	WEIGHT
DEFAULT	*	0.1 MM	?
STANDARD	*	=DEFAULT	?
BGA_P1MM	*	=DEFAULT	?
BGA_P2MM	*	=DEFAULT	?
BGA_P3MM	*	=DEFAULT	?

SPACING_RULE_SET	LAYER	LINE-TO-LINE SPACING	WEIGHT
SPACING_0.15MM	*	0.15 MM	?
SPACING_0.18MM	*	0.18 MM	?
SPACING_0.2MM	*	0.2 MM	?
SPACING_0.25MM	*	0.25 MM	?
SPACING_0.3MM	*	0.3 MM	?
SPACING_0.4MM	*	0.4 MM	?
SPACING_0.5MM	*	0.5 MM	?
SPACING_0.6MM	*	0.6 MM	?
SWITCHNODE	*	0.6 MM	1000
SWITCHNODE	TOP,BOTTOM	0.2 MM	1000

NET_SPACING_TYPE1	NET_SPACING_TYPE2	AREA_TYPE	SPACING_RULE_SET
*	*	BGA_P1MM	BGA_P1MM
MEM_CLK	*	BGA_P1MM	BGA_P2MM
CLK_FSB	*	BGA_P1MM	BGA_P2MM
CLK_PCIE	*	BGA_P1MM	BGA_P2MM
CLK_MED	*	BGA_P1MM	BGA_P2MM
FSB_DSTB	FSB_DSTB	BGA_P1MM	BGA_P3MM

SPACING_RULE_SET	LAYER	LINE-TO-LINE SPACING	WEIGHT
CLK_SPACING_0.5MM	*	0.5 MM	?
CLK_SPACING_0.6MM	*	0.6 MM	?
CLK_SPACING_0.5MM	TOP,BOTTOM	0.2 MM	?
CLK_SPACING_0.6MM	TOP,BOTTOM	0.2 MM	?

www.laptop-schematics.com

M72/M78 RULE DEFINITIONS

SYNC_MASTER=K2_MLB SYNC_DATE=01/08/2008

NOTICE OF PROPRIETARY PROPERTY

THE INFORMATION CONTAINED HEREIN IS THE PROPRIETARY PROPERTY OF APPLE COMPUTER, INC. THE POSSESSOR AGREES TO THE FOLLOWING

I TO MAINTAIN THE DOCUMENT IN CONFIDENCE

II NOT TO REPRODUCE OR COPY IT

III NOT TO REVEAL OR PUBLISH IN WHOLE OR PART

APPLE INC.

SIZE	DRAWING NUMBER	REV.
D	051-7484	A

SCALE: NONE SHT 109 OF 118

Title: Basenet Report
Design: mlb
Date: Jan 8 14:44:54 2008

Base nets and synonyms for mlb_lib.MLB(@mlb_lib.mlb(sch_1))

Base Signal	Synonyms	Location([Zone][dir])
0V9S0_COMP_REF	0V9S0_COMP_REF - @mlb_lib.MLB	70C6
1V05REG_BOOT	1V05REG_BOOT - @mlb_lib.MLB	73C4
1V05REG_BOOT_R	1V05REG_BOOT_R - @mlb_lib.MLB	73C3
1V05REG_ISEN	1V05REG_ISEN - @mlb_lib.MLB	73C4
1V05REG_LGATE	1V05REG_LGATE - @mlb_lib.MLB	73C3
1V05REG_OCSET	1V05REG_OCSET - @mlb_lib.MLB	73B4
1V05REG_SNUBBER_R	1V05REG_SNUBBER_R - @mlb_lib.MLB	73C2
1V05REG_SOFT	1V05REG_SOFT - @mlb_lib.MLB	73C4
1V05REG_SWITCHNODE	1V05REG_SWITCHNODE - @mlb_lib.MLB	73B3 108D1
1V05REG_UGATE	1V05REG_UGATE - @mlb_lib.MLB	73C4
1V05REG_VSEN	1V05REG_VSEN - @mlb_lib.MLB	73B3
1V05S0_EN	1V05S0_EN - @mlb_lib.MLB	73B4
1V05S0_RUNSS	1V05S0_RUNSS - @mlb_lib.MLB	70C5 73C3 74C3
1V05S0_RUNSS_BUF	1V05S0_RUNSS_BUF - @mlb_lib.MLB	70C6
1V5REG_BOOT	1V5REG_BOOT - @mlb_lib.MLB	73C5
1V5REG_BOOT_R	1V5REG_BOOT_R - @mlb_lib.MLB	73C6
1V5REG_ISEN	1V5REG_ISEN - @mlb_lib.MLB	73C5
1V5REG_LGATE	1V5REG_LGATE - @mlb_lib.MLB	73C5
1V5REG_OCSET	1V5REG_OCSET - @mlb_lib.MLB	73B5
1V5REG_SNUBBER_R	1V5REG_SNUBBER_R - @mlb_lib.MLB	73B7
1V5REG_SOFT	1V5REG_SOFT - @mlb_lib.MLB	73C5
1V5REG_SWITCHNODE	1V5REG_SWITCHNODE - @mlb_lib.MLB	73C6 108D1
1V5REG_UGATE	1V5REG_UGATE - @mlb_lib.MLB	73C5
1V5REG_VSEN	1V5REG_VSEN - @mlb_lib.MLB	73B7
1V5S0_RUNSS	1V5S0_RUNSS - @mlb_lib.MLB	70A5 73C5
1V5S0_RUNSS_BUF	1V5S0_RUNSS_BUF - @mlb_lib.MLB	70A6
1V8S0_COMP_REF	1V8S0_COMP_REF - @mlb_lib.MLB	70D6
1V8S3_BOOT	1V8S3_BOOT - @mlb_lib.MLB	75C5
1V8S3_BOOT_RC	1V8S3_BOOT_RC - @mlb_lib.MLB	75D5
1V8S3_COMP	1V8S3_COMP - @mlb_lib.MLB	75C6
1V8S3_COMP_R	1V8S3_COMP_R - @mlb_lib.MLB	75C6
1V8S3_EN	1V8S3_EN - @mlb_lib.MLB	75C6
1V8S3_FB	1V8S3_FB - @mlb_lib.MLB	75C6
1V8S3_FCCM	1V8S3_FCCM - @mlb_lib.MLB	75C6
1V8S3_FSET	1V8S3_FSET - @mlb_lib.MLB	75C6
1V8S3_ISEN	1V8S3_ISEN - @mlb_lib.MLB	75C5
1V8S3_LG	1V8S3_LG - @mlb_lib.MLB	75C5
1V8S3_PHASE	1V8S3_PHASE - @mlb_lib.MLB	75C5 108D1
1V8S3_SNUBBER_R	1V8S3_SNUBBER_R - @mlb_lib.MLB	75C3
1V8S3_UG	1V8S3_UG - @mlb_lib.MLB	75C5
1V8S3_VCC	1V8S3_VCC - @mlb_lib.MLB	75D6
1V25REG_BOOT	1V25REG_BOOT - @mlb_lib.MLB	74C5
1V25REG_BOOT_R	1V25REG_BOOT_R - @mlb_lib.MLB	74C6
1V25REG_ISEN	1V25REG_ISEN - @mlb_lib.MLB	74C5
1V25REG_LGATE	1V25REG_LGATE - @mlb_lib.MLB	74C5
1V25REG_OCSET	1V25REG_OCSET - @mlb_lib.MLB	74B5
1V25REG_SNUBBER_R	1V25REG_SNUBBER_R - @mlb_lib.MLB	74B7
1V25REG_SOFT	1V25REG_SOFT - @mlb_lib.MLB	74C5
1V25REG_SWITCHNODE	1V25REG_SWITCHNODE - @mlb_lib.MLB	74C6 108D1
1V25REG_UGATE	1V25REG_UGATE - @mlb_lib.MLB	74C5
1V25REG_VSEN	1V25REG_VSEN - @mlb_lib.MLB	74B7
1V25S0_RUNSS	1V25S0_RUNSS - @mlb_lib.MLB	70B5 74C5
1V25S0_RUNSS_BUF	1V25S0_RUNSS_BUF - @mlb_lib.MLB	70B6
3V3S0_COMP_REF	3V3S0_COMP_REF - @mlb_lib.MLB	70D6
3V3S3_BG	3V3S3_BG - @mlb_lib.MLB	76B5
3V3S3_BOOST	3V3S3_BOOST - @mlb_lib.MLB	76B5
3V3S3_BOOST_R	3V3S3_BOOST_R - @mlb_lib.MLB	76C6
3V3S3_ITH	3V3S3_ITH - @mlb_lib.MLB	76B5
3V3S3_ITH_R	3V3S3_ITH_R - @mlb_lib.MLB	76B6
3V3S3_RUNSS	3V3S3_RUNSS - @mlb_lib.MLB	76B5
3V3S3_SNS_N	3V3S3_SNS_N - @mlb_lib.MLB	76C6
3V3S3_SNS_P	3V3S3_SNS_P - @mlb_lib.MLB	76C6
3V3S3_SW	3V3S3_SW - @mlb_lib.MLB	76B5 108D1
3V3S3_TG	3V3S3_TG - @mlb_lib.MLB	76C5
3V3S3_VOSNS	3V3S3_VOSNS - @mlb_lib.MLB	76B5
5VS0_COMP_REF	5VS0_COMP_REF - @mlb_lib.MLB	70C6
5VS3_COMP_REF	5VS3_COMP_REF - @mlb_lib.MLB	76A7
5VS5_0V76_REF	5VS5_0V76_REF - @mlb_lib.MLB	70C6
5VS5_1V53_REF	5VS5_1V53_REF - @mlb_lib.MLB	70D6
5VS5_2V80_REF	5VS5_2V80_REF - @mlb_lib.MLB	70D6
5VS5_4V24_REF1	5VS5_4V24_REF1 - @mlb_lib.MLB	70D6
5VS5_4V24_REF2	5VS5_4V24_REF2 - @mlb_lib.MLB	76A7
5VS5_4V29_REF	5VS5_4V29_REF - @mlb_lib.MLB	76D7
5VS5_BG	5VS5_BG - @mlb_lib.MLB	76B4
5VS5_BOOST	5VS5_BOOST - @mlb_lib.MLB	76B4
5VS5_BOOST_R	5VS5_BOOST_R - @mlb_lib.MLB	76C3
5VS5_ITH	5VS5_ITH - @mlb_lib.MLB	76B4
5VS5_ITH_R	5VS5_ITH_R - @mlb_lib.MLB	76B3
5VS5_RUNSS	5VS5_RUNSS - @mlb_lib.MLB	76B4
5VS5_SNS_N	5VS5_SNS_N - @mlb_lib.MLB	76C3
5VS5_SNS_P	5VS5_SNS_P - @mlb_lib.MLB	76C3
5VS5_SW	5VS5_SW - @mlb_lib.MLB	76B4 108D1
5VS5_TG	5VS5_TG - @mlb_lib.MLB	76C4
5VS5_VOSNS	5VS5_VOSNS - @mlb_lib.MLB	76B4
12VS0_6V0_REF	12VS0_6V0_REF - @mlb_lib.MLB	76D7
12VS0_COMP_REF	12VS0_COMP_REF - @mlb_lib.MLB	76D7
=ENET_VMAIN_AVLBL	=ENET_VMAIN_AVLBL - @mlb_lib.MLB	37C2 38B3
	PP3V3_S0 - @mlb_lib.MLB	6B8 6C6 6D7 7C5 7D3 13D6 53C3 70C3 70D3 70D8 77B6 78C1
	=PP3V3_DDC_LCD - @mlb_lib.MLB	90A8 90D5
	=PP3V3_S0_VIDEO - @mlb_lib.MLB	6A4 90D7 91B4 91B4 91B7 94D2
	=PP3V3_S0_NB_VCCA_PEG_BG - @mlb_lib.MLB	6A4 19C6 21A6
	=PP3V3_S0_NB_FOLLOW - @mlb_lib.MLB	6A4 21C2
	=PP3V3_S0_TSENS - @mlb_lib.MLB	6A4 55B5 55D5 55D5 55D6 55D8
	=PP3V3_S0_SMC - @mlb_lib.MLB	6A4 53D5
	=PP3V3_S0MSWDL_SB_VCCCL3_3 - @mlb_lib.MLB	6A4 26A6 27D4
	=PP3V3_S0MSWDL_SB_VCCLAN3_3 - @mlb_lib.MLB	6A4 26A3 27D4
	=PP3V3_S0_SB_VCC3_3_VCCPCORE - @mlb_lib.MLB	6B4 26C3
	=PP3V3R1V5_S0_SB_VCCHDA - @mlb_lib.MLB	6B4 26B3 27B4
	=PP3V3_S0_SB_VCC3_3_DMI - @mlb_lib.MLB	6B4 26C3 27C4
	=PP3V3_S0_SB_VCC3_3_SATA - @mlb_lib.MLB	6B4 26C3 27C4
	=PP3V3_S0MWOL_SB_CLINK0 - @mlb_lib.MLB	6B4 25C1
	=PP3V3_S0M_CK505 - @mlb_lib.MLB	6B4 29D2 29D8 30D1
	=PP3V3_S0_SATALED - @mlb_lib.MLB	6B4 45C3
	=PP3V3_S0_MXM - @mlb_lib.MLB	6B4 85A3 85C4 85C8 85C8 85D2
	=PP3V3_S0_CK505 - @mlb_lib.MLB	6B4 29C7 30D7
	=PP3V3_S0_SMBUS_SMC_B_S0 - @mlb_lib.MLB	6B4 52C5
	=PP3V3_S0_SMBUS_SMC_MGMT - @mlb_lib.MLB	6B4 52B3
	=PP3V3_S0_SMBUS_SMC_0_S0 - @mlb_lib.MLB	6B4 52D5
	=PP3V3_S0_SMC_LS - @mlb_lib.MLB	6B4 50D2
	=PP3V3_S0_LPCPLUS - @mlb_lib.MLB	6B4 51C4
	=PP3V3_S0_SMBUS_SB - @mlb_lib.MLB	6B4 52D8
	=PP3V3_S0_IMVP - @mlb_lib.MLB	6B4 71D8
	=PP3V3_S0_AUDIO - @mlb_lib.MLB	6B4 98C4 98C6
	=PPSPD_S0_MEM - @mlb_lib.MLB	6B4 31A7 32A3 32A7
	=PP3V3_S0_FAN - @mlb_lib.MLB	6B4 56B7 56C7 57C7
	=PP3V3_S0_SB_PM - @mlb_lib.MLB	6B4 28A7
	=PP3V3_S0_PATA - @mlb_lib.MLB	6B4 44C6
	=PP3V3_S0_SB_PCI - @mlb_lib.MLB	6B4 24A3
	=PP3V3_S0_SB_VCC3_3_IDE - @mlb_lib.MLB	6B4 26C3 27D4
	=PP3V3_S0_SB_VCC3_3_PCI - @mlb_lib.MLB	6B4 26B3 27C4
	=PP3V3_S0_SB_GPIO - @mlb_lib.MLB	6B4 23D2 23D7 25B3 25D8
	=PP3V3_S0_SB_VCCGLAN3_3 - @mlb_lib.MLB	6B4 26A6
	=PP3V3_S0_SB - @mlb_lib.MLB	6C4 27D8
	=PP3V3_S0_NB_VCCHV - @mlb_lib.MLB	6C4 16B7 16C7 16C7 19B3 21A8
	PP3V3_S0 - @mlb_lib.MLB	6B8 6C6 6D7 7C5 7D3 13D6 53C3 70C3 70D3 70D8 77B6 78C1
	=PPSPD_S0_MEM - @mlb_lib.MLB	6B4 31A7 32A3 32A7
	=PP3V3_S0_VIDEO - @mlb_lib.MLB	6A4 90D7 91B4 91B4 91B7 94D2
	=PP3V3_S0_TSENS - @mlb_lib.MLB	6A4 55B5 55D5 55D5 55D6 55D8
	=PP3V3_S0_SMC_LS - @mlb_lib.MLB	6B4 50D2
	=PP3V3_S0_SMC - @mlb_lib.MLB	6A4 53D5
	=PP3V3_S0_SMBUS_SMC_MGMT - @mlb_lib.MLB	6B4 52B3
	=PP3V3_S0_SMBUS_SMC_B_S0 - @mlb_lib.MLB	6B4 52C5
	=PP3V3_S0_SMBUS_SMC_0_S0 - @mlb_lib.MLB	6B4 52D5
	=PP3V3_S0_SMBUS_SB - @mlb_lib.MLB	6B4 52D8
	=PP3V3_S0_SB_VCCGLAN3_3 - @mlb_lib.MLB	6B4 26A6
	=PP3V3_S0_SB_VCC3_3_VCCPCORE - @mlb_lib.MLB	6B4 26C3
	=PP3V3_S0_SB_VCC3_3_SATA - @mlb_lib.MLB	6B4 26C3 27C4
	=PP3V3_S0_SB_VCC3_3_PCI - @mlb_lib.MLB	6B4 26B3 27C4
	=PP3V3_S0_SB_VCC3_3_IDE - @mlb_lib.MLB	6B4 26C3 27D4
	=PP3V3_S0_SB_VCC3_3_DMI - @mlb_lib.MLB	6B4 26C3 27C4
	=PP3V3_S0_SB_PM - @mlb_lib.MLB	6B4 28A7
	=PP3V3_S0_SB_PCI - @mlb_lib.MLB	6B4 24A3
	=PP3V3_S0_SB_GPIO - @mlb_lib.MLB	6B4 23D2 23D7 25B3 25D8
	=PP3V3_S0_SB - @mlb_lib.MLB	6C4 27D8
	=PP3V3_S0_SATALED - @mlb_lib.MLB	6B4 45C3
	=PP3V3_S0_PATA - @mlb_lib.MLB	6B4 44C6
	=PP3V3_S0_NB_VCCHV - @mlb_lib.MLB	6C4 16B7 16C7 16C7 19B3 21A8
	=PP3V3_S0_NB_VCCA_PEG_BG - @mlb_lib.MLB	6A4 19C6 21A6
	=PP3V3_S0_NB_FOLLOW - @mlb_lib.MLB	6A4 21C2
	=PP3V3_S0_MXM - @mlb_lib.MLB	6B4 85A3 85C4 85C8 85C8 85D2
	=PP3V3_S0_LPCPLUS - @mlb_lib.MLB	6B4 51C4
	=PP3V3_S0_IMVP - @mlb_lib.MLB	6B4 71D8
	=PP3V3_S0_FAN - @mlb_lib.MLB	6B4 56B7 56C7 57C7
	=PP3V3_S0_ENET - @mlb_lib.MLB	6A4 38B1
	=PP3V3_S0_CK505 - @mlb_lib.MLB	6B4 29C7 30D7
	=PP3V3_S0_AUDIO - @mlb_lib.MLB	6B4 98C4 98C6
	=PP3V3_S0M_CK505 - @mlb_lib.MLB	6B4 29D2 29D8 30D1
	=PP3V3_S0MWOL_SB_VCCLAN3_3 - @mlb_lib.MLB	6A4 26A3 27D4
	=PP3V3_S0MWOL_SB_VCCCL3_3 - @mlb_lib.MLB	6A4 26A6 27D4
	=PP3V3_S0MWOL_SB_CLINK0 - @mlb_lib.MLB	6B4 25C1
	=PP3V3R1V5_S0_SB_VCCHDA - @mlb_lib.MLB	6B4 26B3 27B4
=GFX_VR_EN	=GFX_VR_EN - @mlb_lib.MLB	16B3 22A8
	TP_GFX_VR_EN - @mlb_lib.MLB	22A7
=GND_NB_VSSA_LVDS	=GND_NB_VSSA_LVDS - @mlb_lib.MLB	19C6 22C1
	TP_NB_VSSA_LVDS - @mlb_lib.MLB	22C2
=NB_CLINK_MPWROK	=NB_CLINK_MPWROK - @mlb_lib.MLB	16A3 22C2
	VR_PWRGOOD_DELAY - @mlb_lib.MLB	7C4 7C7 16B6 22C1 70C2 71C7
=PP0V9_S0M_MEM_TERM	=PP0V9_S0M_MEM_TERM - @mlb_lib.MLB	6D4 33D5
	PP0V9_S0 - @mlb_lib.MLB	6D6 7D3 70C8 75A3
=PP0V9_S3M_MEM_NBVRE FA	=PP0V9_S3M_MEM_NBVREFA - @mlb_lib.MLB	7C7 16C2 22B1
	PP0V9_S3M_MEM_NBVREFA - @mlb_lib.MLB	22B2
=PP0V9_S3M_MEM_NBVRE FB	=PP0V9_S3M_MEM_NBVREFB - @mlb_lib.MLB	7C7 16C2 22A1
	PP0V9_S3M_MEM_NBVREFB - @mlb_lib.MLB	22A2
=PP0V9_S3_MEM_A_VREF	=PP0V9_S3_MEM_A_VREF - @mlb_lib.MLB	31C1 31D6
	PP0V9_S3_MEM_A_VREF - @mlb_lib.MLB	31C2
=PP0V9_S3_MEM_B_VREF	=PP0V9_S3_MEM_B_VREF - @mlb_lib.MLB	32C1 32D7
	PP0V9_S3_MEM_B_VREF - @mlb_lib.MLB	32C2
=PP1V2_ENET_PHY	=PP1V2_ENET_PHY - @mlb_lib.MLB	37D6 38A3
	PP1V2_S3_ENET - @mlb_lib.MLB	38A3
=PP1V05_S0M_NB_VCCAX M	=PP1V05_S0M_NB_VCCAXM - @mlb_lib.MLB	6C4 18B3 18C1 21D8
	=PP1V05_S0_NB_FOLLOW - @mlb_lib.MLB	6C4 21C4
	=PPVCORE_S0_SB - @mlb_lib.MLB	6C4 26D3 27B1
	PP1V05_S0 - @mlb_lib.MLB	6C6 7D3 34C3 73A4 73C1
	=PP1V05_S0_NB_PCIE - @mlb_lib.MLB	6C4 21D5
	PP1V05_S0 - @mlb_lib.MLB	6C6 7D3 34C3 73A4 73C1
	=PPVCORE_S0_SB - @mlb_lib.MLB	6C4 26D3 27B1
	=PP1V05_S0_NB_PCIE - @mlb_lib.MLB	6C4 21D5
	=PP1V05_S0_NB_FOLLOW - @mlb_lib.MLB	6C4 21C4
=PP1V05_S0_CPU	=PP1V05_S0_CPU - @mlb_lib.MLB	6D4 10B5 10B6 10C5 10D5 11C6 12A3 13D6 50D2
	=PP1V05_S0_SB_CPU_IO - @mlb_lib.MLB	6C4 23D2 26C3 27B2
	=PPVCORE_S0_NB_FOLLOW - @mlb_lib.MLB	6D4 21B4
	PPMCH_CORE_S0 - @mlb_lib.MLB	6D6 7D3 55A6 73A2 74C1
	=PP1V25R1V05_S0_NB_VTT - @mlb_lib.MLB	6D4 19D3 21C8
	=PP1V25R1V05_S0_FSB_NB - @mlb_lib.MLB	6D4 14B7 30B8 30C8 30C8
	=PPVCORE_S0_NB - @mlb_lib.MLB	6D4 18D3 18D7 21D8
	=PP1V25R1V05_S0_NB_VTT - @mlb_lib.MLB	6D4 19D3 21C8
	=PP1V25R1V05_S0_FSB_NB - @mlb_lib.MLB	6D4 14B7 30B8 30C8 30C8
	=PP1V05_S0_SB_CPU_IO - @mlb_lib.MLB	6C4 23D2 26C3 27B2
=PP1V5_S0_CPU	=PP1V5_S0_CPU - @mlb_lib.MLB	6C4 11B6 12B3
	=PP1V5_S0_MINI - @mlb_lib.MLB	6C4 34C2
	PP1V5_S0 - @mlb_lib.MLB	6C6 7D3 73C8
	=PP1V5_S0_SB - @mlb_lib.MLB	6C4 27C8
	PP1V5_S0_SB_VCCGLANPLL - @mlb_lib.MLB	26A6 27B6
	=PP1V5_S0_SB_VCC1_5_A - @mlb_lib.MLB	6C4 26B6
	=PP1V5_S0_SB_VCCUSBPLL - @mlb_lib.MLB	6C4 26A6 27C2
	=PP1V5_S0_SB_VCC1_5_A_USB_CORE - @mlb_lib.MLB	6C4 26B6 27C2
	=PP1V5_S0_SB_VCC1_5_A_ATX - @mlb_lib.MLB	6C4 26B6 27D2
	=PP1V5_S0_SB_VCC1_5_A_ARX - @mlb_lib.MLB	6C4 26B6 27D2
	=PP1V5_S0_NB_TVDAC - @mlb_lib.MLB	6C4 22B3
	PP1V5_S0 - @mlb_lib.MLB	6C6 7D3 73C8
	=PP1V5_S0_SB_VCCUSBPLL - @mlb_lib.MLB	6C4 26A6 27C2
	=PP1V5_S0_SB_VCC1_5_A_USB_CORE - @mlb_lib.MLB	6C4 26B6 27C2
	=PP1V5_S0_SB_VCC1_5_A_ATX - @mlb_lib.MLB	6C4 26B6 27D2
	=PP1V5_S0_SB_VCC1_5_A_ARX - @mlb_lib.MLB	6C4 26B6 27D2
	=PP1V5_S0_SB_VCC1_5_A - @mlb_lib.MLB	6C4 26B6
	=PP1V5_S0_SB - @mlb_lib.MLB	6C4 27C8
	=PP1V5_S0_NB_TVDAC - @mlb_lib.MLB	6C4 22B3
	=PP1V5_S0_MINI - @mlb_lib.MLB	6C4 34C2
=PP1V5_S0_SB_VCCGLAN 1_5	=PP1V5_S0_SB_VCCGLAN1_5 - @mlb_lib.MLB	26A6 27B6
	PP1V5_S0_SB_VCC1_5_B - @mlb_lib.MLB	23D7 24C2 26D6 27C6
=PP1V8_S0_MXM	=PP1V8_S0_MXM - @mlb_lib.MLB	6D4 84C8
	PP1V8_S0 - @mlb_lib.MLB	6D6 7D3 70D8 78B5
=PP1V8_S3M_MEM_NB	=PP1V8_S3M_MEM_NB - @mlb_lib.MLB	6D3 16D2 18D7 21C8 22B3
	=PP1V8_S3M_NB_VCC - @mlb_lib.MLB	6D3 21A4
	=PP1V8_S3_ENET - @mlb_lib.MLB	6D3 38B7
	PP1V8_S3 - @mlb_lib.MLB	6D4 7D3 75B3 75C1 78C6
	=PP1V8_S3_MEMVTT - @mlb_lib.MLB	6D3 75B6
	=PP1V8_S3_MEM - @mlb_lib.MLB	6D3 31B2 31D2 31D3 31D6 32B2 32D2 32D3 32D6
	PP1V8_S3 - @mlb_lib.MLB	6D4 7D3 75B3 75C1 78C6
	=PP1V8_S3_MEMVTT - @mlb_lib.MLB	6D3 75B6
	=PP1V8_S3_MEM - @mlb_lib.MLB	6D3 31B2 31D2 31D3 31D6 32B2 32D2 32D3 32D6
	=PP1V8_S3_ENET - @mlb_lib.MLB	6D3 38B7
	=PP1V8_S3M_NB_VCC - @mlb_lib.MLB	6D3 21A4
=PP1V25_S0M_NB_PLL	=PP1V25_S0M_NB_PLL - @mlb_lib.MLB	6C4 21D3
	=PP1V25_S0M_NB_VCCD_HPLL - @mlb_lib.MLB	19A6 21D1
	=PP1V25_S0_SB_DMI - @mlb_lib.MLB	6C4 26C3 27C1
	PP1V25_S0 - @mlb_lib.MLB	6C6 7D3 74C8
	=PP1V25_S0_NB_VCC - @mlb_lib.MLB	6C4 21D5
	=PP1V25_S0_NB_PLL - @mlb_lib.MLB	6C4 21B4
	=PP1V25_S0M_NB_VCC - @mlb_lib.MLB	6C4 21A8
	=PP1V25_S0M_NB_VCCA - @mlb_lib.MLB	6C4 21B8
	=PP1V25_S0_NB_VCCDMI - @mlb_lib.MLB	6C4 19C3 21A8
=PP2V5_S0_MXM	=PP2V5_S0_MXM - @mlb_lib.MLB	6D4 85A3
	PP2V5_S0 - @mlb_lib.MLB	6D6 7D3 77B4
=PP3V3_ENET_PHY	=PP3V3_ENET_PHY - @mlb_lib.MLB	37D6 38D6
	=PP3V3_S3_ENET - @mlb_lib.MLB	6D3 38C7 39A8
	=PP3V3_S3_BT - @mlb_lib.MLB	6D3 47D3
	=PP3V3_S3_MINI - @mlb_lib.MLB	6D3 34D2
	PP3V3_S3 - @mlb_lib.MLB	6A7 6D4 7C6 7D3 70D2 75D7 76B8 78C4
	=PP3V3_S3_MINI - @mlb_lib.MLB	6D3 34D2
	=PP3V3_S3_ENET - @mlb_lib.MLB	6D3 38C7 39A8
	=PP3V3_S3_BT - @mlb_lib.MLB	6D3 47D3
=PP3V3_S5_FAN	=PP3V3_S5_FAN - @mlb_lib.MLB	6D1 56B7 56D7 57D7
	=PP3V3_S5_SMBUS_SMC_A_S5 - @mlb_lib.MLB	6D1 52D3
	PP3V3_S5 - @mlb_lib.MLB	6A8 6D2 7C3 70B3 70C7 70D3 75D8 77D3
	=PP3V3_S5_SMCUSBMUX - @mlb_lib.MLB	6D1 46D5
	=PP3V3_S5_SMBUS_SMC_BSA - @mlb_lib.MLB	6D1 52C3
	=PP3V3_S5_LPCPLUS - @mlb_lib.MLB	6D1 7D4 51C6
	=PP3V3_S5_SB_3V3_VCCSUSHDA - @mlb_lib.MLB	6D1 26B3 27B4
	=PP3V3_S5_SB_CLINK1 - @mlb_lib.MLB	6D1 25B1
	=PP3V3_S5_SB_GPIO - @mlb_lib.MLB	6D1 25D8
	=PP3V3_S5_ROM - @mlb_lib.MLB	6D1 61C6
	=PP3V3_S5_SMC - @mlb_lib.MLB	6D1 49D4 50B1 50D7
	=PP3V3_S5_FW - @mlb_lib.MLB	6D1 40C2 40D3 40D4 42B3 42B6 42B8 42C8 42D3 43A8
	=PP3V3_S5_SMBUS_SB_ME - @mlb_lib.MLB	6D1 52A8
	=PP3V3_S5_SB_VCCSUS3_3_USB - @mlb_lib.MLB	6D1 26A3 27C5
	=PP3V3_S5_SB_VCCSUS3_3 - @mlb_lib.MLB	6D1 26A3 27D5
	=PP3V3_S5_SB_USB - @mlb_lib.MLB	6D1 24C8
	=PP3V3_S5_SB_PM - @mlb_lib.MLB	6D1 28A5
	=PP3V3_S5_SB_GPIO - @mlb_lib.MLB	6D1 25D8
	=PP3V3_S5_SB_CLINK1 - @mlb_lib.MLB	6D1 25B1
	=PP3V3_S5_SB_3V3_VCCSUSHDA - @mlb_lib.MLB	6D1 26B3 27B4
	=PP3V3_S5_SB - @mlb_lib.MLB	6D1 25A3 25A8 27D8 28D7
	=PP3V3_S5_ROM - @mlb_lib.MLB	6D1 61C6
	=PP3V3_S5_LPCPLUS - @mlb_lib.MLB	6D1 7D4 51C6
	=PP3V3_S5_FW - @mlb_lib.MLB	6D1 40C2 40D3 40D4 42B3 42B6 42B8 42C8 42D3 43A8
=PP5V_S0_AUDIO	=PP5V_S0_AUDIO - @mlb_lib.MLB	6A4 98C4 98C6
	=PP5V_S0_MXM - @mlb_lib.MLB	6A4 84C8
	=PPV_S0_LCD_20INCH - @mlb_lib.MLB	6A4 90C8
	PP5V_S0 - @mlb_lib.MLB	6A6 7D3 70C8 71D8 72D7 73C7 74C7 78D1 94D6
	=PP5V_S0_SATA - @mlb_lib.MLB	6A4 6D6
	=PP5V_S0_LPCPLUS - @mlb_lib.MLB	6A4 7D4 51C6
	=PP5V_S0_PATA - @mlb_lib.MLB	6A4 44B6 44D6
	=PP5V_S0_SB - @mlb_lib.MLB	6A4 27D8
	PP5V_S0 - @mlb_lib.MLB	6A6 7D3 70C8 71D8 72D7 73C7 74C7 78D1 94D6
	=PPV_S0_LCD_20INCH - @mlb_lib.MLB	6A4 90C8
	=PP5V_S0_SB - @mlb_lib.MLB	6A4 27D8
	=PP5V_S0_PATA - @mlb_lib.MLB	6A4 44B6 44D6
	=PP5V_S0_MXM - @mlb_lib.MLB	6A4 84C8
	=PP5V_S0_LPCPLUS - @mlb_lib.MLB	6A4 7D4 51C6
=PP5V_S3_BNDI	=PP5V_S3_BNDI - @mlb_lib.MLB	6C3 47A3 47D7
	=PP5V_S3_MEMVTT - @mlb_lib.MLB	6C3 75B6
	PP5V_S3 - @mlb_lib.MLB	6C4 7D3 70D3 75D8 76A8 78D5
	=PP5V_S3_MEMVTT - @mlb_lib.MLB	6C3 75B6
=PP5V_S5_SB	=PP5V_S5_SB - @mlb_lib.MLB	6C1 27D8
	=PP5V_S5_USB - @mlb_lib.MLB	6C1 46C8 46D8
	PP5V_S5 - @mlb_lib.MLB	6C2 7C3 70A7 70D8 76A8 76B1 76B5 76D8 77D6 78C7 78D4 78D7
	=PPVIN_S5_SMCVREF - @mlb_lib.MLB	6C1 50B8
	PP5V_S5 - @mlb_lib.MLB	6C2 7C3 70A7 70D8 76A8 76B1 76B5 76D8 77D6 78C7 78D4 78D7
	=PPVIN_S5_SMCVREF - @mlb_lib.MLB	6C1 50B8
	=PP5V_S5_USB - @mlb_lib.MLB	6C1 46C8 46D8
=PP12V_S0_AUDIO_SPKR AMP	=PP12V_S0_AUDIO_SPKRAMP - @mlb_lib.MLB	6A4 98C6
	=PP12V_S0_CPU - @mlb_lib.MLB	6A4 53B8 71D8 72D7
	=PPV_S0_LCD_24INCH - @mlb_lib.MLB	6A4 90C8
	=PPV_S0_MXM_PWRSRC - @mlb_lib.MLB	6A4 53D4
	P12V_S0 - @mlb_lib.MLB	6A6 7D3 53B3 53B4 73D7 74D7 76D8
	=PP12V_S0_FAN - @mlb_lib.MLB	6A4 56B6 56D7 57D6
	P12V_S0 - @mlb_lib.MLB	6A6 7D3 53B3 53B4 73D7 74D7 76D8
	=PPV_S0_MXM_PWRSRC - @mlb_lib.MLB	6A4 53D4
	=PPV_S0_LCD_24INCH - @mlb_lib.MLB	6A4 90C8
	=PP12V_S0_FAN - @mlb_lib.MLB	6A4 56B6 56D7 57D6
	=PP12V_S0_CPU - @mlb_lib.MLB	6A4 53B8 71D8 72D7
=PP12V_S5_FET	=PP12V_S5_FET - @mlb_lib.MLB	6C1
	PP12V_S5 - @mlb_lib.MLB	6C2 7C3 53B5 53C4 70D8 75D8 76A8 76D5 76D8
	=PP12V_S5_FW - @mlb_lib.MLB	6C1 43D8
	PP12V_S5 - @mlb_lib.MLB	6C2 7C3 53B5 53C4 70D8 75D8 76A8 76D5 76D8
=PPVCORE_S0_CPU	=PPVCORE_S0_CPU - @mlb_lib.MLB	6D4 11B5 11D6 12D7 53B6 53D8
	PPVCORE_CPU - @mlb_lib.MLB	6D6 7D3 71D1 72C1
=SB_CLINK_MPWROK	=SB_CLINK_MPWROK - @mlb_lib.MLB	25C3 28B7
	PM_SB_PWROK - @mlb_lib.MLB	7C4 7C4 25C3 28B6 70C1
=SMC_SMS_INT	=SMC_SMS_INT - @mlb_lib.MLB	49B5 50B2
	SMC_SMS_INT - @mlb_lib.MLB	50B2
ACDC_TEMP	ACDC_TEMP - @mlb_lib.MLB	6D6 50C2
	SMC_ANALOG_ID - @mlb_lib.MLB	49A8 50C3
ALL_SYS_PWRGD	ALL_SYS_PWRGD - @mlb_lib.MLB	7C4 7C4 49D8 50C2 70C1 84C7
	PM_LAN_PWRGD - @mlb_lib.MLB	49C5 50C3
ALS_GAIN	ALS_GAIN - @mlb_lib.MLB	49A5 50D5
	NC_ALS_GAIN - @mlb_lib.MLB	50D3
ALS_LEFT	ALS_LEFT - @mlb_lib.MLB	49A8 50D5
	TP_ALS_LEFT - @mlb_lib.MLB	50D3
ALS_RIGHT	ALS_RIGHT - @mlb_lib.MLB	49A8

8		7		6		5		4		3		2		1
CK505_PCI3_CLK	CK505_PCI3_CLK - @mlb_lib.MLB	29B5 30A5 105D3	DMI_S2N_P<3..1>	DMI_S2N_P<3..1> - @mlb_lib.MLB	101D3	FSB_DINV_L<3>	FSB_DINV_L<3> - @mlb_lib.MLB	7D7 7D8 10B2 14B3 100C3	FW_PORT0_TPB_P	FW_PORT0_TPB_P - @mlb_lib.MLB	43C5 43C6 106D3		
CK505_PCI4_CLK	CK505_PCI4_CLK - @mlb_lib.MLB	29B5 30A5 105D3	DMI_S2N_P<2>	DMI_S2N_P<2> - @mlb_lib.MLB	16B3 24D2	FSB_DPWR_L	FSB_DPWR_L - @mlb_lib.MLB	7C7 10B2 14B3 100D3		FW_P0_TPB_P - @mlb_lib.MLB	40C6 43C8		
	TP_CK505_PCI4_CLK - @mlb_lib.MLB	30A3	DMI_S2N_P<3>	DMI_S2N_P<3> - @mlb_lib.MLB	16B3 24D2	FSB_DRDY_L	FSB_DRDY_L - @mlb_lib.MLB	10D6 14B3 100D3	FW_PORT0_VP	FW_PORT0_VP - @mlb_lib.MLB	43D3		
CK505_PCI5_CLK_FCTSE	CK505_PCI5_CLK_FCTSEL -	29B5 30D8 105D3	DVI_DDC_CLK	DVI_DDC_CLK - @mlb_lib.MLB	94D2	FSB_DSTB_L_N<0>	FSB_DSTB_L_N<0> - @mlb_lib.MLB	7D7 7D8 10C4 14B3 100C3	FW_PORT0_VP_F	FW_PORT0_VP_F - @mlb_lib.MLB	43D5		
L	@mlb_lib.MLB		DVI_DDC_CLK_UF	DVI_DDC_CLK_UF - @mlb_lib.MLB	94D3 94D5	FSB_DSTB_L_N<1>	FSB_DSTB_L_N<1> - @mlb_lib.MLB	7D7 7D8 10B4 14B3 100C3	FW_PORT1_TPA_FL_N	FW_PORT1_TPA_FL_N - @mlb_lib.MLB	43B2 106D3		
CK505_PCIF0_CLK_ITPE	CK505_PCIF0_CLK_ITPEN -	29B7 30A5 105D3	DVI_DDC_DATA	DVI_DDC_DATA - @mlb_lib.MLB	94C2	FSB_DSTB_L_N<2>	FSB_DSTB_L_N<2> - @mlb_lib.MLB	7D7 7D8 10C2 14B3 100C3	FW_PORT1_TPA_FL_P	FW_PORT1_TPA_FL_P - @mlb_lib.MLB	43B2 106D3		
N	@mlb_lib.MLB		DVI_DDC_DATA_UF	DVI_DDC_DATA_UF - @mlb_lib.MLB	94C3 94D5	FSB_DSTB_L_N<3>	FSB_DSTB_L_N<3> - @mlb_lib.MLB	7D7 7D8 10B2 14B3 100C3	FW_PORT1_TPA_N	FW_PORT1_TPA_N - @mlb_lib.MLB	43B6 43C6 106D3		
CK505_PCIF1_CLK	CK505_PCIF1_CLK - @mlb_lib.MLB	29B5 30A5 105D3	DVI_HOTPLUG_DET	DVI_HOTPLUG_DET - @mlb_lib.MLB	24A6 28B2	FSB_DSTB_L_P<0>	FSB_DSTB_L_P<0> - @mlb_lib.MLB	7D7 7D8 10C4 14B3 100D3		FW_P1_TPA_N - @mlb_lib.MLB	40C6 43C8		
CK505_REF0_FSC	CK505_REF0_FSC - @mlb_lib.MLB	29A3 30A8 105D3		SB_GPIO4 - @mlb_lib.MLB	28B2	FSB_DSTB_L_P<1>	FSB_DSTB_L_P<1> - @mlb_lib.MLB	7D7 7D8 10B4 14B3 100C3	FW_PORT1_TPA_P	FW_PORT1_TPA_P - @mlb_lib.MLB	43B6 43C6 106D3		
CK505_REF1	CK505_REF1 - @mlb_lib.MLB	29A3 30B2	DVI_HPD_UF	DVI_HPD_UF - @mlb_lib.MLB	94C3 94D5	FSB_DSTB_L_P<2>	FSB_DSTB_L_P<2> - @mlb_lib.MLB	7D7 7D8 10C2 14A3 100C3		FW_P1_TPA_P - @mlb_lib.MLB	40C6 43C8		
	TP_CK505_REF1 - @mlb_lib.MLB	7C3 30B1	ENET_CLK25M_XTALI	ENET_CLK25M_XTALI - @mlb_lib.MLB	37B4	FSB_DSTB_L_P<3>	FSB_DSTB_L_P<3> - @mlb_lib.MLB	7D7 7D8 10B2 14A3 100C3	FW_PORT1_TPB_FL_N	FW_PORT1_TPB_FL_N - @mlb_lib.MLB	43B2 106D3		
CK505_SRC1_N	CK505_SRC1_N - @mlb_lib.MLB	29B3 30C5 105C3	ENET_CLK25M_XTALO	ENET_CLK25M_XTALO - @mlb_lib.MLB	37B4	FSB_D_L<0>	FSB_D_L<0> - @mlb_lib.MLB	7D7 7D8 10C4 14D5 100D3	FW_PORT1_TPB_FL_P	FW_PORT1_TPB_FL_P - @mlb_lib.MLB	43B2 106D3		
	GPU_CLK100M_PCIE_N - @mlb_lib.MLB	30C3 85C7 105B3	ENET_CTAP_<0>	ENET_CTAP_<0> - @mlb_lib.MLB	39B5	FSB_D_L<1>	FSB_D_L<1> - @mlb_lib.MLB	10C4 14D5	FW_PORT1_TPB_N	FW_PORT1_TPB_N - @mlb_lib.MLB	43A6 43C6 106D3		
CK505_SRC1_P	CK505_SRC1_P - @mlb_lib.MLB	29B3 30C5 105C3	ENET_CTAP_<1>	ENET_CTAP_<1> - @mlb_lib.MLB	39B5	FSB_D_L<15..1>	FSB_D_L<15..1> - @mlb_lib.MLB	100D3		FW_P1_TPB_N - @mlb_lib.MLB	40C6 43C8		
	GPU_CLK100M_PCIE_P - @mlb_lib.MLB	30C3 85C7 105B3	ENET_CTAP_<2>	ENET_CTAP_<2> - @mlb_lib.MLB	39B5	FSB_D_L<2>	FSB_D_L<2> - @mlb_lib.MLB	10C4 14D5	FW_PORT1_TPB_P	FW_PORT1_TPB_P - @mlb_lib.MLB	43B6 43C6 106D3		
CK505_SRC2_N	CK505_SRC2_N - @mlb_lib.MLB	29B3 30C5 105C3	ENET_CTAP_<3>	ENET_CTAP_<3> - @mlb_lib.MLB	39B5	FSB_D_L<3>	FSB_D_L<3> - @mlb_lib.MLB	10C4 14D5		FW_P1_TPB_P - @mlb_lib.MLB	40C6 43C8		
	SB_CLK100M_DMI_N - @mlb_lib.MLB	7B8 7C3 24D2 30C3 105B3	ENET_CTAP_COMMON	ENET_CTAP_COMMON - @mlb_lib.MLB	39A4	FSB_D_L<4>	FSB_D_L<4> - @mlb_lib.MLB	10C4 14D5	FW_PORT1_VP	FW_PORT1_VP - @mlb_lib.MLB	43B3		
CK505_SRC2_P	CK505_SRC2_P - @mlb_lib.MLB	29B3 30C5 105C3	ENET_CTRL12	ENET_CTRL12 - @mlb_lib.MLB	38A5 38B1	FSB_D_L<5>	FSB_D_L<5> - @mlb_lib.MLB	10C4 14D5	FW_PORT1_VP_F	FW_PORT1_VP_F - @mlb_lib.MLB	43D5		
	SB_CLK100M_DMI_P - @mlb_lib.MLB	7B8 24C2 30C3 105B3		TP_YUKON_CTRL12 - @mlb_lib.MLB	37C2 38B3	FSB_D_L<6>	FSB_D_L<6> - @mlb_lib.MLB	10C4 14D5	FW_PORTS_VP	FW_PORTS_VP - @mlb_lib.MLB	43D7		
CK505_SRC3_N	CK505_SRC3_N - @mlb_lib.MLB	29B3 30C5 105C3	ENET_CTRL19	ENET_CTRL19 - @mlb_lib.MLB	38B1 38C5	FSB_D_L<7>	FSB_D_L<7> - @mlb_lib.MLB	10C4 14D5	FW_PORTS_VP_R	FW_PORTS_VP_R - @mlb_lib.MLB	40C7 43D6		
	PCIE_CLK100M_FW_N - @mlb_lib.MLB	7D6 30C3 40C3 105B3		TP_YUKON_CTRL18 - @mlb_lib.MLB	37C2 38B3	FSB_D_L<8>	FSB_D_L<8> - @mlb_lib.MLB	10C4 14D5	FW_PU_RST_L	FW_PU_RST_L - @mlb_lib.MLB	40B6		
CK505_SRC3_P	CK505_SRC3_P - @mlb_lib.MLB	29B3 30C5 105C3	ENET_LED_ACT_L	ENET_LED_ACT_L - @mlb_lib.MLB	37B2 39A8	FSB_D_L<9>	FSB_D_L<9> - @mlb_lib.MLB	10C4 14D5	FW_R0	FW_R0 - @mlb_lib.MLB	40B6		
	PCIE_CLK100M_FW_P - @mlb_lib.MLB	7D6 30C3 40C3 105B3	ENET_LED_LINK10_100_	ENET_LED_LINK10_100_L -	37B2 39A8	FSB_D_L<10>	FSB_D_L<10> - @mlb_lib.MLB	10C4 14D5	FW_RESET_L	FW_RESET_L - @mlb_lib.MLB	7D6 28C1 40B3		
CK505_SRC4_N	CK505_SRC4_N - @mlb_lib.MLB	29B3 30B5 105C3	L	@mlb_lib.MLB		FSB_D_L<11>	FSB_D_L<11> - @mlb_lib.MLB	10C4 14D5	FW_REXT	FW_REXT - @mlb_lib.MLB	40B6		
	SB_CLK100M_SATA_N - @mlb_lib.MLB	7C8 23B6 30B3 105B3	ENET_LED_LINK1000_L	ENET_LED_LINK1000_L - @mlb_lib.MLB	37B2 39A8	FSB_D_L<12>	FSB_D_L<12> - @mlb_lib.MLB	10C4 14D5	FW_SCL	FW_SCL - @mlb_lib.MLB	40B3		
CK505_SRC4_P	CK505_SRC4_P - @mlb_lib.MLB	29B3 30B5 105C3	ENET_LED_LINK_L	ENET_LED_LINK_L - @mlb_lib.MLB	37B2 39A8	FSB_D_L<13>	FSB_D_L<13> - @mlb_lib.MLB	10C4 14C5	FW_TPCPS	FW_TPCPS - @mlb_lib.MLB	40B6		
	SB_CLK100M_SATA_P - @mlb_lib.MLB	7C8 23B6 30B3 105B3	ENET_LOM_DIS_L	ENET_LOM_DIS_L - @mlb_lib.MLB	37C2	FSB_D_L<14>	FSB_D_L<14> - @mlb_lib.MLB	10C4 14C5	FW_TRST_L	FW_TRST_L - @mlb_lib.MLB	7C3 40C3		
CK505_SRC5_N	CK505_SRC5_N - @mlb_lib.MLB	29B3 30B5 105C3	ENET_MDI0	ENET_MDI0 - @mlb_lib.MLB	37B7 104B3	FSB_D_L<15>	FSB_D_L<15> - @mlb_lib.MLB	10C4 14C5	FW_VAUX_DETECT	FW_VAUX_DETECT - @mlb_lib.MLB	40C3		
	NB_CLK100M_PCIE_N - @mlb_lib.MLB	7C3 7C7 16C3 30B3 105B3	ENET_MDI1	ENET_MDI1 - @mlb_lib.MLB	37B6 104B3	FSB_D_L<16>	FSB_D_L<16> - @mlb_lib.MLB	7D7 7D8 10C4 14C5 100C3	FW_XI	FW_XI - @mlb_lib.MLB	40B6		
CK505_SRC5_P	CK505_SRC5_P - @mlb_lib.MLB	29B3 30B5 105C3	ENET_MDI2	ENET_MDI2 - @mlb_lib.MLB	37B6 104B3	FSB_D_L<17>	FSB_D_L<17> - @mlb_lib.MLB	10C4 14C5	FW_XO	FW_XO - @mlb_lib.MLB	40B6		
	NB_CLK100M_PCIE_P - @mlb_lib.MLB	7C7 16C3 30B3 105B3	ENET_MDI3	ENET_MDI3 - @mlb_lib.MLB	37B5 104B3	FSB_D_L<31..17>	FSB_D_L<31..17> - @mlb_lib.MLB	100C3	FW_XO_R	FW_XO_R - @mlb_lib.MLB	40B7		
CK505_SRC6_N	CK505_SRC6_N - @mlb_lib.MLB	29B3 30B5 105C3	ENET_MDI_N<0>	ENET_MDI_N<0> - @mlb_lib.MLB	37B8 39C7 104B3	FSB_D_L<18>	FSB_D_L<18> - @mlb_lib.MLB	10C4 14C5	GFX_VID<1>	GFX_VID<1> - @mlb_lib.MLB	16B3 22B8		
	PCIE_CLK100M_MINI_N - @mlb_lib.MLB	30B3 34C6 105B3	ENET_MDI_N<1>	ENET_MDI_N<1> - @mlb_lib.MLB	37B8 39C7 104B3	FSB_D_L<19>	FSB_D_L<19> - @mlb_lib.MLB	10B4 14C5	GFX_VID<2>	GFX_VID<2> - @mlb_lib.MLB	16B3 22A8		
CK505_SRC6_P	CK505_SRC6_P - @mlb_lib.MLB	29B3 30B5 105C3	ENET_MDI_N<2>	ENET_MDI_N<2> - @mlb_lib.MLB	37B8 39B7 104A3	FSB_D_L<20>	FSB_D_L<20> - @mlb_lib.MLB	10B4 14C5	GFX_VID<3>	GFX_VID<3> - @mlb_lib.MLB	16B3 22A8		
	PCIE_CLK100M_MINI_P - @mlb_lib.MLB	30B3 34C6 105B3	ENET_MDI_N<3>	ENET_MDI_N<3> - @mlb_lib.MLB	37B8 39B7 104A3	FSB_D_L<21>	FSB_D_L<21> - @mlb_lib.MLB	10B4 14C5	GFX_VID<4>	GFX_VID<4> - @mlb_lib.MLB	16B3 22A8		
CK505_SRC7_N	CK505_SRC7_N - @mlb_lib.MLB	29B3 30B5 105C3	ENET_MDI_P<0>	ENET_MDI_P<0> - @mlb_lib.MLB	37B8 39C7 104B3	FSB_D_L<22>	FSB_D_L<22> - @mlb_lib.MLB	10B4 14C5	GLAN_COMP	GLAN_COMP - @mlb_lib.MLB	23C6 104B3		
CK505_SRC7_P	CK505_SRC7_P - @mlb_lib.MLB	29B3 30B5 105C3	ENET_MDI_P<1>	ENET_MDI_P<1> - @mlb_lib.MLB	37B8 39C7 104B3	FSB_D_L<23>	FSB_D_L<23> - @mlb_lib.MLB	10B4 14C5	GND_IMVP6_SGND	GND_IMVP6_SGND - @mlb_lib.MLB	71B6		
CK505_SRC8_N	CK505_SRC8_N - @mlb_lib.MLB	29B3 30B5 105C3	ENET_MDI_P<2>	ENET_MDI_P<2> - @mlb_lib.MLB	37B8 39B7 104B3	FSB_D_L<24>	FSB_D_L<24> - @mlb_lib.MLB	10B4 14C5	GND_PP1V5REG_SGND	GND_PP1V5REG_SGND - @mlb_lib.MLB	73B7		
	PCIE_CLK100M_ENET_N - @mlb_lib.MLB	7D6 30B3 37C8 105B3	ENET_MDI_P<3>	ENET_MDI_P<3> - @mlb_lib.MLB	37B8 39B7 104A3	FSB_D_L<25>	FSB_D_L<25> - @mlb_lib.MLB	10B4 14C5	GND_PP1V8REG_SGND	GND_PP1V8REG_SGND - @mlb_lib.MLB	75C5 75D6		
CK505_SRC8_P	CK505_SRC8_P - @mlb_lib.MLB	29A3 30B5 105C3	ENET_MDI_R_N<0>	ENET_MDI_R_N<0> - @mlb_lib.MLB	108B3	FSB_D_L<26>	FSB_D_L<26> - @mlb_lib.MLB	10B4 14C5	GND_PP1V25REG_SGND	GND_PP1V25REG_SGND - @mlb_lib.MLB	74B7		
	PCIE_CLK100M_ENET_P - @mlb_lib.MLB	7D6 30B3 37C8 105B3	ENET_MDI_R_N<1>	ENET_MDI_R_N<1> - @mlb_lib.MLB	108B3	FSB_D_L<27>	FSB_D_L<27> - @mlb_lib.MLB	10B4 14C5	GND_PP5VREG_SGND	GND_PP5VREG_SGND - @mlb_lib.MLB	76A7		
CK505_XTAL_IN	CK505_XTAL_IN - @mlb_lib.MLB	29C5	ENET_MDI_R_N<2>	ENET_MDI_R_N<2> - @mlb_lib.MLB	108B3	FSB_D_L<28>	FSB_D_L<28> - @mlb_lib.MLB	10B4 14C5	GND_SMC_AVSS	GND_SMC_AVSS - @mlb_lib.MLB	49B2 50B7 53A2 53A3 53B1		
CK505_XTAL_OUT	CK505_XTAL_OUT - @mlb_lib.MLB	29C5	ENET_MDI_R_N<3>	ENET_MDI_R_N<3> - @mlb_lib.MLB	108B3	FSB_D_L<29>	FSB_D_L<29> - @mlb_lib.MLB	10B4 14C5			53C3 53C6 53D3 53D6		
CLINK_NB_CLK	CLINK_NB_CLK - @mlb_lib.MLB	7A7 7A8 16A3 25C3 104B3	ENET_MDI_R_P<0>	ENET_MDI_R_P<0> - @mlb_lib.MLB	108B3	FSB_D_L<30>	FSB_D_L<30> - @mlb_lib.MLB	10B4 14C5	GPU_BLU	GPU_BLU - @mlb_lib.MLB	85C4 91B8 108B3		
CLINK_NB_DATA	CLINK_NB_DATA - @mlb_lib.MLB	7A7 7A8 16A3 25C3 104B3	ENET_MDI_R_P<1>	ENET_MDI_R_P<1> - @mlb_lib.MLB	108B3	FSB_D_L<31>	FSB_D_L<31> - @mlb_lib.MLB	10B4 14C5	GPU_BUF_HSYNC	GPU_BUF_HSYNC - @mlb_lib.MLB	108A3		
CLINK_NB_RESET_L	CLINK_NB_RESET_L - @mlb_lib.MLB	16A3 25C3 104B3	ENET_MDI_R_P<2>	ENET_MDI_R_P<2> - @mlb_lib.MLB	108B3	FSB_D_L<32>	FSB_D_L<32> - @mlb_lib.MLB	10C2 14C5	GPU_BUF_VSYNC	GPU_BUF_VSYNC - @mlb_lib.MLB	108A3		
CLINK_WLAN_CLK	CLINK_WLAN_CLK - @mlb_lib.MLB	34A8	ENET_MDI_R_P<3>	ENET_MDI_R_P<3> - @mlb_lib.MLB	108B3	FSB_D_L<40..32>	FSB_D_L<40..32> - @mlb_lib.MLB	100C3	GPU_DDC_A_CLK	GPU_DDC_A_CLK - @mlb_lib.MLB	85C7 94D1		
	TP_CLINK_WLAN_CLK - @mlb_lib.MLB	25C3 34A6	ENET_MDI_T_N<0>	ENET_MDI_T_N<0> - @mlb_lib.MLB	39C5 108B3	FSB_D_L<33>	FSB_D_L<33> - @mlb_lib.MLB	10C2 14C5	GPU_DDC_A_DATA	GPU_DDC_A_DATA - @mlb_lib.MLB	85C7 94C1		
CLINK_WLAN_DATA	CLINK_WLAN_DATA - @mlb_lib.MLB	34A8	ENET_MDI_T_N<1>	ENET_MDI_T_N<1> - @mlb_lib.MLB	39C5 108B3	FSB_D_L<34>	FSB_D_L<34> - @mlb_lib.MLB	10C2 14C5	GPU_DDC_C_CLK	GPU_DDC_C_CLK - @mlb_lib.MLB	85A4 85D1 90A8		
	TP_CLINK_WLAN_DATA - @mlb_lib.MLB	25C3 28C4 34A6	ENET_MDI_T_N<2>	ENET_MDI_T_N<2> - @mlb_lib.MLB	39B5 108B3	FSB_D_L<35>	FSB_D_L<35> - @mlb_lib.MLB	10C2 14C5	GPU_DDC_C_DATA	GPU_DDC_C_DATA - @mlb_lib.MLB	85A4 85D1 90A6		
CLINK_WLAN_RESET_L	CLINK_WLAN_RESET_L - @mlb_lib.MLB	34A8	ENET_MDI_T_N<3>	ENET_MDI_T_N<3> - @mlb_lib.MLB	39B5 108B3	FSB_D_L<36>	FSB_D_L<36> - @mlb_lib.MLB	10C2 14C5	GPU_DIGON	GPU_DIGON - @mlb_lib.MLB	85A4 90B8		
	TP_CLINK_WLAN_RESET_L -	25D5 34A6	ENET_MDI_T_P<0>	ENET_MDI_T_P<0> - @mlb_lib.MLB	39C5 108B3	FSB_D_L<37>	FSB_D_L<37> - @mlb_lib.MLB	10C2 14C5	GPU_ENABLE_BL	GPU_ENABLE_BL - @mlb_lib.MLB	85A5		
	@mlb_lib.MLB		ENET_MDI_T_P<1>	ENET_MDI_T_P<1> - @mlb_lib.MLB	39C5 108B3	FSB_D_L<38>	FSB_D_L<38> - @mlb_lib.MLB	10C2 14C5	GPU_GRN	GPU_GRN - @mlb_lib.MLB	85C4 91B8 108B3		
CLK_PWRGD	CLK_PWRGD - @mlb_lib.MLB	25C3 29A3	ENET_MDI_T_P<2>	ENET_MDI_T_P<2> - @mlb_lib.MLB	39B5 108B3	FSB_D_L<39>	FSB_D_L<39> - @mlb_lib.MLB	10C2 14B5	GPU_H2SYNC	GPU_H2SYNC - @mlb_lib.MLB	85C7 91A4 108B3		
CPUVCORE_ISENSE_CAL	CPUVCORE_ISENSE_CAL - @mlb_lib.MLB	53B6	ENET_MDI_T_P<3>	ENET_MDI_T_P<3> - @mlb_lib.MLB	39B5 108B3	FSB_D_L<40>	FSB_D_L<40> - @mlb_lib.MLB	10C2 14B5	GPU_HPD	GPU_HPD - @mlb_lib.MLB	85A7 94C1		
CPUVSENSE_IN	CPUVSENSE_IN - @mlb_lib.MLB	53D7	ENET_RESET_L	ENET_RESET_L - @mlb_lib.MLB	7D6 28C1 37B8	FSB_D_L<41>	FSB_D_L<41> - @mlb_lib.MLB	7D7 7D8 10C2 14B5 100C3	GPU_HSK_THRMD_N	GPU_HSK_THRMD_N - @mlb_lib.MLB	55A5 55A6 108A3		
CPU_A20M_L	CPU_A20M_L - @mlb_lib.MLB	7C8 10C8 23C4 100B3	EXCARD_OC_L	EXCARD_OC_L - @mlb_lib.MLB	24C8	FSB_D_L<42>	FSB_D_L<42> - @mlb_lib.MLB	10C2 14B5	GPU_HSK_THRMD_P	GPU_HSK_THRMD_P - @mlb_lib.MLB	55A6 55B5 108A3		
CPU_BSEL<0>	CPU_BSEL<0> - @mlb_lib.MLB	10B4 30C6 100B3	EXTGPU_LVDS_EN	EXTGPU_LVDS_EN - @mlb_lib.MLB	13C3 24C8	FSB_D_L<47..42>	FSB_D_L<47..42> - @mlb_lib.MLB	100C3	GPU_HSYNC_BUF	GPU_HSYNC_BUF - @mlb_lib.MLB	91A3		
CPU_BSEL<1>	CPU_BSEL<1> - @mlb_lib.MLB	10A4 30B6 100B3	EXTGPU_PWR_EN	EXTGPU_PWR_EN - @mlb_lib.MLB	23C4 28A2	FSB_D_L<43>	FSB_D_L<43> - @mlb_lib.MLB	10C2 14B5	GPU_PRESENT	GPU_PRESENT - @mlb_lib.MLB	6A8 28C1		
CPU_BSEL<2>	CPU_BSEL<2> - @mlb_lib.MLB	10A4 30B6 100A3		TP_EXTGPU_PWR_EN - @mlb_lib.MLB	28A1	FSB_D_L<44>	FSB_D_L<44> - @mlb_lib.MLB	10C2 14B5		SB_GPIO6 - @mlb_lib.MLB	25A5 25C5 28C2		
CPU_COMP<0>	CPU_COMP<0> - @mlb_lib.MLB	10B3 100A3	EXTGPU_RST_L	EXTGPU_RST_L - @mlb_lib.MLB	25A5 25C5 28A2	FSB_D_L<45>	FSB_D_L<45> - @mlb_lib.MLB	10C2 14B5	GPU_PRESENT_DRAIN	GPU_PRESENT_DRAIN - @mlb_lib.MLB	6B7		
CPU_COMP<1>	CPU_COMP<1> - @mlb_lib.MLB	10B3 100A3		TP_EXTGPU_RST_L - @mlb_lib.MLB	28A1	FSB_D_L<46>	FSB_D_L<46> - @mlb_lib.MLB	10C2 14B5	GPU_PRESENT_R	GPU_PRESENT_R - @mlb_lib.MLB	6B7		
CPU_COMP<2>	CPU_COMP<2> - @mlb_lib.MLB	10B3 100A3	F0_GATESLOWDN	F0_GATESLOWDN - @mlb_lib.MLB	56D5	FSB_D_L<47>	FSB_D_L<47> - @mlb_lib.MLB	10C2 14B5	GPU_RED	GPU_RED - @mlb_lib.MLB	85C4 91B8 108B3		
CPU_COMP<3>	CPU_COMP<3> - @mlb_lib.MLB	10B3 100A3	F0_VOLTAGE8R5	F0_VOLTAGE8R5 - @mlb_lib.MLB	56D6	FSB_D_L<48>	FSB_D_L<48> - @mlb_lib.MLB	10C2 14B5	GPU_TV_C	GPU_TV_C - @mlb_lib.MLB	85C4 91B8 108B3		
CPU_DPRSTP_L	CPU_DPRSTP_L - @mlb_lib.MLB	10B2 16B6 23C4 71C7 100A3	F1_GATESLOWDN	F1_GATESLOWDN - @mlb_lib.MLB	56B5	FSB_D_L<58..48>	FSB_D_L<58..48> - @mlb_lib.MLB	100C3	GPU_TV_COMP	GPU_TV_COMP - @mlb_lib.MLB	85C4 91B8 108B3		
CPU_DPSLP_L	CPU_DPSLP_L - @mlb_lib.MLB	10B2 23C4 100B3	F1_VOLTAGE8R5	F1_VOLTAGE8R5 - @mlb_lib.MLB	56B6	FSB_D_L<49>	FSB_D_L<49> - @mlb_lib.MLB	10C2 14B5	GPU_TV_Y	GPU_TV_Y - @mlb_lib.MLB	85C4 91B8 108B3		
CPU_FERR_L	CPU_FERR_L - @mlb_lib.MLB	10C8 23C2 100B3	F2_GATESLOWDN	F2_GATESLOWDN - @mlb_lib.MLB	57D4	FSB_D_L<50>	FSB_D_L<50> - @mlb_lib.MLB	10C2 14B5	GPU_V2SYNC	GPU_V2SYNC - @mlb_lib.MLB	85C7 91B4 108A3		
CPU_GTLREF	CPU_GTLREF - @mlb_lib.MLB	10B4 100A3	F2_VOLTAGE8R5	F2_VOLTAGE8R5 - @mlb_lib.MLB	57D5	FSB_D_L<51>	FSB_D_L<51> - @mlb_lib.MLB	10B2 14B5	GPU_VARY_BL	GPU_VARY_BL - @mlb_lib.MLB	85A4 90B3		
CPU_HSK_THRMD_N	CPU_HSK_THRMD_N - @mlb_lib.MLB	55A5 55A7 108A3	FAN_0_PWR	FAN_0_PWR - @mlb_lib.MLB	56C4	FSB_D_L<52>	FSB_D_L<52> - @mlb_lib.MLB	10B2 14B5	GPU_VSYNC_BUF	GPU_VSYNC_BUF - @mlb_lib.MLB	91B3		
CPU_HSK_THRMD_P	CPU_HSK_THRMD_P - @mlb_lib.MLB	55A7 55B5 108A3	FAN_1_PWR	FAN_1_PWR - @mlb_lib.MLB	56B3	FSB_D_L<53>	FSB_D_L<53> - @mlb_lib.MLB	10B2 14B5	HDA_BIT_CLK	HDA_BIT_CLK - @mlb_lib.MLB	23C8 98C6 103C3		
CPU_IERR_L	CPU_IERR_L - @mlb_lib.MLB	10D6 100B3	FAN_2_PWR	FAN_2_PWR - @mlb_lib.MLB	57C3	FSB_D_L<54>	FSB_D_L<54> - @mlb_lib.MLB	10B2 14B5	HDA_BIT_CLK_R	HDA_BIT_CLK_R - @mlb_lib.MLB	23C6 103C3		
CPU_IGNNE_L	CPU_IGNNE_L - @mlb_lib.MLB	7C8 10C8 23C4 100B3	FAN_TACH0	FAN_TACH0 - @mlb_lib.MLB	56C7	FSB_D_L<55>	FSB_D_L<55> - @mlb_lib.MLB	10B2 14B5	HDA_DOCK_EN_L	HDA_DOCK_EN_L - @mlb_lib.MLB	23B6		
CPU_INIT_L	CPU_INIT_L - @mlb_lib.MLB	7C8 10D6 23C4 51B2 100B3	FAN_TACH1	FAN_TACH1 - @mlb_lib.MLB	56A7	FSB_D_L<56>	FSB_D_L<56> - @mlb_lib.MLB	10B2 14B5	HDA_RST_L	HDA_RST_L - @mlb_lib.MLB	23C8 98C6 103C3		
CPU_INIT_LS3V3	CPU_INIT_LS3V3 - @mlb_lib.MLB	51C4	FAN_TACH2	FAN_TACH2 - @mlb_lib.MLB	57C7	FSB_D_L<57>	FSB_D_L<57> - @mlb_lib.MLB	10B2 14B5	HDA_RST_L_R	HDA_RST_L_R - @mlb_lib.MLB	23C6 103C3		
CPU_INIT_R_L	CPU_INIT_R_L - @mlb_lib.MLB	51B3	FSB_ADSTB_L<0>	FSB_ADSTB_L<0> - @mlb_lib.MLB	7D7 7D8 10D8 14C3 100C3	FSB_D_L<58>	FSB_D_L<58> - @mlb_lib.MLB	10B2 14B5	HDA_SDIN0	HDA_SDIN0 - @mlb_lib.MLB	23C8 98C6 103B3		
CPU_INTR	CPU_INTR - @mlb_lib.MLB	7C8 10B8 23C4 100B3	FSB_ADSTB_L<1>	FSB_ADSTB_L<1> - @mlb_lib.MLB	7D7 7D8 10C8 14C3 100B3	FSB_D_L<59>	FSB_D_L<59> - @mlb_lib.MLB	7D7 7D8 10B2 14B5 100C3	HDA_SDIN_CODEC	HDA_SDIN_CODEC - @mlb_lib.MLB	103B3		
CPU_NMI	CPU_NMI - @mlb_lib.MLB	7C8 10B8 23C4 100B3	FSB_ADS_L	FSB_ADS_L - @mlb_lib.MLB	10D6 14C3 100D3	FSB_D_L<60>	FSB_D_L<60> - @mlb_lib.MLB	10B2 14B5	HDA_SDOUT	HDA_SDOUT - @mlb_lib.MLB	23B8 98C6 103B3		
CPU_PROCHOT_BUF	CPU_PROCHOT_BUF - @mlb_lib.MLB	50D2	FSB_A_L<3>	FSB_A_L<3> - @mlb_lib.MLB	10D8 14D3	FSB_D_L<63..60>	FSB_D_L<63..60> - @mlb_lib.MLB	100C3	HDA_SDOUT_R	HDA_SDOUT_R - @mlb_lib.MLB	23B6 103B3		
CPU_PROCHOT_L	CPU_PROCHOT_L - @mlb_lib.MLB	10C5 50D3 55D1 100B3	FSB_A_L<5..3>	FSB_A_L<5..3> - @mlb_lib.MLB	100C3	FSB_D_L<61>	FSB_D_L<61> - @mlb_lib.MLB	10B2 14B5	HDA_SYNC	HDA_SYNC - @mlb_lib.MLB	23C8 98C6 103C3		
CPU_PROCHOT_L_R	CPU_PROCHOT_L_R - @mlb_lib.MLB	50D2	FSB_A_L<4>	FSB_A_L<4> - @mlb_lib.MLB	10D8 14D3	FSB_D_L<62>	FSB_D_L<62> - @mlb_lib.MLB	10B2 14B5	HDA_SYNC_R	HDA_SYNC_R - @mlb_lib.MLB	23C6 103C3		
CPU_PSI_L	CPU_PSI_L - @mlb_lib.MLB	10A2 28B7	FSB_A_L<5>	FSB_A_L<5> - @mlb_lib.MLB	10D8 14D3	FSB_D_L<63>	FSB_D_L<63> - @mlb_lib.MLB	10B2 14B5	HDD_THRMD_N	HDD_THRMD_N - @mlb_lib.MLB	55A5 55B7 108A3		
	IMVP6_PSI_L - @mlb_lib.MLB	28B6 71C7	FSB_A_L<6>	FSB_A_L<6> - @mlb_lib.MLB	7D7 7D8 10D8 14D3 100C3	FSB_HITM_L	FSB_HITM_L - @mlb_lib.MLB	7C7 10C6 14B3 100D3	HDD_THRMD_P	HDD_THRMD_P - @mlb_lib.MLB	55B5 55B7 108A3		
CPU_PWRGD	CPU_PWRGD - @mlb_lib.MLB	7C4 10B2 13C7 23C4 100B3	FSB_A_L<7>	FSB_A_L<7> - @mlb_lib.MLB	10D8 14D3	FSB_HIT_L	FSB_HIT_L - @mlb_lib.MLB	7C7 10C6 14B3 100D3	IDE_CSEL	IDE_CSEL - @mlb_lib.MLB	44B5		
CPU_SET_SPEED	CPU_SET_SPEED - @mlb_lib.MLB	25A7 25B3	FSB_A_L<16..7>	FSB_A_L<16..7> - @mlb_lib.MLB	100C3	FSB_LOCK_L	FSB_LOCK_L - @mlb_lib.MLB	7D7 7D8 10D6 14B3 100D3	IDE_DASP_L	IDE_DASP_L - @mlb_lib.MLB	44B5		
CPU_SMI_L	CPU_SMI_L - @mlb_lib.MLB	7C8 10B8 23C4 100B3	FSB_A_L<8>	FSB_A_L<8> - @mlb_lib.MLB	10D8 14D3	FSB_REQ_L<0>	FSB_REQ_L<0> - @mlb_lib.MLB	7C

IMVP6_DFB	IMVP6_DFB - @mlb_lib.MLB	71A8 71B5
IMVP6_DROOP	IMVP6_DROOP - @mlb_lib.MLB	71A8 71B4
IMVP6_FB	IMVP6_FB - @mlb_lib.MLB	71A8 71B7
IMVP6_FCCM	IMVP6_FCCM - @mlb_lib.MLB	71A8 71C5 72C7
IMVP6_FET_RC1	IMVP6_FET_RC1 - @mlb_lib.MLB	71A6 71C3
IMVP6_FET_RC2	IMVP6_FET_RC2 - @mlb_lib.MLB	71A4 71B3
IMVP6_FET_RC3	IMVP6_FET_RC3 - @mlb_lib.MLB	72A7 72C3
IMVP6_ISEN1	IMVP6_ISEN1 - @mlb_lib.MLB	71A6 71C3 72C1
IMVP6_ISEN2	IMVP6_ISEN2 - @mlb_lib.MLB	71A4 71C5
IMVP6_ISEN3	IMVP6_ISEN3 - @mlb_lib.MLB	71C5 72A7 72B1
IMVP6_LGATE1	IMVP6_LGATE1 - @mlb_lib.MLB	71A6 71D4
IMVP6_LGATE2	IMVP6_LGATE2 - @mlb_lib.MLB	71A4 71C4
IMVP6_LGATE3	IMVP6_LGATE3 - @mlb_lib.MLB	72A7 72C6
IMVP6_NTC	IMVP6_NTC - @mlb_lib.MLB	71C7
IMVP6_NTC_R	IMVP6_NTC_R - @mlb_lib.MLB	71C8
IMVP6_OCSET	IMVP6_OCSET - @mlb_lib.MLB	71A8 71B5
IMVP6_PHASE1	IMVP6_PHASE1 - @mlb_lib.MLB	71A6 71D4 108D1
IMVP6_PHASE2	IMVP6_PHASE2 - @mlb_lib.MLB	71A4 71C4 108D1
IMVP6_PHASE3	IMVP6_PHASE3 - @mlb_lib.MLB	72A7 72C6 108D1
IMVP6_PMON	IMVP6_PMON - @mlb_lib.MLB	53C8 71C5
IMVP6_PWM1	IMVP6_PWM1 - @mlb_lib.MLB	71A6 71D5
IMVP6_PWM2	IMVP6_PWM2 - @mlb_lib.MLB	71A4 71C5
IMVP6_PWM3	IMVP6_PWM3 - @mlb_lib.MLB	71C5 72A7 72C7
IMVP6_RBIAS	IMVP6_RBIAS - @mlb_lib.MLB	71A8 71B7
IMVP6_SOFT	IMVP6_SOFT - @mlb_lib.MLB	71A8 71C7
IMVP6_UGATE1	IMVP6_UGATE1 - @mlb_lib.MLB	71A6 71D4
IMVP6_UGATE2	IMVP6_UGATE2 - @mlb_lib.MLB	71A4 71C4
IMVP6_UGATE3	IMVP6_UGATE3 - @mlb_lib.MLB	72A7 72C6
IMVP6_VDIFF	IMVP6_VDIFF - @mlb_lib.MLB	71A8 71B7
IMVP6_VDIFF_RC	IMVP6_VDIFF_RC - @mlb_lib.MLB	71B8
IMVP6_VID<0>	IMVP6_VID<0> - @mlb_lib.MLB	12C1 71C7
IMVP6_VID<6..0>	IMVP6_VID<6..0> - @mlb_lib.MLB	100A3
IMVP6_VID<1>	IMVP6_VID<1> - @mlb_lib.MLB	12C1 71C7
IMVP6_VID<2>	IMVP6_VID<2> - @mlb_lib.MLB	12C1 71C7
IMVP6_VID<3>	IMVP6_VID<3> - @mlb_lib.MLB	12C1 71C7
IMVP6_VID<4>	IMVP6_VID<4> - @mlb_lib.MLB	12C1 71C7
IMVP6_VID<5>	IMVP6_VID<5> - @mlb_lib.MLB	12C1 71C7
IMVP6_VID<6>	IMVP6_VID<6> - @mlb_lib.MLB	12C1 71C7
IMVP6_VO	IMVP6_VO - @mlb_lib.MLB	71A8 71B4 72C1
IMVP6_VO1	IMVP6_VO1 - @mlb_lib.MLB	71A6 71D1 72A7
IMVP6_VO2	IMVP6_VO2 - @mlb_lib.MLB	71A4 71B1 72A7
IMVP6_VO3	IMVP6_VO3 - @mlb_lib.MLB	72A7 72A7 72C2
IMVP6_VO_R	IMVP6_VO_R - @mlb_lib.MLB	71B4
IMVP6_VR_TT_L	IMVP6_VR_TT_L - @mlb_lib.MLB	71C7
IMVP6_VSEN_N	IMVP6_VSEN_N - @mlb_lib.MLB	71A5 100A3
IMVP6_VSEN_P	IMVP6_VSEN_P - @mlb_lib.MLB	71A5 100A3
IMVP6_VSUM	IMVP6_VSUM - @mlb_lib.MLB	71A8 71C4 72B1
IMVP6_VSUM1	IMVP6_VSUM1 - @mlb_lib.MLB	71A6 71C2 72A7
IMVP6_VSUM2	IMVP6_VSUM2 - @mlb_lib.MLB	71A4 71B2 72A7
IMVP6_VSUM3	IMVP6_VSUM3 - @mlb_lib.MLB	72A7 72A7 72C3
IMVP6_VW	IMVP6_VW - @mlb_lib.MLB	71A8 71B7
IMVP_DPRSLPVR	IMVP_DPRSLPVR - @mlb_lib.MLB	71C7 100B3
IMVP_PGD_IN	IMVP_PGD_IN - @mlb_lib.MLB	70B3
IMVP_VR_ON	IMVP_VR_ON - @mlb_lib.MLB	7C4 49C8 71C7
INT_PIRQA_L	INT_PIRQA_L - @mlb_lib.MLB	24A4 24A8 104C3
INT_PIRQB_L	INT_PIRQB_L - @mlb_lib.MLB	24A4 24A8 104C3
INT_PIRQC_L	INT_PIRQC_L - @mlb_lib.MLB	24A4 24A8 104C3
INT_PIRQD_L	INT_PIRQD_L - @mlb_lib.MLB	24A4 24A8 104C3
INT_PIRQE_L	INT_PIRQE_L - @mlb_lib.MLB	24A4 24A6 98B7 104C3
INT_PIRQF_L	INT_PIRQF_L - @mlb_lib.MLB	24A4 24A6 104C3
INT_SERIRQ	INT_SERIRQ - @mlb_lib.MLB	7D4 25C8 49C8 51B4
INV_EN_BL_OR_PANEL_I D	INV_EN_BL_OR_PANEL_ID - @mlb_lib.MLB	6D6 28B2 85A3
IPHS_SW_INT_TO_SB	IPHS_SW_INT_TO_SB - @mlb_lib.MLB	98C6
IPHS_SW_SUPBIAS_EN_L	IPHS_SW_SUPBIAS_EN_L - @mlb_lib.MLB	98C6
ISENSE_CAL_EN	ISENSE_CAL_EN - @mlb_lib.MLB	49B8 50A2 53A8
ISENSE_CAL_EN_L	ISENSE_CAL_EN_L - @mlb_lib.MLB	53B8
ISENSE_CAL_LS12V	ISENSE_CAL_LS12V - @mlb_lib.MLB	53B7
ISENSE_CAL_EN_L_R	ISENSE_CAL_EN_L_R - @mlb_lib.MLB	53B8
ITP_CPURST_L	ITP_CPURST_L - @mlb_lib.MLB	100A3
ITS_ALIVE	ITS_ALIVE - @mlb_lib.MLB	6A7
ITS_PLUGGED_IN	ITS_PLUGGED_IN - @mlb_lib.MLB	6A8
LAN_ENERGY_DET	LAN_ENERGY_DET - @mlb_lib.MLB	23C6 28A2
LAN_PHYPC	TP_LAN_ENERGY_DET - @mlb_lib.MLB LAN_PHYPC - @mlb_lib.MLB	28A1 25A5 25C5
LCD_PWM	LCD_PWM - @mlb_lib.MLB	6D8 90B1
LCD_PWREN_DIV	LCD_PWREN_DIV - @mlb_lib.MLB	90C8
LCD_PWREN_L	LCD_PWREN_L - @mlb_lib.MLB	90B7
LCD_PWREN_L_RC	LCD_PWREN_L_RC - @mlb_lib.MLB	90C7
LCD_SHOULD_ON	LCD_SHOULD_ON - @mlb_lib.MLB	6A6
LED4300_1	LED4300_1 - @mlb_lib.MLB	39A7
LED4301_1	LED4301_1 - @mlb_lib.MLB	39A7
LED4302_1	LED4302_1 - @mlb_lib.MLB	39A6
LED4303_1	LED4303_1 - @mlb_lib.MLB	39A6
LINDACARD_GPIO	LINDACARD_GPIO - @mlb_lib.MLB	7C4 25A7 25D5 51B4
LPC_AD<0>	LPC_AD<0> - @mlb_lib.MLB	7D4 23D4 49C8 51C6
LPC_AD<1>	LPC_AD<1> - @mlb_lib.MLB	7A8 7C6 7D4 23D4 49C8 51C6
LPC_AD<2>	LPC_AD<2> - @mlb_lib.MLB	7D4 23D4 49C8 51C4
LPC_AD<3>	LPC_AD<3> - @mlb_lib.MLB	7D4 23D4 49C8 51C4
LPC_FRAME_L	LPC_FRAME_L - @mlb_lib.MLB	7D4 23D4 49C8 51B6
LVDS_A_CLK_N	LVDS_A_CLK_N - @mlb_lib.MLB TP_LVDS_A_CLK_N - @mlb_lib.MLB	15C5 22D8 22D7
LVDS_A_CLK_P	LVDS_A_CLK_P - @mlb_lib.MLB TP_LVDS_A_CLK_P - @mlb_lib.MLB	15C5 22D8 22D7
LVDS_A_DATA_N<0>	LVDS_A_DATA_N<0> - @mlb_lib.MLB	15C5 22D8
LVDS_A_DATA_N<1>	LVDS_A_DATA_N<1> - @mlb_lib.MLB	15C5 22C8
LVDS_A_DATA_N<2>	LVDS_A_DATA_N<2> - @mlb_lib.MLB	15C5 22C8
LVDS_A_DATA_P<0>	LVDS_A_DATA_P<0> - @mlb_lib.MLB	15C5 22C8
LVDS_A_DATA_P<1>	LVDS_A_DATA_P<1> - @mlb_lib.MLB	15C5 22C8
LVDS_A_DATA_P<2>	LVDS_A_DATA_P<2> - @mlb_lib.MLB	15C5 22C8
LVDS_BKLT_CTL	LVDS_BKLT_CTL - @mlb_lib.MLB TP_LVDS_BKLT_CTL - @mlb_lib.MLB	15D5 22D8 22D7
LVDS_BKLT_EN	LVDS_BKLT_EN - @mlb_lib.MLB TP_LVDS_BKLT_EN - @mlb_lib.MLB	15D5 22D8 22D7
LVDS_B_CLK_N	LVDS_B_CLK_N - @mlb_lib.MLB TP_LVDS_B_CLK_N - @mlb_lib.MLB	15C5 22D8 22D7
LVDS_B_CLK_P	LVDS_B_CLK_P - @mlb_lib.MLB TP_LVDS_B_CLK_P - @mlb_lib.MLB	15C5 22D8 22D7
LVDS_B_DATA_N<0>	LVDS_B_DATA_N<0> - @mlb_lib.MLB	15C5 22C8
LVDS_B_DATA_N<1>	LVDS_B_DATA_N<1> - @mlb_lib.MLB	15C5 22C8
LVDS_B_DATA_N<2>	LVDS_B_DATA_N<2> - @mlb_lib.MLB	15C5 22C8
LVDS_B_DATA_P<0>	LVDS_B_DATA_P<0> - @mlb_lib.MLB	15C5 22C8
LVDS_B_DATA_P<1>	LVDS_B_DATA_P<1> - @mlb_lib.MLB	15C5 22C8
LVDS_B_DATA_P<2>	LVDS_B_DATA_P<2> - @mlb_lib.MLB	15C5 22C8
LVDS_IBG	LVDS_IBG - @mlb_lib.MLB TP_LVDS_IBG - @mlb_lib.MLB	15D5 22D8 22D7
LVDS_L_CLK_N	LVDS_L_CLK_N - @mlb_lib.MLB	85B4 90A6 108C3
LVDS_L_CLK_P	LVDS_L_CLK_P - @mlb_lib.MLB	85B4 90A8 108C3
LVDS_L_DATA_N<0>	LVDS_L_DATA_N<0> - @mlb_lib.MLB	85A4 90A6
LVDS_L_DATA_N<3..0>	LVDS_L_DATA_N<3..0> - @mlb_lib.MLB	108C3
LVDS_L_DATA_N<1>	LVDS_L_DATA_N<1> - @mlb_lib.MLB	85A4 90A6
LVDS_L_DATA_N<2>	LVDS_L_DATA_N<2> - @mlb_lib.MLB	85A4 90A8
LVDS_L_DATA_N<3>	LVDS_L_DATA_N<3> - @mlb_lib.MLB	85A4 90A8
LVDS_L_DATA_P<0>	LVDS_L_DATA_P<0> - @mlb_lib.MLB	85A4 90A8
LVDS_L_DATA_P<3..0>	LVDS_L_DATA_P<3..0> - @mlb_lib.MLB	108C3
LVDS_L_DATA_P<1>	LVDS_L_DATA_P<1> - @mlb_lib.MLB	85A4 90A6
LVDS_L_DATA_P<2>	LVDS_L_DATA_P<2> - @mlb_lib.MLB	85A4 90A6
LVDS_L_DATA_P<3>	LVDS_L_DATA_P<3> - @mlb_lib.MLB	85A4 90A8
LVDS_VDD_EN	LVDS_VDD_EN - @mlb_lib.MLB TP_LVDS_VDD_EN - @mlb_lib.MLB	15D5 22D8 22D7
LVDS_VREFH	LVDS_VREFH - @mlb_lib.MLB TP_LVDS_VREFH - @mlb_lib.MLB	15D5 22D8 22D7
LVDS_VREFL	LVDS_VREFL - @mlb_lib.MLB TP_LVDS_VREFL - @mlb_lib.MLB	15D5 22D8 22D7
MCH_CORES0_BOOT	MCH_CORES0_BOOT - @mlb_lib.MLB	74C4
MCH_CORES0_BOOT_R	MCH_CORES0_BOOT_R - @mlb_lib.MLB	74C3
MCH_CORES0_ISEN	MCH_CORES0_ISEN - @mlb_lib.MLB	74C4
MCH_CORES0_LGATE	MCH_CORES0_LGATE - @mlb_lib.MLB	74C3
MCH_CORES0_OCSET	MCH_CORES0_OCSET - @mlb_lib.MLB	74B4
MCH_CORES0_SNUBBER_R	MCH_CORES0_SNUBBER_R - @mlb_lib.MLB	74C2
MCH_CORES0_SOFT	MCH_CORES0_SOFT - @mlb_lib.MLB	74C4
MCH_CORES0_SWITCHNOD E	MCH_CORES0_SWITCHNODE - @mlb_lib.MLB	74C3 108D1
MCH_CORES0_UGATE	MCH_CORES0_UGATE - @mlb_lib.MLB	74C4
MCH_CORES0_VSEN	MCH_CORES0_VSEN - @mlb_lib.MLB	74B3
MEMVTT_VREF	MEMVTT_VREF - @mlb_lib.MLB	75A4
MEM_A_A<0>	MEM_A_A<0> - @mlb_lib.MLB	17C5 31B3 33C6
MEM_A_A<14..0>	MEM_A_A<14..0> - @mlb_lib.MLB	102D3
MEM_A_A<1>	MEM_A_A<1> - @mlb_lib.MLB	17C5 31B6 33C6
MEM_A_A<2>	MEM_A_A<2> - @mlb_lib.MLB	17B5 31B3 33C6
MEM_A_A<3>	MEM_A_A<3> - @mlb_lib.MLB	17B5 31B6 33C6
MEM_A_A<4>	MEM_A_A<4> - @mlb_lib.MLB	17B5 31C3 33C6
MEM_A_A<5>	MEM_A_A<5> - @mlb_lib.MLB	17B5 31C6 33C6
MEM_A_A<6>	MEM_A_A<6> - @mlb_lib.MLB	17B5 31C3 33C6
MEM_A_A<7>	MEM_A_A<7> - @mlb_lib.MLB	17B5 31C3 33C6
MEM_A_A<8>	MEM_A_A<8> - @mlb_lib.MLB	17B5 31C6 33C6
MEM_A_A<9>	MEM_A_A<9> - @mlb_lib.MLB	17B5 31C6 33C6
MEM_A_A<10>	MEM_A_A<10> - @mlb_lib.MLB	17B5 31B6 33C6
MEM_A_A<11>	MEM_A_A<11> - @mlb_lib.MLB	17B5 31C3 33C6
MEM_A_A<12>	MEM_A_A<12> - @mlb_lib.MLB	17B5 31C6 33C6
MEM_A_A<13>	MEM_A_A<13> - @mlb_lib.MLB	17B5 31B3 33C6
MEM_A_A<14>	MEM_A_A<14> - @mlb_lib.MLB	16C6 31C3 33C6
MEM_A_BS<0>	MEM_A_BS<0> - @mlb_lib.MLB	17D5 31B6 33B6
MEM_A_BS<2..0>	MEM_A_BS<2..0> - @mlb_lib.MLB	102D3
MEM_A_BS<1>	MEM_A_BS<1> - @mlb_lib.MLB	17D5 31B3 33B6
MEM_A_BS<2>	MEM_A_BS<2> - @mlb_lib.MLB	17D5 31C6 33B6
MEM_A_CAS_L	MEM_A_CAS_L - @mlb_lib.MLB	17D5 31B6 33B6 102D3
MEM_A_DM<0>	MEM_A_DM<0> - @mlb_lib.MLB	17D5 31D3 102C3
MEM_A_DM<1>	MEM_A_DM<1> - @mlb_lib.MLB	17D5 31D3 102C3
MEM_A_DM<2>	MEM_A_DM<2> - @mlb_lib.MLB	17C5 31C3 102C3
MEM_A_DM<3>	MEM_A_DM<3> - @mlb_lib.MLB	17C5 31C6 102C3
MEM_A_DM<4>	MEM_A_DM<4> - @mlb_lib.MLB	17C5 31B3 102C3
MEM_A_DM<5>	MEM_A_DM<5> - @mlb_lib.MLB	17C5 31B6 102C3
MEM_A_DM<6>	MEM_A_DM<6> - @mlb_lib.MLB	17C5 31A3 102C3
MEM_A_DM<7>	MEM_A_DM<7> - @mlb_lib.MLB	17C5 31A6 102C3
MEM_A_DQ<0>	MEM_A_DQ<0> - @mlb_lib.MLB	17D8 31D6
MEM_A_DQ<6..0>	MEM_A_DQ<6..0> - @mlb_lib.MLB	102D3
MEM_A_DQ<1>	MEM_A_DQ<1> - @mlb_lib.MLB	17D8 31D6
MEM_A_DQ<2>	MEM_A_DQ<2> - @mlb_lib.MLB	17D8 31D6
MEM_A_DQ<3>	MEM_A_DQ<3> - @mlb_lib.MLB	17D8 31D6
MEM_A_DQ<4>	MEM_A_DQ<4> - @mlb_lib.MLB	17D8 31D3
MEM_A_DQ<5>	MEM_A_DQ<5> - @mlb_lib.MLB	17D8 31D3
MEM_A_DQ<6>	MEM_A_DQ<6> - @mlb_lib.MLB	17D8 31D3
MEM_A_DQ<7>	MEM_A_DQ<7> - @mlb_lib.MLB	7C7 17D8 31D3 102D3
MEM_A_DQ<8>	MEM_A_DQ<8> - @mlb_lib.MLB	17C8 31D6
MEM_A_DQ<13..8>	MEM_A_DQ<13..8> - @mlb_lib.MLB	102D3
MEM_A_DQ<9>	MEM_A_DQ<9> - @mlb_lib.MLB	17C8 31D6
MEM_A_DQ<10>	MEM_A_DQ<10> - @mlb_lib.MLB	17C8 31D6
MEM_A_DQ<11>	MEM_A_DQ<11> - @mlb_lib.MLB	17C8 31D6
MEM_A_DQ<12>	MEM_A_DQ<12> - @mlb_lib.MLB	17C8 31D3
MEM_A_DQ<13>	MEM_A_DQ<13> - @mlb_lib.MLB	17C8 31D3
MEM_A_DQ<14>	MEM_A_DQ<14> - @mlb_lib.MLB	7C7 17C8 31D3 102D3
MEM_A_DQ<15>	MEM_A_DQ<15> - @mlb_lib.MLB	17C8 31D3 102C3
MEM_A_DQ<16>	MEM_A_DQ<16> - @mlb_lib.MLB	7B7 17C8 31D6 102C3
MEM_A_DQ<17>	MEM_A_DQ<17> - @mlb_lib.MLB	17C8 31D6
MEM_A_DQ<23..17>	MEM_A_DQ<23..17> - @mlb_lib.MLB	102C3
MEM_A_DQ<18>	MEM_A_DQ<18> - @mlb_lib.MLB	17C8 31C6
MEM_A_DQ<19>	MEM_A_DQ<19> - @mlb_lib.MLB	17C8 31C6
MEM_A_DQ<20>	MEM_A_DQ<20> - @mlb_lib.MLB	17C8 31D3
MEM_A_DQ<21>	MEM_A_DQ<21> - @mlb_lib.MLB	17C8 31D3
MEM_A_DQ<22>	MEM_A_DQ<22> - @mlb_lib.MLB	17C8 31C3
MEM_A_DQ<23>	MEM_A_DQ<23> - @mlb_lib.MLB	17C8 31C3
MEM_A_DQ<24>	MEM_A_DQ<24> - @mlb_lib.MLB	17C8 31C6 102C3
MEM_A_DQ<25>	MEM_A_DQ<25> - @mlb_lib.MLB	7B7 17C8 31C6 102C3
MEM_A_DQ<26>	MEM_A_DQ<26> - @mlb_lib.MLB	17C8 31C6
MEM_A_DQ<31..26>	MEM_A_DQ<31..26> - @mlb_lib.MLB	102C3
MEM_A_DQ<27>	MEM_A_DQ<27> - @mlb_lib.MLB	17C8 31C6
MEM_A_DQ<28>	MEM_A_DQ<28> - @mlb_lib.MLB	17C8 31C3
MEM_A_DQ<29>	MEM_A_DQ<29> - @mlb_lib.MLB	17C8 31C3
MEM_A_DQ<30>	MEM_A_DQ<30> - @mlb_lib.MLB	17C8 31C3
MEM_A_DQ<31>	MEM_A_DQ<31> - @mlb_lib.MLB	17C8 31C3
MEM_A_DQ<32>	MEM_A_DQ<32> - @mlb_lib.MLB	17C8 31B6
MEM_A_DQ<38..32>	MEM_A_DQ<38..32> - @mlb_lib.MLB	102C3
MEM_A_DQ<33>	MEM_A_DQ<33> - @mlb_lib.MLB	17C8 31B6
MEM_A_DQ<34>	MEM_A_DQ<34> - @mlb_lib.MLB	17B8 31B6
MEM_A_DQ<35>	MEM_A_DQ<35> - @mlb_lib.MLB	17B8 31B6
MEM_A_DQ<36>	MEM_A_DQ<36> - @mlb_lib.MLB	17B8 31B3
MEM_A_DQ<37>	MEM_A_DQ<37> - @mlb_lib.MLB	17B8 31B3
MEM_A_DQ<38>	MEM_A_DQ<38> - @mlb_lib.MLB	17B8 31B3
MEM_A_DQ<39>	MEM_A_DQ<39> - @mlb_lib.MLB	7B7 17B8 31B3 102C3
MEM_A_DQ<40>	MEM_A_DQ<40> - @mlb_lib.MLB	17B8 31B6
MEM_A_DQ<46..40>	MEM_A_DQ<46..40> - @mlb_lib.MLB	102C3
MEM_A_DQ<41>	MEM_A_DQ<41> - @mlb_lib.MLB	17B8 31B6
MEM_A_DQ<42>	MEM_A_DQ<42> - @mlb_lib.MLB	17B8 31A6
MEM_A_DQ<43>	MEM_A_DQ<43> - @mlb_lib.MLB	17B8 31A6
MEM_A_DQ<44>	MEM_A_DQ<44> - @mlb_lib.MLB	17B8 31B3
MEM_A_DQ<45>	MEM_A_DQ<45> - @mlb_lib.MLB	17B8 31B3
MEM_A_DQ<46>	MEM_A_DQ<46> - @mlb_lib.MLB	17B8 31A3
MEM_A_DQ<47>	MEM_A_DQ<47> - @mlb_lib.MLB	7B7 17B8 31A3 102C3
MEM_A_DQ<48>	MEM_A_DQ<48> - @mlb_lib.MLB	17B8 31A6
MEM_A_DQ<53..48>	MEM_A_DQ<53..48> - @mlb_lib.MLB	102C3
MEM_A_DQ<49>	MEM_A_DQ<49> - @mlb_lib.MLB	17B8 31A6
MEM_A_DQ<50>	MEM_A_DQ<50> - @mlb_lib.MLB	17B8 31A6
MEM_A_DQ<51>	MEM_A_DQ<51> - @mlb_lib.MLB	17B8 31A6
MEM_A_DQ<52>	MEM_A_DQ<52> - @mlb_lib.MLB	17B8 31A3
MEM_A_DQ<53>	MEM_A_DQ<53> - @mlb_lib.MLB	17B8 31A3
MEM_A_DQ<54>	MEM_A_DQ<54> - @mlb_lib.MLB	7B7 17B8 31A3 102C3
MEM_A_DQ<55>	MEM_A_DQ<55> - @mlb_lib.MLB	17B8 31A3 102C3
MEM_A_DQ<56>	MEM_A_DQ<56> - @mlb_lib.MLB	17B8 31A6
MEM_A_DQ<58..56>	MEM_A_DQ<58..56> - @mlb_lib.MLB	102C3
MEM_A_DQ<57>	MEM_A_DQ<57> - @mlb_lib.MLB	17B8 31A6
MEM_A_DQ<58>	MEM_A_DQ<58> - @mlb_lib.MLB	17B8 31A6
MEM_A_DQ<59>	MEM_A_DQ<59> - @mlb_lib.MLB	7B7 17B8 31A6 102C3
MEM_A_DQ<60>	MEM_A_DQ<60> - @mlb_lib.MLB	17A8 31A3
MEM_A_DQ<63..60>	MEM_A_DQ<63..60> - @mlb_lib.MLB	102C3
MEM_A_DQ<61>	MEM_A_DQ<61> - @mlb_lib.MLB	17A8 31A3
MEM_A_DQ<62>	MEM_A_DQ<62> - @mlb_lib.MLB	17A8 31A3
MEM_A_DQ<63>	MEM_A_DQ<63> - @mlb_lib.MLB	17A8 31A3
MEM_A_DQS_N<0>	MEM_A_DQS_N<0> - @mlb_lib.MLB	7B7 17C5 31D6 102B3
MEM_A_DQS_N<1>	MEM_A_DQS_N<1> - @mlb_lib.MLB	7B7 17C5 31D6 102B3
MEM_A_DQS_N<2>	MEM_A_DQS_N<2> - @mlb_lib.MLB	7B7 17C5 31C6 102B3
MEM_A_DQS_N<3>	MEM_A_DQS_N<3> - @mlb_lib.MLB	7B7 17C5 31C3 102B3
MEM_A_DQS_N<4>	MEM_A_DQS_N<4> - @mlb_lib.MLB	7B7 17C5 31B6 102B3
MEM_A_DQS_N<5>	MEM_A_DQS_N<5> - @mlb_lib.MLB	7B7 17C5 31B3 102B3
MEM_A_DQS_N<6>	MEM_A_DQS_N<6> - @mlb_lib.MLB	7B7 17C5 31A6 102B3
MEM_A_DQS_N<7>	MEM_A_DQS_N<7> - @mlb_lib.MLB	7B7 17C5 31A3 102B3
MEM_A_DQS_P<0>	MEM_A_DQS_P<0> - @mlb_lib.MLB	7B7 17C5 31D6 102B3
MEM_A_DQS_P<1>	MEM_A_DQS_P<1> - @mlb_lib.MLB	7B7 17C5 31D6 102B3
MEM_A_DQS_P<2>	MEM_A_DQS_P<2> - @mlb_lib.MLB	7B7 17C5 31C6 102B3
MEM_A_DQS_P<3>	MEM_A_DQS_P<3> - @mlb_lib.MLB	7B7 17C5 31C3 102B3
MEM_A_DQS_P<4>	MEM_A_DQS_P<4> - @mlb_lib.MLB	7B7 17C5 31B6 102B3
MEM_A_DQS_P<5>	MEM_A_DQS_P<5> - @mlb_lib.MLB	7B7 17C5 31B3 102B3
MEM_A_DQS_P<6>	MEM_A_DQS_P<6> - @mlb_lib.MLB	7B7 17C5 31A6 102B3
MEM_A_DQS_P<7>	MEM_A_DQS_P<7> - @mlb_lib.MLB	7B7 17C5 31A3 102B3
MEM_A_RAS_L	MEM_A_RAS_L - @mlb_lib.MLB	17B5 31B3 33B6 102D3
MEM_A_SA<0>	MEM_A_SA<0> - @mlb_lib.MLB	31A4
MEM_A_SA<1>	MEM_A_SA<1> - @mlb_lib.MLB	31A4
MEM_A_WE_L	MEM_A_WE_L - @mlb_lib.MLB	17B5 31B6 33B6 102D3
MEM_B_A<0>	MEM_B_A<0> - @mlb_lib.MLB	17C1 32B3 33B6
MEM_B_A<14..0>	MEM_B_A<14..0> - @mlb_lib.MLB	102D1
MEM_B_A<1>	MEM_B_A<1> - @mlb_lib.MLB	17C1 32B6 33B6
MEM_B_A<2>	MEM_B_A<2> - @mlb_lib.MLB	17B1 32B3 33B6
MEM_B_A<3>	MEM_B_A<3> - @mlb_lib.MLB	17B1 32B6 33B6
MEM_B_A<4>	MEM_B_A<4> - @mlb_lib.MLB	17B1 32C3 33B6
MEM_B_A<5>	MEM_B_A<5> - @mlb_lib.MLB	17B1 32C6 33B6
MEM_B_A<6>	MEM_B_A<6> - @mlb_lib.MLB	17B1 32C3 33B6
MEM_B_A<7>	MEM_B_A<7> - @mlb_lib.MLB	17B1 32C3 33B6
MEM_B_A<8>	MEM_B_A<8> - @mlb_lib.MLB	17B1 32C6 33B6
MEM_B_A<9>	MEM_B_A<9> - @mlb_lib.MLB	17B1 32C6 33B6
MEM_B_A<10>	MEM_B_A<10> - @mlb_lib.MLB	17B1 32B6 33B6
MEM_B_A<11>	MEM_B_A<11> - @mlb_lib.MLB	17B1 32C3 33A6
MEM_B_A<12>	MEM_B_A<12> - @mlb_lib.MLB	17B1 32C6 33A6
MEM_B_A<13>	MEM_B_A<13> - @mlb_lib.MLB	17B1 32B3 33A6
MEM_B_A<14>	MEM_B_A<14> - @mlb_lib.MLB	16C6 32C3 33A6
MEM_B_BS<0>	MEM_B_BS<0> - @mlb_lib.MLB	17D1 32B6 33A6
MEM_B_BS<2..0>	MEM_B_BS<2..0> - @mlb_lib.MLB	102D1
MEM_B_BS<1>	MEM_B_BS<1> - @mlb_lib.MLB	17D1 32B3 33A6
MEM_B_BS<2>	MEM_B_BS<2> - @mlb_lib.MLB	17D1 32C6 33A6
MEM_B_CAS_L	MEM_B_CAS_L - @mlb_lib.MLB	17D1 32B6 33A6 102D1
MEM_B_DM<0>	MEM_B_DM<0> - @mlb_lib.MLB	17D1 32D3 102C1
MEM_B_DM<1>	MEM_B_DM<1> - @mlb_lib.MLB	17D1 32D3 102C1
MEM_B_DM<2>	MEM_B_DM<2> - @mlb_lib.MLB	17C1 32C3 102C1
MEM_B_DM<3>	MEM_B_DM<3> - @mlb_lib.MLB	17C1 32C6 102C1
MEM_B_DM<4>	MEM_B_DM<4> - @mlb_lib.MLB	17C1 32B3 102C1
MEM_B_DM<5>	MEM_B_DM<5> - @mlb_lib.MLB	17C1 32B6 102C1
MEM_B_DM<6>	MEM_B_DM<6> - @mlb_lib.MLB	17C1 32A3 102C1
MEM_B_DM<7>	MEM_B_DM<7> - @mlb_lib.MLB	17C1 32A6 102C1
MEM_B_DQ<0>	MEM_B_DQ<0> - @mlb_lib.MLB	17D4 32D6
MEM_B_DQ<5..0>	MEM_B_DQ<5..0> - @mlb_lib.MLB	102D1
MEM_B_DQ<1>	MEM_B_DQ<1> - @mlb_lib.MLB	17D4 32D6
MEM_B_DQ<2>	MEM_B_DQ<2> - @mlb_lib.MLB	17D4 32D6
MEM_B_DQ<3>	MEM_B_DQ<3> - @mlb_lib.MLB	17D4 32D6
MEM_B_DQ<4>	MEM_B_DQ<4> - @mlb_lib.MLB	17D4 32D3
MEM_B_DQ<5>	MEM_B_DQ<5> - @mlb_lib.MLB	17D4 32D3
MEM_B_DQ<6>	MEM_B_DQ<6> - @mlb_lib.MLB	7B7 17D4 32D3 102D1
MEM_B_DQ<7>	MEM_B_DQ<7> - @mlb_lib.MLB	17D4 32D3 102D1
MEM_B_DQ<8>	MEM_B_DQ<8> - @mlb_lib.MLB	7B7 17C4 32D6 102D1
MEM_B_DQ<9>	MEM_B_DQ<9> - @mlb_lib.MLB	17C4 32D6
MEM_B_DQ<15..9>	MEM_B_DQ<15..9> - @mlb_lib.MLB	102D1
MEM_B_DQ<10>	MEM_B_DQ<10> - @mlb_lib.MLB	17C4 32D6
MEM_B_DQ<11>	MEM_B_DQ<11> - @mlb_lib.MLB	17C4 32D6
MEM_B_DQ<12>	MEM_B_DQ<12> - @mlb_lib.MLB	17C4 32D3
MEM_B_DQ<13>	MEM_B_DQ<13> - @mlb_lib.MLB	17C4 32D3
MEM_B_DQ<14>	MEM_B_DQ<14> - @mlb_lib.MLB	17C4 32D3
MEM_B_DQ<15>	MEM_B_DQ<15> - @mlb_lib.MLB	17C4 32D3
MEM_B_DQ<16>	MEM_B_DQ<16> - @mlb_lib.MLB	17C4 32D6
MEM_B_DQ<22..16>	MEM_B_DQ<22..16> - @mlb_lib.MLB	102D1
MEM_B_DQ<17>	MEM_B_DQ<17> - @mlb_lib.MLB	17C4 32D6

ODD_PWR_EN_L	ODD_PWR_EN_L - @mlb_lib.MLB	24A4 24A6
ODD_RST_5VTOL_L	ODD_RST_5VTOL_L - @mlb_lib.MLB	24B6 44C6 103D3
ODD_THRMD_N	ODD_THRMD_N - @mlb_lib.MLB	55A5 55B6 108A3
ODD_THRMD_P	ODD_THRMD_P - @mlb_lib.MLB	55B5 55B6 108A3
P1V8S0_EN_L	P1V8S0_EN_L - @mlb_lib.MLB	78B7
P1V8S0_EN_L_RC	P1V8S0_EN_L_RC - @mlb_lib.MLB	78B6
P1V8S0_GDRV	P1V8S0_GDRV - @mlb_lib.MLB	78B7
P1V8S0_SS	P1V8S0_SS - @mlb_lib.MLB	78B6
P1V8S0_SS_RC	P1V8S0_SS_RC - @mlb_lib.MLB	78B7
P2V5S0_SW	P2V5S0_SW - @mlb_lib.MLB	108D1
P3V3S0_EN_L	P3V3S0_EN_L - @mlb_lib.MLB	78B3
P3V3S0_SS	P3V3S0_SS - @mlb_lib.MLB	78B2
P3V3S5_FB	P3V3S5_FB - @mlb_lib.MLB	77D5
P3V3S5_SW	P3V3S5_SW - @mlb_lib.MLB	77D5 108D1
P5VREG_FCB	P5VREG_FCB - @mlb_lib.MLB	76A3 76B5
P5VREG_FSEL	P5VREG_FSEL - @mlb_lib.MLB	76A2 76B4
P5VS0_EN_L	P5VS0_EN_L - @mlb_lib.MLB	78D3
P5VS0_SS	P5VS0_SS - @mlb_lib.MLB	78D2
P5VS3_EN_L	P5VS3_EN_L - @mlb_lib.MLB	78D7
P5VS3_SS	P5VS3_SS - @mlb_lib.MLB	78D6
P5VS5_EN	P5VS5_EN - @mlb_lib.MLB	77D6
PANEL_ID	PANEL_ID - @mlb_lib.MLB	28B2
	TP_SB_GPIO20 - @mlb_lib.MLB	25C5 28B1
PCIE_ENET_D2R_C_N	PCIE_ENET_D2R_C_N - @mlb_lib.MLB	37C4 108C3
PCIE_ENET_D2R_C_P	PCIE_ENET_D2R_C_P - @mlb_lib.MLB	37C4 108C3
PCIE_ENET_D2R_N	PCIE_ENET_D2R_N - @mlb_lib.MLB	7B8 24C5 37C8 104C3
PCIE_ENET_D2R_P	PCIE_ENET_D2R_P - @mlb_lib.MLB	7B8 24C5 37C8 104C3
PCIE_ENET_R2D_C_N	PCIE_ENET_R2D_C_N - @mlb_lib.MLB	24C5 37C8 104C3
PCIE_ENET_R2D_C_P	PCIE_ENET_R2D_C_P - @mlb_lib.MLB	24C5 37C8 104C3
PCIE_ENET_R2D_N	PCIE_ENET_R2D_N - @mlb_lib.MLB	7D6 37C4 108C3
PCIE_ENET_R2D_P	PCIE_ENET_R2D_P - @mlb_lib.MLB	7D6 37C4 108C3
PCIE_FW_D2R_C_N	PCIE_FW_D2R_C_N - @mlb_lib.MLB	40C3 108C3
PCIE_FW_D2R_C_P	PCIE_FW_D2R_C_P - @mlb_lib.MLB	40C3 108C3
PCIE_FW_D2R_N	PCIE_FW_D2R_N - @mlb_lib.MLB	7B8 40C2 42A3 104C3
	TP_PCIE_FW_D2R_N - @mlb_lib.MLB	24D5 42A2
PCIE_FW_D2R_P	PCIE_FW_D2R_P - @mlb_lib.MLB	7B8 40C2 42A3 104C3
	TP_PCIE_FW_D2R_P - @mlb_lib.MLB	24D5 42A2
PCIE_FW_R2D_C_N	PCIE_FW_R2D_C_N - @mlb_lib.MLB	40C1 42A2 104C3
	TP_PCIE_FW_R2D_C_N - @mlb_lib.MLB	24D5 42A3
PCIE_FW_R2D_C_P	PCIE_FW_R2D_C_P - @mlb_lib.MLB	40C1 42A2 104C3
	TP_PCIE_FW_R2D_C_P - @mlb_lib.MLB	24D5 42A3
PCIE_FW_R2D_N	PCIE_FW_R2D_N - @mlb_lib.MLB	7D6 40C3 108C3
PCIE_FW_R2D_P	PCIE_FW_R2D_P - @mlb_lib.MLB	7D6 40C3 108C3
PCIE_MINI_D2R_N	PCIE_MINI_D2R_N - @mlb_lib.MLB	7B8 24D5 34C8 104C3
PCIE_MINI_D2R_P	PCIE_MINI_D2R_P - @mlb_lib.MLB	7B8 24C5 34C8 104C3
PCIE_MINI_R2D_C_N	PCIE_MINI_R2D_C_N - @mlb_lib.MLB	24C5 34B8 104C3
PCIE_MINI_R2D_C_P	PCIE_MINI_R2D_C_P - @mlb_lib.MLB	24C5 34B8 104C3
PCIE_MINI_R2D_N	PCIE_MINI_R2D_N - @mlb_lib.MLB	34B6 108C3
PCIE_MINI_R2D_P	PCIE_MINI_R2D_P - @mlb_lib.MLB	34B6 108B3
PCIE_WAKE_L	PCIE_WAKE_L - @mlb_lib.MLB	25C8 34C6 37B8
PCI_AD<0>	PCI_AD<0> - @mlb_lib.MLB	24B8 28C5
	TP_PCI_AD_0 - @mlb_lib.MLB	28C4
PCI_AD<18..0>	PCI_AD<18..0> - @mlb_lib.MLB	104D3
	TP_PCI_AD_18 - @mlb_lib.MLB	28B4
PCI_AD<1>	PCI_AD<1> - @mlb_lib.MLB	24B8 28C5
	TP_PCI_AD_1 - @mlb_lib.MLB	28C4
PCI_AD<2>	PCI_AD<2> - @mlb_lib.MLB	24B8 28C5
	TP_PCI_AD_2 - @mlb_lib.MLB	28C4
PCI_AD<3>	PCI_AD<3> - @mlb_lib.MLB	24B8 28C5
	TP_PCI_AD_3 - @mlb_lib.MLB	28C4
PCI_AD<4>	PCI_AD<4> - @mlb_lib.MLB	24B8 28C5
	TP_PCI_AD_4 - @mlb_lib.MLB	28C4
PCI_AD<5>	PCI_AD<5> - @mlb_lib.MLB	24B8 28C5
	TP_PCI_AD_5 - @mlb_lib.MLB	28C4
PCI_AD<6>	PCI_AD<6> - @mlb_lib.MLB	24B8 28C5
	TP_PCI_AD_6 - @mlb_lib.MLB	28C4
PCI_AD<7>	PCI_AD<7> - @mlb_lib.MLB	24B8 28C5
	TP_PCI_AD_7 - @mlb_lib.MLB	28C4
PCI_AD<8>	PCI_AD<8> - @mlb_lib.MLB	24B8 28C5
	TP_PCI_AD_8 - @mlb_lib.MLB	28C4
PCI_AD<9>	PCI_AD<9> - @mlb_lib.MLB	24B8 28C5
	TP_PCI_AD_9 - @mlb_lib.MLB	28C4
PCI_AD<10>	PCI_AD<10> - @mlb_lib.MLB	24A8 28C5
	TP_PCI_AD_10 - @mlb_lib.MLB	28C4
PCI_AD<11>	PCI_AD<11> - @mlb_lib.MLB	24A8 28C5
	TP_PCI_AD_11 - @mlb_lib.MLB	28C4
PCI_AD<12>	PCI_AD<12> - @mlb_lib.MLB	24A8 28C5
	TP_PCI_AD_12 - @mlb_lib.MLB	28C4
PCI_AD<13>	PCI_AD<13> - @mlb_lib.MLB	24A8 28C5
	TP_PCI_AD_13 - @mlb_lib.MLB	28C4
PCI_AD<14>	PCI_AD<14> - @mlb_lib.MLB	24A8 28C5
	TP_PCI_AD_14 - @mlb_lib.MLB	28C4
PCI_AD<15>	PCI_AD<15> - @mlb_lib.MLB	24A8 28C5
	TP_PCI_AD_15 - @mlb_lib.MLB	28C4
PCI_AD<16>	PCI_AD<16> - @mlb_lib.MLB	24A8 28C5
	PCI_AD<16 - @mlb_lib.MLB	28C4
PCI_AD<17>	PCI_AD<17> - @mlb_lib.MLB	24A8 28C5
	TP_PCI_AD_17 - @mlb_lib.MLB	28C4
PCI_AD<18>	PCI_AD<18> - @mlb_lib.MLB	24A8 28B5
	TP_PCI_AD_18 - @mlb_lib.MLB	28B4
PCI_AD<19>	PCI_AD<19> - @mlb_lib.MLB	24A8 28B5 104D3
	TP_PCI_AD_19 - @mlb_lib.MLB	28B4
PCI_AD<20>	PCI_AD<20> - @mlb_lib.MLB	24A8 28B5 104D3
	TP_PCI_AD_20 - @mlb_lib.MLB	28B4
PCI_AD<21>	PCI_AD<21> - @mlb_lib.MLB	24A8 28B5
	TP_PCI_AD_21 - @mlb_lib.MLB	28B4
PCI_AD<31..21>	PCI_AD<31..21> - @mlb_lib.MLB	104D3
	TP_PCI_AD_31 - @mlb_lib.MLB	28B4
PCI_AD<22>	PCI_AD<22> - @mlb_lib.MLB	24A8 28B5
	TP_PCI_AD_22 - @mlb_lib.MLB	28B4
PCI_AD<23>	PCI_AD<23> - @mlb_lib.MLB	24A8 28B5
	TP_PCI_AD_23 - @mlb_lib.MLB	28B4
PCI_AD<24>	PCI_AD<24> - @mlb_lib.MLB	24A8 28B5
	TP_PCI_AD_24 - @mlb_lib.MLB	28B4
PCI_AD<25>	PCI_AD<25> - @mlb_lib.MLB	24A8 28B5
	TP_PCI_AD_25 - @mlb_lib.MLB	28B4
PCI_AD<26>	PCI_AD<26> - @mlb_lib.MLB	24A8 28B5
	TP_PCI_AD_26 - @mlb_lib.MLB	28B4
PCI_AD<27>	PCI_AD<27> - @mlb_lib.MLB	24A8 28B5
	TP_PCI_AD_27 - @mlb_lib.MLB	28B4
PCI_AD<28>	PCI_AD<28> - @mlb_lib.MLB	24A8 28B5
	TP_PCI_AD_28 - @mlb_lib.MLB	28B4
PCI_AD<29>	PCI_AD<29> - @mlb_lib.MLB	24A8 28B5
	TP_PCI_AD_29 - @mlb_lib.MLB	28B4
PCI_AD<30>	PCI_AD<30> - @mlb_lib.MLB	24A8 28B5
	TP_PCI_AD_30 - @mlb_lib.MLB	28B4
PCI_AD<31>	PCI_AD<31> - @mlb_lib.MLB	24A8 28B5
	TP_PCI_AD_31 - @mlb_lib.MLB	28B4
PCI_CLK33M_LPCPLUS	PCI_CLK33M_LPCPLUS - @mlb_lib.MLB	7D4 30A3 51C4 105C3
PCI_CLK33M_SB	PCI_CLK33M_SB - @mlb_lib.MLB	7B8 24A6 30A3 105B3
PCI_CLK33M_SMC	PCI_CLK33M_SMC - @mlb_lib.MLB	7C6 30A3 49C8 105B3
PCI_CLK33M_TPM	PCI_CLK33M_TPM - @mlb_lib.MLB	105B3
PCI_C_BE_L<0>	PCI_C_BE_L<0> - @mlb_lib.MLB	24B6 28B5
	TP_PCI_C_BE_L_0 - @mlb_lib.MLB	28B4

PCI_C_BE_L<3..0>	PCI_C_BE_L<3..0> - @mlb_lib.MLB	104D3
	TP_PCI_C_BE_L_3 - @mlb_lib.MLB	28B4
PCI_C_BE_L<1>	PCI_C_BE_L<1> - @mlb_lib.MLB	24A6 28B5
	TP_PCI_C_BE_L_1 - @mlb_lib.MLB	28B4
PCI_C_BE_L<2>	PCI_C_BE_L<2> - @mlb_lib.MLB	24A6 28B5
	TP_PCI_C_BE_L_2 - @mlb_lib.MLB	28B4
PCI_C_BE_L<3>	PCI_C_BE_L<3> - @mlb_lib.MLB	24A6 28B5
	TP_PCI_C_BE_L_3 - @mlb_lib.MLB	28B4
PCI_DEVSEL_L	PCI_DEVSEL_L - @mlb_lib.MLB	24A4 24A6 104D3
PCI_FRAME_L	PCI_FRAME_L - @mlb_lib.MLB	24A4 24A6 104D3
PCI_FW_GNT_L	PCI_FW_GNT_L - @mlb_lib.MLB	24B5 104D3
	BOOT_LPC_SPI_L - @mlb_lib.MLB	7D4 24B5 51B6
PCI_FW_REQ_L	PCI_FW_REQ_L - @mlb_lib.MLB	24A4 24B6 104D3
PCI_GNT1_L	PCI_GNT1_L - @mlb_lib.MLB	104D3
PCI_GNT2_L	PCI_GNT2_L - @mlb_lib.MLB	104C3
PCI_IRDY_L	PCI_IRDY_L - @mlb_lib.MLB	24A4 24A6 104D3
PCI_LOCK_L	PCI_LOCK_L - @mlb_lib.MLB	24A4 24A6 104D3
PCI_PAR	PCI_PAR - @mlb_lib.MLB	24A6 28B5 104D3
	TP_PCI_PAR - @mlb_lib.MLB	28B4
PCI_PERR_L	PCI_PERR_L - @mlb_lib.MLB	24A4 24A6 104D3
PCI_PME_FW_L	PCI_PME_FW_L - @mlb_lib.MLB	25B5 25C5 40C3
PCI_REQ1_L	PCI_REQ1_L - @mlb_lib.MLB	7C3 24A4 24B6 104D3
PCI_REQ2_L	PCI_REQ2_L - @mlb_lib.MLB	7C3 24A4 24B6 104D3
PCI_RST_L	PCI_RST_L - @mlb_lib.MLB	24A6 28B5
	TP_PCI_RST_L - @mlb_lib.MLB	28B4
PCI_SERR_L	PCI_SERR_L - @mlb_lib.MLB	24A4 24A6 28C4 104D3
PCI_STOP_L	PCI_STOP_L - @mlb_lib.MLB	24A4 24A6 104D3
PCI_TRDY_L	PCI_TRDY_L - @mlb_lib.MLB	24A4 24A6 104D3
PEG_COMP	PEG_COMP - @mlb_lib.MLB	15D3
PEG_D2R_N<0>	PEG_D2R_N<0> - @mlb_lib.MLB	15D3 84C4
PEG_D2R_N<6..0>	PEG_D2R_N<6..0> - @mlb_lib.MLB	101D3
PEG_D2R_N<1>	PEG_D2R_N<1> - @mlb_lib.MLB	15D3 84C4
PEG_D2R_N<2>	PEG_D2R_N<2> - @mlb_lib.MLB	15D3 84B4
PEG_D2R_N<3>	PEG_D2R_N<3> - @mlb_lib.MLB	15D3 84B4
PEG_D2R_N<4>	PEG_D2R_N<4> - @mlb_lib.MLB	15D3 84B4
PEG_D2R_N<5>	PEG_D2R_N<5> - @mlb_lib.MLB	15D3 84B4
PEG_D2R_N<6>	PEG_D2R_N<6> - @mlb_lib.MLB	15D3 84B4
PEG_D2R_N<7>	PEG_D2R_N<7> - @mlb_lib.MLB	7A7 15D3 84B4 101D3
PEG_D2R_N<8>	PEG_D2R_N<8> - @mlb_lib.MLB	15D3 84B4
PEG_D2R_N<15..8>	PEG_D2R_N<15..8> - @mlb_lib.MLB	101D3
PEG_D2R_N<9>	PEG_D2R_N<9> - @mlb_lib.MLB	15D3 84B4
PEG_D2R_N<10>	PEG_D2R_N<10> - @mlb_lib.MLB	15C3 84B4
PEG_D2R_N<11>	PEG_D2R_N<11> - @mlb_lib.MLB	15C3 84A4
PEG_D2R_N<12>	PEG_D2R_N<12> - @mlb_lib.MLB	15C3 84A4
PEG_D2R_N<13>	PEG_D2R_N<13> - @mlb_lib.MLB	15C3 84A4
PEG_D2R_N<14>	PEG_D2R_N<14> - @mlb_lib.MLB	15C3 84A4
PEG_D2R_N<15>	PEG_D2R_N<15> - @mlb_lib.MLB	15C3 84A4
PEG_D2R_P<0>	PEG_D2R_P<0> - @mlb_lib.MLB	15C3 84C4
PEG_D2R_P<6..0>	PEG_D2R_P<6..0> - @mlb_lib.MLB	101D3
PEG_D2R_P<1>	PEG_D2R_P<1> - @mlb_lib.MLB	15C3 84C4
PEG_D2R_P<2>	PEG_D2R_P<2> - @mlb_lib.MLB	15C3 84B4
PEG_D2R_P<3>	PEG_D2R_P<3> - @mlb_lib.MLB	15C3 84B4
PEG_D2R_P<4>	PEG_D2R_P<4> - @mlb_lib.MLB	15C3 84A4
PEG_D2R_P<5>	PEG_D2R_P<5> - @mlb_lib.MLB	15C3 84B4
PEG_D2R_P<6>	PEG_D2R_P<6> - @mlb_lib.MLB	7A7 15C3 84B4 101D3
PEG_D2R_P<15..8>	PEG_D2R_P<15..8> - @mlb_lib.MLB	101D3
PEG_D2R_P<9>	PEG_D2R_P<9> - @mlb_lib.MLB	15C3 84B4
PEG_D2R_P<10>	PEG_D2R_P<10> - @mlb_lib.MLB	15C3 84B4
PEG_D2R_P<11>	PEG_D2R_P<11> - @mlb_lib.MLB	15C3 84A4
PEG_D2R_P<12>	PEG_D2R_P<12> - @mlb_lib.MLB	15C3 84A4
PEG_D2R_P<13>	PEG_D2R_P<13> - @mlb_lib.MLB	15C3 84A4
PEG_D2R_P<14>	PEG_D2R_P<14> - @mlb_lib.MLB	15C3 84A4
PEG_D2R_P<15>	PEG_D2R_P<15> - @mlb_lib.MLB	15C3 84A4
PEG_R2D_C_N<0>	PEG_R2D_C_N<0> - @mlb_lib.MLB	15C3 84C8
PEG_R2D_C_N<15..0>	PEG_R2D_C_N<15..0> - @mlb_lib.MLB	101D3
PEG_R2D_C_N<1>	PEG_R2D_C_N<1> - @mlb_lib.MLB	15C3 84C8
PEG_R2D_C_N<2>	PEG_R2D_C_N<2> - @mlb_lib.MLB	15C3 84B8
PEG_R2D_C_N<3>	PEG_R2D_C_N<3> - @mlb_lib.MLB	15B3 84B8
PEG_R2D_C_N<4>	PEG_R2D_C_N<4> - @mlb_lib.MLB	15B3 84B8
PEG_R2D_C_N<5>	PEG_R2D_C_N<5> - @mlb_lib.MLB	15B3 84B8
PEG_R2D_C_N<6>	PEG_R2D_C_N<6> - @mlb_lib.MLB	15B3 84B8
PEG_R2D_C_N<7>	PEG_R2D_C_N<7> - @mlb_lib.MLB	15B3 84B8
PEG_R2D_C_N<8>	PEG_R2D_C_N<8> - @mlb_lib.MLB	15B3 84B8
PEG_R2D_C_N<9>	PEG_R2D_C_N<9> - @mlb_lib.MLB	15B3 84B8
PEG_R2D_C_N<10>	PEG_R2D_C_N<10> - @mlb_lib.MLB	15B3 84A8
PEG_R2D_C_N<11>	PEG_R2D_C_N<11> - @mlb_lib.MLB	15B3 84A8
PEG_R2D_C_N<12>	PEG_R2D_C_N<12> - @mlb_lib.MLB	15B3 84A8
PEG_R2D_C_N<13>	PEG_R2D_C_N<13> - @mlb_lib.MLB	15B3 84A8
PEG_R2D_C_N<14>	PEG_R2D_C_N<14> - @mlb_lib.MLB	15B3 84A8
PEG_R2D_C_N<15>	PEG_R2D_C_N<15> - @mlb_lib.MLB	15B3 84A8
PEG_R2D_C_P<0>	PEG_R2D_C_P<0> - @mlb_lib.MLB	15B3 84C8
PEG_R2D_C_P<15..0>	PEG_R2D_C_P<15..0> - @mlb_lib.MLB	101D3
PEG_R2D_C_P<1>	PEG_R2D_C_P<1> - @mlb_lib.MLB	15B3 84C8
PEG_R2D_C_P<2>	PEG_R2D_C_P<2> - @mlb_lib.MLB	15B3 84B8
PEG_R2D_C_P<3>	PEG_R2D_C_P<3> - @mlb_lib.MLB	15B3 84B8
PEG_R2D_C_P<4>	PEG_R2D_C_P<4> - @mlb_lib.MLB	15B3 84B8
PEG_R2D_C_P<5>	PEG_R2D_C_P<5> - @mlb_lib.MLB	15B3 84B8
PEG_R2D_C_P<6>	PEG_R2D_C_P<6> - @mlb_lib.MLB	15B3 84B8
PEG_R2D_C_P<7>	PEG_R2D_C_P<7> - @mlb_lib.MLB	15B3 84B8
PEG_R2D_C_P<8>	PEG_R2D_C_P<8> - @mlb_lib.MLB	15B3 84B8
PEG_R2D_C_P<9>	PEG_R2D_C_P<9> - @mlb_lib.MLB	15B3 84B8
PEG_R2D_C_P<10>	PEG_R2D_C_P<10> - @mlb_lib.MLB	15B3 84B8
PEG_R2D_C_P<11>	PEG_R2D_C_P<11> - @mlb_lib.MLB	15B3 84A8
PEG_R2D_C_P<12>	PEG_R2D_C_P<12> - @mlb_lib.MLB	15A3 84A8
PEG_R2D_C_P<13>	PEG_R2D_C_P<13> - @mlb_lib.MLB	15A3 84A8
PEG_R2D_C_P<14>	PEG_R2D_C_P<14> - @mlb_lib.MLB	15A3 84A8
PEG_R2D_C_P<15>	PEG_R2D_C_P<15> - @mlb_lib.MLB	15A3 84A8
PEG_R2D_N<0>	PEG_R2D_N<0> - @mlb_lib.MLB	84A7
PEG_R2D_N<15..0>	PEG_R2D_N<15..0> - @mlb_lib.MLB	101D3
PEG_R2D_N<1>	PEG_R2D_N<1> - @mlb_lib.MLB	84A7
PEG_R2D_N<2>	PEG_R2D_N<2> - @mlb_lib.MLB	84A7
PEG_R2D_N<3>	PEG_R2D_N<3> - @mlb_lib.MLB	84A7
PEG_R2D_N<4>	PEG_R2D_N<4> - @mlb_lib.MLB	84A7
PEG_R2D_N<5>	PEG_R2D_N<5> - @mlb_lib.MLB	84A7
PEG_R2D_N<6>	PEG_R2D_N<6> - @mlb_lib.MLB	84B7
PEG_R2D_N<7>	PEG_R2D_N<7> - @mlb_lib.MLB	84B7
PEG_R2D_N<8>	PEG_R2D_N<8> - @mlb_lib.MLB	84B7
PEG_R2D_N<9>	PEG_R2D_N<9> - @mlb_lib.MLB	84B7
PEG_R2D_N<10>	PEG_R2D_N<10> - @mlb_lib.MLB	84B7
PEG_R2D_N<11>	PEG_R2D_N<11> - @mlb_lib.MLB	84B7
PEG_R2D_N<12>	PEG_R2D_N<12> - @mlb_lib.MLB	84B7
PEG_R2D_N<13>	PEG_R2D_N<13> - @mlb_lib.MLB	84B7
PEG_R2D_N<14>	PEG_R2D_N<14> - @mlb_lib.MLB	84C7
PEG_R2D_N<15>	PEG_R2D_N<15> - @mlb_lib.MLB	84C7
PEG_R2D_P<0>	PEG_R2D_P<0> - @mlb_lib.MLB	84A7
PEG_R2D_P<15..0>	PEG_R2D_P<15..0> - @mlb_lib.MLB	101D3
PEG_R2D_P<1>	PEG_R2D_P<1> - @mlb_lib.MLB	84A7
PEG_R2D_P<2>	PEG_R2D_P<2> - @mlb_lib.MLB	84A7
PEG_R2D_P<3>	PEG_R2D_P<3> - @mlb_lib.MLB	84A7
PEG_R2D_P<4>	PEG_R2D_P<4> - @mlb_lib.MLB	84A7
PEG_R2D_P<5>	PEG_R2D_P<5> - @mlb_lib.MLB	84B7
PEG_R2D_P<6>	PEG_R2D_P<6> - @mlb_lib.MLB	84B7

PEG_R2D_P<7>	PEG_R2D_P<7> - @mlb_lib.MLB	84B7
PEG_R2D_P<8>	PEG_R2D_P<8> - @mlb_lib.MLB	84B7
PEG_R2D_P<9>	PEG_R2D_P<9> - @mlb_lib.MLB	84B7
PEG_R2D_P<10>	PEG_R2D_P<10> - @mlb_lib.MLB	84B7
PEG_R2D_P<11>	PEG_R2D_P<11> - @mlb_lib.MLB	84B7
PEG_R2D_P<12>	PEG_R2D_P<12> - @mlb_lib.MLB	84B7
PEG_R2D_P<13>	PEG_R2D_P<13> - @mlb_lib.MLB	84B7
PEG_R2D_P<14>	PEG_R2D_P<14> - @mlb_lib.MLB	84C7
PEG_R2D_P<15>	PEG_R2D_P<15> - @mlb_lib.MLB	84C7
PEG_RESET_L	PEG_RESET_L - @mlb_lib.MLB	28C1 85C7
PGOOD_0V9_S0	PGOOD_0V9_S0 - @mlb_lib.MLB	70C4 70C4
PGOOD_1V05_S0	PGOOD_1V05_S0 - @mlb_lib.MLB	70B4 73B3
PGOOD_1V5_S0	PGOOD_1V5_S0 - @mlb_lib.MLB	70B4 73B5
PGOOD_1V8_S0	PGOOD_1V8_S0 - @mlb_lib.MLB	70C4 70D4
PGOOD_1V8_S3	PGOOD_1V8_S3 - @mlb_lib.MLB	70D4 75C8
PGOOD_1V25_S0	PGOOD_1V25_S0 - @mlb_lib.MLB	70B4 74B5
PGOOD_3V3_S0	PGOOD_3V3_S0 - @mlb_lib.MLB	70C8 70D4
PGOOD_3V3_S3	PGOOD_3V3_S3 - @mlb_lib.MLB	70D4 76B4
PGOOD_3V3_S5	PGOOD_3V3_S5 - @mlb_lib.MLB	70B4 77D4
	RSMRST_PWRGD - @mlb_lib.MLB	49D8 70B2
PGOOD_5V_S0	PGOOD_5V_S0 - @mlb_lib.MLB	70C4 70C4
PGOOD_5V_S3_L	PGOOD_5V_S3_L - @mlb_lib.MLB	76A6
PGOOD_12V_S0	PGOOD_12V_S0 - @mlb_lib.MLB	70B8 76D5
PGOOD_CR_S0	PGOOD_CR_S0 - @mlb_lib.MLB	70C7
PGOOD_MCH_CORE_S0	PGOOD_MCH_CORE_S0 - @mlb_lib.MLB	70B4 74B3
PGOOD_S0_OUT1	PGOOD_S0_OUT1 - @mlb_lib.MLB	70C3
PLT_RST_L	PLT_RST_L - @mlb_lib.MLB	24A6 28D4
PM_BATLOW_L	PM_BATLOW_L - @mlb_lib.MLB	25A5 25C3 49B8
PM_BMBUSY_L	PM_BMBUSY_L - @mlb_lib.MLB	16B6 25D5
PM_CLKRUN_L	PM_CLKRUN_L - @mlb_lib.MLB	7B8 7D4 25C8 49C5 51B6
PM_DPRSLPVR	PM_DPRSLPVR - @mlb_lib.MLB	16A6 25C3 71C8 100B3
PM_EXTTS_L<0>	PM_EXTTS_L<0> - @mlb_lib.MLB	16B7 31C3 49B8
PM_EXTTS_L<1>	PM_EXTTS_L<1> - @mlb_lib.MLB	16B7 32C3 49B8
PM_LAN_ENABLE	PM_LAN_ENABLE - @mlb_lib.MLB	25C2 49D8
PM_LATRIGGER_L	PM_LATRIGGER_L - @mlb_lib.MLB	13C3 24C8
PM_PWRBTN_L	PM_PWRBTN_L - @mlb_lib.MLB	25C3 49C8
PM_RI_L	PM_RI_L - @mlb_lib.MLB	25A5 25D5
PM_RSMRST_L	PM_RSMRST_L - @mlb_lib.MLB	25C2 49C8
PM_S4_STATE_L	PM_S4_STATE_L - @mlb_lib.MLB	7C4 7D3 25D3 46C8 49C4
		75D8 78D7
PM_S4_STATE_L_SMC	PM_S4_STATE_L_SMC - @mlb_lib.MLB	49C6
PM_SLP_S3_L	PM_SLP_S3_L - @mlb_lib.MLB	6D8 7C4 25D3 49C4 70A8
		75A5 78B4 78B7 78D4
PM_SLP_S3_L_SMC	PM_SLP_S3_L_SMC - @mlb_lib.MLB	49C6
PM_SLP_S3_OD	PM_SLP_S3_OD - @mlb_lib.MLB	6D7
PM_SLP_S5_L	PM_SLP_S5_L - @mlb_lib.MLB	25D3 49C5 50A2
PM_STPCPU_L	PM_STPCPU_L - @mlb_lib.MLB	25C8 29C3 30C2
PM_STPPCI_L	PM_STPPCI_L - @mlb_lib.MLB	25C8 29C3 30C2
PM_SUS_STAT_L	PM_SUS_STAT_L - @mlb_lib.MLB	7C4 7D4 25D5 49C5 50A2
		51B4
PM_SYSRST_L	PM_SYSRST_L - @mlb_lib.MLB	7B8 25D5 28A3 49B8
PM_THRMTRIP_L	PM_THRMTRIP_L - @mlb_lib.MLB	10C6 16A6 23C2 50C3 100B3
PM_THRM_L	PM_THRM_L - @mlb_lib.MLB	25C5
POWER_BUTTON_L	POWER_BUTTON_L - @mlb_lib.MLB	50C7
PP1V0_S5_FW_AVDD	PP1V0_S5_FW_AVDD - @mlb_lib.MLB	40D3 42A6 42D4
PP1V0_S5_FW_DVDD	PP1V0_S5_FW_DVDD - @mlb_lib.MLB	40D6 42B8 42C4
PP1V05_S0_NB_VCCPEG	PP1V05_S0_NB_VCCPEG - @mlb_lib.MLB	15D2 19B3 21D3
	PP1V05_S0_NB_VCCRXRDMI -	19B3 21C3
	@mlb_lib.MLB	
PP1V5_S0_NB_VCCD_TVD	PP1V5_S0_NB_VCCD_TVDAC -	19B6 22B1
AC	@mlb_lib.MLB	
PP1V5_S0_SB_VCCDMIPL	PP1V5_S0_SB_VCCDMIPLL -	26C3 27A6
L	@mlb_lib.MLB	
PP1V5_S0_SB_VCCDMIPL	PP1V5_S0_SB_VCCDMIPLL_F -	27A8
L_F	@mlb_lib.MLB	
PP1V5_S0_SB_VCCSATAP	PP1V5_S0_SB_VCCSATAPLL -	26B6 27A6
LL	@mlb_lib.MLB	
PP1V5_S0_SB_VCCSATAP	PP1V5_S0_SB_VCCSATAPLL_F -	27A8
LL_F	@mlb_lib.MLB	
PP1V8_S3M_NB_VCCSMCK	PP1V8_S3M_NB_VCCSMCK - @mlb_lib.MLB	19B3 21A2
PP1V8_S3M_NB_VCCSMCK	PP1V8_S3M_NB_VCCSMCK_RC -	21A4
_RC	@mlb_lib.MLB	
PP1V8_S3_R	PP1V8_S3_R - @mlb_lib.MLB	75C1
PP1V9_ENET_CTAP	PP1V9_ENET_CTAP - @mlb_lib.MLB	39D7
PP1V9_ENET_PHY_AVDD	PP1V9_ENET_PHY_AVDD - @mlb_lib.MLB	37C6 104B3
PP1V9_S3_ENET	PP1V9_S3_ENET - @mlb_lib.MLB	37C7 38C3 39D8
PP1V25_S0M_NB_MPLL_R	PP1V25_S0M_NB_MPLL_RC -	21C3
C	@mlb_lib.MLB	
PP1V25_S0M_NB_VCCAXD	PP1V25_S0M_NB_VCCAXD - @mlb_lib.MLB	16A2 19C3 21A6
PP1V25_S0M_NB_VCCA_H	PP1V25_S0M_NB_VCCA_HPLL -	19D6 21D1
PLL	@mlb_lib.MLB	
PP1V25_S0M_NB_VCCA_M	PP1V25_S0M_NB_VCCA_MPLL -	19D6 21C1
PLL	@mlb_lib.MLB	
PP1V25_S0M_NB_VCCA_S	PP1V25_S0M_NB_VCCA_SM -	19C6 21B5
M	@mlb_lib.MLB	
PP1V25_S0M_NB_VCCA_S	PP1V25_S0M_NB_VCCA_SM_CK -	19B6 21B5
M_CK	@mlb_lib.MLB	
PP1V25_S0_NB_PEGPLL	PP1V25_S0_NB_PEGPLL - @mlb_lib.MLB	19C6 21B2
PP1V25_S0_NB_PEGPLL_	PP1V25_S0_NB_PEGPLL_RC -	21B4
RC	@mlb_lib.MLB	
PP1V25_S0_NB_VCCAXF	PP1V25_S0_NB_VCCAXF - @mlb_lib.MLB	19C3 21D3
PP3V3_FW_ESD	PP3V3_FW_ESD - @mlb_lib.MLB	43A6 43A6 43B6 43C5 43D5
PP3V3_G3_SB_RTC	PP3V3_G3_SB_RTC - @mlb_lib.MLB	23D7 26D6 27D5 28D5
PP3V3_S0M_CK505_VDD4	PP3V3_S0M_CK505_VDD48 -	29D4
8	@mlb_lib.MLB	
PP3V3_S0M_CK505_VDDA	PP3V3_S0M

SMBUS_SMC_B_S0_SDA	SMBUS_SMC_B_S0_SDA - @mlb_lib.MLB	52B5 106B3
	=SMBUS_MINI_SDA - @mlb_lib.MLB	34B3 52B3
	=SMB_REMOTE_TEMP_SDA - @mlb_lib.MLB	52B3 55B2
	=SMB_CPU_THRM_SDA - @mlb_lib.MLB	52B3 55C4
	SMB_B_S0_DATA - @mlb_lib.MLB	49A5 52B5
	=SMB_REMOTE_TEMP_SDA - @mlb_lib.MLB	52B3 55B2
	=SMB_CPU_THRM_SDA - @mlb_lib.MLB	52B3 55C4
	=SMBUS_MINI_SDA - @mlb_lib.MLB	34B3 52B3
SMBUS_SMC_MGMT_SCL	SMBUS_SMC_MGMT_SCL - @mlb_lib.MLB	52B2 106B3
	SMB_MGMT_CLK - @mlb_lib.MLB	49C5 52B3
SMBUS_SMC_MGMT_SDA	SMBUS_SMC_MGMT_SDA - @mlb_lib.MLB	52B2 106B3
	SMB_MGMT_DATA - @mlb_lib.MLB	49C8 52B3
SMB_CLK	SMB_CLK - @mlb_lib.MLB	25D5 52D8 103A3
	=SMBUS_CK505_SCL - @mlb_lib.MLB	29B5 52D6
	SMBUS_SB_SCL - @mlb_lib.MLB	52D7
	=I2C_DIMMA_SCL - @mlb_lib.MLB	31A6 52D6
	=I2C_DIMMB_SCL - @mlb_lib.MLB	32A6 52C6
	SMBUS_SB_SCL - @mlb_lib.MLB	52D7
	=SMBUS_CK505_SCL - @mlb_lib.MLB	29B5 52D6
	=I2C_DIMMB_SCL - @mlb_lib.MLB	32A6 52C6
	=I2C_DIMMA_SCL - @mlb_lib.MLB	31A6 52D6
SMB_DATA	SMB_DATA - @mlb_lib.MLB	25D5 52D8 103A3
	=SMBUS_CK505_SDA - @mlb_lib.MLB	29B5 52D6
	SMBUS_SB_SDA - @mlb_lib.MLB	52D7
	=I2C_DIMMA_SDA - @mlb_lib.MLB	31A6 52D6
	=I2C_DIMMB_SDA - @mlb_lib.MLB	32A6 52C6
	SMBUS_SB_SDA - @mlb_lib.MLB	52D7
	=SMBUS_CK505_SDA - @mlb_lib.MLB	29B5 52D6
	=I2C_DIMMB_SDA - @mlb_lib.MLB	32A6 52C6
	=I2C_DIMMA_SDA - @mlb_lib.MLB	31A6 52D6
SMB_ME_CLK	SMB_ME_CLK - @mlb_lib.MLB	25D5 52A8 103A3
	SMBUS_SB_ME_SCL - @mlb_lib.MLB	52A7
SMB_ME_DATA	SMB_ME_DATA - @mlb_lib.MLB	25D5 52A8 103A3
	SMBUS_SB_ME_SDA - @mlb_lib.MLB	52A7
SMC_12V_S0_ISENSE	SMC_12V_S0_ISENSE - @mlb_lib.MLB	50B3 53B1
	SMC_DCIN_ISENSE - @mlb_lib.MLB	49C5 50B5
SMC_12V_S0_ISENSE_R	SMC_12V_S0_ISENSE_R - @mlb_lib.MLB	53B2
SMC_12V_S0_VSENSE	SMC_12V_S0_VSENSE - @mlb_lib.MLB	50B3 53B2
	SMC_PBUS_VSENSE - @mlb_lib.MLB	49C5 50B5
SMC_12V_S5_ISENSE	SMC_12V_S5_ISENSE - @mlb_lib.MLB	50B3 53B1
	SMC_BATT_ISENSE - @mlb_lib.MLB	49C5 50B5
SMC_12V_S5_ISENSE_R	SMC_12V_S5_ISENSE_R - @mlb_lib.MLB	53B2
SMC_12V_S5_VSENSE	SMC_12V_S5_VSENSE - @mlb_lib.MLB	50A3 53B3
	SMC_NB_VX25_ISENSE - @mlb_lib.MLB	49C5 50A5
SMC_ADAPTER_EN	SMC_ADAPTER_EN - @mlb_lib.MLB	49D5 50B5
	TP_SMC_ADAPTER_EN - @mlb_lib.MLB	50B3
SMC_BC_ACOK	SMC_BC_ACOK - @mlb_lib.MLB	49C5 50B2
SMC_BS_ALRT_L	SMC_BS_ALRT_L - @mlb_lib.MLB	49C5 50B2
SMC_CASE_OPEN	SMC_CASE_OPEN - @mlb_lib.MLB	49B5 50A2
SMC_CPU_ISENSE	SMC_CPU_ISENSE - @mlb_lib.MLB	49C5 53C6
SMC_CPU_VSENSE	SMC_CPU_VSENSE - @mlb_lib.MLB	49C5 53D6
SMC_EXCARD_CP	SMC_EXCARD_CP - @mlb_lib.MLB	49B8 50A2
SMC_EXCARD_PWR_EN	SMC_EXCARD_PWR_EN - @mlb_lib.MLB	49B8 50B5
	TP_SMC_EXCARD_PWR_EN - @mlb_lib.MLB	50B3
SMC_EXTAL	SMC_EXTAL - @mlb_lib.MLB	49C3 50C8
SMC_FAN_0_CTL	SMC_FAN_0_CTL - @mlb_lib.MLB	49A8 56D8
SMC_FAN_0_TACH	SMC_FAN_0_TACH - @mlb_lib.MLB	49A8 56C8
SMC_FAN_1_CTL	SMC_FAN_1_CTL - @mlb_lib.MLB	49A8 56B8
SMC_FAN_1_TACH	SMC_FAN_1_TACH - @mlb_lib.MLB	49A8 56A8
SMC_FAN_2_CTL	SMC_FAN_2_CTL - @mlb_lib.MLB	49A8 57D8
SMC_FAN_2_TACH	SMC_FAN_2_TACH - @mlb_lib.MLB	49A8 57C8
SMC_FAN_3_CTL	SMC_FAN_3_CTL - @mlb_lib.MLB	49A8 50C5
	TP_SMC_FAN_3_CTL - @mlb_lib.MLB	50C3
SMC_FAN_3_TACH	SMC_FAN_3_TACH - @mlb_lib.MLB	49A8 50C5
	TP_SMC_FAN_3_TACH - @mlb_lib.MLB	50C3
SMC_FWE	SMC_FWE - @mlb_lib.MLB	49A5 50B2
SMC_GFX_OVERTEMP_L	SMC_GFX_OVERTEMP_L - @mlb_lib.MLB	49A8 85C8
SMC_GFX_THROTTLE_L	SMC_GFX_THROTTLE_L - @mlb_lib.MLB	49C8 85B7
SMC_GPU_ISENSE	SMC_GPU_ISENSE - @mlb_lib.MLB	49C5 53C3
SMC_GPU_VSENSE	SMC_GPU_VSENSE - @mlb_lib.MLB	49C5 53D3
SMC_KBC_MDE	SMC_KBC_MDE - @mlb_lib.MLB	49C2
SMC_LID	SMC_LID - @mlb_lib.MLB	49B5 50B2
SMC_LRESET_L	SMC_LRESET_L - @mlb_lib.MLB	7C6 28D1 49C8
SMC_MANUAL_RST_L	SMC_MANUAL_RST_L - @mlb_lib.MLB	50D7
SMC_MD1	SMC_MD1 - @mlb_lib.MLB	7D4 49C1 51B6
SMC_NMI	SMC_NMI - @mlb_lib.MLB	7C4 49C1 51B4
SMC_ODD_DETECT	SMC_ODD_DETECT - @mlb_lib.MLB	44B3 49B8
SMC_ONOFF_L	SMC_ONOFF_L - @mlb_lib.MLB	49C5 50B2 50C5
SMC_P14	SMC_P14 - @mlb_lib.MLB	49D8 50D5
	TP_SMC_P14 - @mlb_lib.MLB	50D3
SMC_P20	SMC_P20 - @mlb_lib.MLB	49C8 50D5
	TP_SMC_P20 - @mlb_lib.MLB	50D3
SMC_P21	SMC_P21 - @mlb_lib.MLB	49C8 50C5
	TP_SMC_P21 - @mlb_lib.MLB	50C3
SMC_P22	SMC_P22 - @mlb_lib.MLB	49C8 50C5
	TP_SMC_P22 - @mlb_lib.MLB	50C3
SMC_P23	SMC_P23 - @mlb_lib.MLB	49C8 50C5
	TP_SMC_P23 - @mlb_lib.MLB	50C3
SMC_P26	SMC_P26 - @mlb_lib.MLB	49C8 50C5
	TP_SMC_P26 - @mlb_lib.MLB	50C3
SMC_P27	SMC_P27 - @mlb_lib.MLB	49C8 50C5
	TP_SMC_P27 - @mlb_lib.MLB	50C3
SMC_P43	SMC_P43 - @mlb_lib.MLB	49C8 50C5
	TP_SMC_P43 - @mlb_lib.MLB	50C3
SMC_P44	SMC_P44 - @mlb_lib.MLB	49C8 50C5
	TP_SMC_P44 - @mlb_lib.MLB	50C3
SMC_P45	SMC_P45 - @mlb_lib.MLB	49C8 50C5
	TP_SMC_P45 - @mlb_lib.MLB	50C3
SMC_P46	SMC_P46 - @mlb_lib.MLB	49B8 50B5
	TP_SMC_P46 - @mlb_lib.MLB	50B3
SMC_P62	SMC_P62 - @mlb_lib.MLB	49D5 50C5
	TP_SMC_P62 - @mlb_lib.MLB	50C3
SMC_P63	SMC_P63 - @mlb_lib.MLB	49D5 50C5
	TP_SMC_P63 - @mlb_lib.MLB	50C3
SMC_P64	SMC_P64 - @mlb_lib.MLB	49D5 50C5
	TP_SMC_P64 - @mlb_lib.MLB	50C3
SMC_P67	SMC_P67 - @mlb_lib.MLB	49C5 50B2
SMC_P81	SMC_P81 - @mlb_lib.MLB	49C5 50C5
	TP_SMC_P81 - @mlb_lib.MLB	50C3
SMC_PA0	SMC_PA0 - @mlb_lib.MLB	49B8 50B2
SMC_PA1	SMC_PA1 - @mlb_lib.MLB	49B8 50B2
SMC_PB0	SMC_PB0 - @mlb_lib.MLB	49B8 50B2
SMC_PF0	SMC_PF0 - @mlb_lib.MLB	49B5 50C5
	TP_SMC_PF0 - @mlb_lib.MLB	50C3
SMC_PF1	SMC_PF1 - @mlb_lib.MLB	49B5 50C5
	TP_SMC_PF1 - @mlb_lib.MLB	50C3
SMC_PF3	SMC_PF3 - @mlb_lib.MLB	49B5 50B2
SMC_PG0	SMC_PG0 - @mlb_lib.MLB	49B5 50B2
SMC_PH4	SMC_PH4 - @mlb_lib.MLB	49A5 50B2
SMC_PM_G2_EN	SMC_PM_G2_EN - @mlb_lib.MLB	49D5 50C5
	TP_SMC_PM_G2_EN - @mlb_lib.MLB	50C3
SMC_PROCHOT	SMC_PROCHOT - @mlb_lib.MLB	49A5 50C1
SMC_PROCHOT_3_3_L	SMC_PROCHOT_3_3_L - @mlb_lib.MLB	49C5 50D1
SMC_RESET_L	SMC_RESET_L - @mlb_lib.MLB	7C4 7C6 49C3 50D6 51B4

SMC_RSTGATE_L	SMC_RSTGATE_L - @mlb_lib.MLB	49D8 50B5
	TP_SMC_RSTGATE_L - @mlb_lib.MLB	50B3
SMC_RUNTIME_SCI_L	SMC_RUNTIME_SCI_L - @mlb_lib.MLB	25C8 49B8
SMC_RX_L	SMC_RX_L - @mlb_lib.MLB	7C4 46D5 49B8 49C5 50B2
		51B4
SMC_SUS_CLK	SMC_SUS_CLK - @mlb_lib.MLB	49C5 50C3
	SUS_CLK_SB - @mlb_lib.MLB	25D3 50C2
SMC_SYS_KBDLED	SMC_SYS_KBDLED - @mlb_lib.MLB	49B8 50B5
	TP_SMC_SYS_KBDLED - @mlb_lib.MLB	50B3
SMC_SYS_LED	SMC_SYS_LED - @mlb_lib.MLB	49C8 50B5
	TP_SMC_SYS_LED - @mlb_lib.MLB	50B3
SMC_TCK	SMC_TCK - @mlb_lib.MLB	7D4 49B5 50B2 51B4
SMC_TDI	SMC_TDI - @mlb_lib.MLB	7D4 49B5 50B2 51B4
SMC_TDO	SMC_TDO - @mlb_lib.MLB	7D4 49B5 50B2 51B6
SMC_THRMTRIP	SMC_THRMTRIP - @mlb_lib.MLB	49A5 50C1
SMC_TMS	SMC_TMS - @mlb_lib.MLB	7D4 49B5 50B2 51B6
SMC_TRST_L	SMC_TRST_L - @mlb_lib.MLB	7D4 49C1 51B6
SMC_TX_L	SMC_TX_L - @mlb_lib.MLB	7D4 46D5 49B8 49C5 50B2
		51B6
SMC_VCL	SMC_VCL - @mlb_lib.MLB	49D2
SMC_WAKE_SCI_L	SMC_WAKE_SCI_L - @mlb_lib.MLB	13C3 25C8 49C5
SMC_XTAL	SMC_XTAL - @mlb_lib.MLB	49C3 50C8
SMS_ONOFF_L	SMS_ONOFF_L - @mlb_lib.MLB	49A5 50B5
	TP_SMS_ONOFF_L - @mlb_lib.MLB	50B3
SMS_X_AXIS	SMS_X_AXIS - @mlb_lib.MLB	49A8 50D5 108D1
	NC_SMS_X_AXIS - @mlb_lib.MLB	50D3
SMS_Y_AXIS	SMS_Y_AXIS - @mlb_lib.MLB	49A8 50D5 108D1
	NC_SMS_Y_AXIS - @mlb_lib.MLB	50D3
SMS_Z_AXIS	SMS_Z_AXIS - @mlb_lib.MLB	49A8 50D5 108D1
	NC_SMS_Z_AXIS - @mlb_lib.MLB	50D3
SPI_A_SCLK_R	SPI_A_SCLK_R - @mlb_lib.MLB	103A3
SPI_A_SI_R	SPI_A_SI_R - @mlb_lib.MLB	61B4 103A3
SPI_A_SO_R	SPI_A_SO_R - @mlb_lib.MLB	7B3 61B4 103A3
SPI_B_SCLK_R	SPI_B_SCLK_R - @mlb_lib.MLB	103A3
SPI_B_SI_R	SPI_B_SI_R - @mlb_lib.MLB	103A3
SPI_B_SO	SPI_B_SO - @mlb_lib.MLB	103A3
SPI_B_SO_R	SPI_B_SO_R - @mlb_lib.MLB	103A3
SPI_CE_L<0>	SPI_CE_L<0> - @mlb_lib.MLB	7B3 61B6 103A3
SPI_CE_L<1>	SPI_CE_L<1> - @mlb_lib.MLB	103A3
SPI_CE_R_L<0>	SPI_CE_R_L<0> - @mlb_lib.MLB	24C5 61B7 103A3
SPI_CE_R_L<1>	SPI_CE_R_L<1> - @mlb_lib.MLB	103A3
SPI_HOLD_L	SPI_HOLD_L - @mlb_lib.MLB	61B5
SPI_SCLK	SPI_SCLK - @mlb_lib.MLB	7A8 61B6 103A3
SPI_SCLK_R	SPI_SCLK_R - @mlb_lib.MLB	24C5 61B7 103A3
SPI_SI	SPI_SI - @mlb_lib.MLB	103A3
SPI_SI_R	SPI_SI_R - @mlb_lib.MLB	24C5 61B3 103A3
SPI_SO	SPI_SO - @mlb_lib.MLB	7A8 24C5 61B3 103A3
SPI_WP_L	SPI_WP_L - @mlb_lib.MLB	61B5
SYS_ONEWIRE	SYS_ONEWIRE - @mlb_lib.MLB	49B8 50B2
TMDS_CLK_N	TMDS_CLK_N - @mlb_lib.MLB	85A7 94D8 108D3
TMDS_CLK_P	TMDS_CLK_P - @mlb_lib.MLB	85A7 94B8 108D3
TMDS_CONN_CLKN	TMDS_CONN_CLKN - @mlb_lib.MLB	94C4 94C7 108D3
TMDS_CONN_CLKP	TMDS_CONN_CLKP - @mlb_lib.MLB	94B7 94C4 108D3
TMDS_CONN_DN<0>	TMDS_CONN_DN<0> - @mlb_lib.MLB	94C4 94D6
TMDS_CONN_DN<3..0>	TMDS_CONN_DN<3..0> - @mlb_lib.MLB	108D3
TMDS_CONN_DN<1>	TMDS_CONN_DN<1> - @mlb_lib.MLB	94C4 94D6
TMDS_CONN_DN<2>	TMDS_CONN_DN<2> - @mlb_lib.MLB	94C6 94D4
TMDS_CONN_DP<0>	TMDS_CONN_DP<0> - @mlb_lib.MLB	94C4 94D6
TMDS_CONN_DP<3..0>	TMDS_CONN_DP<3..0> - @mlb_lib.MLB	108D3
TMDS_CONN_DP<1>	TMDS_CONN_DP<1> - @mlb_lib.MLB	94C4 94D6
TMDS_CONN_DP<2>	TMDS_CONN_DP<2> - @mlb_lib.MLB	94C6 94D4
TMDS_DATA_N<0>	TMDS_DATA_N<0> - @mlb_lib.MLB	85A7 94D8
TMDS_DATA_N<3..0>	TMDS_DATA_N<3..0> - @mlb_lib.MLB	108D3
TMDS_DATA_N<1>	TMDS_DATA_N<1> - @mlb_lib.MLB	85A7 94D8
TMDS_DATA_N<2>	TMDS_DATA_N<2> - @mlb_lib.MLB	85A7 94C8
TMDS_DATA_P<0>	TMDS_DATA_P<0> - @mlb_lib.MLB	85A7 94D8
TMDS_DATA_P<3..0>	TMDS_DATA_P<3..0> - @mlb_lib.MLB	108D3
TMDS_DATA_P<1>	TMDS_DATA_P<1> - @mlb_lib.MLB	85A7 94C8
TMDS_DATA_P<2>	TMDS_DATA_P<2> - @mlb_lib.MLB	85A7 94C8
TP_CK505_PGMODE	TP_CK505_PGMODE - @mlb_lib.MLB	29B5
TP_CPU_RSVD0	TP_CPU_RSVD0 - @mlb_lib.MLB	10B8
TP_CPU_RSVD1	TP_CPU_RSVD1 - @mlb_lib.MLB	10B8
TP_CPU_RSVD2	TP_CPU_RSVD2 - @mlb_lib.MLB	10B8
TP_CPU_RSVD3	TP_CPU_RSVD3 - @mlb_lib.MLB	10B8
TP_CPU_RSVD4	TP_CPU_RSVD4 - @mlb_lib.MLB	10B8
TP_CPU_RSVD5	TP_CPU_RSVD5 - @mlb_lib.MLB	10B8
TP_CPU_RSVD6	TP_CPU_RSVD6 - @mlb_lib.MLB	10B8
TP_CPU_RSVD7	TP_CPU_RSVD7 - @mlb_lib.MLB	10B8
TP_CPU_RSVD8	TP_CPU_RSVD8 - @mlb_lib.MLB	10B8
TP_CPU_RSVD9	TP_CPU_RSVD9 - @mlb_lib.MLB	10B8
TP_CPU_TEST3	TP_CPU_TEST3 - @mlb_lib.MLB	10B4
TP_CPU_TEST5	TP_CPU_TEST5 - @mlb_lib.MLB	10B4
TP_CPU_TEST6	TP_CPU_TEST6 - @mlb_lib.MLB	10B4
TP_ENET_GLAN_CLK	TP_ENET_GLAN_CLK - @mlb_lib.MLB	23C6
TP_FW_AVREG	TP_FW_AVREG - @mlb_lib.MLB	40B6
TP_FW_CE	TP_FW_CE - @mlb_lib.MLB	7B3 40B6
TP_FW_FW620_L	TP_FW_FW620_L - @mlb_lib.MLB	40B6
TP_FW_JASI_EN	TP_FW_JASI_EN - @mlb_lib.MLB	40B6
TP_FW_MODE_A	TP_FW_MODE_A - @mlb_lib.MLB	40B6
TP_FW_NAND_TREE	TP_FW_NAND_TREE - @mlb_lib.MLB	7C3 40B6
TP_FW_SCIFCLK	TP_FW_SCIFCLK - @mlb_lib.MLB	40B3
TP_FW_SCIFDAIN	TP_FW_SCIFDAIN - @mlb_lib.MLB	40B3
TP_FW_SCIFDOUT	TP_FW_SCIFDOUT - @mlb_lib.MLB	40B3
TP_FW_SCIFMC	TP_FW_SCIFMC - @mlb_lib.MLB	40B3
TP_FW_SDA	TP_FW_SDA - @mlb_lib.MLB	40B3
TP_FW_SE	TP_FW_SE - @mlb_lib.MLB	7C3 40B6
TP_FW_SM	TP_FW_SM - @mlb_lib.MLB	7C3 40B6
TP_FW_TCK	TP_FW_TCK - @mlb_lib.MLB	7C3 40C3
TP_FW_TDI	TP_FW_TDI - @mlb_lib.MLB	7C3 40C3
TP_FW_TDO	TP_FW_TDO - @mlb_lib.MLB	7C3 40C3
TP_FW_TMS	TP_FW_TMS - @mlb_lib.MLB	7C3 40C3
TP_FW_VAUX_DISABLE	TP_FW_VAUX_DISABLE - @mlb_lib.MLB	40C3
TP_FW_VBUF	TP_FW_VBUF - @mlb_lib.MLB	40B6
TP_GPU_DDC_B_CLK	TP_GPU_DDC_B_CLK - @mlb_lib.MLB	85A4
TP_GPU_DDC_B_DATA	TP_GPU_DDC_B_DATA - @mlb_lib.MLB	85A4
TP_HDA_DOCK_RST_L	TP_HDA_DOCK_RST_L - @mlb_lib.MLB	23B6
TP_HDA_SDIN1	TP_HDA_SDIN1 - @mlb_lib.MLB	23C8
TP_HDA_SDIN2	TP_HDA_SDIN2 - @mlb_lib.MLB	23C8
TP_HDA_SDIN3	TP_HDA_SDIN3 - @mlb_lib.MLB	23C8
TP_LAN_D2R<0>	TP_LAN_D2R<0> - @mlb_lib.MLB	23C6
TP_LAN_D2R<1>	TP_LAN_D2R<1> - @mlb_lib.MLB	23C6
TP_LAN_D2R<2>	TP_LAN_D2R<2> - @mlb_lib.MLB	23C6 28C4
TP_LAN_R2D<0>	TP_LAN_R2D<0> - @mlb_lib.MLB	23C6
TP_LAN_R2D<1>	TP_LAN_R2D<1> - @mlb_lib.MLB	23C6
TP_LAN_R2D<2>	TP_LAN_R2D<2> - @mlb_lib.MLB	23C6
TP_LAN_RSTSYNC	TP_LAN_RSTSYNC - @mlb_lib.MLB	23C6
TP_LPC_DRQ0_L	TP_LPC_DRQ0_L - @mlb_lib.MLB	23D4
TP_LVDS_A_DATAN3	TP_LVDS_A_DATAN3 - @mlb_lib.MLB	16C6
TP_LVDS_A_DATAP3	TP_LVDS_A_DATAP3 - @mlb_lib.MLB	16C6
TP_LVDS_B_DATAN3	TP_LVDS_B_DATAN3 - @mlb_lib.MLB	16C6
TP_LVDS_B_DATAP3	TP_LVDS_B_DATAP3 - @mlb_lib.MLB	16C6
TP_LVDS_VBG	TP_LVDS_VBG - @mlb_lib.MLB	15D5
TP_MEM_A_A<15>	TP_MEM_A_A<15> - @mlb_lib.MLB	31C3
TP_MEM_A_RCVEN_L	TP_MEM_A_RCVEN_L - @mlb_lib.MLB	17B5

TP_MEM_B_A<15>	TP_MEM_B_A<15> - @mlb_lib.MLB	32C3
TP_MEM_B_RCVEN_L	TP_MEM_B_RCVEN_L - @mlb_lib.MLB	17B2
TP_MEM_CLKN2	TP_MEM_CLKN2 - @mlb_lib.MLB	16C6
TP_MEM_CLKN5	TP_MEM_CLKN5 - @mlb_lib.MLB	16C6
TP_MEM_CLKP2	TP_MEM_CLKP2 - @mlb_lib.MLB	16C6
TP_MEM_CLKP5	TP_MEM_CLKP5 - @mlb_lib.MLB	16C6
TP_NB_CFG<10>	TP_NB_CFG<10> - @mlb_lib.MLB	16B6
TP_NB_CFG<11>	TP_NB_CFG<11> - @mlb_lib.MLB	16B6
TP_NB_CFG<12>	TP_NB_CFG<12> - @mlb_lib.MLB	7C3 16B6
TP_NB_CFG<13>	TP_NB_CFG<13> - @mlb_lib.MLB	7C3 16B6
TP_NB_CFG<14>	TP_NB_CFG<14> - @mlb_lib.MLB	16B6
TP_NB_CFG<15>	TP_NB_CFG<15> - @mlb_lib.MLB	16B6
TP_NB_CFG<17>	TP_NB_CFG<17> - @mlb_lib.MLB	16B6
TP_NB_CFG<18>	TP_NB_CFG<18> - @mlb_lib.MLB	7C3 16B6
TP_NB_NC<1>	TP_NB_NC<1> - @mlb_lib.MLB	16A6
TP_NB_NC<2>	TP_NB_NC<2> - @mlb_lib.MLB	16A6
TP_NB_NC<3>	TP_NB_NC<3> - @mlb_lib.MLB	16A6
TP_NB_NC<4>	TP_NB_NC<4> - @mlb_lib.MLB	16A6
TP_NB_NC<5>	TP_NB_NC<5> - @mlb_lib.MLB	16A6
TP_NB_NC<6>	TP_NB_NC<6> - @mlb_lib.MLB	16A6
TP_NB_NC<7>	TP_NB_NC<7> - @mlb_lib.MLB	16A6
TP_NB_NC<8>	TP_NB_NC<8> - @mlb_lib.MLB	16A6
TP_NB_NC<9>	TP_NB_NC<9> - @mlb_lib.MLB	16A6
TP_NB_NC<10>	TP_NB_NC<10> - @mlb_lib.MLB	16A6
TP_NB_NC<11>	TP_NB_NC<11> - @mlb_lib.MLB	16A6
TP_NB_NC<12>	TP_NB_NC<12> - @mlb_lib.MLB	16A6
TP_NB_NC<13>	TP_NB_NC<13> - @mlb_lib.MLB	16A6
TP_NB_NC<14>	TP_NB_NC<14> - @mlb_lib.MLB	16A6
TP_NB_NC<15>	TP_NB_NC<15> - @mlb_lib.MLB	16A6
TP_NB_NC<16>	TP_NB_NC<16> - @mlb_lib.MLB	16A6
TP_NB_RSVD<1>	TP_NB_RSVD<1> - @mlb_lib.MLB	16D6
TP_NB_RSVD<2>	TP_NB_RSVD<2> - @mlb_lib.MLB	16D6
TP_NB_RSVD<3>	TP_NB_RSVD<3> - @mlb_lib.MLB	16D6
TP_NB_RSVD<4>	TP_NB_RSVD<4> - @mlb_lib.MLB	16D6
TP_NB_RSVD<5>	TP_NB_RSVD<5> - @mlb_lib.MLB	16D6
TP_NB_RSVD<6>	TP_NB_RSVD<6> - @mlb_lib.MLB	16D6
TP_NB_RSVD<7>	TP_NB_RSVD<7> - @mlb_lib.MLB	16D6
TP_NB_RSVD<8>	TP_NB_RSVD<8> - @mlb_lib.MLB	16D6
TP_NB_RSVD<9>	TP_NB_RSVD<9> - @mlb_lib.MLB	16D6
TP_NB_RSVD<10>	TP_NB_RSVD<10> - @mlb_lib.MLB	16D6
TP_NB_RSVD<11>	TP_NB_RSVD<11> - @mlb_lib.MLB	16D6
TP_NB_RSVD<12>	TP_NB_RSVD<12> - @mlb_lib.MLB	16D6
TP_NB_RSVD<13>	TP_NB_RSVD<13> - @mlb_lib.MLB	16D6
TP_NB_RSVD<14>	TP_NB_RSVD<14> - @mlb_lib.MLB	16D6
TP_NB_RSVD<20>	TP_NB_RSVD<20> - @mlb_lib.MLB	16D6
TP_NB_RSVD<21>	TP_NB_RSVD<21> - @mlb_lib.MLB	16D6
TP_NB_RSVD<22>	TP_NB_RSVD<22> - @mlb_lib.MLB	16C6
TP_NB_RSVD<23>	TP_NB_RSVD<23> - @mlb_lib.MLB	16C6
TP_NB_RSVD<24>	TP_NB_RSVD<24> - @mlb_lib.MLB	16C6
TP_NB_RSVD<25>	TP_NB_RSVD<25> - @mlb_lib.MLB	16C6
TP_NB_RSVD<26>	TP_NB_RSVD<26> - @mlb_lib.MLB	16C6
TP_NB_RSVD<27>	TP_NB_RSVD<27> - @mlb_lib.MLB	16C6
TP_NB_RSVD<34>	TP_NB_RSVD<34> - @mlb_lib.MLB	16C6
TP_NB_RSVD<35>	TP_NB_RSVD<35> - @mlb_lib.MLB	16C6
TP_NB_RSVD<36>	TP_NB_RSVD<36> - @mlb_lib.MLB	16C6
TP_NB_RSVD<41>	TP_NB_RSVD<41> - @mlb_lib.MLB	16C6
TP_NB_RSVD<42>	TP_NB_RSVD<42> - @mlb_lib.MLB	16C6
TP_NB_RSVD<43>	TP_NB_RSVD<43> - @mlb_lib.MLB	16C6
TP_NB_RSVD<44>	TP_NB_RSVD<44> - @mlb_lib.MLB	16C6
TP_NB_RSVD<45>	TP_NB_RSVD<45> - @mlb_lib.MLB	16C6
TP_PCIE_A_D2R_N	TP_PCIE_A_D2R_N - @mlb_lib.MLB	24D5
TP_PCIE_A_D2R_P	TP_PCIE_A_D2R_P - @mlb_lib.MLB	24D5
TP_PCIE_A_R2D_C_N	TP_PCIE_A_R2D_C_N - @mlb_lib.MLB	24D5
TP_PCIE_A_R2D_C_P	TP_PCIE_A_R2D_C_P - @mlb_lib.MLB	24D5
TP_PCIE_B_D2R_N	TP_PCIE_B_D2R_N - @mlb_lib.MLB	24D5
TP_PCIE_B_D2R_P	TP_PCIE_B_D2R_P - @mlb_lib.MLB	24D5
TP_PCIE_B_R2D_C_N	TP_PCIE_B_R2D_C_N - @mlb_lib.MLB	24D5
TP_PCIE_B_R2D_C_P	TP_PCIE_B_R2D_C_P - @mlb_lib.MLB	24D5
TP_PCIE_EXCARD_D2R_N	TP_PCIE_EXCARD_D2R_N - @mlb_lib.MLB	24D5
TP_PCIE_EXCARD_D2R_P	TP_PCIE_EXCARD_D2R_P - @mlb_lib.MLB	24D5
TP_PCIE_EXCARD_R2D_C_N	TP_PCIE_EXCARD_R2D_C_N - @mlb_lib.MLB	24D5
TP_PCIE_EXCARD_R2D_C_P	TP_PCIE_EXCARD_R2D_C_P - @mlb_lib.MLB	24D5
TP_PCI_PME_L	TP_PCI_PME_L - @mlb_lib.MLB	24A6
TP_PM_SLP_M_L	TP_PM_SLP_M_L - @mlb_lib.MLB	25C3
TP_PM_SLP_S4_L	TP_PM_SLP_S4_L - @mlb_lib.MLB	25D3
TP_PP5VREG_PLLIN	TP_PP5VREG_PLLIN - @mlb_lib.MLB	76B5
TP_SB_GPIO51	TP_SB_GPIO51 - @mlb_lib.MLB	24B6
TP_SB_GPIO53	TP_SB_GPIO53 - @mlb_lib.MLB	24B6
TP_SB_GPIO55	TP_SB_GPIO55 - @mlb_lib.MLB	24B6
TP_SB_TP3	TP_SB_TP3 - @mlb_lib.MLB	25B5
TP_SB_TP7	TP_SB_TP7 - @mlb_lib.MLB	25C5
TP_SB_TP8	TP_SB_TP8 - @mlb_lib.MLB	23C4
TP_SPI_CE_R_L<1>	TP_SPI_CE_R_L<1> - @mlb_lib.MLB	24C5
TP_VCCCL1_05_INTERNA L_REG	TP_VCCCL1_05_INTERNAL_REG - @mlb_lib.MLB	26A3
TP_VCCLAN1_05_INTERN AL_REG1	TP_VCCLAN1_05_INTERNAL_REG1 - @mlb_lib.MLB	26A6
TP_VCCLAN1_05_INTERN AL_REG2	TP_VCCLAN1_05_INTERNAL_REG2 - @mlb_lib.MLB	26A6
TP_VCCSUS1_05_INTERN AL_REG1	TP_VCCSUS1_05_INTERNAL_REG1 - @mlb_lib.MLB	26B3
TP_VCCSUS1_05_INTERN AL_REG2	TP_VCCSUS1_05_INTERNAL_REG2 - @mlb_lib.MLB	26B3
TP_VCCSUS1_5_INTERNA L_REG1	TP_VCCSUS1_5_INTERNAL_REG1 - @mlb_lib.MLB	26B3
TP_VCCSUS1_5_INTERNA L_REG2	TP_VCCSUS1_5_INTERNAL_REG2 - @mlb_lib.MLB	26B3
TP_XDP_HOOK2	TP_XDP_HOOK2 - @mlb_lib.MLB	13B6
TP_XDP_HOOK3	TP_XDP_HOOK3 - @mlb_lib.MLB	13B6
U5500_TCRIT1	U5500_TCRIT1 - @mlb_lib.MLB	55B3
U5500_TCRIT2	U5500_TCRIT2 - @mlb_lib.MLB	55B3
U5500_TCRIT3	U5500_TCRIT3 - @mlb_lib.MLB	55A3
U7550_VDDQ	U7550_VDDQ - @m

Title: Cref Part Report
Design: mlb
Date: Jan 8 14:44:54 2008

C600	CAP_402	mlb[6D7]
C623	CAP_805	mlb[6D7]
C624	CAP_1210	mlb[6D8]
C625	CAP_P_6.3X5.5-SM	mlb[6D8]
C626	CAP_402	mlb[6D8]
C627	CAP_402	mlb[6D8]
C628	CAP_402	mlb[6D6]
C629	CAP_402	mlb[6D7]
C630	CAP_402	mlb[6D6]
C631	CAP_402	mlb[6D6]
C701	CAP_402	mlb[7C6]
C702	CAP_402	mlb[7C5]
C703	CAP_402	mlb[7C6]
C704	CAP_402	mlb[7C5]
C1000	CAP_402	mlb[10B5]
C1200	CAP_805	mlb[12D7]
C1201	CAP_805	mlb[12D6]
C1202	CAP_805	mlb[12D6]
C1203	CAP_805	mlb[12D6]
C1204	CAP_805	mlb[12D6]
C1205	CAP_805	mlb[12D5]
C1206	CAP_805	mlb[12D5]
C1207	CAP_805	mlb[12D5]
C1208	CAP_805	mlb[12D4]
C1209	CAP_805	mlb[12D4]
C1210	CAP_805	mlb[12C7]
C1211	CAP_805	mlb[12C6]
C1212	CAP_805	mlb[12C6]
C1213	CAP_805	mlb[12C6]
C1214	CAP_805	mlb[12C6]
C1215	CAP_805	mlb[12C5]
C1216	CAP_805	mlb[12C5]
C1217	CAP_805	mlb[12C5]
C1218	CAP_805	mlb[12C4]
C1219	CAP_805	mlb[12C4]
C1220	CAP_805	mlb[12C7]
C1221	CAP_805	mlb[12C6]
C1222	CAP_805	mlb[12C6]
C1223	CAP_805	mlb[12C6]
C1224	CAP_805	mlb[12C6]
C1225	CAP_805	mlb[12C5]
C1226	CAP_805	mlb[12B7]
C1227	CAP_805	mlb[12B6]
C1228	CAP_805	mlb[12B6]
C1229	CAP_805	mlb[12B6]
C1230	CAP_805	mlb[12B6]
C1231	CAP_805	mlb[12B5]
C1235	CAP_P_6.3X8-SM	mlb[12A3]
C1236	CAP_402	mlb[12A2]
C1237	CAP_402	mlb[12A2]
C1238	CAP_402	mlb[12A2]
C1239	CAP_402	mlb[12A2]
C1240	CAP_402	mlb[12A1]
C1241	CAP_402	mlb[12A1]
C1250	CAP_P_CASE-D2-SM1	mlb[12B7]
C1251	CAP_P_CASE-D2-SM1	mlb[12B6]
C1252	CAP_P_CASE-D2-SM1	mlb[12B5]
C1253	CAP_P_CASE-D2-SM1	mlb[12B5]
C1254	CAP_P_CASE-D2-SM1	mlb[12B6]
C1255	CAP_P_CASE-D2-SM1	mlb[12B5]
C1280	CAP_603	mlb[12B3]
C1281	CAP_402	mlb[12B2]
C1300	CAP_402	mlb[13B5]
C1301	CAP_402	mlb[13B4]
C1410	CAP_402	mlb[14A6]
C1425	CAP_402	mlb[14A7]
C1615	CAP_402	mlb[16C3]
C1616	CAP_402	mlb[16C3]
C1622	CAP_603	mlb[16C1]
C1623	CAP_402	mlb[16C1]
C1624	CAP_603	mlb[16C1]
C1625	CAP_402	mlb[16C1]
C1640	CAP_402	mlb[16A3]
C1801	CAP_402	mlb[18A4]
C1802	CAP_402	mlb[18A4]
C1803	CAP_402	mlb[18A4]
C1804	CAP_402	mlb[18A4]
C1805	CAP_402	mlb[18A5]
C1806	CAP_402	mlb[18A5]
C1807	CAP_402	mlb[18A5]
C1911	CAP_402	mlb[19A3]
C1912	CAP_402	mlb[19A3]
C1913	CAP_402	mlb[19A3]
C2100	CAP_P_6.3X8-SM	mlb[21D7]
C2101	CAP_805	mlb[21D7]
C2102	CAP_402	mlb[21D7]
C2103	CAP_402	mlb[21D6]
C2104	CAP_402	mlb[21D6]
C2110	CAP_805	mlb[21C7]
C2111	CAP_402	mlb[21C7]
C2112	CAP_402	mlb[21C7]
C2113	CAP_402	mlb[21C6]
C2114	CAP_402	mlb[21C6]
C2115	CAP_402	mlb[21C6]
C2120	CAP_P_6.3X8-SM	mlb[21C7]
C2121	CAP_603	mlb[21C7]
C2122	CAP_603	mlb[21C7]
C2123	CAP_603	mlb[21C6]
C2124	CAP_402	mlb[21C6]
C2130	CAP_P_6.3X8-SM	mlb[21C7]
C2131	CAP_805	mlb[21C7]
C2132	CAP_805	mlb[21C7]
C2135	CAP_402	mlb[21C7]
C2140	CAP_P_6.3X8-SM	mlb[21B7]
C2141	CAP_805	mlb[21B7]
C2142	CAP_805	mlb[21B6]
C2143	CAP_603	mlb[21B6]
C2144	CAP_402-1	mlb[21B6]
C2145	CAP_805	mlb[21B6]
C2146	CAP_603	mlb[21B6]
C2148	CAP_402	mlb[21B6]
C2150	CAP_805	mlb[21A7]
C2151	CAP_402-1	mlb[21A6]
C2160	CAP_402	mlb[21A7]
C2161	CAP_402	mlb[21A7]
C2165	CAP_402	mlb[21A7]
C2170	CAP_603	mlb[21D4]
C2171	CAP_402-1	mlb[21D4]
C2173	CAP_P_SM-CASE-C1	mlb[21C4]
C2174	CAP_603	mlb[21C4]
C2177	CAP_603	mlb[21C4]
C2180	CAP_402	mlb[21D2]
C2181	CAP_805	mlb[21D2]
C2182	CAP_402	mlb[21D2]
C2183	CAP_805	mlb[21C3]
C2184	CAP_402	mlb[21C2]
C2190	CAP_603	mlb[21B4]
C2191	CAP_402	mlb[21B3]
C2192	CAP_402	mlb[21B3]
C2195	CAP_603	mlb[21A4]
C2196	CAP_805	mlb[21A3]
C2197	CAP_402	mlb[21A3]
C2200	CAP_402	mlb[22B2]
C2201	FILTER_3P_A_NFM18	mlb[22B2]
C2213	CAP_603	mlb[22B2]
C2500	CAP_402	mlb[25C2]
C2501	CAP_402	mlb[25B2]
C2600	CAP_402	mlb[26A3]
C2601	CAP_402	mlb[26A3]
C2700	CAP_P_SM-CASE-C1	mlb[27C7]
C2701	CAP_402	mlb[27A6]
C2702	CAP_402	mlb[27B1]
C2703	CAP_402-1	mlb[27C8]
C2704	CAP_402	mlb[27D8]
C2705	CAP_805	mlb[27C7]
C2706	CAP_805	mlb[27C7]
C2707	CAP_603	mlb[27C7]
C2708	CAP_603	mlb[27A6]
C2711	CAP_402	mlb[27D1]
C2712	CAP_402	mlb[27C1]
C2714	CAP_402	mlb[27D1]
C2715	CAP_402	mlb[27C1]
C2717	CAP_402	mlb[27A6]
C2718	CAP_402	mlb[27B1]
C2719	CAP_402	mlb[27D3]
C2721	CAP_402	mlb[27B3]
C2722	CAP_402	mlb[27B1]
C2723	CAP_402	mlb[27B1]
C2724	CAP_603	mlb[27B1]
C2725	CAP_402	mlb[27D3]
C2726	CAP_402	mlb[27C3]
C2727	CAP_402	mlb[27C3]
C2728	CAP_402	mlb[27C3]
C2729	CAP_402	mlb[27D5]
C2730	CAP_402	mlb[27D5]
C2731	CAP_402	mlb[27D5]
C2732	CAP_603	mlb[27B7]
C2733	CAP_603	mlb[27C5]
C2734	CAP_402	mlb[27D5]
C2735	CAP_603	mlb[27A6]
C2736	CAP_603	mlb[27B7]
C2737	CAP_402	mlb[27C3]
C2738	CAP_402	mlb[27C3]
C2739	CAP_805	mlb[27C1]
C2741	CAP_402	mlb[27B3]
C2805	CAP_402	mlb[28D5]
C2808	CAP_402	mlb[28C6]
C2809	CAP_402	mlb[28C6]
C2810	CAP_402	mlb[28D6]
C2811	CAP_402	mlb[28A7]
C2900	CAP_402	mlb[29D7]
C2901	CAP_603	mlb[29D6]
C2902	CAP_402	mlb[29D6]
C2903	CAP_402	mlb[29D6]
C2904	CAP_402	mlb[29D5]
C2905	CAP_402	mlb[29D5]
C2906	CAP_402	mlb[29D5]
C2907	CAP_603	mlb[29C5]
C2908	CAP_402	mlb[29C5]
C2909	CAP_402	mlb[29D4]
C2910	CAP_603	mlb[29D3]
C2911	CAP_402	mlb[29D2]
C2912	CAP_402	mlb[29D4]
C2913	CAP_402	mlb[29D3]
C2914	CAP_603	mlb[29D3]
C2915	CAP_402	mlb[29C4]
C2916	CAP_603	mlb[29C3]
C2989	CAP_402	mlb[29C6]
C2990	CAP_402	mlb[29C6]
C3100	CAP_603	mlb[31B2]
C3101	CAP_603	mlb[31B2]
C3110	CAP_402	mlb[31B2]
C3111	CAP_402	mlb[31B2]
C3112	CAP_402	mlb[31B1]
C3113	CAP_402	mlb[31B1]
C3114	CAP_402	mlb[31B2]
C3115	CAP_402	mlb[31B2]
C3116	CAP_402	mlb[31B1]
C3117	CAP_402	mlb[31B1]
C3118	CAP_402	mlb[31B2]
C3119	CAP_402	mlb[31B2]
C3120	CAP_402	mlb[31B1]
C3121	CAP_402	mlb[31B1]
C3122	CAP_402	mlb[31A1]
C3123	CAP_402	mlb[31A1]
C3130	CAP_603	mlb[31D6]
C3131	CAP_402	mlb[31D6]
C3140	CAP_603	mlb[31A7]
C3141	CAP_402	mlb[31A6]
C3200	CAP_603	mlb[32B2]
C3201	CAP_603	mlb[32B2]
C3210	CAP_402	mlb[32B2]
C3211	CAP_402	mlb[32B2]
C3212	CAP_402	mlb[32B1]
C3213	CAP_402	mlb[32B1]
C3214	CAP_402	mlb[32B2]
C3215	CAP_402	mlb[32B2]
C3216	CAP_402	mlb[32B1]
C3217	CAP_402	mlb[32B1]
C3218	CAP_402	mlb[32B2]
C3219	CAP_402	mlb[32B2]
C3220	CAP_402	mlb[32B1]
C3221	CAP_402	mlb[32B1]
C3222	CAP_402	mlb[32A1]
C3223	CAP_402	mlb[32A1]
C3230	CAP_603	mlb[32D6]
C3231	CAP_402	mlb[32D6]
C3240	CAP_603	mlb[32A6]
C3241	CAP_402	mlb[32A6]
C3300	CAP_402	mlb[33D4]
C3302	CAP_402	mlb[33D4]
C3305	CAP_402	mlb[33D4]
C3307	CAP_402	mlb[33D4]
C3310	CAP_402	mlb[33C4]
C3312	CAP_402	mlb[33C4]
C3330	CAP_402	mlb[33C4]
C3332	CAP_402	mlb[33C4]
C3334	CAP_402	mlb[33C4]
C3336	CAP_402	mlb[33C4]
C3338	CAP_402	mlb[33C4]
C3340	CAP_402	mlb[33C4]
C3342	CAP_402	mlb[33B4]
C3344	CAP_402	mlb[33B4]
C3346	CAP_402	mlb[33B4]
C3348	CAP_402	mlb[33B4]
C3350	CAP_402	mlb[33B4]
C3352	CAP_402	mlb[33B4]
C3354	CAP_402	mlb[33B4]
C3356	CAP_402	mlb[33B4]
C3358	CAP_402	mlb[33A4]
C3360	CAP_402	mlb[33A4]
C3362	CAP_402	mlb[33A4]
C3364	CAP_402	mlb[33A4]
C3366	CAP_402	mlb[33A4]
C3368	CAP_402	mlb[33A4]
C3370	CAP_402	mlb[33A4]
C3400	CAP_402	mlb[34C3]
C3401	CAP_603	mlb[34C3]
C3410	CAP_402	mlb[34C3]
C3420	CAP_402	mlb[34C3]
C3421	CAP_603	mlb[34C3]
C3430	CAP_402	mlb[34B7]
C3431	CAP_402	mlb[34B7]
C3700	CAP_603	mlb[37D6]
C3701	CAP_402	mlb[37D6]
C3702	CAP_402	mlb[37D5]
C3703	CAP_402	mlb[37D5]
C3704	CAP_402	mlb[37D5]
C3705	CAP_402	mlb[37D4]
C3706	CAP_402	mlb[37D4]
C3707	CAP_402	mlb[37D4]
C3708	CAP_402	mlb[37D3]
C3710	CAP_603	mlb[37D6]
C3711	CAP_402	mlb[37D6]
C3712	CAP_402	mlb[37D5]
C3713	CAP_402	mlb[37D5]
C3714	CAP_402	mlb[37D5]
C3715	CAP_402	mlb[37D4]
C3720	CAP_603	mlb[37C5]
C3721	CAP_402	mlb[37C5]
C3722	CAP_402	mlb[37C5]
C3723	CAP_402	mlb[37C4]
C3724	CAP_402	mlb[37C4]
C3730	CAP_402	mlb[37C7]
C3731	CAP_402	mlb[37C7]
C3735	CAP_402	mlb[37C5]
C3736	CAP_402	mlb[37C5]
C3740	CAP_402	mlb[37B7]
C3742	CAP_402	mlb[37B6]
C3744	CAP_402	mlb[37B6]
C3746	CAP_402	mlb[37B5]
C3750	CAP_402	mlb[37B5]
C3751	CAP_402	mlb[37B5]
C3780	CAP_402	mlb[37B2]
C3800	CAP_805	mlb[38C6]
C3801	CAP_402	mlb[38C6]
C3802	CAP_805	mlb[38C6]
C3803	CAP_603	mlb[38C5]
C3804	CAP_402	mlb[38C5]
C3805	CAP_603	mlb[38C4]
C3810	CAP_805	mlb[38B6]
C3811	CAP_402	mlb[38B6]
C3812	CAP_805	mlb[38B6]
C3813	CAP_603	mlb[38B5]
C3814	CAP_402	mlb[38B5]
C3815	CAP_603	mlb[38A4]
C3816	CAP_402	mlb[38A4]
C3900	CAP_402	mlb[39D7]
C3901	CAP_402	mlb[39D7]
C3902	CAP_402	mlb[39D6]
C3903	CAP_402	mlb[39D6]
C3910	CAP_1808	mlb[39A3]
C4000	CAP_402	mlb[40B7]
C4001	CAP_402	mlb[40B7]
C4010	CAP_402	mlb[40C2]
C4011	CAP_402	mlb[40C2]
C4020	CAP_402	mlb[40C3]
C4021	CAP_402	mlb[40C3]
C4090	CAP_402	mlb[40B6]
C4200	CAP_402-LF	mlb[42C7]
C4201	CAP_402-LF	mlb[42C7]
C4210	CAP_402	mlb[42C6]
C4211	CAP_402	mlb[42C5]
C4212	CAP_805-1	mlb[42C5]
C4213	CAP_805-1	mlb[42C5]
C4230	CAP_402	mlb[42A5]
C4231	CAP_402	mlb[42A5]
C4240	CAP_402	mlb[42A7]
C4241	CAP_402	mlb[42A7]
C4242	CAP_402	mlb[42A7]
C4250	CAP_402	mlb[42B7]
C4251	CAP_402	mlb[42B7]
C4252	CAP_402	mlb[42B7]
C4253	CAP_402	mlb[42B6]
C4254	CAP_402	mlb[42B6]
C4260	CAP_402	mlb[42B7]
C4261	CAP_402	mlb[42B7]
C4262	CAP_402	mlb[42B7]
C4263	CAP_402	mlb[42B6]
C4264	CAP_402	mlb[42B6]
C4265	CAP_402	mlb[42B6]
C4266	CAP_402	mlb[42B6]
C4280	CAP_402	mlb[42A6]
C4281	CAP_402	mlb[42A6]
C4290	CAP_402	mlb[42B5]
C4291	CAP_402	mlb[42B5]
C4300	CAP_603-1	mlb[43D3]
C4301	CAP_603-1	mlb[43B3]
C4310	CAP_402	mlb[43D4]
C4311	CAP_402	mlb[43D4]
C4312	CAP_402	mlb[43C4]
C4313	CAP_402	mlb[43C4]
C4320	CAP_402	mlb[43B5]
C4321	CAP_402	mlb[43B5]
C4322	CAP_402	mlb[43A5]
C4323	CAP_402	mlb[43A5]
C4332	CAP_402	mlb[43C2]
C4335	CAP_603-1	mlb[43C2]
C4350	CAP_402	mlb[43C7]
C4354	CAP_402	mlb[43B7]
C4360	CAP_402	mlb[43D7]
C4364	CAP_402	mlb[43B7]
C4404	CAP_402	mlb[44B6]
C4405	CAP_402	mlb[44B3]
C4406	CAP_805	mlb[44B3]
C4510	CAP_402	mlb[45D6]
C4511	CAP_402	mlb[45D6]
C4515	CAP_402	mlb[45C6]
C4516	CAP_402	mlb[45C6]
C4600	CAP_P_CASE-D2-LF	mlb[46C8]
C4601	CAP_402	mlb[46C8]
C4602	CAP_402	mlb[46C7]
C4603	CAP_402	mlb[46C7]
C4604	CAP_402	mlb[46D8]
C4605	CAP_402	mlb[46D7]
C4613	CAP_402	mlb[46D2]
C4623	CAP_402	mlb[46C5]
C4633	CAP_402	mlb[46A5]
C4650	CAP_402	mlb[46D5]
C4700	CAP_805-1	mlb[47D7]
C4701	CAP_402	mlb[47D6]
C4720	CAP_805-1	mlb[47D3]
C4721	CAP_402	mlb[47D3]
C4781	CAP_402	mlb[47A2]
C4902	CAP_805	mlb[49D4]
C4903	CAP_402	mlb[49D4]
C4904	CAP_402	mlb[49D3]
C4905	CAP_402	mlb[49D3]
C4906	CAP_402	mlb[49D3]
C4907	CAP_402	mlb[49D2]
C4920	CAP_402	mlb[49C3]
C5000	CAP_402	mlb[50D7]
C5001	CAP_402	mlb[50D7]
C5010	CAP_402	mlb[50C6]
C5020	CAP_402	mlb[50C7]
C5021	CAP_402	mlb[50C7]
C5065	CAP_402	mlb[50B8]
C5066	CAP_603	mlb[50B7]
C5067	CAP_402	mlb[50B7]
C5309	CAP_402	mlb[53D6]
C5359	CAP_402	mlb[53D3]
C5370	CAP_402	mlb[53C7]
C5380	CAP_402	mlb[53C5]
C5381	CAP_402	mlb[53C4]
C5382	CAP_402	mlb[53B3]
C5383	CAP_402	mlb[53B1]
C5384	CAP_402	mlb[53B1]
C5386	CAP_402	mlb[53A4]
C5388	CAP_402	mlb[53A3]
C5500	CAP_402	mlb[55C7]
C5501	CAP_402	mlb[55B4]
C5502	CAP_805-1	mlb[55B4]
C5503	CAP_402	mlb[55B4]
C5510	CAP_402	mlb[55A7]
C5511	CAP_402	mlb[55A6]
C5550	CAP_402	mlb[55B7]
C5551	CAP_402	mlb[55B6]
C5560	CAP_402	mlb[55C5]
C5570	CAP_402	mlb[55D3]
C5580	CAP_402	mlb[55C4]
C5601	CAP_805	mlb[56D5]
C5602	CAP_P_6.3X5.5SM1	mlb[56C4]
C5603	CAP_805	mlb[56B5]
C5605	CAP_P_6.3X5.5SM1	mlb[56B3]
C5701	CAP_805	mlb[57C5]
C5702	CAP_P_6.3X5.5SM1	mlb[57C3]
C6100	CAP_402	mlb[61C4]
C7000	CAP_402	mlb[70C6]
C7001	CAP_402	mlb[70C6]
C7002	CAP_402	mlb[70C6]
C7003	CAP_402	mlb[70C6]
C7010	CAP_603	mlb[70D6]
C7052	CAP_402	mlb[70D2]
C7056	CAP_402	mlb[70D1]
C7060	CAP_402	mlb[70A5]
C7061	CAP_402	mlb[70B5]
C7062	CAP_402	mlb[70B5]
C7090	CAP_402	mlb[70A3]
C7100	CAP_402	mlb[71C4]
C7101	CAP_1206-1	mlb[71D1]
C7102	CAP_402	mlb[71B4]
C7103	CAP_402	mlb[71C2]
C7104	CAP_402	mlb[71B2]
C7105	CAP_402	mlb[71C8]
C7106	CAP_402	mlb[71B8]
C7107	CAP_402	mlb[71B7]
C7108	CAP_1206-1	mlb[71D1]
C7109	CAP_P_TH	mlb[71D5]
C7110	CAP_402	mlb[71C7]
C7111	CAP_402	mlb[71B2]
C7112	CAP_402	mlb[71C2]
C7113	CAP_402	mlb[71B7]
C7114	CAP_402	mlb[71B8]
C7115	CAP_603	mlb[71D4]
C7116	CAP_402	mlb[71B4]
C7121	CAP_402	mlb[71A5]
C7126	CAP_603-1	mlb[71D6]
C7127	CAP_603	mlb[71C4]
C7128	CAP_402	mlb[71B4]
C7129	CAP_402	mlb[71B5]
C7130	CAP_402	mlb[71D6]
C7131	CAP_402	mlb[71B5]
C7132	CAP_402	mlb[71A5]
C7133	CAP_402	mlb[71A5]
C7134	CAP_402	mlb[71B5]
C7135	CAP_603	mlb[71D4]
C7136	CAP_603	mlb[71C4]
C7145	CAP_402	mlb[71D1]
C7146	CAP_402	mlb[71C1]
C7147	CAP_402	mlb[71D3]
C7148	CAP_402	mlb[71C3]
C7150	CAP_1206-1	mlb[71D4]
C7152	CAP_1206-1	mlb[71D4]
C7154	CAP_P_TH	mlb[71D2]
C7155	CAP_1206-1	mlb[71D1]
C7156	CAP_1206-1	mlb[71D4]
C7190	CAP_402	mlb[71C3]
C7192	CAP_402	mlb[71B3]
C7196	CAP_402	mlb[71D6]
C7200	CAP_402	mlb[72C4]
C7201	CAP_1206-1	mlb[72D2]

www.laptopschematics.com

C7203	CAP_402	mlb[72C2]
C7208	CAP_1206-1	mlb[72D2]
C7212	CAP_402	mlb[72C3]
C7215	CAP_603	mlb[72C5]
C7235	CAP_603	mlb[72D6]
C7245	CAP_402	mlb[72C2]
C7247	CAP_402	mlb[72D4]
C7254	CAP_P_TH	mlb[72D2]
C7255	CAP_1206-1	mlb[72D2]
C7290	CAP_402	mlb[72C4]
C7300	CAP_P_CASE-D2-SM	mlb[73C8]
C7301	CAP_805	mlb[73B8]
C7302	CAP_402	mlb[73B7]
C7303	CAP_805	mlb[73C7]
C7304	CAP_805	mlb[73C8]
C7305	CAP_805	mlb[73C7]
C7310	CAP_603	mlb[73C7]
C7324	CAP_402	mlb[73B7]
C7330	CAP_603-1	mlb[73D6]
C7331	CAP_603	mlb[73C6]
C7332	CAP_402	mlb[73B5]
C7335	CAP_402	mlb[73B6]
C7340	CAP_P_TH	mlb[73D7]
C7341	CAP_1206-1	mlb[73D7]
C7342	CAP_1206-1	mlb[73D6]
C7345	CAP_402	mlb[73B3]
C7360	CAP_603	mlb[73D2]
C7361	CAP_603	mlb[73C2]
C7364	CAP_402	mlb[73B2]
C7370	CAP_402	mlb[73B2]
C7372	CAP_402	mlb[73B4]
C7381	CAP_1206-1	mlb[73D2]
C7382	CAP_1206-1	mlb[73D2]
C7390	CAP_P_CASE-D2-SM	mlb[73C1]
C7391	CAP_P_CASE-D2-SM	mlb[73C2]
C7392	CAP_805	mlb[73C1]
C7393	CAP_805	mlb[73C1]
C7400	CAP_P_CASE-D2-SM	mlb[74C8]
C7401	CAP_805	mlb[74C8]
C7402	CAP_402	mlb[74B7]
C7403	CAP_P_CASE-D2-SM	mlb[74C7]
C7404	CAP_805	mlb[74C8]
C7410	CAP_603	mlb[74C7]
C7424	CAP_402	mlb[74B7]
C7430	CAP_603-1	mlb[74D6]
C7431	CAP_603	mlb[74C6]
C7432	CAP_402	mlb[74B5]
C7435	CAP_402	mlb[74B6]
C7440	CAP_P_TH	mlb[74D7]
C7441	CAP_1206-1	mlb[74D7]
C7442	CAP_1206-1	mlb[74D6]
C7445	CAP_402	mlb[74B3]
C7460	CAP_603-1	mlb[74D2]
C7461	CAP_603	mlb[74C2]
C7464	CAP_402	mlb[74B2]
C7470	CAP_402	mlb[74B2]
C7472	CAP_402	mlb[74B4]
C7480	CAP_P_TH	mlb[74D3]
C7481	CAP_1206-1	mlb[74D2]
C7482	CAP_1206-1	mlb[74D2]
C7490	CAP_P_TH1	mlb[74C2]
C7491	CAP_P_TH1	mlb[74C1]
C7492	CAP_805	mlb[74C1]
C7493	CAP_805	mlb[74C1]
C7500	CAP_603	mlb[75D5]
C7501	CAP_603	mlb[75D6]
C7502	CAP_603	mlb[75D6]
C7503	CAP_402	mlb[75C2]
C7506	CAP_402	mlb[75C8]
C7507	CAP_402	mlb[75C6]
C7508	CAP_603	mlb[75C7]
C7509	CAP_402	mlb[75D4]
C7510	CAP_402	mlb[75C5]
C7530	CAP_P_TH	mlb[75D5]
C7531	CAP_603	mlb[75D4]
C7532	CAP_P_TH	mlb[75D5]
C7533	CAP_1206-1	mlb[75D5]
C7534	CAP_1206-1	mlb[75D4]
C7540	CAP_805	mlb[75C3]
C7541	CAP_805	mlb[75C3]
C7542	CAP_P_CASE-D2-SM	mlb[75C2]
C7543	CAP_P_CASE-D2-SM	mlb[75C2]
C7544	CAP_P_CASE-D2-SM	mlb[75C2]
C7545	CAP_402	mlb[75C3]
C7547	CAP_402	mlb[75D7]
C7550	CAP_402	mlb[75B4]
C7551	CAP_805-1	mlb[75A6]
C7552	CAP_805-1	mlb[75A4]
C7553	CAP_402	mlb[75A6]
C7555	CAP_P_CASE-C3	mlb[75A4]
C7559	CAP_603	mlb[75B5]
C7560	CAP_402	mlb[75D8]
C7564	CAP_402	mlb[75C3]
C7585	CAP_402	mlb[75A3]
C7586	CAP_402	mlb[75A2]
C7587	CAP_402	mlb[75A2]
C7588	CAP_402	mlb[75A2]
C7589	CAP_402	mlb[75A1]
C7590	CAP_402	mlb[75B3]
C7591	CAP_402	mlb[75B2]
C7592	CAP_402	mlb[75B2]
C7593	CAP_402	mlb[75B2]
C7594	CAP_402	mlb[75B1]
C7595	CAP_402	mlb[75B3]
C7596	CAP_402	mlb[75B2]
C7597	CAP_402	mlb[75B2]
C7598	CAP_402	mlb[75B2]
C7599	CAP_402	mlb[75B1]
C7600	CAP_603	mlb[76C4]
C7601	CAP_603	mlb[76A4]
C7602	CAP_402	mlb[76A4]
C7604	CAP_402	mlb[76A3]
C7605	CAP_402	mlb[76B5]
C7607	CAP_402	mlb[76A3]
C7608	CAP_402	mlb[76D2]
C7609	CAP_402	mlb[76D7]
C7612	CAP_603	mlb[76A7]
C7613	CAP_402	mlb[76A7]
C7621	CAP_402	mlb[76B6]
C7622	CAP_402	mlb[76C5]
C7624	CAP_402	mlb[76C6]
C7625	CAP_402	mlb[76B6]
C7626	CAP_402	mlb[76B6]
C7628	CAP_402	mlb[76B7]
C7629	CAP_402	mlb[76B7]
C7630	CAP_402	mlb[76A5]
C7631	CAP_402	mlb[76C7]
C7632	CAP_402	mlb[76C2]
C7640	CAP_1206-1	mlb[76D6]
C7641	CAP_1206-1	mlb[76D6]
C7642	CAP_1206-1	mlb[76D6]
C7643	CAP_1206-1	mlb[76D6]
C7650	CAP_805	mlb[76B7]
C7651	CAP_P_CASE-D3L	mlb[76B8]
C7652	CAP_805	mlb[76B8]
C7653	CAP_805	mlb[76C8]
C7654	CAP_805	mlb[76C8]
C7661	CAP_402	mlb[76B3]
C7662	CAP_402	mlb[76C4]
C7664	CAP_402	mlb[76C3]
C7665	CAP_402	mlb[76B4]
C7666	CAP_402	mlb[76B3]
C7668	CAP_402	mlb[76B2]
C7669	CAP_402	mlb[76B2]
C7670	CAP_402	mlb[76B4]
C7680	CAP_1206-1	mlb[76D3]
C7681	CAP_1206-1	mlb[76D4]
C7682	CAP_P_SM-1	mlb[76D4]
C7689	CAP_402	mlb[76B4]
C7690	CAP_805	mlb[76B2]
C7691	CAP_P_CASE-D3L	mlb[76B1]
C7692	CAP_P_CASE-D3L	mlb[76B1]
C7693	CAP_P_CASE-D3L	mlb[76B1]
C7700	CAP_805	mlb[77B5]
C7705	CAP_805	mlb[77B5]
C7706	CAP_603	mlb[77B4]
C7710	CAP_805	mlb[77D6]
C7712	CAP_402-1	mlb[77D4]
C7715	CAP_805	mlb[77D3]
C7800	CAP_402	mlb[78D2]
C7801	CAP_402	mlb[78D2]
C7810	CAP_402	mlb[78D6]
C7811	CAP_402	mlb[78D6]
C7850	CAP_402	mlb[78B2]
C7851	CAP_402	mlb[78C2]
C7895	CAP_402	mlb[78B7]
C7896	CAP_402	mlb[78B5]
C7899	CAP_402	mlb[78C6]
C8400	CAP_P_SM-LF	mlb[84C5]
C8401	CAP_805	mlb[84C7]
C8410	CAP_402	mlb[84C7]
C8411	CAP_402	mlb[84C7]
C8412	CAP_402	mlb[84C4]
C8413	CAP_402	mlb[84C4]
C8414	CAP_402	mlb[84C4]
C8415	CAP_402	mlb[84C4]
C8416	CAP_402	mlb[84C3]
C8420	CAP_402	mlb[84C7]
C8421	CAP_402	mlb[84C7]
C8422	CAP_402	mlb[84C7]
C8423	CAP_402	mlb[84C7]
C8424	CAP_402	mlb[84B7]
C8425	CAP_402	mlb[84B7]
C8426	CAP_402	mlb[84B7]
C8427	CAP_402	mlb[84B7]
C8428	CAP_402	mlb[84B7]
C8429	CAP_402	mlb[84B7]
C8430	CAP_402	mlb[84B7]
C8431	CAP_402	mlb[84B7]
C8432	CAP_402	mlb[84B7]
C8433	CAP_402	mlb[84B7]
C8434	CAP_402	mlb[84B7]
C8435	CAP_402	mlb[84B7]
C8436	CAP_402	mlb[84B7]
C8437	CAP_402	mlb[84B7]
C8438	CAP_402	mlb[84B7]
C8439	CAP_402	mlb[84B7]
C8440	CAP_402	mlb[84B7]
C8441	CAP_402	mlb[84A7]
C8442	CAP_402	mlb[84A7]
C8443	CAP_402	mlb[84A7]
C8444	CAP_402	mlb[84A7]
C8445	CAP_402	mlb[84A7]
C8446	CAP_402	mlb[84A7]
C8447	CAP_402	mlb[84A7]
C8448	CAP_402	mlb[84A7]
C8449	CAP_402	mlb[84A7]
C8450	CAP_402	mlb[84A7]
C8451	CAP_402	mlb[84A7]
C8500	CAP_805	mlb[85A5]
C8510	CAP_402	mlb[85A4]
C8511	CAP_402	mlb[85A4]
C8570	CAP_402	mlb[85D2]
C9000	CAP_603-1	mlb[90C7]
C9001	CAP_402	mlb[90C5]
C9010	CAP_402	mlb[90A8]
C9020	CAP_1210	mlb[90C5]
C9130	CAP_402	mlb[91B7]
C9131	CAP_805-1	mlb[91B7]
C9140	CAP_402	mlb[91A5]
C9141	CAP_402	mlb[91B5]
C9142	CAP_402	mlb[91B5]
C9143	CAP_402	mlb[91A6]
C9144	CAP_402	mlb[91B6]
C9145	CAP_402	mlb[91B6]
C9160	CAP_402	mlb[91B4]
C9161	CAP_402	mlb[91B4]
C9162	CAP_402	mlb[91A2]
C9163	CAP_402	mlb[91A2]
C9410	CAP_603	mlb[94C3]
C9411	CAP_402	mlb[94D3]
C9413	CAP_402	mlb[94C2]
C9414	CAP_402	mlb[94C2]
C9800	CAP_805	mlb[98C5]
C9801	CAP_402	mlb[98C4]
C9802	CAP_402	mlb[98C4]
D2185	DIODE_SCHOT_SOT23	mlb[21C4]
D2186	DIODE_SCHOT_SOT23	mlb[21B4]
D2702	DIODE_SCHOT_6PB_SOT-363	mlb[27D8 27D8]
D2800	DIODE_SCHOT_6PB_SOT-363	mlb[28D6]
D4390	ZENER_SOT23	mlb[43A6]
D4600	DIODE_SCHOT_3P_A_SC-75	mlb[46C2]
D4601	DIODE_SCHOT_3P_A_SC-75	mlb[46B5]
D4602	DIODE_SCHOT_3P_A_SC-	mlb[46A5]
D5600	DIODE_SOT23	mlb[56C4]
D5601	DIODE_SOT23	mlb[56B4]
D5700	DIODE_SOT23	mlb[57C4]
D7100	DIODE_SCHOT_SMB	mlb[71D2]
D7101	DIODE_SCHOT_SMB	mlb[71B2]
D7200	DIODE_SCHOT_SMB	mlb[72C3]
D7300	DIODE_SCHOT_5P_TLM83-3	mlb[73B6]
D7301	DIODE_SCHOT_SOT23	mlb[73C6]
D7373	DIODE_SCHOT_5P_TLM83-3	mlb[73B3]
D7374	DIODE_SCHOT_SOT23	mlb[73C3]
D7400	DIODE_SCHOT_5P_TLM83-3	mlb[74B6]
D7401	DIODE_SCHOT_SOT23	mlb[74C6]
D7473	DIODE_SCHOT_5P_TLM83-3	mlb[74B3]
D7474	DIODE_SCHOT_SOT23	mlb[74C4]
D7520	DIODE_SCHOT_5P_TLM83-3	mlb[75C4]
D7600	DIODE_SCHOT_5P_TLM83-3	mlb[76B7]
D7601	DIODE_SCHOT_5P_TLM83-3	mlb[76B2]
D7624	DIODE_SCHOT_SOD-323	mlb[76C6]
D7664	DIODE_SCHOT_SOD-323	mlb[76C3]
D7750	DIODE_SCHOT_SOD-123	mlb[77B5]
D7810	DIODE_SCHOT_SOD-123	mlb[78C6]
D9400	ZENER_CASE4Z5	mlb[94C1]
D9410	DIODE_SCHOT_SOD-123	mlb[94D6]
DE4300	DIODE_SCHOT_SM	mlb[43D7]
DP4310	DIODE_DUAL_6P_SOT-363	mlb[43D4 43D3]
DP4311	DIODE_DUAL_6P_SOT-363	mlb[43C4 43C3]
DP4320	DIODE_DUAL_6P_SOT-363	mlb[43B5 43B4]
DP4321	DIODE_DUAL_6P_SOT-363	mlb[43A5 43A4]
DS4599	LED_2.0X1.25MM-SM	mlb[45C2]
F4300	FUSE_SM	mlb[43D6]
F4310	FUSE_SM	mlb[43D6]
F9410	FUSE_805	mlb[94D5]
FL4300	FILTER_4P_L701-SM	mlb[43B3]
FL4310	FILTER_4P_L701-SM	mlb[43B3]
J600	CON_M12RT_D_THB_M-RT-TH	mlb[6D7]
J1000	MEROM_BGA-SKT-P	mlb[10C3 10D7]
J1000	MEROM_BGA-SKT-P	mlb[11D3 11D7]
J1300	CON_F60ST_D_SM1_F-ST-SM	mlb[13C4]
J2800	BATTERY_2P_SM	mlb[28D8]
J3100	CON_F200RT_DDR2DIMM_5MT_SM_F-RT-SM	mlb[31D5]
J3200	CON_F200RT_DDR2DIMM_5MT_SM_F-RT-SM	mlb[32D5]
J3400	CON_F52RT_D2MT_SM_F-RT-SM	mlb[34C5]
J3900	CON_RJ45_8ANG_D3MT_TH_F-ANG-TH	mlb[39C3]
J4300	CON_F9ANG_1394B_D6MT_TH_F-ANG-TH1	mlb[43C2]
J4301	CON_F6ANG_S3MT_1394A_TH_F-ANG-TH	mlb[43B2]
J4401	CON_M50ST_D2MT_SM1_M-ST-SM	mlb[44C4]
J4510	CON_M7ST_SATA_SM_M-S-T-SM	mlb[45D7]
J4610	CON_F4ANG_S4MT_USB_T-H_F-ANG-TH1	mlb[46D1]
J4620	CON_F4ANG_S4MT_USB_T-H_F-ANG-TH1	mlb[46B4]
J4630	CON_F4ANG_S4MT_USB_T-H_F-ANG-TH1	mlb[46A4]
J4700	CON_M5ST_S2MT_SM_M-S-T-SM	mlb[47B5]
J4720	CON_M4ST_S2MT_SM_M-S-T-SM	mlb[47D2]
J4780	CON_M4ST_S2MT_SM_M-S-T-SM	mlb[47B2]
J5010	CON_M2ST_S2MT_SM_M-S-T-SM	mlb[50C6]
J5100	CON_F30STSM_5047_SM1	mlb[51B5]
J5500	CON_M5ST_S2MT_SM_PN1-VD_M-ST-SM	mlb[55D7]
J5510	CON_M2ST_S2MT_SM_M-S-T-SM	mlb[55A7]
J5511	CON_M2RT_S2MT_SM_M-R-T-SM	mlb[55A5]
J5550	CON_M3RT_S2MT_SM_M-R-T-SM	mlb[55B7]
J5551	CON_M2RT_S2MT_SM_M-R-T-SM1	mlb[55B5]
J5560	CON_M5ST_S2MT_SM_PN1-VD_M-ST-SM	mlb[55D6]
J5600	CON_M4RT_S2MT_SM_M-R-T-SM2	mlb[56D3]
J5601	CON_M4RT_S2MT_SM_M-R-T-SM2	mlb[56B2]
J5700	CON_M4ST_S2MT_SM_M-S-T-SM	mlb[57C2]
J8400	CON_F232RT_MXM_SM1_F-RT-SM	mlb[84C5]
J8400	CON_F232RT_MXM_SM1_F-RT-SM	mlb[85C6]
J9002	CON_F30ST_D_SM_F-ST-SM	mlb[90B7]
J9410	CON_DVI_F32ST_Q2MT_SM_F-ST-SM1	mlb[94D5]
J9800	CON_F22RT_S2MT_SM_F-RT-SM	mlb[98C5]
L2150	IND_0603	mlb[21A7]
L2173	IND_1210	mlb[21D4]
L2181	IND_0603	mlb[21D2]
L2183	IND_0603	mlb[21C2]
L2190	IND_0805	mlb[21B3]
L2195	IND_0805	mlb[21A3]
L2700	IND_0805-1	mlb[27C8]
L2702	IND_0805	mlb[27A7]
L2703	IND_1210	mlb[27A7]
L2901	IND_0402	mlb[29D7]
L2902	IND_0402	mlb[29D3]
L2903	IND_0402	mlb[29C7]
L3800	IND_0805-1	mlb[38C6]
L3810	IND_0805-1	mlb[38B6]
L4200	IND_0402-LF	mlb[42D5]
L4210	IND_0402-LF	mlb[42B2]
L4211	IND_0402-LF	mlb[42B2]
L4300	IND_SM	mlb[43D3]
L4301	IND_SM	mlb[43B4]
L4610	IND_SM	mlb[46D3]
L4612	FILTER_4P_L701-SM	mlb[46D3]
L4620	IND_SM	mlb[46C6]
L4622	FILTER_4P_L701-SM	mlb[46B6]
L4630	IND_SM	mlb[46B6]
L4632	FILTER_4P_L701-SM	mlb[46A6]
L4700	IND_SM	mlb[47D6]
L4701	FILTER_4P_L701-SM	mlb[47B6]
L4710	FILTER_4P_L701-SM	mlb[47A6]
L7100	IND_MSQ1211R36LE-TH	mlb[71D2]
L7101	IND_MSQ1211R36LE-TH	mlb[71B2]
L7200	IND_MSQ1211R36LE-TH	mlb[72C3]
L7300	IND_MMD06EZ-SM	mlb[73C7]
L7360	IND_MMD06EZ-SM	mlb[73C2]
L7400	IND_MMD06EZ-SM	mlb[74C7]
L7460	IND_IHLP5050-MMD12CE-SM	mlb[74C2]
L7580	IND_IHLP5050-MMD12CE-SM	mlb[75C3]
L7620	IND_MMD06EZ-SM	mlb[76B7]
L7680	IND_MSQ12113R0LE-TH	mlb[76B2]
L7710	IND_IHLP	mlb[77D4]
L9000	IND_SM	mlb[90C6]
L9140	IND_0402	mlb[91A5]
L9141	IND_0402	mlb[91B5]
L9142	IND_0402	mlb[91B5]
L9160	IND_0402	mlb[91B2]
L9161	IND_0402	mlb[91A2]
L9400	FILTER_4P_SM	mlb[94D7]
L9401	FILTER_4P_SM	mlb[94D7]
L9402	FILTER_4P_SM	mlb[94C7]
L9403	FILTER_4P_SM	mlb[94B7]
L9410	IND_SM-1	mlb[94D4]
LED601	LED_2.0X1.25MM-SM	mlb[6A8]
LED602	LED_2.0X1.25MM-SM	mlb[6A7]
LED603	LED_2.0X1.25MM-SM	mlb[6A6]
LED604	LED_2.0X1.25MM-SM	mlb[6B7]
LED3900	LED_2.0X1.25MM-SM	mlb[39A7]
LED3901	LED_2.0X1.25MM-SM	mlb[39A7]
LED3902	LED_2.0X1.25MM-SM	mlb[39A7]
LED3903	LED_2.0X1.25MM-SM	mlb[39A6]
LED4400	LED_2.0X1.25MM-SM	mlb[44B5]
PP1000	PROBEPOINT_SM	mlb[7D7]
PP1001	PROBEPOINT_SM	mlb[7D7]
PP1002	PROBEPOINT_SM	mlb[7D7]
PP1003	PROBEPOINT_SM	mlb[7D7]
PP1004	PROBEPOINT_SM	mlb[7D7]
PP1005	PROBEPOINT_SM	mlb[7D7]
PP1006	PROBEPOINT_SM	mlb[7D7]
PP1007	PROBEPOINT_SM	mlb[7D7]
PP1008	PROBEPOINT_SM	mlb[7D7]
PP1009	PROBEPOINT_SM	mlb[7D7]
PP1010	PROBEPOINT_SM	mlb[7D7]
PP1011	PROBEPOINT_SM	mlb[7D7]
PP1012	PROBEPOINT_SM	mlb[7D7]
PP1013	PROBEPOINT_SM	mlb[7D7]
PP1014	PROBEPOINT_SM	mlb[7D7]
PP1015	PROBEPOINT_SM	mlb[7D7]
PP1016	PROBEPOINT_SM	mlb[7D7]
PP1017	PROBEPOINT_SM	mlb[7D7]
PP1018	PROBEPOINT_SM	mlb[7D7]
PP1019	PROBEPOINT_SM	mlb[7D7]
PP1020	PROBEPOINT_SM	mlb[7D7]
PP1021	PROBEPOINT_SM	mlb[7C7]
PP1022	PROBEPOINT_SM	mlb[7C7]
PP1023	PROBEPOINT_SM	mlb[7C7]
PP1024	PROBEPOINT_SM	mlb[7C7]
PP1025	PROBEPOINT_SM	mlb[7C7]
PP1026	PROBEPOINT_SM	mlb[7C7]
PP1027	PROBEPOINT_SM	mlb[7C7]
PP1028	PROBEPOINT_SM	mlb[7C7]
PP1029	PROBEPOINT_SM	mlb[7C7]
PP1030	PROBEPOINT_SM	mlb[7C7]
PP1031	PROBEPOINT_SM	mlb[7C7]
PP1032	PROBEPOINT_SM	mlb[7C7]
PP1033	PROBEPOINT_SM	mlb[7C7]
PP1034	PROBEPOINT_SM	mlb[7C7]
PP1035	PROBEPOINT_SM	mlb[7C7]
PP1400	PROBEPOINT_SM	mlb[7D6]
PP1401	PROBEPOINT_SM	mlb[7D6]
PP1402	PROBEPOINT_SM	mlb[7D6]
PP1403	PROBEPOINT_SM	mlb[7D6]
PP1404	PROBEPOINT_SM	mlb[7D6]
PP1405	PROBEPOINT_SM	mlb[7D6]
PP1406	PROBEPOINT_SM	mlb[7D6]
PP1407	PROBEPOINT_SM	mlb[7D6]
PP1408	PROBEPOINT_SM	mlb[7D6]
PP1409	PROBEPOINT_SM	mlb[7D6]
PP1410	PROBEPOINT_SM	mlb[7D6]
PP1411	PROBEPOINT_SM	mlb[7D6]
PP1412	PROBEPOINT_SM	mlb[7D6]
PP1413	PROBEPOINT_SM	mlb[7D6]
PP1414	PROBEPOINT_SM	mlb[7D6]
PP1415	PROBEPOINT_SM	mlb[7D6]
PP1416	PROBEPOINT_SM	mlb[7D6]
PP1417	PROBEPOINT_SM	mlb[7D6]
PP1418	PROBEPOINT_SM	mlb[7D6]
PP1419	PROBEPOINT_SM	mlb[7D6]
PP1420	PROBEPOINT_SM	mlb[7D6]
PP1421	PROBEPOINT_SM	mlb[7C6]
PP1422	PROBEPOINT_SM	mlb[7C6]
PP1423	PROBEPOINT_SM	mlb[7C6]
PP1424	PROBEPOINT_SM	mlb[7C6]
PP1425	PROBEPOINT_SM	mlb[7C6]
PP1426	PROBEPOINT_SM	mlb[7C6]
PP1427	PROBEPOINT_SM	mlb[7C6]
PP1428	PROBEPOINT_SM	mlb[7C6]
PP1429	PROBEPOINT_SM	mlb[7C6]
PP1430	PROBEPOINT_SM	mlb[7C6]
PP1431	PROBEPOINT_SM	mlb[7C6]
PP1432	PROBEPOINT_SM	mlb[7C6]
PP1433	PROBEPOINT_SM	mlb[7C6]
PP1434	PROBEPOINT_SM	mlb[7C6]
PP1435	PROBEPOINT_SM	mlb[7C6]
PP1436	PROBEPOINT_SM	mlb[7C6]
PP1437	PROBEPOINT_SM	mlb[7C6]
PP1438	PROBEPOINT_SM	mlb[7C6]

www.laptopschematics.com

PP1439	PROBEPOINT_SM	mlb[7C6]
PP1440	PROBEPOINT_SM	mlb[7C6]
PP1441	PROBEPOINT_SM	mlb[7C6]
PP1442	PROBEPOINT_SM	mlb[7C6]
PP1443	PROBEPOINT_SM	mlb[7C6]
PP1444	PROBEPOINT_SM	mlb[7B6]
PP1445	PROBEPOINT_SM	mlb[7B6]
PP1446	PROBEPOINT_SM	mlb[7B6]
PP1447	PROBEPOINT_SM	mlb[7B6]
PP1448	PROBEPOINT_SM	mlb[7B6]
PP1449	PROBEPOINT_SM	mlb[7B6]
PP1450	PROBEPOINT_SM	mlb[7B6]
PP1451	PROBEPOINT_SM	mlb[7B6]
PP1452	PROBEPOINT_SM	mlb[7B6]
PP1453	PROBEPOINT_SM	mlb[7B6]
PP1454	PROBEPOINT_SM	mlb[7B6]
PP1455	PROBEPOINT_SM	mlb[7B6]
PP1456	PROBEPOINT_SM	mlb[7B6]
PP1457	PROBEPOINT_SM	mlb[7B6]
PP1458	PROBEPOINT_SM	mlb[7B6]
PP1459	PROBEPOINT_SM	mlb[7B6]
PP1460	PROBEPOINT_SM	mlb[7B6]
PP1461	PROBEPOINT_SM	mlb[7B6]
PP1462	PROBEPOINT_SM	mlb[7B6]
PP1463	PROBEPOINT_SM	mlb[7B6]
PP1464	PROBEPOINT_SM	mlb[7B6]
PP1465	PROBEPOINT_SM	mlb[7B6]
PP1466	PROBEPOINT_SM	mlb[7B6]
PP1467	PROBEPOINT_SM	mlb[7B6]
PP1468	PROBEPOINT_SM	mlb[7B6]
PP1469	PROBEPOINT_SM	mlb[7B6]
PP1470	PROBEPOINT_SM	mlb[7A6]
PP1471	PROBEPOINT_SM	mlb[7A6]
PP1472	PROBEPOINT_SM	mlb[7A6]
PP1473	PROBEPOINT_SM	mlb[7A6]
PP1474	PROBEPOINT_SM	mlb[7A6]
PP1475	PROBEPOINT_SM	mlb[7A6]
PP1476	PROBEPOINT_SM	mlb[7A6]
PP1477	PROBEPOINT_SM	mlb[7A6]
PP1478	PROBEPOINT_SM	mlb[7A6]
PP1479	PROBEPOINT_SM	mlb[7A6]
PP1480	PROBEPOINT_SM	mlb[7A6]
PP1481	PROBEPOINT_SM	mlb[7A6]
PP1482	PROBEPOINT_SM	mlb[7A6]
PP1483	PROBEPOINT_SM	mlb[7A6]
PP1484	PROBEPOINT_SM	mlb[7A6]
PP1485	PROBEPOINT_SM	mlb[7A6]
PP1486	PROBEPOINT_SM	mlb[7A6]
PP1487	PROBEPOINT_SM	mlb[7A6]
PP1488	PROBEPOINT_SM	mlb[7A6]
PP1489	PROBEPOINT_SM	mlb[7A6]
PP1490	PROBEPOINT_SM	mlb[7A6]
PP1491	PROBEPOINT_SM	mlb[7A6]
PP1492	PROBEPOINT_SM	mlb[7A6]
PP1493	PROBEPOINT_SM	mlb[7A6]
PP2100	PROBEPOINT_SM	mlb[7C7]
PP2101	PROBEPOINT_SM	mlb[7C7]
PP2102	PROBEPOINT_SM	mlb[7C7]
PP2103	PROBEPOINT_SM	mlb[7B7]
PP2104	PROBEPOINT_SM	mlb[7B7]
PP2105	PROBEPOINT_SM	mlb[7B7]
PP2106	PROBEPOINT_SM	mlb[7B7]
PP2107	PROBEPOINT_SM	mlb[7B7]
PP2108	PROBEPOINT_SM	mlb[7B7]
PP2109	PROBEPOINT_SM	mlb[7B7]
PP2110	PROBEPOINT_SM	mlb[7B7]
PP2111	PROBEPOINT_SM	mlb[7B7]
PP2112	PROBEPOINT_SM	mlb[7B7]
PP2113	PROBEPOINT_SM	mlb[7B7]
PP2114	PROBEPOINT_SM	mlb[7B7]
PP2115	PROBEPOINT_SM	mlb[7B7]
PP2116	PROBEPOINT_SM	mlb[7B7]
PP2117	PROBEPOINT_SM	mlb[7B7]
PP2118	PROBEPOINT_SM	mlb[7B7]
PP2119	PROBEPOINT_SM	mlb[7B7]
PP2120	PROBEPOINT_SM	mlb[7B7]
PP2121	PROBEPOINT_SM	mlb[7A7]
PP2122	PROBEPOINT_SM	mlb[7A7]
PP2123	PROBEPOINT_SM	mlb[7A7]
PP2124	PROBEPOINT_SM	mlb[7A7]
PP2125	PROBEPOINT_SM	mlb[7A7]
PP2126	PROBEPOINT_SM	mlb[7A7]
PP2127	PROBEPOINT_SM	mlb[7A7]
PP2128	PROBEPOINT_SM	mlb[7A7]
PP2129	PROBEPOINT_SM	mlb[7A7]
PP2130	PROBEPOINT_SM	mlb[7A7]
PP2131	PROBEPOINT_SM	mlb[7A7]
PP2132	PROBEPOINT_SM	mlb[7B7]
PP2133	PROBEPOINT_SM	mlb[7B7]
PP3700	PROBEPOINT_SM	mlb[7D5]
PP3701	PROBEPOINT_SM	mlb[7D5]
PP3702	PROBEPOINT_SM	mlb[7D5]
PP3703	PROBEPOINT_SM	mlb[7D5]
PP3704	PROBEPOINT_SM	mlb[7D5]
PP4000	PROBEPOINT_SM	mlb[7D5]
PP4001	PROBEPOINT_SM	mlb[7D5]
PP4002	PROBEPOINT_SM	mlb[7D5]
PP4003	PROBEPOINT_SM	mlb[7D5]
PP4004	PROBEPOINT_SM	mlb[7D5]
PP4900	PROBEPOINT_SM	mlb[7C5]
PP4901	PROBEPOINT_SM	mlb[7C5]
PP4902	PROBEPOINT_SM	mlb[7C5]
PP4903	PROBEPOINT_SM	mlb[7C5]
Q600	TRA_2N7002_SOT23-LF	mlb[6A8]
Q610	TRA_2N7002_SOT23-LF	mlb[6D7]
Q3800	TRA_PBSS5540Z_SOT223	mlb[38C4]
Q3810	TRA_PBSS5540Z_SOT223	mlb[38A4]
Q4200	TRA_BCP69_SOT223-4	mlb[42D6]
Q4600	TRA_2N7002_SOT23-LF	mlb[46C8]
Q5077	TRA_DUAL_MMDT3904_SOT-363-LF	mlb[50D1 50D2]
Q5095	TRA_2N7002DW_SOT-363-LF	mlb[50C2 50C2]
Q5190	TRA_DUAL_MMDT3904_SOT-363-LF	mlb[51B3 51C4]
Q5339	TRA_2N7002_SOT23-LF	mlb[53B7]
Q5341	TRA_FDC796N_SUPERSOT-6	mlb[53B6]
Q5570	TRA_2N7002DW_SOT-363	mlb[55D1 55C2]
Q5600	TRA_NTHS5443T1_1206A-03-LF	mlb[56D4]
Q5602	TRA_2N7002_SOT23-LF	mlb[56D6]
Q5603	TRA_NTHS5443T1_1206A-03-LF	mlb[56B4]
Q5605	TRA_2N7002_SOT23-LF	mlb[56B6]
Q5700	TRA_NTHS5443T1_1206A-03-LF	mlb[57D4]
Q5702	TRA_2N7002_SOT23-LF	mlb[57C5]
Q7006	TRA_DUAL_SSM6N15FE_SOT563	mlb[70A7 70B6]
Q7007	TRA_DUAL_SSM6N15FE_SOT563	mlb[70A6 70B6]
Q7100	TRA_MOSFET_NCHN_5P1_MLP5X6-LFPAK	mlb[71D3]
Q7101	TRA_MOSFET_NCHN_5P2_MLP5X6-LFPAK	mlb[71D3]
Q7102	TRA_MOSFET_NCHN_5P1_MLP5X6-LFPAK	mlb[71C3]
Q7103	TRA_MOSFET_NCHN_5P2_MLP5X6-LFPAK	mlb[71B3]
Q7104	TRA_MOSFET_NCHN_5P2_MLP5X6-LFPAK	mlb[71C3]
Q7105	TRA_MOSFET_NCHN_5P2_MLP5X6-LFPAK	mlb[71B3]
Q7200	TRA_MOSFET_NCHN_5P1_MLP5X6-LFPAK	mlb[72C4]
Q7201	TRA_MOSFET_NCHN_5P2_MLP5X6-LFPAK	mlb[72C4]
Q7204	TRA_MOSFET_NCHN_5P2_MLP5X6-LFPAK	mlb[72C3]
Q7300	TRA_FDMS9620S_MLP	mlb[73C6]
Q7360	TRA_FDMS9620S_MLP	mlb[73C3]
Q7400	TRA_FDMS9620S_MLP	mlb[74C6]
Q7460	TRA_FDM6296_MICROFET 3X3	mlb[74C3]
Q7461	TRA_FDM6296_MICROFET 3X3	mlb[74C3]
Q7520	TRA_MOSFET_NCHN_5P1_MLP5X6-LFPAK	mlb[75D4]
Q7521	TRA_MOSFET_NCHN_5P2_MLP5X6-LFPAK	mlb[75C4]
Q7603	TRA_2N7002_SOT23-LF	mlb[76A6]
Q7620	TRA_FDMS9620S_MLP	mlb[76C7]
Q7640	TRA_SINGLE_MOSFET_PC HN_SOT-23	mlb[53B7]
Q7660	TRA_MOSFET_NCHN_5P1_MLP5X6-LFPAK	mlb[76C3]
Q7661	TRA_MOSFET_NCHN_5P2_MLP5X6-LFPAK	mlb[76B3]
Q7800	TRA_IRF7410_SO-8	mlb[78D2]
Q7801	TRA_SINGLE_MOSFET_NC HN_SOT23	mlb[78D3]
Q7810	TRA_IRF7410_SO-8	mlb[78D6]
Q7811	TRA_SINGLE_MOSFET_NC HN_SOT23	mlb[78D7]
Q7850	TRA_IRF7410_SO-8	mlb[78C2]
Q7851	TRA_SINGLE_MOSFET_NC HN_SOT23	mlb[78B3]
Q7895	TRA_MOSFET_NCHN_8P_S O-8	mlb[78B6]
Q7896	TRA_2N7002_SOT23-LF	mlb[78B7]
Q7897	TRA_SINGLE_MOSFET_NC HN_SOT23	mlb[78B6]
Q9000	TRA_SI3443DV_TSOP-LF	mlb[90C7]
Q9001	TRA_2N7002_SOT23-LF	mlb[90B7]
Q9411	TRA_2N7002DW_SOT-363	mlb[94D2 94C2]
R600	RES_402	mlb[6A7]
R602	RES_402	mlb[6A8]
R604	RES_402	mlb[6B7]
R605	RES_603	mlb[6A6]
R610	RES_402	mlb[6D7]
R1002	RES_402	mlb[10D5]
R1003	RES_402	mlb[10C5]
R1004	RES_402	mlb[10C5]
R1005	RES_402	mlb[10B5]
R1006	RES_402	mlb[10B5]
R1007	RES_402	mlb[10A4]
R1012	RES_402	mlb[10A4]
R1016	RES_402	mlb[10B1]
R1017	RES_402	mlb[10B1]
R1018	RES_402	mlb[10B1]
R1019	RES_402	mlb[10B1]
R1020	RES_402	mlb[10B7]
R1021	RES_402	mlb[10B7]
R1022	RES_402	mlb[10A7]
R1023	RES_402	mlb[10A7]
R1024	RES_402	mlb[10A7]
R1030	RES_402	mlb[10A4]
R1100	RES_402	mlb[11B5]
R1101	RES_402	mlb[11A5]
R1290	RES_402	mlb[12C2]
R1291	RES_402	mlb[12C2]
R1292	RES_402	mlb[12C2]
R1293	RES_402	mlb[12C2]
R1294	RES_402	mlb[12C2]
R1295	RES_402	mlb[12C2]
R1296	RES_402	mlb[12C2]
R1303	RES_402	mlb[13B2]
R1315	RES_402	mlb[13C6]
R1330	RES_402	mlb[13C5]
R1331	RES_402	mlb[13C5]
R1399	RES_402	mlb[13C7]
R1410	RES_402	mlb[14B6]
R1411	RES_402	mlb[14A6]
R1415	RES_402	mlb[14A6]
R1420	RES_402	mlb[14B6]
R1421	RES_402	mlb[14B6]
R1425	RES_402	mlb[14A7]
R1426	RES_402	mlb[14A7]
R1510	RES_402	mlb[15D3]
R1610	RES_402	mlb[16C2]
R1611	RES_402	mlb[16C2]
R1620	RES_402	mlb[16C1]
R1622	RES_402	mlb[16C1]
R1624	RES_402	mlb[16C1]
R1630	RES_402	mlb[16B7]
R1631	RES_402	mlb[16B7]
R1640	RES_402	mlb[16A3]
R1641	RES_402	mlb[16A3]
R1655	RES_402	mlb[16D7]
R1659	RES_402	mlb[16D7]
R1666	RES_402	mlb[16C7]
R1669	RES_402	mlb[16C7]
R1670	RES_402	mlb[16C7]
R1690	RES_402	mlb[16A3]
R1691	RES_402	mlb[16A3]
R2141	RES_603	mlb[21B7]
R2145	RES_603	mlb[21B7]
R2150	RES_603	mlb[21A7]
R2170	RES_603	mlb[21D4]
R2183	RES_402	mlb[21C2]
R2185	RES_402	mlb[21C3]
R2186	RES_402	mlb[21B3]
R2190	RES_402	mlb[21B3]
R2195	RES_402	mlb[21A3]
R2200	RES_402	mlb[22B2]
R2201	RES_402	mlb[22A2]
R2202	RES_402	mlb[22B2]
R2203	RES_402	mlb[22A2]
R2300	RES_402	mlb[23D7]
R2301	RES_402	mlb[23D7]
R2302	RES_402	mlb[23D6]
R2303	RES_402	mlb[23D3]
R2304	RES_402	mlb[23C3]
R2305	RES_402	mlb[23C3]
R2306	RES_402	mlb[23D3]
R2308	RES_402	mlb[23C3]
R2309	RES_402	mlb[23C3]
R2310	RES_402	mlb[23D6]
R2311	RES_402	mlb[23D6]
R2313	RES_402	mlb[23C7]
R2314	RES_402	mlb[23C7]
R2315	RES_402	mlb[23C7]
R2316	RES_402	mlb[23B7]
R2400	RES_402	mlb[24C7]
R2401	RES_402	mlb[24C7]
R2402	RES_402	mlb[24C7]
R2403	RES_402	mlb[24C7]
R2404	RES_402	mlb[24C7]
R2405	RES_402	mlb[24C6]
R2406	RES_402	mlb[24B6]
R2407	RES_402	mlb[24C6]
R2408	RES_402	mlb[24C6]
R2409	RES_402	mlb[24C6]
R2413	RES_402	mlb[24C3]
R2414	RES_402	mlb[24B3]
R2415	RES_402	mlb[24B5]
R2423	RES_402	mlb[24A3]
R2424	RES_402	mlb[24A3]
R2425	RES_402	mlb[24A3]
R2426	RES_402	mlb[24A3]
R2427	RES_402	mlb[24A3]
R2428	RES_402	mlb[24A3]
R2429	RES_402	mlb[24A3]
R2430	RES_402	mlb[24A3]
R2431	RES_402	mlb[24A3]
R2432	RES_402	mlb[24A3]
R2433	RES_402	mlb[24A3]
R2436	RES_402	mlb[24A3]
R2437	RES_402	mlb[24A3]
R2438	RES_402	mlb[24A3]
R2439	RES_402	mlb[24A3]
R2440	RES_402	mlb[24A3]
R2441	RES_402	mlb[24A3]
R2442	RES_402	mlb[24A3]
R2500	RES_402	mlb[25D7]
R2502	RES_402	mlb[25D7]
R2504	RES_402	mlb[25D6]
R2505	RES_402	mlb[25D6]
R2506	RES_402	mlb[25D6]
R2507	RES_402	mlb[25D6]
R2510	RES_402	mlb[25D6]
R2511	RES_402	mlb[25A8]
R2512	RES_402	mlb[25A8]
R2514	RES_402	mlb[25A7]
R2515	RES_402	mlb[25A7]
R2516	RES_402	mlb[25A7]
R2523	RES_402	mlb[25B3]
R2524	RES_402	mlb[25C2]
R2525	RES_402	mlb[25C2]
R2526	RES_402	mlb[25C2]
R2527	RES_402	mlb[25B2]
R2528	RES_402	mlb[25B2]
R2529	RES_402	mlb[25B2]
R2530	RES_402	mlb[25B4]
R2531	RES_402	mlb[25B4]
R2532	RES_402	mlb[25D3]
R2533	RES_402	mlb[25D2]
R2534	RES_402	mlb[25D2]
R2535	RES_402	mlb[25D3]
R2536	RES_402	mlb[25A4]
R2544	RES_402	mlb[25A4]
R2545	RES_402	mlb[25A4]
R2546	RES_402	mlb[25A4]
R2547	RES_402	mlb[25D6]
R2550	RES_402	mlb[25D7]
R2551	RES_402	mlb[25D7]
R2552	RES_402	mlb[25D7]
R2553	RES_402	mlb[25D7]
R2596	RES_402	mlb[25A4]
R2597	RES_402	mlb[25A4]
R2598	RES_402	mlb[25A4]
R2700	RES_603	mlb[27A8]
R2701	RES_402	mlb[27D8]
R2702	RES_402	mlb[27D8]
R2710	RES_402	mlb[28B2]
R2735	RES_402	mlb[27A8]
R2800	RES_402	mlb[28D5]
R2803	RES_402	mlb[28A6]
R2806	RES_402	mlb[28D6]
R2807	RES_402	mlb[28D7]
R2809	RES_402	mlb[28C7]
R2810	RES_402	mlb[28C7]
R2850	RES_402	mlb[28B1]
R2881	RES_402	mlb[28D2]
R2883	RES_402	mlb[28D2]
R2885	RES_402	mlb[28D2]
R2890	RES_402	mlb[28C2]
R2891	RES_402	mlb[28D2]
R2892	RES_402	mlb[28C2]
R2893	RES_402	mlb[28C2]
R2896	RES_402	mlb[28A4]
R2897	RES_402	mlb[28A4]
R2900	RES_402	mlb[29C6]
R2901	RES_402	mlb[29D3]
R2902	RES_402	mlb[29C3]
R2903	RES_402	mlb[29B6]
R3026	RES_402	mlb[30A4]
R3027	RES_402	mlb[30A4]
R3030	RES_402	mlb[30A4]
R3032	RES_402	mlb[30C7]
R3033	RES_402	mlb[30C7]
R3034	RES_402	mlb[30A7]
R3035	RES_402	mlb[30A7]
R3046	RES_402	mlb[30C1]
R3047	RES_402	mlb[30C1]
R3050	RES_402	mlb[30D1]
R3051	RES_402	mlb[30D1]
R3052	RES_402	mlb[30D1]
R3053	RES_402	mlb[30C1]
R3054	RES_402	mlb[30C1]
R3055	RES_402	mlb[30C1]
R3067	RES_402	mlb[30D7]
R3080	RES_402	mlb[30C7]
R3081	RES_402	mlb[30C7]
R3082	RES_402	mlb[30C7]
R3083	RES_402	mlb[30C7]
R3084	RES_402	mlb[30B7]
R3085	RES_402	mlb[30B7]
R3086	RES_402	mlb[30B7]
R3087	RES_402	mlb[30B7]
R3088	RES_402	mlb[30B7]
R3089	RES_402	mlb[30B7]
R3090	RES_402	mlb[30B7]
R3091	RES_402	mlb[30B7]
R3098	RES_402	mlb[30B4]
R3100	RES_402	mlb[31D2]
R3101	RES_402	mlb[31C2]
R3140	RES_402	mlb[31A3]
R3141	RES_402	mlb[31A3]
R3200	RES_402	mlb[32C2]
R3201	RES_402	mlb[32C2]
R3240	RES_402	mlb[32A3]
R3241	RES_402	mlb[32A3]
R3300	RES_402	mlb[33D5]
R3301	RES_402	mlb[33D5]
R3302	RES_402	mlb[33D5]
R3303	RES_402	mlb[33D5]
R3304	RES_402	mlb[33C5]
R3305	RES_402	mlb[33C5]
R3400	RES_402	mlb[34C7]
R3401	RES_402	mlb[34C7]
R3410	RES_402	mlb[34A5]
R3720	RES_402	mlb[37C6]
R3740	RES_402	mlb[37B7]
R3741	RES_402	mlb[37B7]
R3742	RES_402	mlb[37B6]
R3743	RES_402	mlb[37B6]
R3744	RES_402	mlb[37B6]
R3745	RES_402	mlb[37B5]
R3746	RES_402	mlb[37B5]
R3747	RES_402	mlb[37B5]
R3760	RES_402	mlb[37C2]
R3765	RES_402	mlb[37B2]
R3780	RES_402	mlb[37B2]
R3781	RES_402	mlb[37B2]
R3801	RES_402	mlb[38C4]
R3811	RES_402	mlb[38A5]
R3900	RES_402	mlb[39D7]
R3901	RES_603	mlb[39A7]
R3902	RES_603	mlb[39A7]
R3903	RES_603	mlb[39A7]
R3904	RES_603	mlb[39A6]
R3910	RES_402	mlb[39A4]
R3911	RES_402	mlb[39A4]
R3912	RES_402	mlb[39A4]
R3913	RES_402	mlb[39A4]
R4000	RES_402	mlb[40B6]
R4001	RES_402	mlb[40C7]
R4002	RES_402	mlb[40C7]
R4010	RES_402	mlb[40C2]
R4011	RES_402	mlb[40B2]
R4012	RES_402	mlb[40B2]
R4013	RES_402	mlb[40C2]
R4080	RES_402	mlb[40B8]
R4090	RES_402	mlb[40B6]
R4200	RES_402	mlb[42C7]
R4250	RES_402	mlb[42D3]
R4251	RES_402	mlb[42D2]
R4252	RES_402	mlb[42D2]
R4260	RES_402	mlb[42C3]
R4261	RES_402	mlb[42C2]
R4262	RES_402	mlb[42C2]
R4300	RES_2512	mlb[43D7]
R4301	RES_2512	mlb[43D7]
R4302	RES_805	mlb[43D7]
R4335	RES_402	mlb[43B2]
R4350	RES_402	mlb[43C7]
R4351	RES_402	mlb[43C7]
R4352	RES_402	mlb[43B7]
R4353	RES_402	mlb[43B7]
R4354	RES_402	mlb[43B7]
R4360	RES_402	mlb[43C7]
R4361	RES_402	mlb[43C7]
R4362	RES_402	mlb[43B7]
R4363	RES_402	mlb[43B7]
R4364	RES_402	mlb[43B7]
R4390	RES_402	mlb[43A7]
R4403	RES_402	mlb[44C5]
R4451	RES_402	mlb[44C5]
R4453	RES_402	mlb[44C4]
R4454	RES_402	mlb[44C4]
R4457	RES_402	mlb[44B6]
R4458	RES_402	mlb[44B5]
R4459	RES_402	mlb[44B5]
R4590	RES_402	mlb[45B1]
R4599	RES_603	mlb[45C2]
R4600	RES_402	mlb[46D8]
R4650	RES_402	mlb[46D4]
R4651	RES_402	mlb[46C4]
R4652	RES_402	mlb[46C4]
R4701	RES_402	mlb[47B6]
R4702	RES_402	mlb[47B6]
R4710	RES_402	mlb[47A6]
R4711	RES_402	mlb[47A6]
R4721	RES_402	mlb[47D1]
R4901	RES_402	mlb[49C1]
R4902	RES_402	mlb[49C2]
R4903	RES_402	mlb[49C1]
R4909	RES_402	mlb[49C1]
R4950	RES_402	mlb[49C4]
R4951	RES_402	mlb[49C4]
R4998	RES_402	mlb[49C2]
R4999	RES_402	mlb[49D4]
R5000	RES_402	mlb[50D6]
R5010	RES_402	mlb[50C6]
R5032	RES_402	mlb[50B1]

www.laptop-schematics.com

R5033	RES_402	mlb[50B1]
R5034	RES_402	mlb[50B1]
R5035	RES_402	mlb[50B1]
R5036	RES_402	mlb[50B1]
R5037	RES_402	mlb[50B1]
R5038	RES_402	mlb[50B1]
R5039	RES_402	mlb[50B1]
R5040	RES_402	mlb[50B1]
R5041	RES_402	mlb[50B1]
R5042	RES_402	mlb[50B1]
R5043	RES_402	mlb[50B1]
R5046	RES_402	mlb[50A1]
R5047	RES_402	mlb[50B1]
R5048	RES_402	mlb[50A1]
R5070	RES_402	mlb[50D2]
R5071	RES_402	mlb[50D3]
R5078	RES_402	mlb[50D1]
R5080	RES_402	mlb[50B1]
R5082	RES_402	mlb[50B1]
R5083	RES_402	mlb[50A1]
R5084	RES_402	mlb[50A1]
R5088	RES_402	mlb[50A1]
R5090	RES_402	mlb[50B1]
R5091	RES_402	mlb[50B1]
R5092	RES_402	mlb[50B1]
R5093	RES_402	mlb[50B1]
R5094	RES_402	mlb[50B1]
R5096	RES_402	mlb[50B1]
R5190	RES_402	mlb[51B2]
R5191	RES_402	mlb[51C3]
R5192	RES_402	mlb[51C4]
R5200	RES_402	mlb[52D7]
R5201	RES_402	mlb[52D7]
R5230	RES_402	mlb[52A7]
R5231	RES_402	mlb[52A7]
R5250	RES_402	mlb[52D4]
R5251	RES_402	mlb[52D4]
R5260	RES_402	mlb[52C4]
R5261	RES_402	mlb[52C4]
R5270	RES_402	mlb[52D2]
R5271	RES_402	mlb[52D2]
R5280	RES_402	mlb[52C2]
R5281	RES_402	mlb[52C2]
R5290	RES_402	mlb[52B2]
R5291	RES_402	mlb[52B2]
R5309	RES_402	mlb[53D7]
R5339	RES_402	mlb[53B7]
R5340	RES_402	mlb[53A8]
R5341	RES_402	mlb[53B7]
R5342	RES_402	mlb[53B7]
R5343	RES_1206	mlb[53B5]
R5353	RES_402	mlb[53D4]
R5354	RES_402	mlb[53D4]
R5370	RES_402	mlb[53C7]
R5380	RES_SENSE_2512-1	mlb[53D3]
R5381	RES_SENSE_2512-1	mlb[53C4]
R5382	RES_SENSE_2512	mlb[53B4]
R5383	RES_402	mlb[53B2]
R5384	RES_402	mlb[53B2]
R5385	RES_402	mlb[53B4]
R5386	RES_402	mlb[53A4]
R5387	RES_402	mlb[53B3]
R5388	RES_402	mlb[53A3]
R5500	RES_402	mlb[55B2]
R5501	RES_402	mlb[55A2]
R5510	RES_402	mlb[55B3]
R5511	RES_402	mlb[55B3]
R5512	RES_402	mlb[55B3]
R5570	RES_402	mlb[55D4]
R5571	RES_402	mlb[55D2]
R5572	RES_402	mlb[55D2]
R5573	RES_402	mlb[55D2]
R5600	RES_402	mlb[56C7]
R5601	RES_402	mlb[56A7]
R5602	RES_1206	mlb[56D6]
R5603	RES_805	mlb[56D5]
R5605	RES_805	mlb[56D5]
R5606	RES_402	mlb[56D6]
R5607	RES_805	mlb[56B5]
R5609	RES_805	mlb[56B5]
R5610	RES_1206	mlb[56B6]
R5611	RES_402	mlb[56B6]
R5698	RES_402	mlb[56A7]
R5699	RES_402	mlb[56C7]
R5700	RES_402	mlb[57C7]
R5701	RES_805	mlb[57D5]
R5703	RES_805	mlb[57D5]
R5704	RES_1206	mlb[57D5]
R5705	RES_402	mlb[57D6]
R5797	RES_402	mlb[57C8]
R6100	RES_402	mlb[61C5]
R6101	RES_402	mlb[61C5]
R6114	RES_402	mlb[61B4]
R6190	RES_402	mlb[61B6]
R6191	RES_402	mlb[61B6]
R6193	RES_402	mlb[61B3]
R7000	RES_402	mlb[70D8]
R7001	RES_402	mlb[70D8]
R7002	RES_402	mlb[70C8]
R7003	RES_402	mlb[70C8]
R7005	RES_402	mlb[70D5]
R7006	RES_402	mlb[70D5]
R7007	RES_402	mlb[70D5]
R7008	RES_402	mlb[70D5]
R7010	RES_402	mlb[70D7]
R7011	RES_402	mlb[70C7]
R7013	RES_402	mlb[70D7]
R7014	RES_402	mlb[70C7]
R7018	RES_402	mlb[70D7]
R7019	RES_402	mlb[70C7]
R7020	RES_402	mlb[70D7]
R7021	RES_402	mlb[70C7]
R7030	RES_402	mlb[70C3]
R7031	RES_402	mlb[70C3]
R7032	RES_402	mlb[70C3]
R7034	RES_402	mlb[70D3]
R7035	RES_402	mlb[70B3]
R7036	RES_402	mlb[70B3]
R7037	RES_402	mlb[70B3]
R7038	RES_402	mlb[70B3]
R7039	RES_402	mlb[70C3]
R7040	RES_402	mlb[70C7]
R7041	RES_402	mlb[70B7]
R7060	RES_402	mlb[70A7]

R7061	RES_402	mlb[70A6]
R7062	RES_402	mlb[70A6]
R7063	RES_402	mlb[70B6]
R7064	RES_402	mlb[70B6]
R7065	RES_402	mlb[70C6]
R7066	RES_402	mlb[70C6]
R7070	RES_402	mlb[70C7]
R7080	RES_402	mlb[70D3]
R7081	RES_402	mlb[70D3]
R7092	RES_402	mlb[70B3]
R7100	RES_402	mlb[71C2]
R7101	RES_603	mlb[71C2]
R7102	RES_1206	mlb[71B3]
R7103	RES_1206	mlb[71D3]
R7104	RES_402	mlb[71C1]
R7105	RES_402	mlb[71B2]
R7106	RES_603	mlb[71B2]
R7107	RES_402	mlb[71B1]
R7108	RES_402	mlb[71C8]
R7109	RES_402	mlb[71B7]
R7110	RES_402	mlb[71B7]
R7111	RES_402	mlb[71B8]
R7112	RES_402	mlb[71D7]
R7114	RES_402	mlb[71B7]
R7115	RES_402	mlb[71B4]
R7116	RES_402	mlb[71B4]
R7117	RES_402	mlb[71B5]
R7118	RES_402	mlb[71B5]
R7119	RES_402	mlb[71C8]
R7120	RES_402	mlb[71D7]
R7121	RES_402	mlb[71D7]
R7122	RES_402	mlb[71A4]
R7123	RES_402	mlb[71A4]
R7126	THERMISTER_402	mlb[71C8]
R7127	RES_402	mlb[71C7]
R7130	RES_402	mlb[71B4]
R7131	THERMISTER_0603-LF	mlb[71B4]
R7140	RES_603	mlb[71B1]
R7141	RES_603	mlb[71C1]
R7142	RES_402	mlb[71D4]
R7143	RES_402	mlb[71C4]
R7197	RES_402	mlb[71D6]
R7199	RES_402	mlb[71C7]
R7200	RES_402	mlb[72C3]
R7201	RES_603	mlb[72B3]
R7203	RES_1206	mlb[72C3]
R7204	RES_402	mlb[72C2]
R7241	RES_603	mlb[72C2]
R7250	RES_402	mlb[72C5]
R7300	RES_402	mlb[73B7]
R7301	RES_402	mlb[73B7]
R7306	RES_1206	mlb[73C7]
R7310	RES_1206	mlb[73A3]
R7311	RES_1206	mlb[73A3]
R7312	RES_1206	mlb[73A3]
R7313	RES_1206	mlb[73A3]
R7321	RES_402	mlb[73C5]
R7323	RES_402	mlb[73B5]
R7331	RES_402	mlb[73C5]
R7356	RES_1206	mlb[73C2]
R7361	RES_402	mlb[73C3]
R7371	RES_402	mlb[73C3]
R7382	RES_402	mlb[73C4]
R7383	RES_402	mlb[73B4]
R7384	RES_402	mlb[73B4]
R7390	RES_402	mlb[73B2]
R7391	RES_402	mlb[73B2]
R7400	RES_402	mlb[74B7]
R7401	RES_402	mlb[74B7]
R7406	RES_1206	mlb[74C7]
R7421	RES_402	mlb[74C5]
R7423	RES_402	mlb[74B5]
R7431	RES_402	mlb[74C5]
R7456	RES_1206	mlb[74C2]
R7461	RES_402	mlb[74C4]
R7471	RES_402	mlb[74C3]
R7483	RES_402	mlb[74B4]
R7490	RES_402	mlb[74B2]
R7491	RES_402	mlb[74B2]
R7500	RES_402	mlb[75D5]
R7501	RES_402	mlb[75C2]
R7504	RES_402	mlb[75D7]
R7505	RES_402	mlb[75C7]
R7506	RES_402	mlb[75C7]
R7507	RES_402	mlb[75D5]
R7508	RES_402	mlb[75C7]
R7510	RES_402	mlb[75C4]
R7521	RES_402	mlb[75C1]
R7522	RES_402	mlb[75C1]
R7539	RES_402	mlb[75D6]
R7551	RES_402	mlb[75B5]
R7556	RES_1206	mlb[75C3]
R7600	RES_402	mlb[76C5]
R7601	RES_402	mlb[76A7]
R7602	RES_402	mlb[76A7]
R7603	RES_402	mlb[76A3]
R7604	RES_402	mlb[76A3]
R7606	RES_402	mlb[76A4]
R7607	RES_402	mlb[76A4]
R7612	RES_402	mlb[76A6]
R7613	RES_402	mlb[76D7]
R7614	RES_402	mlb[76D7]
R7615	RES_402	mlb[76D7]
R7616	RES_402	mlb[76D7]
R7617	RES_402	mlb[76D7]
R7618	RES_402	mlb[76D6]
R7621	RES_402	mlb[76C7]
R7624	RES_402	mlb[76C6]
R7625	RES_402	mlb[76B6]
R7626	RES_402	mlb[76C7]
R7627	RES_402	mlb[76B7]
R7628	RES_402	mlb[76B7]
R7629	RES_402	mlb[76C7]
R7630	RES_402	mlb[76A7]
R7631	RES_402	mlb[76A7]
R7661	RES_402	mlb[76C2]
R7664	RES_402	mlb[76C3]
R7665	RES_402	mlb[76B4]
R7666	RES_402	mlb[76C2]
R7667	RES_402	mlb[76B2]
R7668	RES_402	mlb[76B2]
R7669	RES_402	mlb[76C2]
R7670	RES_402	mlb[76C4]
R7692	RES_402	mlb[76A6]

R7710	RES_402	mlb[77D6]
R7711	RES_402	mlb[77D6]
R7712	RES_402	mlb[77D4]
R7713	RES_402	mlb[77C4]
R7800	RES_402	mlb[78D3]
R7801	RES_402	mlb[78D3]
R7810	RES_402	mlb[78D7]
R7811	RES_402	mlb[78D6]
R7850	RES_402	mlb[78B3]
R7851	RES_402	mlb[78B3]
R7870	RES_402	mlb[78C7]
R7895	RES_402	mlb[78B7]
R7896	RES_402	mlb[78B6]
R7897	RES_402	mlb[78B6]
R7898	RES_402	mlb[78B6]
R8500	RES_402	mlb[85C7]
R8501	RES_402	mlb[85C5]
R8502	RES_402	mlb[85C7]
R8503	RES_402	mlb[85A4]
R8505	RES_402	mlb[85B4]
R8570	RES_402	mlb[85D3]
R9000	RES_402	mlb[90C8]
R9001	RES_402	mlb[90C7]
R9002	RES_805	mlb[90C8]
R9003	RES_805	mlb[90C8]
R9070	RES_402	mlb[90B7]
R9074	RES_402	mlb[90B2]
R9075	RES_402	mlb[90B2]
R9090	RES_805	mlb[90C6]
R9099	RES_402	mlb[90C8]
R9140	RES_402	mlb[91A6]
R9141	RES_402	mlb[91B6]
R9142	RES_402	mlb[91B6]
R9160	RES_402	mlb[91B3]
R9161	RES_402	mlb[91A3]
R9400	RES_402	mlb[94D7]
R9402	RES_402	mlb[94D7]
R9403	RES_402	mlb[94D7]
R9404	RES_402	mlb[94C7]
R9405	RES_402	mlb[94C7]
R9408	RES_402	mlb[94C7]
R9409	RES_402	mlb[94C7]
R9410	RES_402	mlb[94D2]
R9411	RES_402	mlb[94D2]
R9412	RES_402	mlb[94D2]
R9413	RES_402	mlb[94C2]
R9414	RES_402	mlb[94C2]
R9415	RES_402	mlb[94B7]
R9420	RES_402	mlb[94D1]
R9421	RES_402	mlb[94D1]
R9422	RES_402	mlb[94C2]
R9800	RES_402	mlb[98C6]
R9801	RES_402	mlb[98B6]
RP3300	RPAK4P_SM-LF	mlb[33C4 33C4 33C4 33C4]
RP3305	RPAK4P_SM-LF	mlb[33B4 33C4 33C4 33C4]
RP3310	RPAK4P_SM-LF	mlb[33D4 33A4 33A4 33A4]
RP3330	RPAK4P_SM-LF	mlb[33D4 33B4 33B4 33B4]
RP3334	RPAK4P_SM-LF	mlb[33B4 33B4 33B4 33B4]
RP3338	RPAK4P_SM-LF	mlb[33A4 33B4 33B4 33A4]
RP3342	RPAK4P_SM-LF	mlb[33B4 33C4 33C4 33C4]
RP3346	RPAK4P_SM-LF	mlb[33D4 33C4 33B4 33C4]
RP3350	RPAK4P_SM-LF	mlb[33B4 33A4 33B4 33B4]
RP3354	RPAK4P_SM-LF	mlb[33B4 33A4 33A4 33B4]
RP3358	RPAK4P_SM-LF	mlb[33C4 33C4 33C4 33C4]
RP3362	RPAK4P_SM-LF	mlb[33A4 33C4 33D4 33A4]
S5000	SWI_TACT_4SM_EVQPH_S M-LF	mlb[50D8]
S5010	SWI_TACT_4SM_EVQPH_S M-LF	mlb[50C7]
SC0700	SPRING_CLIP_1P_EMI_C LIP-SM1	mlb[7B6]
SC0701	SPRING_CLIP_1P_EMI_C LIP-SM1	mlb[7B5]
SC0702	SPRING_CLIP_1P_EMI_C LIP-SM-K2	mlb[7B5]
SDF0717	PCB_STANDOFF	mlb[7A3]
SDF0721	PCB_STANDOFF	mlb[7A3]
SDF0726	HSK_NUT_TH	mlb[7A6]
SDF0727	HSK_NUT_TH	mlb[7A5]
SDF0750	PCB_STANDOFF	mlb[7A3]
SDF0751	PCB_STANDOFF	mlb[7A2]
SDF3400	PCB_STANDOFF	mlb[34A5]
SDF4400	PCB_STANDOFF	mlb[44D4]
SDF4401	PCB_STANDOFF	mlb[44A4]
SDF4721	PCB_STANDOFF	mlb[47D1]
SDF9000	PCB_STANDOFF	mlb[90B7]
SDF9001	PCB_STANDOFF	mlb[90A7]
SDF9800	PCB_STANDOFF	mlb[98D5]
SDF9801	PCB_STANDOFF	mlb[98D5]
SDF9803	PCB_STANDOFF	mlb[98B5]
SDF9804	PCB_STANDOFF	mlb[98B5]
SW2800	SWI_TACT_4SM_EVQPH_S M-LF	mlb[28A4]
T3900	XFR_LFE9245A_SOI	mlb[39C5]
U1400	CRESTLINE_FCBGA	mlb[14D4]
U1400	CRESTLINE_FCBGA	mlb[15D4]
U1400	CRESTLINE_FCBGA	mlb[16D5]
U1400	CRESTLINE_FCBGA	mlb[17D3 17D7]
U1400	CRESTLINE_FCBGA	mlb[18D3 18D7]
U1400	CRESTLINE_FCBGA	mlb[19D5]
U1400	CRESTLINE_FCBGA	mlb[20D4 20D7]
U2300	SB_ICH8M_BGA	mlb[23D5]
U2300	SB_ICH8M_BGA	mlb[24B7 24D4]
U2300	SB_ICH8M_BGA	mlb[25D4]
U2300	SB_ICH8M_BGA	mlb[26D5 26D8]
U2803	MC74VHC1G00_SC70-5	mlb[28A7]
U2900	CLK_SYN_SLG8LP537_QF N	mlb[29C5]
U3700	88E8058_QFN	mlb[37C4]
U3780	EEPROM_M24C08_SO8	mlb[37B2]
U4000	FW643_BGA	mlb[40C5]
U4600	SWI_TPS2060_MSOP	mlb[46C7]
U4601	SWI_TPS2068_MSOP	mlb[46D7]
U4650	PI3USB10_TDFN	mlb[46D4]
U4900	SMC_H8S2116_BGA	mlb[49A3 49C3 49B7 49D7]
U5000	VDET_RN5VD_SOT23-5A	mlb[50D7]
U5380	MAX4073_SC70	mlb[53C4]
U5381	MAX4377_UMAX	mlb[53B3]
U5500	LM95214_LLP	mlb[55B4]
U5570	EMC1402_MSOP	mlb[55D4]
U6100	FLASH_SST25VF016B_SO I_SOI	mlb[61C5]
U7010	COMPARATOR_LM339A_SO I-LF	mlb[70D6]

U7052	MC74VHC1G08_SOT23-5- LF	mlb[70C2]
U7056	MC74VHC1G08_SOT23-5- LF	mlb[70C2]
U7100	ISL6260C_QFN	mlb[71C6]
U7101	ISL6208_QFN	mlb[71D5]
U7102	ISL6208_QFN	mlb[71C5]
U7201	ISL6208_QFN	mlb[72C7]
U7300	ISL6539_SSOP	mlb[73C5]
U7400	ISL6539_SSOP	mlb[74C5]
U7500	ISL6269_QFN	mlb[75D6]
U7501	SN74LVC1G07_SC70	mlb[75D8]
U7550	LREG_BD3533FVM_MSOP-8	mlb[75B4]
U7600	LTC3728L_QFN	mlb[76C5]
U7601	COMPARATOR_LM393_SOI -1-LF	mlb[76D6 76A7]
U7710	TPS62050_MSOP	mlb[77D5]
U7750	VREG_TA48025BF_HSOP3	mlb[77B5]
U8570	EEPROM_M24C02_SO8	mlb[85D2]
U9130	VIDEO_TS3V330_SOP	mlb[91B7]
U9160	74LVC1G125LF_SOT23-5	mlb[91B4]
U9161	74LVC1G125LF_SOT23-5	mlb[91A4]
VR5065	VREF_REF3133_SOT23-3	mlb[50B8]
XW4900	SHORT_SM	mlb[49C2]
XW5309	SHORT_SM	mlb[53D7]
XW5500	SHORT_SM	mlb[55A4]
XW5501	SHORT_SM	mlb[55A4]
XW5502	SHORT_SM	mlb[55A4]
XW5503	SHORT_SM	mlb[55A4]
XW7100	SHORT_SM	mlb[71A6]
XW7101	SHORT_SM	mlb[71B2]
XW7102	SHORT_SM	mlb[71B1]
XW7103	SHORT_SM	mlb[71D2]
XW7104	SHORT_SM	mlb[71D1]
XW7203	SHORT_SM	mlb[72C3]
XW7204	SHORT_SM	mlb[72C2]
XW7300	SHORT_SM	mlb[73B4]
XW7400	SHORT_SM	mlb[74B4]
XW7500	SHORT_SM	mlb[75C5]
XW7600	SHORT_SM	mlb[76A5]
Y2800	CRYSTAL_4PIN_SM-LF	mlb[28C7]
Y2901	CRYSTAL_5X3.2-SM	mlb[29C6]
Y3750	CRYSTAL_SM-3-LF	mlb[37B5]
Y4000	CRYSTAL_HC49-USMD	mlb[40B7]
Y5020	CRYSTAL_SM-4	mlb[50C8]
ZH500	HOLE_VIA	mlb[7C1]
ZH501	HOLE_VIA	mlb[7C1]
ZH502	HOLE_VIA	mlb[7C1]
ZH503	HOLE_VIA	mlb[7C1]
ZH504	HOLE_VIA	mlb[7B1]
ZH505	HOLE_VIA	mlb[7B1]
ZH506	HOLE_VIA	mlb[7B1]
ZH507	HOLE_VIA	mlb[7B1]
ZH508	HOLE_VIA	mlb[7B1]
ZH509	HOLE_VIA	mlb[7B1]
ZH510	HOLE_VIA	mlb[7C1]
ZH511	HOLE_VIA	mlb[7C1]
ZH512	HOLE_VIA	mlb[7C1]
ZH513	HOLE_VIA	mlb[7C1]
ZH514	HOLE_VIA	mlb[7B1]
ZH515	HOLE_VIA	mlb[7B1]
ZH516	HOLE_VIA	mlb[7B1]
ZH517	HOLE_VIA	mlb[7B1]
ZH518	HOLE_VIA	mlb[7B1]
ZH519	HOLE_VIA	mlb[7B1]
ZH520	HOLE_VIA	mlb[7C1]
ZH521	HOLE_VIA	mlb[7C1]
ZH522	HOLE_VIA	mlb[7C1]
ZH523	HOLE_VIA	mlb[7C1]
ZH524	HOLE_VIA	mlb[7B1]
ZH525	HOLE_VIA	mlb[7B1]
ZH526	HOLE_VIA	mlb[7B1]
ZH527	HOLE_VIA	mlb[7B1]
ZH528	HOLE_VIA	mlb[7B1]
ZH529	HOLE_VIA	mlb[7B1]
ZH0700	MTGHOLE	mlb[7A5]
ZH0701	MTGHOLE	mlb[7A5]
ZH0702	MTGHOLE	mlb[7A4]
ZH0703	MTGHOLE	mlb[7A4]
ZH0711	MTGHOLE	mlb[7A6]
ZH0712	MTGHOLE	mlb[7A5]
ZH0714	MTGHOLE	mlb[7A5]
ZH0715	MTGHOLE	mlb[7A5]
ZH0718	MTGHOLE	mlb[7A5]
ZH0720	MTGHOLE	mlb[7A4]
ZH0722	MTGHOLE	mlb[7B4]
ZH0723	MTGHOLE	mlb[7B4]
ZH0724	MTGHOLE	mlb[7B3]
ZH0725	MTGHOLE	mlb[7B3]
ZH0750	MTGHOLE	mlb[7A4]

www.laptop-schematics.com